



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN, UP TO 10KV

CIE/666

Hand-cranked analog insulation tester in seasoned wooden body — up to 10,000V, wider range than metal-body CIE/444.

UP TO 10000V

Insulation Tester — Wooden Body, Hand-Driven

A hand-driven generator-type insulation tester in a seasoned wooden cabinet — wider voltage range than the metal-body CIE/444, suited to HV switchgear and higher-class transformer testing up to 10,000 V.

- **No batteries required** — hand-cranked A.C. generator
- **Centrifugal governor** — holds output voltage constant
- **Seasoned wooden body** — detachable lid, handle, lock
- **3-second response** — quick direct reading
- **7 rated voltages** — 100V to 10,000V, build-to-order

Supplied as base instrument only — carrying case, test leads, and range options available at extra cost.

Manufactured in India since 1963 — trusted by MSEB, Indian Railways, WBSETCL, etc.



- V Up to 10000V** Rated voltage range
- 0 Battery-Free** Hand-cranked generator
- 3 3 Seconds** Response time

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish, detachable lid & lock
Generator Type	Hand-driven A.C. generator, centrifugal governor
Scale Length	100 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m. or more
Response Time	3 seconds
Rated Voltages	100V / 250V / 500V / 1000V / 2500V / 5000V / 10000V
100V Range Options	0-20 · 0-50 · 0-100 MΩ
250V Range Options	0-50 · 0-100 · 0-250 MΩ
500V Range Options	0-100 · 0-200 · 0-500 · 0-1000 · 0-2000 MΩ
1000V Range Options	0-100 · 0-200 · 0-500 · 0-1000 · 0-2000 MΩ
2500V Range Options	0-1000 · 0-2000 · 0-2500 · 0-5000 · 0-10000 · 0-20000 · 50-50000 MΩ
5000V Range Options	0-5000 · 0-10000 · 0-20000 · 50-50000 · 100-100000 MΩ
10000V Range Options	0-10000 · 0-20000 · 50-50000 · 100-100000 MΩ
Ordering	Build-to-order — specify voltage & resistance range
Dimensions (L×W×H)	265 × 165 × 185 mm (approx.)
Weight	4.1 kg (approx.)
Warranty	12 months against manufacturing defects

02 Typical Applications

- Rotating plant and stationary apparatus maintenance
- Insulation control and switching equipment checks
- HV switchgear and transformer testing to 10,000V
- Locating shorts, defects, and insulation failures

03 Optional Accessories

- + Carrying case
- + Test leads, 1m/2m
- + H.V. test leads, 2m
- + Dual voltage/range option

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.