



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

MICRO-OHM METER · BENCH-TOP, 4-TERMINAL KELVIN

MR-253A

Bench-top digital micro-ohm meter with 4-terminal (Kelvin) measurement - 1999 $\mu\Omega$ to 19.99 k Ω across 8 ranges. 7-segment LED display.

MR-253A

Digital Micro-Ohm Meter

A compact, precision bench-top micro-ohm meter for measuring low values of resistance - in cables, transformer and motor windings, switch and relay contacts, PCB tracks, and ammeter shunt wires. Four-terminal (Kelvin) measurement eliminates errors from lead and contact resistance.

- **4-terminal (Kelvin) technique** - eliminates lead & contact error
- **8 ranges, single instrument** - 1999 $\mu\Omega$ to 19.99 k Ω
- **$\pm 0.5\%$ ± 2 digits** - precision low-drift accuracy
- **Auto test-current scaling** - 1A down to 0.01mA by range
- **3½-digit LED display** - 1999-count, seven-segment
- **MOS LSI technology** - compact, reliable, easy to service

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- 4 **4-Terminal** Kelvin measurement
- Ω **$\mu\Omega$ to k Ω** 8 ranges, single unit
- $\pm$ **$\pm 0.5\%$ ± 2 digits** Accuracy

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Display	3½-digit, 1999 counts, seven-segment LED
Measurement Technique	4-terminal (Kelvin) - eliminates lead & contact resistance error
Accuracy	$\pm 0.5\%$ ± 2 digits
Power	230 V, 50 Hz, single phase
Dimensions (W×H×D)	192 × 96 × 230 mm (approx.)
Weight	2.25 kg (approx.)
Warranty	12 months against manufacturing defects

02 Measurement Ranges - Resolution & Test Current

RANGE	RESOLUTION	TEST CURRENT
0-1999 $\mu\Omega$	1 $\mu\Omega$	1 A
0-19.99 m Ω	0.01 m Ω	1 A
0-199.9 m Ω	0.1 m Ω	1 A
0-1999 m Ω	1 m Ω	0.1 A (100 mA)
0-19.99 Ω	0.01 Ω	0.01 A (10 mA)
0-199.9 Ω	0.1 Ω	0.001 A (1 mA)
0-1999 Ω	1 Ω	0.0001 A (0.1 mA)
0-19.99 k Ω	0.01 k Ω	0.00001 A (0.01 mA)

03 Typical Applications

- Cable and wire resistance measurement
- Transformer and motor winding resistance checks
- Switch and relay contact resistance testing
- PCB track resistance testing and ammeter shunt calibration

04 What's in the Box

- ✓ 2 pairs of test leads