



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL CLAMP MULTIMETER · TRUE-RMS AC/DC

DCM 5410 TR

True-RMS AC/DC clamp multimeter up to 1000 A, plus capacitance, frequency, and temperature.

UP TO 1000A

Digital Clamp Multimeter — True-RMS AC/DC, up to 1000 A

A True-RMS AC/DC clamp multimeter for current up to 1000 A — suited to solar, battery, and DC distribution work.

- **AC/DC current up to 1000A** — 60/600/1000A, True-RMS
- **Capacitance & frequency** — 10mF max, 10Hz–10MHz
- **Temperature** — -20°C to 1000°C
- **Low-Z ACV** — avoids false ghost-voltage readings

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- A** Up to 1000A Max AC/DC current, True-RMS
- T** -20° to 1000°C Temperature range
- ✓** CAT III 600V Safety rating

01 Full Specification Sheet

PARAMETER	SPECIFICATION
AC Current Ranges	60 A / 600 A / 1000 A (True-RMS)
DC Current Ranges	60 A / 600 A / 1000 A
DC Voltage	600 mV / 6 V / 60 V / 600 V / 1000 V
AC Voltage (True-RMS)	6 V / 60 V / 600 V / 750 V
Capacitance	1 nF – 10 mF (8 ranges)
Frequency	10 Hz – 10 MHz
Temperature	-20°C to 1000°C / -4°F to 1832°F
Low Impedance ACV	6 V / 60 V / 300 V – ≤3 K Ω input
Resistance	600 Ω / 6K Ω / 60K Ω / 600K Ω / 6M Ω / 20M Ω / 60M Ω
Display	6000 Counts LCD, auto-ranging
NCV / Live Wire Test	Provided
Jaw Opening (Max.)	40 mm
Safety Category	CAT III 600 V
Power Supply	2×AAA 1.5V Batteries
Dimensions (L×W×H)	230 × 75 × 40 mm
Weight (incl. battery)	Approx. 315 g
Warranty	12 months against manufacturing defects

02 Typical Applications

- AC and DC current measurement on panels and boards
- Solar and battery system diagnostics (DC clamp)
- Electrical maintenance and switchgear testing
- Combined electrical and temperature diagnostics

03 What's in the Box

- ✓ Test leads
- ✓ Carrying pouch
- ✓ User manual
- ✓ 2×AAA batteries