



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

RELAY TEST SET · SINGLE PHASE

RTS-5

Single-phase relay test set — 0–200 A AC current (14V/4V), 0–240V AC, built-in digital timer.

0–200A · 8 RANGES

Secondary Current Injection Relay Test Set

A secondary current injection relay test set for testing protective, over-current, and earth fault relays — continuously variable AC current from 0–1A to 0–200A across eight ranges, with a built-in dual-range digital timer that starts on energising and stops automatically when the relay under test actuates.

- **0–200A across 8 ranges** — continuously variable, 14V or 4V
- **0–240V AC alternative output** — via Volt/Current selector
- **Digital timer** — 9.999s (1ms) or 99.99s (10ms) resolution
- **Digital ammeter & voltmeter** — built-in, multi-range
- **NO/NC selector** — for relay auxiliary contacts

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- A 0–200A** 8 continuously variable ranges
- T Digital Timer** 1ms / 10ms resolution
- V Fixed Voltages** 50V & 110V A.C. at 1A

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Input	230 V, single phase, 50 Hz A.C.
Current Output	0–1/2/5/10/20A at 14V or 4V; 0–50/100/200A at 4V
Output Voltage (alternative)	0–240 V A.C. at 1 A (mutually exclusive with current)
Fixed Voltages	50 V & 110 V A.C. at 1 A
Timer	9.999 sec (1ms res.) or 99.99 sec (10ms res.)
Ammeter	Rectangular multi-range digital, 0–1/2/5/10/25/50/100/200A
Voltmeter	Rectangular A.C., 0–300 V
Duty	Intermittent – 5 min ON / 10 min OFF
Cooling	Air natural
Warranty	12 months against manufacturing defects

02 Typical Applications

- Protective and over-current relay testing
- Earth fault relay testing
- Relay commissioning and maintenance in substations and panels