Label Frame Protocol

Offset	Length	Type	Data	Details
0	1	Data Length	0x02	AD Structure Data Length
1	1	Flag Data Type	0x01	AD Type is Flags
2	1	Flag Data	0x06	LE General Discoverable Mode, BR/EDR not supported
3	1	Data Length	/	AD Structure Data Length
4	1	AD Type	0xFF	AD Type is Manufacturer Specific Data
5	2	Company ID	0x3906	LE, Manufacturer ID, 0x0639 = Minew
7	1	Frame Type	0xCA	Minew Connect V3
8	1	Frame Version	0x1B	Sensor Frame
9	1bit	Encrypto Flag	-	0: Disable, 1: Enable
9	7bit	Sub-version	0x01	Sub-version
10	2	Product ID	/	Product ID, 0x001B = MTB06
12	1bit	CTE Flag	-	0: Disable, 1: Enable
12	5bit	CTE Length[1]	-	CTE Length Value, range 2~20, unit: 8us
12	2bit	Encrypto Range	-	Encryption Range, refer to Encrypto Range
13	6	MAC Address	/	LE, Product Serial Number ID, default equal to MAC address. 0x0165332211AC = AC:11:22:33:65:01
19	2	Battery Voltage	/	BE, Battery Voltage, Units: mV
21	2	SOC Temperature	/	8.8 Fixed Point, 0x1973 => 25.44℃

[1] The parameters here are only valid when the CTE Flag value is 1.

23	1	TBD	/	Reserved
24	1	Measured Power	/	Calibrated RSSI value at 1m
25	2	Nonce Salt	/	-
27	4	Nonce Counter	/	-

Encrypto Range

Value	Details
0	Encrypt the entire segment, including the encryption of the MAC Address, Battery Voltage, SOC Temperature, and TBD fields
1 ~ 3	Reserved

Note:

When decrypting, the nonce parameter equals Nonce Counter + Nonce Salt. If the parameter order is incorrect, it will lead to parsing errors, preventing the restoration of the correct raw data.