

OSBAMS Rev.2 Controller RC1 - Fabrication notes

RC1 - REVIEW CANDIDATE - NOT FOR FABRICATION

OSBAMS Rev.2 Controller — Fabrication notes (2026-10-01)

RC1 - REVIEW CANDIDATE - NOT FOR FABRICATION. These are working notes for the RC1 review package, not an order specification.

Board

- Name OSBAMS Rev.2 Controller, revision RC1, size 100 x 90 mm, single piece (no panelization specified yet), 4 copper layers, 1.6 mm FR-4 (TG $\geq$ 150 C suggested), outer copper 1 oz, inner copper 0.5 oz or 1 oz.
- Layer use: L1 components + signals, L2 solid GND plane, L3 routing + GND fill, L4 components/signals + GND fill. A separate **GND_HOST island** (isolated USB side) occupies x 74.5-97.5 mm, y 2.5-47.5 mm on all layers with a 3 mm gap to GND under the ISO7721.
- Finish: ENIG recommended (0.5 mm pitch LQFP-64, QFN-20). Soldermask green or black, white silkscreen. Lead-free.
- Edge: plain rectangle, no V-cut, 4 x M3 NPTH (3.2 mm) at (4,4), (96,4), (4,86), (96,86). 3 fiducials 1 mm / 2 mm mask opening.
- Design rules used: track $\geq$ 0.15 mm (default 0.2 mm, power 0.4-0.5 mm), clearance $\geq$ 0.2 mm (pack-level nets 0.4 mm), via 0.6/0.3 mm, copper-to-edge 0.3 mm. Measured in this layout: min track 0.20 mm, min via 0.50/0.30 mm. Check against PCBWay's current 4-layer capability before ordering.
- Controlled impedance: none required (no high-speed nets; USB 2.0 full-speed D+/D- are short, 90 ohm not controlled in RC1 - review).
- Silkscreen: connector names, pin numbers, polarity, OSBAMS Rev.2 Controller, RC1 2026-10-01, 44 V / 10 A MAX, NOT FOR FABRICATION (remove at release).

Files

Gerber/drill files in this folder are a **KiCad 10.0.6 export of a script-generated design**. They are for review and DFM discussion only. **Regenerate them from the .kicad_pcb on your own KiCad installation (and re-run ERC/DRC) before any order.** Do not fabricate from the files in this package.

Open fabrication gates

See PCBWAY_RELEASE_CANDIDATE_REPORT.md (BLOCKERS BEFORE PCBWAY ORDER).