

Retail Display Fixture - Assembly & Installation Guide

PORTFOLIO SAMPLE - Fictional product created to demonstrate instruction-sheet design. Not LG&P; work.

Purpose

Demonstrates how I would convert engineering inputs into a concise, installer-facing sequence with parts identification, tool callouts, safety notes, verification points, and revision metadata.

Before You Begin

Tools: #2 Phillips screwdriver, 4 mm hex key, level, tape measure. **Estimated assembly:** 25-35 minutes, 2 people.

Parts Checklist

ID	Component	Qty	Verification
A	Base frame	1	No visible damage; feet installed
B	Upright panel	2	Left/right pair; mounting holes aligned
C	Header panel	1	Logo face oriented outward
D	Shelf	3	Front lip faces customer side
H1	M6 x 20 mm socket screw	12	Match thread/length before use
H2	M6 washer	12	One per H1 screw

Assembly Sequence

1. Position the base

Place Base Frame A on a level surface with the finished customer-facing edge forward. Confirm all four leveling feet contact the floor.

2. Install uprights

With a second person supporting the panel, align Upright B with the base mounting holes. Install H1 screws with H2 washers finger-tight. Repeat for the opposite upright.

3. Square and tighten

Measure diagonally corner-to-corner. Adjust until the two diagonal measurements are within 3 mm. Tighten all base fasteners evenly.

4. Install shelves

Starting at the lowest position, engage each Shelf D with the upright slots. Verify the front lip faces outward and the shelf is fully seated before loading.

5. Install header

Align Header C across both uprights. Install remaining H1/H2 hardware. Do not overtighten; stop when the washer is fully seated.

6. Final verification

Level the fixture, confirm all fasteners are secure, verify no sharp edges or pinch hazards are exposed, and perform a light stability check before merchandising.

Installer Verification

■ Parts count matches checklist ■ Fixture level ■ All hardware secure ■ Shelves fully seated ■ Header aligned ■ No visible damage

Revision Record

Sample Rev A - Initial portfolio release. In a production workflow, every engineering drawing/BOM change would be reconciled against this sheet before release.