
Purpose: Ensure correct material identification, prevent mix-ups and damage, and maintain a 5S-compliant work area.

Area: _____	SOP No.: SOP-5S-____	Version: 01	Effective date: ____ / ____ / _____


001	**Separate classification**	Each tray must contain only one material code / one material type. Do not mix materials with different codes, statuses or lots.
002	**Correct position and orientation**	Use the correct tray / molded insert for each material type. Place components in the correct slot and orientation; do not stack, tilt, shift or place them outside the designated positions.
003	**Neat arrangement**	Arrange materials neatly and evenly; do not pile them up. Do not allow materials to spill, mix with adjacent trays or be placed directly on the worktable.
004	**Clear identification labels**	Each tray must have a label showing the correct material code, name / specification and quantity. Place the label where it is easy to see and not obstructed; the information must match the contents.
005	**Quantity / status control**	Check the actual quantity against the label / documents when receiving, issuing and handing over materials. NG, pending-inspection or unidentified-status materials must be kept separately and clearly marked.
006	**Material protection**	Do not drop, impact, bend or touch contact pins / sensitive surfaces. For ESD-sensitive components, use trays and anti-static measures as required by the process.
007	**Empty / damaged tray control**	Return empty trays to the designated location. Remove cracked, dirty, deformed or non-positioning trays from use and report them to the person in charge.
008	**Maintain 5S after handling**	After taking or returning materials, close the cover (if applicable), align the tray neatly, clean the area and keep unrelated items off the worktable.



Classify by material code



Place in the correct molded slot



Arrange materials neatly



Ensure labels are easy to identify

Responsibility: Employees must follow this SOP. The team leader / supervisor checks at the start, during and end of each shift. Isolate any abnormality and report it to the person in charge.