

PCB-Loader — Standard Operating Procedure

PCB-Loader — Standard Operating Procedure

- 1. Purpose
- 2. Normal operating envelope
- 3. Idle reasons
- 4. Faults & corrective actions
- 5. Preventive maintenance schedule
- 6. References

PCB-Loader — Standard Operating Procedure

Audience: Maintenance Tech · Line Manager **Applies to:** Line-E, station 1, PCB-Loader

1. Purpose

The PCB-Loader is the entry point of Line-E (Electronics Assembly). It feeds bare PCBs from magazine racks onto the conveyor for SMT-Placement. A stoppage starves the entire 8-station line.

2. Normal operating envelope

- Ideal cycle time: **5 s** — fastest station in the factory
- Max acceptable cycle time: **7 s**
- Expected reject rate: **0 %**
- Fault probability per cycle: **0.1 %**
- Input buffer capacity: **5 parts**

3. Idle reasons

idle_reason	Meaning here	First check
Starved	Magazine racks empty.	Refill magazine; check Production Schedule.
Blocked	SMT-Placement (station 2) buffer full.	Verify SMT-Placement state.

4. Faults & corrective actions

4.1 Feed-Jam

- **Symptoms in telemetry:** fault_type = "Feed-Jam". Loader stops; all downstream Line-E stations report Starved.
- **Likely root cause:** PCB stuck in feeder gate; magazine misaligned.
- **Corrective action:**
 - 1. LOTO. Clear the jammed PCB.

2. Verify magazine alignment.
- **Restart criteria:** 10 PCBs feed cleanly.

4.2 Magazine-Empty

- **Symptoms in telemetry:** `fault_type = "Magazine-Empty"`. Although it reads as a fault, this is essentially a refill condition.
- **Likely root cause:** kit consumed faster than expected.
- **Corrective action:**
 1. Refill the magazine.
 2. Confirm lot traceability captured.
- **Restart criteria:** continuous feed for 5 cycles.

4.3 Sensor-Block

- **Symptoms in telemetry:** `fault_type = "Sensor-Block"`. Pickoff sensor reads "present" when no PCB is at the gate.
- **Likely root cause:** sensor fouled, dust accumulation, or misalignment.
- **Corrective action:**
 1. Clean and realign the sensor.
 2. Verify trigger margin.
- **Restart criteria:** clean transitions on 10 cycles.

5. Preventive maintenance schedule

- **Daily:** check magazine; clean sensors.
- **Weekly:** lubricate feed mechanism.
- **Monthly:** alignment verification.
- **Quarterly:** mechanical overhaul.

6. References

- Maintenance_Workflow_Overview.pdf
- Line-E_02_SMT-Placement_SOP.pdf
- Production_Lines_Reference.pdf