

Reflow-Oven — Standard Operating Procedure

Reflow-Oven — Standard Operating Procedure

- 1. Purpose
- 2. Normal operating envelope
- 3. Idle reasons
- 4. Faults & corrective actions
- 5. Preventive maintenance schedule
- 6. References

Reflow-Oven — Standard Operating Procedure

Audience: Maintenance Tech · Line Manager **Applies to:** Line-E, station 3, Reflow-Oven

1. Purpose

The Reflow-Oven melts solder paste to bond SMT components placed by SMT-Placement. A precise multi-zone temperature profile is essential to joint quality. At 45 s ideal cycle, it is one of the longer steps on Line-E.

2. Normal operating envelope

- Ideal cycle time: **45 s**
- Max acceptable cycle time: **55 s**
- Expected reject rate: **≤ 2 %**
- Fault probability per cycle: **0.4 %**
- Input buffer capacity: **5 parts**

3. Idle reasons

idle_reason	Meaning here	First check
Starved	SMT-Placement (station 2) is not feeding boards.	Verify SMT-Placement state.
Blocked	AOI-Inspection (station 4) cannot accept the soldered board.	Verify AOI-Inspection state.

4. Faults & corrective actions

4.1 Temp-Drift

- **Symptoms in telemetry:** fault_type = "Temp-Drift". Joint quality rejects rise at AOI; reject types cluster around cold-joint or solder-ball.

- **Likely root cause:** thermocouple drift, zone heater degraded.
- **Corrective action:**
 1. Profile against a Mole / data-logger.
 2. Calibrate or replace thermocouples.
 3. Replace failed heating zone if applicable.
- **Restart criteria:** profile within ± 5 °C of recipe across zones.

4.2 Conveyor-Slip

- **Symptoms in telemetry:** `fault_type = "Conveyor-Slip"`. PCBs do not travel through the oven at the right speed; thermal profile broken.
- **Likely root cause:** conveyor belt slippage, drive motor slowing.
- **Corrective action:**
 1. LOTO. Tension the conveyor.
 2. Inspect drive motor; replace if loaded.
- **Restart criteria:** consistent conveyor speed.

4.3 Element-Fail

- **Symptoms in telemetry:** `fault_type = "Element-Fail"`. One or more zones fall short of setpoint.
- **Likely root cause:** heating element failed open.
- **Corrective action:**
 1. LOTO. Resistance-check elements; replace the failed zone.
 2. Re-validate profile.
- **Restart criteria:** zone temperatures balanced.

5. Preventive maintenance schedule

- **Daily:** record profile.
- **Weekly:** clean conveyor and tunnel.
- **Monthly:** thermocouple verification.
- **Quarterly:** element check; conveyor service.

6. References

- Maintenance_Workflow_Overview.pdf
- Safety_Lockout_Tagout_Procedure.pdf
- Line-E_02_SMT-Placement_SOP.pdf
- Line-E_04_AOI-Inspection_SOP.pdf