

Wave-Solder — Troubleshooting Guide (Faultiest Station on Line-E)

Wave-Solder — Troubleshooting Guide

- 1. Purpose
- 2. Normal operating envelope
- 3. Idle reasons
- 4. Faults & corrective actions
- 5. Preventive maintenance schedule
- 6. References

Wave-Solder — Troubleshooting Guide

Audience: Maintenance Tech (primary) · Line Manager · Quality Worker **Applies to:** Line-E, station 6, Wave-Solder

1. Purpose

Wave-Solder bonds the through-hole leads inserted at station 5. With a 0.7 % per-cycle fault probability — the **highest on Line-E** — it is the single most common cause of downtime on the electronics line. This troubleshooting guide is the fast path from a Fault telemetry event back to Running for the three tracked fault types.

2. Normal operating envelope

- Ideal cycle time: **35 s**
- Max acceptable cycle time: **44 s**
- Expected reject rate: **≤ 3 %**
- Fault probability per cycle: **0.7 %** (line max)
- Input buffer capacity: **5 parts**

3. Idle reasons

idle_reason	Meaning here	First check
Starved	Through-Hole-Insert (station 5) is not feeding boards.	Verify Through-Hole-Insert state.
Blocked	Functional-Test (station 7) buffer full.	Verify Functional-Test state.

Because of this station’s high fault rate, **most downstream Starved events on Line-E trace back to this station**. When triaging starvation on stations 7 or 8, check Wave-Solder first.

4. Faults & corrective actions

4.1 Solder-Temp-Drift

- **Symptoms in telemetry:** fault_type = "Solder-Temp-Drift". Joint quality rejects rise at Functional-Test; cold-joint codes cluster.
- **Likely root cause:** thermocouple drift, heater control failing.
- **Corrective action:**
 1. Verify pot temperature against a calibrated probe.
 2. If drift > 5 °C, calibrate or replace the thermocouple.
 3. Inspect heater elements; replace if degraded.
- **Restart criteria:** pot temperature stable within ± 3 °C of setpoint for 10 minutes.

4.2 Flux-Low

- **Symptoms in telemetry:** fault_type = "Flux-Low". Wetting defects rise; some leads show open joints.
- **Likely root cause:** flux reservoir near-empty; spray nozzles clogged.
- **Corrective action:**
 1. Refill flux reservoir.
 2. Inspect and clean spray nozzles.
 3. Verify flux coverage on a test board.
- **Restart criteria:** uniform flux coverage observed on the test board.

4.3 Conveyor-Speed-Fault

- **Symptoms in telemetry:** fault_type = "Conveyor-Speed-Fault". Time in the wave is wrong; large solder defect spike.
- **Likely root cause:** drive motor encoder failure, or VFD tripped.
- **Corrective action:**
 1. LOTO. Inspect encoder cable and connection.
 2. Verify VFD fault code; reset or replace.
- **Restart criteria:** conveyor speed stable across 5 minutes.

5. Preventive maintenance schedule

- **Daily:** dross removal; flux check; profile log.
- **Weekly:** clean spray nozzles; inspect fingers.
- **Monthly:** solder analysis for contamination.
- **Quarterly:** full conveyor service.

6. References

- Maintenance_Workflow_Overview.pdf
- Safety_Lockout_Tagout_Procedure.pdf
- OEE_Targets_and_Escalation.pdf
- Line-E_05_Through-Hole-Insert_SOP.pdf
- Line-E_07_Functional-Test_SOP.pdf