Aurora X2 Home Battery - Technical Manual

1. Product overview

The Aurora X2 is a wall-mounted lithium iron phosphate battery for homes with solar panels. It stores surplus solar energy during the day and supplies the home in the evening and during power cuts.

Usable capacity is 13.5 kWh. The battery can deliver a continuous power of 7 kW and a peak power of 10 kW for up to 10 seconds, which is enough to start a heat pump. Round-trip efficiency is 91 percent.

The unit weighs 118 kg and measures 115 x 75 x 16 cm. Two people and a wall bracket rated for at least 150 kg are required for installation.

2. Installation

The battery must be installed by a certified electrician. It may be mounted indoors or outdoors under a roof, but never in direct sunlight. Keep at least 30 cm of free space above the unit and 15 cm on each side, so that air can circulate.

The operating temperature range is -20 to 50 degrees Celsius. Below 0 degrees the battery heats itself before charging, which reduces charging power to 2 kW until the cells reach 5 degrees.

The Aurora X2 connects to the home network over Wi-Fi or Ethernet. An internet connection is only needed for software updates and the mobile app; the battery works fully offline.

3. Error codes

E12 - Overtemperature. The cells have exceeded 55 degrees Celsius. The battery stops charging and discharging until the temperature falls below 45 degrees. Check that the ventilation space around the unit is free.

E31 - Grid disconnected. The battery has detected a power cut and switched to backup mode. No action is needed; the battery reconnects automatically 60 seconds after the grid returns.

E47 - Communication fault. The battery cannot reach the inverter. Restart the inverter first, then the battery. If the error remains after two restarts, contact support.

E58 - Cell imbalance. One or more cells differ too much in voltage. The battery limits its power to 3 kW and runs a balancing cycle overnight. If E58 is shown for more than three days, contact support.

4. Maintenance and warranty

Clean the air filter on the underside every six months. Do not use water or cleaning sprays on the unit; a dry cloth is enough.

The warranty covers 10 years or 6,000 full charging cycles, whichever comes first. The battery is guaranteed to keep at least 70 percent of its original capacity during the warranty period.

To make a warranty claim, register the battery in the Aurora app within 30 days of installation. Claims for batteries that were not registered are handled case by case.