King Fahd University of Petroleum & Minerals

Department of Aerospace Engineering

RoboMaster Assessment 1: Teleoperation, Telemetry, and ROS 2 Integration

Course: SCE 672 – Advanced Robotics **Instructor:** Prof. Aamer Iqbal Bhatti
Student Name: Raian E Rabbani **Student ID:** 202617880
Department: Aerospace Engineering **Date:** September 2026

Problem 1: System Setup and Driver Installation

(i) Operating System Setup

Instead of dual-booting Ubuntu, I set up my environment using **WSL 2 (Ubuntu 24.04)** on Windows. The handout advises against using virtual machines due to USB latency and dropped UDP packets, but WSL 2 handled the robot connections cleanly without these issues.

Here is how I verified that both connection methods work:

- **Wired USB (RNDIS):** I attached the RoboMaster's USB network device to WSL with `usbipd wsl attach`. I verified the connection by pinging `192.168.42.2`, getting consistent < 1 ms replies with no packet loss.
- **Wi-Fi Hotspot (AP):** I enabled mirrored networking in `.wslconfig` so WSL shares the host Wi-Fi adapter directly. Once connected to the robot's AP network, I verified that WSL pings `192.168.12.1` directly and runs the Python SDK without socket errors.

(ii) ROS 2 and Simulation Setup

Inside Ubuntu on WSL 2, I installed the ROS 2 Jazzy desktop package along with Gazebo Harmonic and development tools:

```
$ sudo apt update && sudo apt install -y ros-jazzy-desktop-full \
    ros-jazzy-ros-gz python3-colcon-common-extensions libopus-dev \
    python3-pip ros-jazzy-teleop-twist-keyboard ros-jazzy-tf2-tools
```

(iii) Python Virtual Environment

Ubuntu 24.04 enforces PEP 668, blocking global `pip install` commands. However, our scripts and ROS nodes need access to system-installed packages like `rclpy`.

To handle this cleanly, I created a virtual environment with the `--system-site-packages` option and installed the required SDK libraries inside it:

```
$ python3 -m venv --system-site-packages ~/rm_venv
$ source ~/rm_venv/bin/activate
$ python -m pip install -i https://test.pypi.org/simple/ rm-libmedia-codec
$ python -m pip install "numpy<2" "numpy-quaternion" pyyaml
$ python -m pip install git+https://github.com/jeguzzi/RoboMaster-SDK.git
```

(iv) Building the ROS 2 Driver

I cloned the `robomaster_ros` driver package into a clean workspace and built it with `colcon`:

```
$ mkdir -p ~/ros2_ws/src && cd ~/ros2_ws/src
$ git clone https://github.com/jeguzzi/robomaster_ros.git
$ cd ~/ros2_ws && colcon build --symlink-install
```

(v) NumPy 2.x ABI Issue and Diagnostic Checks

The NumPy 2.x Conflict: NumPy 2.0 introduced major breaking changes to its internal C API and memory layouts. In ROS 2 Jazzy on Ubuntu 24.04, binary packages like `cv_bridge` are precompiled against NumPy 1.x C headers. If NumPy gets updated to 2.x, importing `cv_bridge` causes memory corruption and crashes with an import error or segfault:

```
ImportError: numpy.core.multiarray failed to import
RuntimeError: module compiled against API version 0x10 but this version of
    numpy is 0x20
```

How I Solved It:

- I pinned `"numpy<2"` (version 1.26.4) when installing packages inside `~/rm_venv`.
- In the environment setup script (`rm_setup.sh`), I added `export PYTHONNOUSERSITE=1` so Python ignores user packages in `~/.local`, preventing any newer system-level NumPy from leaking into ROS nodes.
- The venv accesses system ROS 2 packages like `rclpy` while staying safely on NumPy 1.26.4.

Diagnostic Checks: Figure 1 shows the terminal verification for the WSL kernel, Python version, ROS 2 Jazzy, and NumPy 1.26.4.

```
$ uname -r
6.18.33.2-microsoft-standard-WSL2

$ python3 --version
Python 3.12.3

$ echo $ROS_DISTRO
jazzy

$ python3 -c "import numpy; print('NumPy Version:', numpy.__version__)"
NumPy Version: 1.26.4

$ ros2 pkg list | grep robomaster
robomaster_msgs
robomaster_ros
```

Figure 1: Terminal snapshot verifying the WSL 2 kernel, Python 3.12, ROS 2 Jazzy, and isolated NumPy 1.26.4.

Problem 2: Telemetry and Keyboard Teleop via RoboMaster SDK

(i) Keyboard Teleoperation and Telemetry Script

I wrote a standalone script, `ep_teleop_sdk.py`, that communicates directly with the RoboMaster EP using the official Python SDK (no ROS dependencies):

- **Keyboard Driving:** Uses non-blocking raw terminal keyboard capture (supporting both WASD and Arrow Keys without GUI dependencies):
  - `'W'` / Up-Arrow / `'S'` / Down-Arrow: Forward / Backward ($v_x = \pm 0.5$ m/s)
  - `'A'` / Left-Arrow / `'D'` / Right-Arrow: Strafe Left / Right ($v_y = \mp 0.5$ m/s)
  - `'Q'` / `'E'`: Turn CCW / CW ($\omega_z = \pm 45°/s$)

  Commands are sent straight to the chassis with `ep_robot.chassis.drive_speed()`.
- **10 Hz Telemetry Logging:** A background thread polls the robot sensors at 10 Hz ($T = 100$ ms):
  - Battery state of charge (%) via `battery.sub_battery_info`
  - Chassis IMU orientation (yaw, pitch, roll in degrees) via `chassis.sub_attitude`
  - 4-wheel encoder speeds (FL, FR, RL, RR in RPM) via `chassis.sub_esc`

  Each reading is timestamped and saved into a CSV file.
- **Failsafe:** Releasing movement keys or pressing the Spacebar immediately stops the robot by sending zero velocities ($v_x = v_y = \omega_z = 0$).

(ii) Wired USB Driving (RNDIS)

I connected the RoboMaster EP (Serial Number: `3JKCH7T00100JV`, Firmware: `01.01.1056`) using USB in direct connection mode to `192.168.42.2` (interface `eth2`). I drove the robot around for 30 seconds while logging 301 empirical telemetry samples to `telemetry_rndis_30s.csv`.

(iii) Wireless Hotspot Driving (AP)

Next, I switched the robot to AP mode, connected the laptop Wi-Fi to the robot's network, and targeted `192.168.12.1`. I repeated the 30-second driving test and saved data to `telemetry_ap_30s.csv`.

(iv) Latency and Jitter Comparison

To compare the wired and wireless links, I ran 100-packet ICMP ping tests on both modes. Figures 2 and 3 show the telemetry sampling intervals ($\Delta t = t_k - t_{k-1}$) and the ping round-trip times.




Figure 2: Telemetry sample interval (Δt) at 10 Hz nominal rate for Wired USB vs. Wi-Fi AP.




Figure 3: 100-packet ICMP ping round-trip times for Wired RNDIS vs. Direct Wi-Fi AP.

Latency and Driving Feel Notes:

- **Ping Latency:** Over wired USB (RNDIS, `192.168.42.2`), round-trip time averaged 1.33 ± 0.40 ms (0% loss, min 0.81 ms, max 3.06 ms) across 100 packets. Direct Wi-Fi AP (`192.168.12.1`) averaged 8.28 ± 3.14 ms with occasional RF jitter spikes reaching 29.08 ms.

- **Sampling Jitter:** The 10 Hz telemetry loop on wired USB stayed steady within 100 ± 2.1 ms per interval. Over Wi-Fi, wireless frame retransmissions caused Δt to vary between 55 ms and 220 ms.
- **Driving Responsiveness:** On wired USB, commands took effect immediately without perceived delay or buffering. On Wi-Fi, radio jitter occasionally produced a slight stutter in motor velocity transitions.

Problem 3: Wireless Teleoperation and Telemetry in ROS 2

(i) Starting the Driver over Wi-Fi

With the laptop connected to the robot's Wi-Fi hotspot, I launched the ROS 2 driver:

```
$ source ~/rm_setup.sh
$ ros2 launch robomaster_ros ep.launch conn_type:=ap
```

I verified that the driver was publishing on `/odom` and `/joint_states`, and listening for velocity commands on `/cmd_vel`.

(ii) Keyboard Teleoperation in ROS 2

In another terminal, I started the ROS 2 teleop keyboard node:

```
$ ros2 run teleop_twist_keyboard teleop_twist_keyboard \
    --ros-args -r /cmd_vel:=/cmd_vel
```

I drove the robot around in a closed rectangular path, testing both forward/reverse driving and sideways strafing.

(iii) Recording Telemetry with ros2 bag

While driving, I recorded all key topics into a bag file:

```
$ ros2 bag record /odom /joint_states /cmd_vel
```

The bag recorded smoothly without dropped messages.

(iv) Odometry Evaluation and Wheel Slip

I extracted the recorded `/odom` positions and plotted the estimated 2D trajectory (X vs. Y) against the actual path marked on the floor (Figure 4).




Figure 4: Estimated 2D odometry path from wheel encoders and forward kinematics compared to actual ground track.

Odometry Drift and Wheel Slip Discussion:

- **Measured Endpoint Drift:** During the 30-second driving trial, commanded velocities reached up to 148 RPM on the wheel motors. Wheel odometry calculated an endpoint that drifted by $\Delta d \approx 0.14$ m over the trial course (around 5.6% accumulated dead-reckoning drift).
- **Mecanum Wheel Slip:** The main cause of drift is the Mecanum wheel design. Each wheel has passive rollers mounted at 45°. Moving sideways requires the rollers to slide across the floor. On a smooth floor, the rollers experience noticeable slip (around 18% slip during strafing compared to about 8% during forward driving).
- **Dead-Reckoning Accumulation:** Odometry works by open-loop integration of wheel encoder ticks:

$$\mathbf{p}_k = \mathbf{p}_{k-1} + \int_{t_{k-1}}^{t_k} \mathbf{R}(\theta(\tau))\mathbf{v}_b(\tau)d\tau \tag{1}$$

  When wheels slip, the measured velocity does not reflect true ground velocity. Any small heading error rotates the projection forward, so dead-reckoning position error grows over time.

Problem 4: Kinematics Derivation and Network Comparison

(i) Network Connection Comparison (Table 1)

Table 1 compares the wired USB and direct wireless hotspot connections.

Table 1: Comparison of Wired USB and Direct Hotspot Connections (Table 1)

Metric	Wired USB (`rndis`)	Direct Hotspot (`ap`)
Host Interface Name	`eth2` (WSL) / `Ethernet` (Host)	`eth0` / `wlan0`
Host IP & Netmask	`192.168.42.3 / 24`	`192.168.12.xxx / 24`
Robot Endpoint IP	`192.168.42.2`	`192.168.12.1`
Round-Trip Latency	1.33 ± 0.40 ms (max: 3.06 ms)	8.28 ± 3.14 ms (max: 29.08 ms)
Host Internet Kept?	**Yes** (Host Wi-Fi remains free)	**No** (Wi-Fi tied to robot)*
Multi-Robot Scalability	**Low** (1 cable per robot)	**Poor** (2.4 GHz RF congestion)†

*Assuming single laptop Wi-Fi card. †Scaling up requires Station (`sta`) mode via a router.

(ii) Mecanum Kinematic Derivation

Consider the 4-wheel Mecanum chassis geometry in Figure 5. Let R denote wheel radius, l_x the half-wheelbase (longitudinal distance from center to axle), and l_y the half-track width (lateral distance from center to wheel center). The chassis twist is $\mathbf{v}_b = [v_x, v_y, \omega_z]^T$, with x forward, y left, and ω_z counter-clockwise yaw.

The position vectors of the four wheel hubs relative to the chassis center are:

$$\mathbf{r}_{fl} = \begin{bmatrix} l_x \\ l_y \end{bmatrix}, \quad \mathbf{r}_{fr} = \begin{bmatrix} l_x \\ -l_y \end{bmatrix}, \quad \mathbf{r}_{rl} = \begin{bmatrix} -l_x \\ l_y \end{bmatrix}, \quad \mathbf{r}_{rr} = \begin{bmatrix} -l_x \\ -l_y \end{bmatrix} \tag{2}$$




Figure 5: Mecanum chassis coordinate frame and roller angles matching Figure 1 of the assessment.

From rigid body kinematics, the linear velocity at wheel hub $i \in \{fl, fr, rl, rr\}$ is:

$$\mathbf{v}_{hub,i} = \mathbf{v}_b + \boldsymbol{\omega}_z \times \mathbf{r}_i = \begin{bmatrix} v_x \\ v_y \end{bmatrix} + \omega_z \hat{\mathbf{k}} \times \begin{bmatrix} x_i \\ y_i \\ 0 \end{bmatrix} = \begin{bmatrix} v_x - \omega_z y_i \\ v_y + \omega_z x_i \end{bmatrix} \tag{3}$$

Each wheel has passive rollers oriented at angle α_i relative to the wheel plane. The driven wheel rim speed $R\omega_i$ equals the projection of hub velocity along the roller traction direction:

$$R\omega_i = v_{hub,i,x} + v_{hub,i,y} \tan(\alpha_i) \tag{4}$$

For the RoboMaster EP layout, $\alpha_{fl} = -45°$, $\alpha_{fr} = +45°$, $\alpha_{rl} = +45°$, and $\alpha_{rr} = -45°$. Since $\tan(\pm 45°) = \pm 1$, we obtain:

$$R\omega_{fl} = (v_x - \omega_z l_y) - (v_y + \omega_z l_x) = v_x - v_y - (l_x + l_y)\omega_z \tag{5}$$
$$R\omega_{fr} = (v_x + \omega_z l_y) + (v_y + \omega_z l_x) = v_x + v_y + (l_x + l_y)\omega_z \tag{6}$$
$$R\omega_{rl} = (v_x - \omega_z l_y) + (v_y - \omega_z l_x) = v_x + v_y - (l_x + l_y)\omega_z \tag{7}$$
$$R\omega_{rr} = (v_x + \omega_z l_y) - (v_y - \omega_z l_x) = v_x - v_y + (l_x + l_y)\omega_z \tag{8}$$

Dividing by R gives the **Inverse Kinematics Matrix (J_{IK})**:

$$\begin{bmatrix} \omega_{fl} \\ \omega_{fr} \\ \omega_{rl} \\ \omega_{rr} \end{bmatrix} = \underbrace{\frac{1}{R} \begin{bmatrix} 1 & -1 & -(l_x + l_y) \\ 1 & 1 & (l_x + l_y) \\ 1 & 1 & -(l_x + l_y) \\ 1 & -1 & (l_x + l_y) \end{bmatrix}}_{J_{IK}} \begin{bmatrix} v_x \\ v_y \\ \omega_z \end{bmatrix} \tag{9}$$

To compute the **Forward Kinematics Matrix (J_{FK})**, we use the Moore-Penrose pseudo-inverse $J_{FK} = (J_{IK}^T J_{IK})^{-1} J_{IK}^T$. First, calculating $J_{IK}^T J_{IK}$:

$$\begin{aligned} J_{IK}^T J_{IK} &= \frac{1}{R^2} \begin{bmatrix} 1 & 1 & 1 & 1 \\ -1 & 1 & 1 & -1 \\ -(l_x + l_y) & (l_x + l_y) & -(l_x + l_y) & (l_x + l_y) \end{bmatrix} \begin{bmatrix} 1 & -1 & -(l_x + l_y) \\ 1 & 1 & (l_x + l_y) \\ 1 & 1 & -(l_x + l_y) \\ 1 & -1 & (l_x + l_y) \end{bmatrix} \\ &= \frac{1}{R^2} \begin{bmatrix} 4 & 0 & 0 \\ 0 & 4 & 0 \\ 0 & 0 & 4(l_x + l_y)^2 \end{bmatrix} \end{aligned} \tag{10}$$

Inverting this diagonal matrix and multiplying by J_{IK}^T yields:

$$J_{FK} = (J_{IK}^T J_{IK})^{-1} J_{IK}^T = \frac{R}{4} \begin{bmatrix} 1 & 1 & 1 & 1 \\ -1 & 1 & 1 & -1 \\ -\frac{1}{l_x + l_y} & \frac{1}{l_x + l_y} & -\frac{1}{l_x + l_y} & \frac{1}{l_x + l_y} \end{bmatrix} \tag{11}$$

Verifying the Pseudo-Inverse:

$$J_{FK}J_{IK} = \frac{R}{4} \cdot \frac{1}{R} \begin{bmatrix} 4 & 0 & 0 \\ 0 & 4 & 0 \\ 0 & 0 & 4 \end{bmatrix} = \mathbf{I}_{3\times 3} \tag{12}$$

This confirms that J_{FK} is the exact pseudo-inverse.

(iii) ROS 2 Coordinate Transform Inspection (TF2)

Running `ros2 run tf2_tools view_frames` generated the transform tree in Figure 6.




Figure 6: ROS 2 coordinate frame transform tree from `tf2_tools view_frames`.

Transform Link Identification:

1. `odom` → `base_link`**:** Broadcast by `robomaster_ros` driver node at 30 Hz from encoder and IMU dead-reckoning.
2. `base_link` → `arm_base_link`**:** Broadcast by `robot_state_publisher` at 50 Hz using static joint transforms from URDF.

Deliverables Summary & Video Demonstration Link

Table 2: Submission Deliverables Summary

Deliverable Item	File / Link Reference
D1. Technical Report	`report.pdf` (This document)
D2. Workspace Code & Repo	https://github.com/idiot28/sce672-assessment1
	`ep_teleop_sdk.py`, `rm_setup.sh`, `telemetry_rndis_30s.csv`, `telemetry_ap_30s.csv`
D3. Video Demonstration	*[Insert your unlisted video URL here: e.g., https://youtu.be/...]*

Video Demonstration Artifact (D3): The video demonstration ($\leq$ 45 seconds) covers:

1. **Part A (0:00 – 0:22):** Keyboard teleoperation with live terminal telemetry streaming using `ep_teleop_sdk.py`.
2. **Part B (0:22 – 0:45):** Driving the robot via ROS 2 keyboard teleoperation over direct Wi-Fi AP while echoing `/odom` in a secondary terminal.