

[illegible]

History

Parameter mapping ERICSSON (L12B) - NSN (RL40)

[illegible]

MOC_Name	MO
AdmissionControl	
AdmissionControl	
AdmissionControl	
AdmissionControl	
AdmissionControl	
AdmissionControl	
AdmissionControl	
AdmissionControl	
AirIfLoadProfile	
AirIfLoadProfile	
AirIfLoadProfile	
AirIfLoadProfile	
AirIfLoadProfile	
AirIfLoadProfile	
AnrFunction	
AnrFunction	
AnrFunction	
AnrFunction	
AnrFunction	
AnrFunction	
AnrFunctionEUTran	
AnrFunctionEUTran	
AnrFunctionEUTran	
AnrFunctionEUTran	
Cdma2000FreqBandRelation	
Cdma2000FreqBandRelation	
Cdma2000FreqBandRelation	
DataRadioBearer	

DataRadioBearer	
DataRadioBearer	
DataRadioBearer	

[illegible]

[illegible]

[illegible]

EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	

EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
GeranFreqGroupRelation	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	

[illegible]

[illegible]

EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellFDD	
EUtranCellRelation	
EUtranCellRelation	
EUtranCellRelation	

EUtranCellRelation	
EUtranCellRelation	
EUtranCellRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	

EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
EUtranFreqRelation	
LogicalChannelGroup	
MACConfiguration	
MACConfiguration	
MACConfiguration	
MACConfiguration	
Paging	
Paging	

Paging	
Paging	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
PmEventService	
QciProfilePredefined	QciProfilePredefined=qci1
QciProfilePredefined	QciProfilePredefined=qci2
QciProfilePredefined	QciProfilePredefined=qci5
QciProfilePredefined	QciProfilePredefinedId=default
QciProfilePredefined	QciProfilePredefinedId=qci4
QciProfilePredefined	QciProfilePredefinedId=qci5
QciProfilePredefined	QciProfilePredefinedId=qci6
QciProfilePredefined	QciProfilePredefinedId=qci8
QciProfilePredefined	QciProfilePredefinedId=qci9
QciProfilePredefined	
QciProfilePredefined	
QciProfilePredefined	
RbsConfiguration	
RbsConfiguration	
Rcs	
ReportConfigA1Prim	
ReportConfigA1Prim	
ReportConfigA1Prim	

[illegible]

ReportConfigB2Geran	
ReportConfigB2Geran	
ReportConfigB2Geran	
ReportConfigB2Geran	
ReportConfigB2Geran	
ReportConfigB2Geran	

ReportConfigB2Utra	
ReportConfigB2Utra	
ReportConfigB2Utra	
ReportConfigB2Utra	
ReportConfigB2Utra	
ReportConfigB2Utra	
ReportConfigB2Utra	

ReportConfigB2Utra

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovPrim

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

ReportConfigEUtraBadCovSec

[illegible]

[illegible]

[illegible]

UeMeasControl	
UeMeasControl	
UeMeasControl	
UeMeasControl	
UeMeasControl	
UtranFreqRelation	
UtranFreqRelation	
UtranFreqRelation	
EUtranCellFDD	
EUtranCellFDD	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	
System Constant/Internal	

Ericsson Parameter Details-12B

Parameters Name
dINonGbrRatio
dITransNwBandwidth
emergencyArpLimit
nrOfBearersReserved
nrOfRrcConnectedReserved
paArpOverride
uINonGbrRatio
uITransNwBandwidth
ailgHighPrio
ailgLowPrioModType
dIPrbLoadLevel
noOfOcngPrbSeries
trafficModelPrb_bitRatePerQci
trafficModelPrb_qciDistSinrMedium
anrUesEUtraIntraFMax
anrUesEUtraIntraFMin
cellAddRsrpThresholdEutran
removeNcellTime
removeNenbTime
removeNrelTime
anrIntraFreqState
anrUesEUtraIntraFMax
anrUesEUtraIntraFMin
cellAddRsrpThresholdEutran
cellReselectionPriority
threshXHighHrpd
threshXLowHrpd
dIMaxRetxThreshold

dIPollPDU

tPollRetransmitDI

tPollRetransmitUI

tStatusProhibitDI
tStatusProhibitUI
ulMaxRetxThreshold
ulPollPDU
dITransNwBandwidth
dnsLookupOnTai
dnsLookupTimer
dscpLabel
enodebplmnid_mnclength
nnsfMode

oaMLinkSuperVisionActive
s1RetryTimer
schedulingStrategy
tHODataFwdReordering
timeAndPhaseSynchCritical
ulSchedulerDynamicBWAllocationEnabled
ulTransNwBandwidth
x2IpAddrViaS1Active
x2retryTimerMaxAuto
x2retryTimerStart

acBarringInfo_acBarringFactorForMoData

acBarringInfo_acBarringFactorForMoSignalling

acBarringInfo_acBarringForEmergency

acBarringInfo_acBarringInfoPresent

acBarringInfo_acBarringMoDataPresent

acBarringInfo_acBarringMoSignallingPresent

acBarringInfo_acBarringSpecialAcForMoData

acBarringInfo_acBarringSpecialAcForMoSignalling

acBarringInfo_acBarringTimeForMoData

acBarringInfo_acBarringTimeForMoSignalling
additionalPlmnReservedList
agpsSuplActive
altitude
cellRange
changeNotification_changeNotificationSIB1
changeNotification_changeNotificationSIB2
changeNotification_changeNotificationSIB3
changeNotification_changeNotificationSIB4
changeNotification_changeNotificationSIB5
changeNotification_changeNotificationSIB6
changeNotification_changeNotificationSIB7
changeNotification_changeNotificationSIB8
confidence
configurableFrequencyStart
covTriggerdBAndHoAllowed
dIChannelBandwidth
dIConfigurableFrequencyStart
dIFrequencyAllocationProportion

dlInterferenceManagementActive
drxActive
eutranCellCoverage_posCellBearing
eutranCellCoverage_posCellOpeningAngle
eutranCellCoverage_posCellRadius
frameStartOffset_subFrameOffset
frameStartOffset_symbolOffset
frameStartOffset_timeOffset
idleModeMobilityControlInfoActive
modificationPeriodCoeff
noOfPucchCqiUsers
noOfPucchSrUsers
nrOfSymbolsPdcch
orientMajorAxis
otdoaSuplActive
partOfRadioPower
partOfSectorPower

pMaxServingCell

primaryPlmnReserved

prsConfigIndex

prsPeriod

pucchOverdimensioning

pZeroNominalPucch

pZeroNominalPusch

qRxLevMin

qRxLevMin

qRxLevMinOffset

siPeriodicity_siPeriodicitySI1

siPeriodicity_siPeriodicitySI2

siPeriodicity_siPeriodicitySI3

siPeriodicity_siPeriodicitySI4
siPeriodicity_siPeriodicitySI5
siPeriodicity_siPeriodicitySI6
siPeriodicity_siPeriodicitySI7
siWindowLength
systemInformationBlock3_nCellChangeHigh
systemInformationBlock3_nCellChangeMedium
systemInformationBlock3_qHyst
systemInformationBlock3_qHystSfHigh
systemInformationBlock3_qHystSfMedium

systemInformationBlock3_sIntraSearch
systemInformationBlock3_sNonIntraSearch
systemInformationBlock3_tEvaluation
systemInformationBlock3_threshServingLow
systemInformationBlock3_tHystNormal
systemInformationBlock6_tReselectionUtra
systemInformationBlock6_tReselectionUtraSfHigh
systemInformationBlock6_tReselectionUtraSfMedium
systemInformationBlock7_tReselectionGeran
systemInformationBlock7_tReselectionGeranSfHigh
systemInformationBlock7_tReselectionGeranSfMedium
systemInformationBlock8_searchWindowSizeCdma
systemInformationBlock8_tReselectionCdmaHrpd
systemInformationBlock8_tReselectionCdmaHrpdSfHigh
systemInformationBlock8_tReselectionCdmaHrpdSfMedium
threshServingLow

ulChannelBandwidth
ulConfigurableFrequencyStart
ulFrequencyAllocationProportion
ulInterferenceManagementActive
uncertAltitude
uncertSemiMajor
uncertSemiMinor
cellIndividualOffsetEUTran
coverageIndicator
includeInSystemInformation

isHoAllowed

qOffsetCellEUTran

supportedMobilityRelationType

allowedMeasBandwidth

cellReselectionPriority

connectedModeMobilityPrio

includeInSystemInformation

mobilityAction

pMax

presenceAntennaPort1

qOffsetFreq

qRxLevMin

threshXHigh

threshXLow

tReselectionEutra

tReselectionEutraSfHigh

tReselectionEutraSfMedium

ulMinBitRate

dIMaxHARQTx

tPeriodicBSRTimer

tTimeAlignmentTimer

ulMaxHARQTx

defaultPagingCycle

maxNoOfPagingRecords

nB
pagingDiscardTimer
cellTraceDataLevel
cellTraceFileSize
cellTraceHighPrioReserve
rbsUeTraceEventStreamingPort
streamPortPmUeTrace
totalCellTraceStorageSize
totalEventStorageSize
totalUeTraceStorageSize
ueTraceFileSize
absPrioOverride
absPrioOverride
absPrioOverride
rlcMode
dataFwdPerQciEnabled
dataFwdPerQciEnabled
dataFwdPerQciEnabled
dataFwdPerQciEnabled
dataFwdPerQciEnabled
aqmMode
dataFwdPerQciEnabled
dIMinBitRate
ConfigFaultReason_faultReason
rbsConfigLevel
tInactivityTimer
a1ThresholdRsrpPrim
a1ThresholdRsrqPrim
hysteresisA1Prim

timeToTriggerA1Prim
a1ThresholdRsrpSec
a1ThresholdRsrqSec
hysteresisA1Sec
timeToTriggerA1Sec
a5Threshold1Rsrp
a5Threshold1Rsrq
a5Threshold2Rsrp
a5Threshold2Rsrq
hysteresisA5
timeToTriggerA5
triggerQuantityA5
a5Threshold1RsrpAnrDelta
a5Threshold1RsrqAnrDelta
a5Threshold2RsrpAnrDelta
a5Threshold2RsrqAnrDelta
hysteresisA5
timeToTriggerA5
b2Threshold1Rsrp
b2Threshold1Rsrq
b2Threshold2Cdma2000
hysteresisB2
timeToTriggerB2
triggerQuantityB2

b2Threshold1Rsrp

b2Threshold1Rsrq

b2Threshold2Geran

hysteresisB2

timeToTriggerB2

triggerQuantityB2

b2Threshold1Rsrp
b2Threshold1Rsrq
b2Threshold2EcNoUtra
b2Threshold2RscpUtra
hysteresisB2
timeToTriggerB2
triggerQuantityB2

triggerQuantityUtraB2

a2ThresholdRsrpPrim

a2ThresholdRsrqPrim

hysteresisA2Prim

reportAmountA2Prim

reportIntervalA2Prim

reportQuantityA2Prim

timeToTriggerA2Prim

triggerQuantityA2Prim

a2ThresholdRsrpSec

a2ThresholdRsrqSec

hysteresisA2Sec

reportAmountA2Sec

reportIntervalA2Sec

reportQuantityA2Sec

timeToTriggerA2Sec

triggerQuantityA2Sec

a3offset
hysteresisA3
reportAmountA3
reportIntervalA3
reportQuantityA3
timeToTriggerA3
triggerQuantityA3
a3offsetAnrDelta
hysteresisA3
timeToTriggerA3
a1ThresholdRsrpPm
a1ThresholdRsrqPm
a2ThresholdRsrpPm
a2ThresholdRsrqPm
a3OffsetPm
a3ReportOnLeavePm
a4ThresholdRsrpPm
a4ThresholdRsrqPm
a5ThresholdRsrpPm1
a5ThresholdRsrpPm2
a5ThresholdRsrqPm1
a5ThresholdRsrqPm2
hysteresisPm
maxReportCellsPm
measSelectionEUtraPm
reportAmountPm
reportIntervalPm

reportQuantityPm
timeToTriggerPm
triggerQuantityPm
n310
n311
t300
t301
t302
t304
t310
t311
t320

mixedModeRadio
cipheringAlgorithms
integrityProtectionAlgorithms
rbldSupervisionActive
dlMaxRetxThreshold
ulMaxRetxThreshold
systConstants
a5B2MobilityTimer
badCoverageMeasSelection
bestCellReleaseActive
filterCoefficientEUtraRsrp
filterCoefficientEUtraRsrq
maxMeasCdma2000eHrpd
maxMeasEUtraOther
maxMeasGeran
maxMeasInterFreqEUtra

maxMeasUtraFdd
measQuantityUtraFDD
measurementPriority
sMeasure
ueMeasurementsActive
threshXHigh
threshXLow
qRxLevMin
noOfTxAntennas
noOfRxAntennas
maxHarqMsg3Tx
maxNrOfRaPreambles
raResponseWindowSize
preambleTransMax
macContentionResolutionTimer
powerRampingStep
preambleInitialReceivedTargetPower
deltaPreambleMsg3

Baseline_Value
500
1000
7
0
0
7
500
1000
2 (NO_HIGH_PRIO_LOAD)
0 (QPSK_MOD_SCH)
0
1
0 0 0 0 0 0 0 0
100 0 0 0 0 0 0 0
2
0
-950(-95dB)
5
1
5
2
0
-950
0
20
20
8

16

50

50

25
25
8
16
1000
1 (ON)
0
24
2
1 (RPLMN_IF_SAME_AS_SPLMN)

1
30
1 (ROUND_ROBIN)
100
0
1
1000
1
1440
30

95
95
0
0
0
0
false false false false false
false false false false false
64

64
false false false false false
0
0
15
0
0
0
0
0
0
0
0
0
100
0
1
10000
0
100

1
1
0
1200
15000
0
0
0
0
2
120
120
1
0
0
100
100

1000
0
-1
3 (PP1280)
0
-103
-96
-120
-115
1000 (0dB)
8
16
32

64
64
64
10
10
5
4
-4
-4

62
16
30
0
30
2
100 (1)
100 (1)
2
100 (1)
100 (1)
10
2
100 (1)
100(1)
0

	10000
	0
	100
	1
	0
	0
	0
	0
	0 (NONE)
	1

1
0
1 (HANDOVER_AND_CELL_RESELECTION)
6
6
7
1
1 (HANDOVER)

1000
1
0
-120
4
0
1
50 (0.5)
50 (0.5)
0
4
5
0
4
256
3

2 (T)
3
1
1000
0
51543
51543
80000
100000
16000
1000
1 (HI_PRIO_OVERRIDE)
1 (HI_PRIO_OVERRIDE)
1 (HI_PRIO_OVERRIDE)
0 (AM)
1
1
1
1
1
1 (MODE1)
1
0
10
0 (UNDEFINED)
10
-136
-192
10(1dB)

640
-136
-192
10(1dB)
640
-140
-195
-136
-192
10(1dB)
640
0 (RSRP)
1
10
1
10
10(1dB)
640
-140
-195
-15
10(1dB)
640
0 (RSRP)

-140

-195

-110

10(1dB)

640

0 (RSRP)

-140

-195

-240 (-24dB)

-115

10(1dB)

640

0 (RSRP)

0 (RSCP)

-118

-195

20(2dB)

0

2 (MS_480)

1 (BOTH)

640

0 (RSRP)

-118

-195

20(2dB)

0

2 (MS_480)

1 (BOTH)

640

0 (RSRP)

30 (3dB)
0
0
2 (MS_480)
1 (BOTH)
320
0 (RSRP)
0
0
640
-140
-195
-140
-195
5 (0.5dB)
0
-140
-195
-140
-140
-195
-195
10(1dB)
4
0 (PERIODICAL)
0
2 (MS_480)

1 (BOTH)
640
0 (RSRP)
20
1
1000
400
5
1000
2000
3000
30

0
6 (EEA1_EEA2)
5 (EIA1_EIA2)
0
8
8
110:-108
0
2 (BOTH)
0
4
11
5
5
5
7

5
0 (RSCP)
0 (ANR_PRIO)
0 (disabled)
0
4
0
-119
0 or 2
0 or 2
4
64
4
10(Hard Constant)
6(mapped to 48)-SC:111
4(Hard Constant)
-110(System Constant)
6

NSN Parameter Details - RL 40

[illegible]

pollPdu

64

tPollRetr

120ms

tPollRetr

120ms

tProhib	50ms
tProhib	50ms
drbAmMxRtxTh	16
pollPdu	64
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
mncLength	3
Not available	Not available

linkOAMEnabled	0
Not available	Not available
dlsFdAlg	PFsch
Not available	Not available
btsSyncMode	FreqSync (0)
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available

ocAcProbFac	95%
sigAcProbFac	95%
eCallAcBarred	2 (Not Barred)
Not available	Not available
acBarOc	
acBarSig	
ocAcBarAC	0
sigAcBarAC	0
ocAcBarTime	4 (64)

sigAcBarTime	4 (64)
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
dIChBw	
Not available	Not available
Not available	Not available

Not available	Not available
actDrx	1
antBearing	
antBeamwidth	
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
modPeriodCoeff	2 (0)
Not available	Not available
Not available	Not available
maxNrSymPdcch	3
Not available	Not available
actOtdoa	0 (FALSE)
Not available	Not available
Not available	Not available

pMaxOwnCell	23
primPlmnCellres	

prsConfigurationIndex

151 (151)

Not available	Not available
Not available	Not available
p0NomPucch	-116
p0NomPusch	-80
qrxlevmin	-130
qRxLevMinGer	-105 dBm
qRxLevMinOffset	2
Not available	Not available
siMessagePeriodicity	
siMessagePeriodicity	

siMessagePeriodicity	
siMessagePeriodicity	
siMessagePeriodicity	
siMessagePeriodicity	
siWindowLen	10 ms
nCellChgHigh	
nCellChgMed	
qHyst	2dB (2)
qHystSfHigh	-
qHystSfMed	-

sIntrasearch	46
sNonIntrsearch	8
tEvaluation	-
threshSrvLow	4
tHystNormal	-
tResUtra	1
utrResTiFHM	0.5 (1)
utrResTiFMM	0.5 (1)
tResGer	1
gerResTiFHM	0.5(1)
gerResTiFMM	0.5(1)
searchWinSize	16 (NOTUSED)
tResHrpd	-
hrpResTiFHM	NOT USED
hrpResTiFMM	NOT USED
threshSrvLow	4

ulChBw	
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
cellIndOffNeigh	15 (0 dB)
Not available	Not available
Not available	Not available

handoverAllowed	0 (Allowed)
qOffsetCell	15 (0)
Not available	Not available
measBdw	
eutCelResPrio	
Not available	Not available
Not available	Not available
Not available	Not available

pMaxOwnCell	23
intraPresAntP	1
qOffFrq	0 dB (15)
grxlevmin	-124 dBm
interFrqThrH	
interFrqThrL	
tReselEutr	1
celResTiFHM	
celResTiFMM	
Not available	Not available
harqMaxTrDI	4
tPeriodicBsr	20ms (3)
taTimer	10240 (6)
harqMaxTrUI	5
defPagCyc	128rf (2)
Not available	Not available

pagingNb	quarterT
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
rlcMode	RLC_AM (0)
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
minBitrateDI	30
Not available	Not available
Not available	Not available
inactivityTimer	10
threshold2a	98 (not Used)
Not available	
hysThreshold2a	4 (2dB)

[illegible]

b2Threshold1GERAN	20 (-120 dbm)
Not available	Not available
b2Threshold2RssiGERAN	15 (-95 dbm)
hysB2ThresholdGERAN	1 (2dB)
b2TimeToTriggerGERANMeas	10 (512ms)
Not available	Not available

b2Threshold1Utra	23 (-117 dbm)
Not available	Not available
b2Threshold2UtraEcn0	19 (-14.5)
b2Threshold2UtraRscp	0 (-115 dbm)
hysB2ThresholdUtra	1 (2 dB)
b2TimeToTriggerUtraMeas	8 (320ms)
Not available	Not available

measQuantityUtra	0 (CPICH RSCP)
1) threshold2Wcdma 2) threshold2GERAN 3) threshold2InterFreq	1) 98 (Not used) 2) 32 3) 98 (Not Used)
Not available	Not available
1) hysThreshold2Wcdma 2) hysThreshold2GERAN 3) hysThreshold2InterFreq	1) 0 2) 0 3) 0
Not available	Not available
Not available	Not available
Not available	Not available
1) a2TimeToTriggerActWcdmaMeas 2) a2TimeToTriggerActGERANMeas 3) a2TimeToTriggerActInterFreqMeas	1) Not used (16) 2) NotUsed (16) 3) Not Used (16)
Not available	Not available
threshold4	1 (-139 dbm)
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
a2TimeToTriggerRedirect	7 (256 ms)
Not available	Not available

[illegible]

Not available	Not available
Not available	Not available
Not available	Not available
n310	n10 (6)
n311	n1 (0)
t300	200ms (1)
t301	200ms (1)
t302	8000 ms
t304	1000ms (5)
t310	2000ms (6)
t311	3000ms (1)
t320	180min (180)

rfSharingEnabled	0
eea0, eea1, eea2	1, 8, 9
ela0, ela1, ela2	0, 9, 9
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available
filterCoefficientRSRP	fc4 (4)
filterCoefficientRSRQ	fc4 (4)
Not available	Not available
Not available	Not available
Not available	Not available
Not available	Not available

Not available	Not available
measQuantityUtra	cpichRSCP (0)
Not available	Not available
threshold1	90
Not available	Not available
utraFrqThrH	4
utraFrqThrL	0
qRxLevMinUtra	-115
numOfTxPorts	2 (1)
Not available	Not available
harqMaxMsg3	5
raNondedPreamb	40 (9)
raRespWinSize	10 (7)
preambTxMax	10 (6)
raContResoT	32ms (3)
prachPwrRamp	2dB (1)
ulpcIniPrePwr	-104 dBm (8)
deltaPreMsg3	1

Parameter Description
Absolute priority of the Bandclass of CDMA2000 HRPD Absolute priority (0 means: lowest priority). Equal priorities between RATs are not supported according to [3GPP 36.304].
High threshold towards this Bandclass of CDMA2000 HRPD This specifies the high threshold used in reselection towards CDMA2000 HRPD
Low threshold towards this Bandclass of CDMA2000 HRPD This specifies the low threshold used in reselection towards CDMA2000 HRPD
This parameter is used by the transmitting side of each AM RLC entity to count the number of transmissions of an AMD PDU. This parameter is set so that a radio link failure can be detected by the eNB before the maximum number of transmissions has been reached. This parameter is only used in the DRB configuration. This parameter is on a higher level than ARQ and HARQ. This parameter is vendor-specific.

This parameter specifies the parameter pollPDU of [36.331]
The parameter Poll PDU defines the number of RLC PDUs that are sent on a logical channel before the RLC polling bit is set.

This parameter specifies the parameter t-pollRetransmit of [36.331]
This timer is used by the transmitting side of an AM RLC entity in order to retransmit a poll.
The used minimum value of the timer shall be larger than the calculated round-trip time with considerations of HARQ retransmissions and out-of-sequence arrival. The value of the timer shall be larger than twice of the timerReorder.

This parameter specifies the parameter t-pollRetransmit of [36.331]
This timer is used by the transmitting side of an AM RLC entity in order to retransmit a poll.
The used minimum value of the timer shall be larger than the calculated round-trip time with considerations of HARQ retransmissions and out-of-sequence arrival. The value of the timer shall be larger than twice of the timerReorder.

This parameter specifies the parameter t-StatusProhibit of [36.331]
This timer is used by the receiving side of an AM RLC entity in order to prohibit transmission of a STATUS PDU

This parameter specifies the parameter t-StatusProhibit of [36.331]
This timer is used by the receiving side of an AM RLC entity in order to prohibit transmission of a STATUS PDU

This parameter is used by the transmitting side of each AM RLC entity to count the number of transmissions of an AMD PDU. This parameter is set so that a radio link failure can be detected by the eNB before the maximum number of transmissions has been reached. This parameter is only used in the DRB configuration. This parameter is on a higher level than ARQ and HARQ. This parameter is vendor-specific.

This parameter specifies the parameter pollPDU of [36.331]
The parameter Poll PDU defines the number of RLC PDUs that are sent on a logical channel before the RLC polling bit is set.

Replaced by AdmissionControl::dlTransNwBandwidth. Since L11B

This parameter determines the range of the primary MNC of the eNB.

Enables the Link OAM functionality for this ethernet link. In consequence:

- the values of all statistics counters of the Link OAM feature for this interface are set to 0
- the Link OAM alarms for this interface are cleared
- the Link OAM discovery process is started, either in active or in passive mode.

Parameter to choose between different available algorithms for frequency domain scheduling.
Available algorithms are
TTA: fair allocation property based on ratio of relative to wideband channel quality
PFsch: proportional fair allocation property based on ratio of immediate to average scheduled channel quality

With this parameter the the synchronization mode of the eNB can be selected.
LTE systems supporting MBSFN or co-operate with CDMA 2000 system require a tight timing on air interface transmission synchronization. In all those cases phase synchronization should be selected.
For LTE systems which do not require such accurate phase synchronization, the 50ppb frequency accuracy is achieved via normal frequency synchronization. For those that value should be set.
If phase synchronization is selected, only synchronization reference sources which are capable to accuracy needed by phase synchronization shall be selected. To meet a relative phase accuracy BTS can not come up without GPS connection existence and operation.

Replaced by AdmissionControl::ulTransNwBandwidth. Since L11B.

The access probability factor defines the probability for a UE to establish an RRC connection.

The UE draws a random number ($0 = \text{rand} < 1$). If rand is higher than the value indicated by the access probability factor, the UE considers the access barring check to be unsuccessful.

The access probability factor defines the probability for a UE to establish an RRC connection.

The UE draws a random number ($0 = \text{rand} < 1$). If rand is higher than the value indicated by the access probability factor, the UE considers the access barring check to be unsuccessful.

Access Class barring for AC 10.

The access barred for emergency calls flag indicates that access is barred for emergency calls in this cell.

Access class barring for originating calls.

Access barring for signaling.

Access class barring list (5 bit) for originating calls for AC 11-15 (leftmost bit is for AC 11, the second bit in the list is for AC 12, and so on...).

The default is no access class barred.

Access class barring list (5 bit) for signaling for AC 11-15 (leftmost bit is for AC 11, the second bit in the list is for AC 12, and so on...).

The default is no access class barred.

The access class barring time defines the time that the access barring check remains unsuccessful while the UE is not performing an emergency call. In this case, the UE starts timer T303 using this parameter. Timer value in minutes.

The access class barring time defines the time that the access barring check remains unsuccessful while the UE is not performing an emergency call. In this case, the UE starts timer T303 using this parameter. Timer value in minutes.

maxNumOfCce depends on dlChBw parameter:

- if dlChBw is 5MHz then maxNumOfCce is 21
- if dlChBw is 10MHz then maxNumOfCce is 43
- if dlChBw is 15MHz then maxNumOfCce is 65
- if dlChBw is 20MHz then maxNumOfCce is 87

All the rest of the parameters in formula are O&M parameters, and MaxPucchResourceSize has a maximum allowed value, which shall not be exceeded

Maximum 10 MHz downlink channel bandwidth may be used with a single FSMD to configure more than 2 cells or with a single FSME to configure more than 3 cells.

Parameter to activate or deactivate the DRX feature in a cell.
Note for the case where periodic subband CQI reporting (periodicCqiFeedbackType) is enabled together with DRX functionality: It may not be possible to synchronize DRX start offset such that the wideband CQI report is received during the DRX OnDuration (due to periodicities) and that may cause small performance degradation in DL whenever fresh wideband channel quality information cannot be get in time. It is up to an operator whether to prevent activation of periodic subband CQI reporting and DRX in parallel because of this restriction.

Antenna Bearing

The antenna beamwidth for the band. Some RET types may automatically update the beamwidth information based on the configuration data downloaded into the RET device. Some devices may also restrict overwriting the field.

The parameter defines the length of the modification period.
 $\text{Modification period} = \text{modificationPeriodCoeff} * \text{defaultPagingCycle} / 10 \text{ ms.}$
Modification period is equal or lower than 1024.
(n2 corresponds to value 2, n4 corresponds to value 4 and n8 corresponds to value 8.)

The parameter defines how many OFDM symbols can be used for PDCCH channel transmission. eNB selects based on usage the actual value for each TTI, which and value is signaled to the UEs in PCFICH.

Activates the transmission of PRS signals according to the PRS configuration

The IE P-Max is used to limit the UE's uplink transmission power on a carrier frequency; it is also used to calculate the parameter P-compensation defined in TS 36.304 .

Corresponds to parameter PEMAX in TS 36.101.

The UE transmit power should not exceed the minimum of this value (in dBm), if provided, and the maximum UE power for the UE power class, PUMAX, as specified in TS 36.101.

Indicates if the cell/PLMN combination is reserved for operator use. Cells reserved for operator use are treated as barred by 'normal' UEs without a USIM with AC 11 or 15 inserted. UEs with AC 11 or 15 USIM inserted are specific operator UEs and thus allowed to camp on and access such cells. The default value is not reserved.

151-157: 160ms period

471-477: 320ms period

1111-1117: 640ms period

2391-2397: 1280ms period

The periodicity and offset can be computed according to 3GPP TS 36.211

This parameter defines the cell specific nominal power to be used for PUCCH power calculation in UE uplink power control equation (P2), for controlling mean received SNR for control data.

This parameter defines the cell specific nominal power for the PUSCH. Used for P_{0_PUSCH} calculation in UE uplink power control equation (P1) for controlling the mean received SNR for user data during (re)transmission corresponding to a received PDCCH with DCI format 0 associated with a new packet transmission. This parameter is used to control mean received SNR for user data.

Specifies the minimum required RX RSRP level in the cell.
($Q_{rxlevmin}$ in 36.304)

This specifies the minimum required RX level in the cell in dBm
Affects the minimum required RX level in the cell.

Defines the common System Information scheduling window. The parameter SI Window Length defines the common System Information scheduling window for all SIs.
The parameter defines the number of cell changes to enter the high mobility state. For the idle mode, it corresponds to NCR_H in TS 36.304.
The parameter defines the number of cell changes to enter the medium mobility state. For idle mode, it corresponds to NCR_M in TS 36.304.
The Qhyst parameter provides the hysteresis value in dB for ranking criteria in the cell reselection procedure. The parameter is used to minimize pingpong.
The parameter defines an additional hysteresis value to be applied in the high mobility state to the cell reselection procedure hysteresis value (q-Hyst). Value db-6 corresponds to -6dB, db-4 corresponds to -4dB and so on.
The parameter defines an additional hysteresis value to be applied in the medium mobility state to the cell reselection procedure hysteresis value (q-Hyst). Value db-6 corresponds to -6dB, db-4 corresponds to -4dB and so on.

The Sintrasearch parameter defines the threshold (in dB) for intra-frequency measurements. The UE can omit measurements of intra-frequency neighbor cells if the serving cell is above a certain threshold.
The sNonintrsearch parameter defines the threshold (in dB) for inter-RAT and inter-frequency measurements.
Timer TCRmax defines the duration for evaluating the criteria to enter mobility states. For idle mode, it corresponds to TCRmax in TS 36.304.
Specifies the threshold for the serving frequency used in reselection evaluation towards lower priority EUTRAN frequency or RAT.
Timer TCRmaxHyst defines the additional duration for evaluating the criteria to enter normal mobility state. For idle mode, it corresponds to TCRmaxHyst in TS 36.304.
UTRA cell reselection timer
The field t-ReselectionUTRA is multiplied by this factor if the UE is in the high mobility state as defined in 36.304.
The field t-ReselectionUTRA is multiplied by this factor if the UE is in the medium mobility state as defined in 36.304.
GERAN cell reselection timer
The field t-ReselectionGERAN is multiplied with this factor if the UE is in the high mobility state as defined in 36.304
The field t-ReselectionGERAN is multiplied with this factor if the UE is in the medium mobility state as defined in 36.304.
The search window size is a CDMA parameter to be used to assist in searching for the neighboring pilots
CDMA2000 HRPD Cell Reselection Timer
CDMA2000 HRPD Cell Reselection Timer factor if the UE is in High Mobility state. The field tResHrpd is multiplied with this factor if the UE is in High Mobility state as defined in 36.304
CDMA2000 HRPD Cell Reselection Timer factor if the UE is in Medium Mobility state. The field tResHrpd is multiplied with this factor if the UE is in Medium Mobility state as defined in 36.304.
Specifies the threshold for the serving frequency used in reselection evaluation towards lower priority EUTRAN frequency or RAT.

Uplink channel bandwidth defines the UL bandwidth for the eNode-B transmission in a cell. Maximum 10 MHz uplink channel bandwidth may be used with single FSMD to configure more than 2 cells or with single FSME to configure more than 3 cells.

Uplink channel bandwidth defines the UL bandwidth for the eNB transmission in a cell, and also defines the number of available Physical Resource Blocks. The uplink channel bandwidth mapping to number of Physical Resource Blocks is:

5.0 MHz = 25 UL PRBS

10.0 MHz = 50 UL PRBS

15.0 MHz = 75 UL PRBS

20.0 MHz = 100 UL PRBS Maximum 10 MHz uplink channel bandwidth may be used with single FSMD to configure more than 2 cells or with single FSME to configure more than 3 cells.

Cell Individual Offset (CIO) of Neighbor cells for insertion into the CIO Cell List of EUTRA Serving or Neighbor Carrier Measurement Object.

All CIOs different from zero will be considered by eNB for Measurement Configuration (up to a limit of 32 CIOs per carrier frequency).

If this parameter is modified, the LNREL parameter cellIndOffNeighDelta is implicitly set to 0.

The parameter controls handover blacklisting. The instance of LNREL and the related cell relationship, defined by ECGI, identifies the specific cell to cell relation. The parameter allows HO for this neighbor relation, only S1 HO or no HO at all. The blacklisting applies in addition to blacklisting via the LNCEL parameter blacklistHoL. The meaning is as follows: 'allowed' means that any S1 or X2 outgoing handover is allowed. 'onlyS1' means that outgoing handover via S1 is allowed but not via X2. 'forbidden' means that no outgoing S1 or X2 handover is triggered.
The parameter defines a cell-specific offset (in dB) that is used in the cell reselection procedure.
The IE AllowedMeasBandwidth is used to indicate the maximum allowed measurement bandwidth common for all neighbouring cells on a carrier frequency. The values mbw6, mbw15, mbw25, mbw50, mbw75, mbw100 indicate 6, 15, 25, 50, 75 and 100 resource blocks respectively.
Absolute priority of the EUTRA carrier frequency Equal priorities between RATs are not supported according to [3GPP 36.304].

The IE P-Max is used to limit the UE's uplink transmission power on a carrier frequency; it is also used to calculate the parameter P-compensation defined in TS 36.304 . Corresponds to parameter PEMAX in TS 36.101. The UE transmit power should not exceed the minimum of this value (in dBm), if provided, and the maximum UE power for the UE power class, PUMAX, as specified in TS 36.101.
Indicates whether all the neighboring cells use Antenna Port 1. When set to TRUE, the UE may assume that at least two cell-specific antenna ports are used in all neighboring cells.
Frequency-specific offset for equal priority E-UTRAN frequencies.
Specifies the minimum required RX RSRP level in the cell. (Qrxlevmin in 36.304)
This specifies the threshold used by the UE when reselecting towards a higher priority frequency X than the currently serving frequency
This specifies the threshold used in reselection towards frequency X priority from a higher priority frequency
The Treselection parameter defines the cell reselection timer value. It allows averaging of the target cell quality before cell reselection is performed.
The cell reselection timer (t-ReselectionEUTRAN) is multiplied by this factor if the UE is in the medium high mobility state.
The cell reselection timer (t-ReselectionEUTRAN) is multiplied by this factor if the UE is in the medium mobility state.
Indicates the maximum number of HARQ transmissions in DL that is configured for each UE at initial access to a specific cell.
Time period of the periodic Buffer Status Report for the reporting of the UE transmission buffer utilization. Further information to the O&M parameter can be found in [SFS-BM].
Determines the number of subframes after which a UE assumes it is out-of-sync in UL if no Time Alignment command was received.
Indicates the maximum number of HARQ transmissions in UL that is configured for each UE at initial access to a specific cell.
The default paging cycle defines the cell-specific paging DRX cycle duration. It also determines the maximum paging DRX duration applicable in the cell. Referred to as ' T ' in TS 36.304. Value rf32 corresponds to 32 radio frames, rf64 corresponds to 64 radio frames and so on.

Paging nB defines the number of possible paging occasions per radio frame, i.e. the density of paging occasions. This parameter is used to calculate the number of paging occasions within one paging DRX duration, which in turn is used to calculate the paging occasion.

Minimum bit rate that shall be granted in DL TTI.

The parameter defines the time period for the indication of the UE inactivity in both DL and UL directions.

Threshold for RSRP of serving cell for stopping of Inter-RAT (InterFreq) Measurements

Threshold for RSRP of serving cell. If Inter-RAT (InterFreq) measurements are active and value exceeds Th2a (event A1) then Inter-RAT measurements are stopped. $Th2_XXX \leq Th2a$ for $XXX = \text{InterFreq, WCDMA, GSM}$

Related Hysteresis of Threshold for RSRP of serving cell for stopping of Inter-RAT (InterFreq) Measurements
Parameter is used within the entry and leave condition of the A1 triggered reporting condition. The IE value is multiplied by 2.

Time to trigger deactivation of all measurements
Duration for which the event A1 must be valid, such that Inter-Frequency/Inter-RAT measurements are deactivated

Threshold for RSRP of serving cell. If RSRP of serving cell is lower than threshold3 and RSRP of neighbor cell is greater than threshold3a, a handover is triggered.

Threshold for RSRP of intra-frequency neighbor cell. If RSRP of serving cell is lower than threshold3 and RSRP of neighbor cell is greater than threshold3a, a handover is triggered.

Related hysteresis of thresholds th3 and th3a for RSRP

Time for which the specific criteria for the measurement event A5 must be met in order to trigger a measurement report. Value definitions as stated in 3GPP TS36.331: value MS0 corresponds to 0 ms, MS40 to 40 ms and so on.

Threshold for RSRP of serving cell. If RSRP of serving value < b2Threshold1GERAN and RSRP of GERAN neighbour cell > b2Threshold2GERAN then handover is triggered (B2 event)

Receive level threshold for serving cell in B2 event. Used in measurement event type B2 where the event is triggered if the serving cell becomes worse than b2Threshold1GERAN AND the GERAN neighbour cell becomes better than b2Threshold2GERAN.
Set in ReportConfigInterRAT for GERAN

Threshold for RSSI of GERAN neighbour cell. If RSRP of serving value < b2Threshold1 and RSSI of GERAN neighbour cell > b2Threshold2GERAN then handover is triggered (B2 event).

Receive level threshold for GERAN neighbour cell in B2 event. Used in measurement event type B2 where the event is triggered if the serving cell becomes worse than b2Threshold1 AND the GERAN neighbour cell becomes better than b2Threshold2RssiGERAN.
Set in ReportConfigInterRAT for GERAN.
Note: The mapping for RSRP based GERAN thresholds is different from the one defined in 3GPP TS 36.133 and are defined in TS 45.008

Related Hysteresis of Handover Margin for HO to GERAN
Parameter is used within the entry and leaves condition of the B2 triggered reporting condition. The IE value is multiplied by 2.

Duration for which the RSRP based event B2 must be valid
Time for which the specific criteria for the RSRP based measurement event B2 must be met in order to trigger a measurement report.

Threshold for RSRP of serving cell. If RSRP of serving value < b2Threshold1Utra and RSCP or EcN of WCDMA neighbour cell > b2Threshold2Utra < EcNo, Rscp > then handover is triggered (B2 event)
Receive level threshold for serving cell in B2 event. Used in measurement event type B2 where the event is triggered if the serving cell becomes worse than b2Threshold1Utra AND the WCDMA neighbour cell becomes better than b2Threshold2Utra < EcNo, Rscp > (dep. measQuantityUtra).
Set in ReportConfigInterRAT for WCDMA

Threshold for UTRA neighbour cell on the current frequency, such that it is considered to be good and reported in the measurement result of B2 event. Applicable only if measQuantityUTRA-FDD=cpich-EcN0. cpich-EcN0 corresponds to CPICH_Ec/No in TS 25.133 for FDD.
Set in ReportConfigInterRAT for WCDMA.
Parameter is optional depending on measQuantityUtra.

Threshold for UTRA neighbour cell on the current frequency, such that it is considered to be good and reported in the measurement result of B2 event. Applicable only if measQuantityUTRA-FDD=cpich-RSCP. cpich-RSCP corresponds to CPICH_RSCP in TS 25.133 for FDD.
Set in ReportConfigInterRAT for WCDMA.
Parameter is optional depending on measQuantityUtra.

Related Hysteresis of Handover Margin for HO to WCDMA. Parameter is used within the entry and leave condition of the B2 triggered reporting condition. The IE value is multiplied by 2.

Duration for which the RSRP based event B2 must be valid. Time for which the specific criteria for the RSRP based measurement event B2 must be met in order to trigger a measurement report.

Defines which quantity to use for Event B2 measurements towards this frequency set in QuantityConfigUTRA

The quantities used to evaluate the triggering condition for the event.
cpich-RSCP corresponds to CPICH_RSCP in TS 25.133 for FDD.
cpich-EcN0 corresponds to CPICH_Ec/No in TS 25.133 for FDD.
This parameter refers to event B2 for HO to WCDMA.

Threshold for RSRP of serving cell for start of WCDMA /GERAN/ INTERFREQ Measurements

Threshold for RSRP of serving cell. If the value is below threshold2WCDMA /GERAN/ INTERFREQ (event A2) , WCDMA /GERAN/ INTERFREQ measurements are started.

Related Hysteresis of Threshold for RSRP of serving cell for start of WCDMA/GERAN /INTERFREQ measurements

Parameter is used within the entry and leave condition of the A2 triggered reporting condition. The IE value is multiplied by 2.

Time to trigger activation of GERAN / WCDMA / INTERFREQ measurements
Duration for which the event A2 must be valid, such that GSM / WCDMA / INTERFREQ measurements are activated

Threshold for RSRP of intra-frequency neighbor cell cell. If RSRP of serving value < Th4 then re-direct is triggered.

Handover margin for better cell HO. Used in measurement event type A3 where the event is triggered when the neighbor cell becomes better than the serving cell by the value of the A3 offset.

Related Hysteresis of Handover Margin for Better Cell Handover of Intra-Frequency
Parameter is used within the entry and leave condition of the A3 triggered reporting condition. The IE value is multiplied by 2.

This parameter defines the interval with which measurement reports are repeatedly sent as long as the specific criteria for the measurement event A3 are met. Value definitions as stated in 3GPP TS36.331: value MS120 corresponds to 120 ms, MS240 to 240 ms and so on, while value MIN1 corresponds to 1 min, MIN6 to 6 min and so on.

Time for which the specific criteria for the measurement event A3 must be met in order to trigger a measurement report. Value definitions as stated in 3GPP TS36.331: value MS0 corresponds to 0 ms, MS40 to 40 ms and so on.

This is the maximum number of consecutive "out of sync" indications received from lower layers. n1 corresponds to 1 and so on.
Maximum number of consecutive "in-sync" indications received from lower layers. n1 corresponds to 1 and so on.
Timer T300 supervises the RRC connection establishment procedure. Start: Transmission of RRCConnectionRequest Stop: Reception of RRCConnectionSetup or RRCConnectionReject message, cell re-selection and upon abortion of connection establishment by upper layers At expiry: Perform the actions as specified in 36.331, 5.3.3.6
Timer T301 supervises the RRC connection re-establishment procedure. Start: Transmission of RRCConnectionReestablishmentRequest Stop: Reception of RRCConnectionReestablishment or RRCConnectionReestablishmentReject message as well as when the selected cell becomes unsuitable At expiry: Go to RRC_IDLE
eNB sends this parameter to the UE in the message RRC CONNECTION REJECT. The UE will consider access to the cell as barred for the time specified by t302.
Timer T304 supervises the successful completion of a handover or cell change.
Timer T310 supervises the recovery from physical layer problems.
Timer T311 supervises the RRC connection re-establishment.
T320 defines the validity time of dedicated priorities defined in IdleModeMobilityControlInfo.

This parameter enables the RF sharing with GSM in LTE BTS.

Parameter is used only for automatic licence activation and in addition this parameter is used for shared RF modules IP address configuration.

This means that the Multi Carrier Power Amplifiers (MCPA) transmitting both GSM/EDGE RF and LTE RF carrier signals at the same 3GPP frequency band.

When operating in RF sharing mode, a single RF Module is connected to 2 System Modules simultaneously.

Flexi EDGE System Module is operating in GSM/EDGE SW mode and Flexi Multimode System Module in LTE SW mode. Both are connected to the one and same Flexi Multiradio RF Module.

The ciphering algorithm supported by the eNB.

- EEA0: NULL.
- EEA1: SNOW 3G.
- EEA2: AES.

The integrity protection algorithm supported by the eNB.

- EIA0: NULL.
- EIA1: SNOW 3G.
- EIA2: AES.

Specifies the filtering coefficient used for RSRP (to be set in QuantityConfigEUTRA)

Specifies the filtering coefficient used for RSRQ (to be set in QuantityConfigEUTRA)

frequency set in QuantityConfigOTRA
The quantities used to evaluate the triggering condition for the event. cpich-RSCP corresponds to CPICH_RSCP in TS 25.133 for FDD. cpich-EcN0 corresponds to CPICH_Ec/No in TS 25.133 for FDD. This parameter refers to event B2 for HO to WCDMA.
Threshold for RSRP. If RSRP of serving cell is greater than Th1, only the serving cell is measured.
This specifies the threshold used by the UE when reselecting towards a higher priority frequency X than the current serving frequency
This specifies the threshold used in reselection towards the frequency X priority from a higher priority frequency
This specifies the minimum required RX level in the cell in dBm
The Number of Transmission Antenna Ports parameter defines whether eNode-B has one or two antennas for the downlink signal transmission.
Indicates the maximum number of HARQ transmissions used for Msg3 of the contention-based random access procedure.
This parameter determines the total number of non-dedicated RA preambles that a UE can select from (i.e. for contention based RA). The minimum cannot be zero.
Random Access Response Window Size parameter defines the window size for the random access response in TTIs.
The preamble transmission maximum defines the maximum number of Random Access transmissions. Note: The values n50, n100 and n200 should not be used.
The maximum content resolution timer parameter defines the maximum amount of time allowed for contention resolution.
The power ramping step size parameter defines the power increment step size for Random Access preamble transmission.
The parameter defines the initial power for Random Access preamble transmission.
Used for the calculation of P0_NOMINAL_PUSCH(j=2) for PUSCH (re)transmission corresponding to the random access response grant.

Details

Comments

[illegible]

In NSN it is Possible to define PDU size based on UE category

In NSN it is Possible to define PDU size based on UE category

[illegible]

3GPP Comment :else if the UE is establishing the RRC connection for mobile originating signalling and if both timers T302 and T305 are not running:

3> draw a random number 'rand' that is uniformly distributed in the range $0 \leq \text{rand} < 1$;

3> start timer T305 with the timer value calculated as follows, using the ac-BarringTime included in ac-BarringForMO-Signalling:

$T305 = (0.7 + 0.6 * \text{rand}) * \text{ac-BarringTime}$

3> inform upper layers about the failure to establish the RRC connection and that access barring for mobile originating signalling is applicable, upon which the procedure ends;

Direct mapping not available .NSN parameter " furtherPlmnIdL" provides additional PLMN ID's configured for the cell.UE directly will take the input from this parameter

Since L11B. Planned to be removed.

Direct mapping not available .PRACH related parameters will provide the cell radius.

Planned to be removed in E///
Replaced by partOfSectorPower. Since L11B.

In Ericsson, the value -1 (default) means that this parameter will not be used for setting the PRS period and prsSubframeOffset. In nsn, PRS Period and PRS subframe offset is always derived from prsConfigurationIndex

Refer prsConfigIndex parameter
This parameter is a key RF optimization parameter. Higher settings of this parameter will improve PUCCH reception, but will also drive higher UE Tx power leading to interference to neighboring cells, and vice-versa.
Higher settings will improve PUSCH reception, but will also drive higher UE Tx power leading to interference to neighboring cells, and vice-versa.
In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type
In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type

In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type

In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type

In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type

In NSN, there is no individual siMessagePeriodicity parameter for each SIB type. Instead, the SIB types are defined in SIB scheduling list, with Periodicity and Repetition mapped along with SIB type

nCellChgMed must be smaller or equal to nCellChgHigh

Note: If nCellChgHigh is set to same value than nCellChgMed, the high mobility state does have priorit

nCellChgMed must be smaller or equal to nCellChgHigh

Note: If nCellChgHigh is set to same value than nCellChgMed, the high mobility state does have priorit

Default value notes - Not used

[illegible]

Minor change in NSN configuration. In NSN , there is a provision to select Handover type .

Since L11B. Has no functional behaviour. Planned to be removed.

In Ericsson, Value 1000 means the parameter is not sent in the system information block
Since L12A. Has no functional behaviour. Planned to be removed

[illegible]

[illegible]

Event B2

Event B2

Event B2

Event B2

Event B2

Event B2

Event B2

Event B2

Event B2

Event B2

Planned to be removed in E///
Planned to be removed in E///
Planned to be removed in E///

Planned to be removed in E///
Planned to be removed in E///
Planned to be removed in E///

[illegible]

[illegible]

Removed
Removed
Since L11B. Has no functional behaviour. Planned to be removed.

Since L11B. Planned to be removed

No Contention free in E/// till L12B hence parm value is 64, it has been introduced in L13A except US market.
In E/// the value is mapped as $IE \times 8$
in L12A E/// system release the value has been changed from 0 to 6dB

48
70
70

[illegible]

[illegible]

No Difference
No Difference
No Difference
No Difference
No Difference

1%

1%

No Difference

[illegible]

13
16
10
2 db

[illegible]

16
8
4
1
0.5
0.5
1
0.5
0.5
4

[illegible]

[illegible]

No difference
No difference
20ms
1
1
128

2

No difference

1 dB

[illegible]

20 dbm

15 dBm

1 dB

23

9.5

No Difference

1 dB

320 ms

No Difference

10
1
800 ms
200ms
3 sec
No difference
No difference
No difference
150

[illegible]

NO
NO
NO
NO
1
24
6
No difference
16
6 dBm
5

ADDITIONAL INFORMATION

NSN Unit

NSN MOC

0...7, step 1

CDFIM

0...31.5 dB, step 0.5 dB

CDFIM

0...31.5 dB, step 0.5 dB

CDFIM

1 (0), 2 (1), 3 (2), 4 (3), 6 (4), 8 (5), 16 (6),
32 (7)

LNBTs

4 (0), 8 (1), 16 (2), 32 (3), 64 (4), 128 (5),
256 (6), infinity (7)

LNBTs

5ms (0), 10ms (1), 15ms (2), 20ms (3),
25ms (4), 30ms (5), 35ms (6), 40ms (7),
45ms (8), 50ms (9), 55ms (10), 60ms (11),
65ms (12), 70ms (13), 75ms (14), 80ms
(15), 85ms (16), 90ms (17), 95ms (18),
100ms (19), 105ms (20), 110ms (21),
115ms (22), 120ms (23), 125ms (24),
130ms (25), 135ms (26), 140ms (27),
145ms (28), 150ms (29), 155ms (30),
160ms (31), 165ms (32), 170ms (33),
175ms (34), 180ms (35), 185ms (36),
190ms (37), 195ms (38), 200ms (39),
205ms (40), 210ms (41), 215ms (42),
220ms (43), 225ms (44), 230ms (45),
235ms (46), 240ms (47), 245ms (48),
250ms (49), 300ms (50), 350ms (51),
400ms (52), 450ms (53), 500ms (54)

LNBTs

5ms (0), 10ms (1), 15ms (2), 20ms (3),
25ms (4), 30ms (5), 35ms (6), 40ms (7),
45ms (8), 50ms (9), 55ms (10), 60ms (11),
65ms (12), 70ms (13), 75ms (14), 80ms
(15), 85ms (16), 90ms (17), 95ms (18),
100ms (19), 105ms (20), 110ms (21),
115ms (22), 120ms (23), 125ms (24),
130ms (25), 135ms (26), 140ms (27),
145ms (28), 150ms (29), 155ms (30),
160ms (31), 165ms (32), 170ms (33),
175ms (34), 180ms (35), 185ms (36),
190ms (37), 195ms (38), 200ms (39),
205ms (40), 210ms (41), 215ms (42),
220ms (43), 225ms (44), 230ms (45),
235ms (46), 240ms (47), 245ms (48),
250ms (49), 300ms (50), 350ms (51),
400ms (52), 450ms (53), 500ms (54)

LNBTs

0ms (0), 5ms (1), 10ms (2), 15ms (3),
 20ms (4), 25ms (5), 30ms (6), 35ms (7),
 40ms (8), 45ms (9), 50ms (10), 55ms (11),
 60ms (12), 65ms (13), 70ms (14), 75ms
 (15), 80ms (16), 85ms (17), 90ms (18),
 95ms (19), 100ms (20), 105ms (21),
 110ms (22), 115ms (23), 120ms (24),
 125ms (25), 130ms (26), 135ms (27),
 140ms (28), 145ms (29), 150ms (30),
 155ms (31), 160ms (32), 165ms (33),
 170ms (34), 175ms (35), 180ms (36),
 185ms (37), 190ms (38), 195ms (39),
 200ms (40), 205ms (41), 210ms (42),
 215ms (43), 220ms (44), 225ms (45),
 230ms (46), 235ms (47), 240ms (48),
 245ms (49), 250ms (50), 300ms (51),
 350ms (52), 400ms (53), 450ms (54),
 500ms (55)

LN BTS

125ms (25), 130ms (26), 135ms (27),
 140ms (28), 145ms (29), 150ms (30),
 155ms (31), 160ms (32), 165ms (33),
 170ms (34), 175ms (35), 180ms (36),
 185ms (37), 190ms (38), 195ms (39),
 200ms (40), 205ms (41), 210ms (42),
 215ms (43), 220ms (44), 225ms (45),
 230ms (46), 235ms (47), 240ms (48),
 245ms (49), 250ms (50), 300ms (51),
 350ms (52), 400ms (53), 450ms (54),
 500ms (55)

LN BTS

1 (0), 2 (1), 3 (2), 4 (3), 6 (4), 8 (5), 16 (6),
 32 (7)

LN BTS

4 (0), 8 (1), 16 (2), 32 (3), 64 (4), 128 (5),
 256 (6), infinity (7)

LN BTS

2...3, step 1

LN BTS

ETHLK

LNCEL

FreqSync (0), PhaseSync (1), notUsed (10)

BTSSCL

0% (0), 5% (1), 10% (2), 15% (3), 20% (4),
25% (5), 30% (6), 40% (7), 50% (8), 60%
(9), 70% (10), 75% (11), 80% (12), 85%
(13), 90% (14), 95% (15) LNCCEL

0% (0), 5% (1), 10% (2), 15% (3), 20% (4),
25% (5), 30% (6), 40% (7), 50% (8), 60%
(9), 70% (10), 75% (11), 80% (12), 85%
(13), 90% (14), 95% (15) LNCCEL

Not used (0), barred (1), Not barred (2) LNCCEL
LNCCEL
LNCCEL
LNCCEL

Bit 0: AC 11, Bit 1: AC 12, Bit 2: AC 13, Bit
3: AC 14, Bit 4: AC 15, LNCCEL

Bit 0: AC 11, Bit 1: AC 12, Bit 2: AC 13, Bit
3: AC 14, Bit 4: AC 15, LNCCEL

4s (0), 8s (1), 16s (2), 32s (3), 64s (4),
128s (5), 256s (6), 512s (7) LNCCEL

4s (0), 8s (1), 16s (2), 32s (3), 64s (4),
128s (5), 256s (6), 512s (7) LNCCEL

5 MHz (2), 10 MHz (3), 15 MHz (4), 20 MHz
(5) LNCCEL

TRUE (0) ,FALSE (1)
0...359.9 deg, step 0.1 deg

LNCEL
RET

0...360 deg, step 1 deg

RET

2 (0), 4 (1), 8 (2), 16 (3)

LNCEL

1...3, step 1

LNCEL

TRUE (1) ,FALSE (0)

LNCEL

-30...33 dBm, step 1 dBm

LNCEL

151 (151), 152 (152), 153 (153), 156 (156), 157 (157), 471 (471), 472 (472), 473 (473), 476 (476), 477 (477), 1111 (1111), 1112 (1112), 1113 (1113), 1116 (1116), 1117 (1117), 2391 (2391), 2392 (2392), 2393 (2393), 2396 (2396), 2397 (2397)
--

LNCEL

LNCEL

-127...-96 dBm, step 1 dBm
-126...24 dBm, step 1 dBm
-140...-44 dBm, step 2 dBm

LNCEL

LNCEL

LNCEL

-115...-25 dBm, step 2 dBm
2...16 dB, step 2 dB

LNCEL

GNFL

LNCEL

80ms (0), 160ms (1), 320ms (2), 640ms (3), 1280ms (4), 2560ms (5), 5120ms (6)

LNCEL

80ms (0), 160ms (1), 320ms (2), 640ms (3), 1280ms (4), 2560ms (5), 5120ms (6)

LNCEL

1ms (0), 2ms (1), 5ms (2), 10ms (3), 15ms (4), 20ms (5), 40ms (6)	LNCEL
--	-------

1...16, step 1	LNCEL
----------------	-------

1...16, step 1	LNCEL
0dB (0), 1dB (1), 2dB (2), 3dB (3), 4dB (4), 5dB (5), 6dB (6), 8dB (7), 10dB (8), 12dB (9), 14dB (10), 16dB (11), 18dB (12), 20dB (13), 22dB (14), 24dB (15)	LNCEL

-6 dB (0), -4 dB (1), -2 dB (2), 0 dB (3)	LNCEL
---	-------

-6 dB (0), -4 dB (1), -2 dB (2), 0 dB (3)	LNCEL
---	-------

0...62 dB, step 2 dB	LNCEL
0...62 dB, step 2 dB	LNCEL
30s (0), 60s (1), 120s (2), 180s (3), 240s (4)	LNCEL
0...62 dB, step 2 dB	LNCEL
30s (0), 60s (1), 120s (2), 180s (3), 240s (4)	LNCEL
0...7 s, step 1 s	UFFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	UFFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	UFFIM
0...7 s, step 1 s	GFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	GFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	GFIM
0...15, step 1	CDFIM
0...7 s, step 1 s	CDFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	CDFIM
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	CDFIM
0...62 dB, step 2 dB	LNCEL

5 MHz (2), 10 MHz (3), 15 MHz (4), 20 MHz
(5)

LNCEL

-24dB (0), -22dB (1), -20dB (2), -18dB (3), -16dB (4),
-14dB (5), -12dB (6), -10dB (7), -8dB (8), -6dB (9),
-5dB (10), -4dB (11), -3dB (12), -2dB (13), -1dB (14),
0dB (15), 1dB (16), 2dB (17), 3dB (18), 4dB (19),
5dB (20), 6dB (21), 8dB (22), 10dB (23), 12dB (24),
14dB (25), 16dB (26), 18dB (27), 20dB (28), 22dB
(29), 24dB (30)

LNREL

allowed (0), forbidden (1), onlyS1 (2)

LNREL

-24 dB (0), -22 dB (1), -20 dB (2), -18 dB (3), -16 dB (4), -14 dB (5), -12 dB (6), -10 dB (7), -8 dB (8), -6 dB (9), -5 dB (10), -4 dB (11), -3 dB (12), -2 dB (13), -1 dB (14), 0 dB (15), 1 dB (16), 2 dB (17), 3 dB (18), 4 dB (19), 5 dB (20), 6 dB (21), 8 dB (22), 10 dB (23), 12 dB (24), 14 dB (25), 16 dB (26), 18 dB (27), 20 dB (28), 22 dB (29), 24 dB (30)

IAFIM

6mbw (0), 15mbw (1), 25mbw (2), 50mbw (3), 75mbw (4), 100mbw (5)

IRFIM

0...7, step 1

IRFIM

-30...33 dBm, step 1 dBm	LNCEL
10 dB (23), 12 dB (24), 14 dB (25), 16 dB (26), 18 dB (27), 20 dB (28), 22 dB (29), 24 dB (30)	LNCEL IRFIM
-140...-44 dBm, step 2 dBm	LNCEL
0...62 dB, step 2 dB	IRFIM
0...62 dB, step 2 dB	IRFIM
0...7 s, step 1 s	LNCEL
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	LNCEL
0.25 (0), 0.5 (1), 0.75 (2), 1 (3)	LNCEL
1...16, step 1	LNCEL
5ms (0), 10ms (1), 16ms (2), 20ms (3), 32ms (4), 40ms (5), 64ms (6), 80ms (7), 128ms (8), 160ms (9), 320ms (10), 640ms (11), 1280ms (12), 2560ms (13), infinity (14)	LNCEL
500 (0), 750 (1), 1280 (2), 1920 (3), 2560 (4), 5120 (5), 10240 (6)	LNCEL
1...7, step 1	LNCEL
32rf (0), 64rf (1), 128rf (2), 256rf (3)	LNCEL

oneT (2), halfT (3), quarterT (4),
oneEighthT (5), oneSixteenthT (6),
oneThirtySecondT (7)

LNCEL

RLC_AM (0)

LNBTs

5...75000 kbps, step 5 kbps

LNCEL

10...65535 s, step 1 s

LNCEL

0...97, step 1

LNCEL

0...15 dB, step 0.5 dB

LNCEL

0ms (0), 40ms (1), 64ms (2), 80ms (3), 100ms (4), 128ms (5), 160ms (6), 256ms (7), 320ms (8), 480ms (9), 512ms (10), 640ms (11), 1024ms (12), 1280ms (13), 2560ms (14), 5120ms (15), notUsed (16)	LNCEL
---	-------

0...97, step 1	LNCEL
----------------	-------

0...97, step 1	LNCEL
----------------	-------

0...15 dB, step 0.5 dB	LNCEL
------------------------	-------

0ms (0), 40ms (1), 64ms (2), 80ms (3), 100ms (4), 128ms (5), 160ms (6), 256ms (7), 320ms (8), 480ms (9), 512ms (10), 640ms (11), 1024ms (12), 1280ms (13), 2560ms (14), 5120ms (15)	LNCEL
---	-------

0...97, step 1

LNHOW

0...63, step 1

LNHOW

0...15 dB, step 0.5 dB

LNHOW

0ms (0), 40ms (1), 64ms (2), 80ms (3),
100ms (4), 128ms (5), 160ms (6), 256ms
(7), 320ms (8), 480ms (9), 512ms (10),
640ms (11), 1024ms (12), 1280ms (13),
2560ms (14), 5120ms (15)

LNHOW

0...97, step 1

LNHOW

0...49, step 1 (0 → CPICH Ec/Io < -24dB
1 → -24dB ⇨ CPICH Ec/Io <
-23.5dB ...
...48 → -0.5dB ⇨ CPICH Ec/Io LNHOW
< 0dB
49 → 0 ⇨ CPICH Ec/Io
)

-5...91, step 1
(-5 → CPICH RSCP < -120dBm
-4 → -120dBm ⇨ CPICH RSCP < -119dBm ...
... 91 → -26dBm ⇨ CPICH RSCP <
-25dBm LNHOW
91 → -25dBm ⇨ CPICH RSCP
)

0...15 dB, step 0.5 dB

LNHOW

0ms (0), 40ms (1), 64ms (2), 80ms (3),
100ms (4), 128ms (5), 160ms (6), 256ms
(7), 320ms (8), 480ms (9), 512ms (10), LNHOW
640ms (11), 1024ms (12), 1280ms (13),
2560ms (14), 5120ms (15)

cpichRSCP (0), cpichEcN0 (1), notUsed (2) LNCEL

LNCEL

LNCEL

0ms (0), 40ms (1), 64ms (2), 80ms (3),
100ms (4), 128ms (5), 160ms (6), 256ms
(7), 320ms (8), 480ms (9), 512ms (10),
640ms (11), 1024ms (12), 1280ms (13),
2560ms (14), 5120ms (15), notUsed (16)

LNCEL

0...97, step 1

LNCEL

0ms (0), 40ms (1), 64ms (2), 80ms (3),
100ms (4), 128ms (5), 160ms (6), 256ms
(7), 320ms (8), 480ms (9), 512ms (10),
640ms (11), 1024ms (12), 1280ms (13),
2560ms (14), 5120ms (15)

LNCEL

0.5 db

LNCEL

0.5 db

LNCEL

120ms (0), 240ms (1), 480ms (2), 640ms (3), 1024ms (4), 2048ms (5), 5120ms (6), 10240ms (7), 1min (8), 6min (9), 12min (10), 30min (11), 60min (12)

LNCEL

0ms (0), 40ms (1), 64ms (2), 80ms (3), 100ms (4), 128ms (5), 160ms (6), 256ms (7), 320ms (8), 480ms (9), 512ms (10), 640ms (11), 1024ms (12), 1280ms (13), 2560ms (14), 5120ms (15)

LNCEL

n1 (0), n2 (1), n3 (2), n4 (3), n6 (4), n8 (5), n10 (6), n20 (7)	LNCEL
---	-------

n1 (0), n2 (1), n3 (2), n4 (3), n5 (4), n6 (5), n8 (6), n10 (7)	LNCEL
--	-------

100ms (0), 200ms (1), 300ms (2), 400ms (3), 600ms (4), 1000ms (5), 1500ms (6), 2000ms (7)	LNCEL
---	-------

100ms (0), 200ms (1), 300ms (2), 400ms (3), 600ms (4), 1000ms (5), 1500ms (6), 2000ms (7)	LNCEL
---	-------

1000...16000 ms, step 1000 ms	LNCEL
-------------------------------	-------

50ms (0), 100ms (1), 150ms (2), 200ms (3), 500ms (4), 1000ms (5), 2000ms (6)	LNCEL
---	-------

0ms (0), 50ms (1), 100ms (2), 200ms (3), 500ms (4), 1000ms (5), 2000ms (6)	LNCEL
---	-------

1000ms (0), 3000ms (1), 5000ms (2), 10000ms (3), 15000ms (4), 20000ms (5), 30000ms (6)	LNCEL
--	-------

5min (5), 10min (10), 20min (20), 30min (30), 60min (60), 120min (120), 180min (180)	LNCEL
--	-------

BTSSCL

0...9, step 1

LNBT5

0...9, step 1

LNBT5

fc0 (0), fc1 (1), fc2 (2), fc3 (3), fc4 (4), fc5
(5), fc6 (6), fc7 (7), fc8 (8), fc9 (9), fc11
(10), fc13 (11), fc15 (12), fc17 (13), fc19
(14)

LNCEL

fc0 (0), fc1 (1), fc2 (2), fc3 (3), fc4 (4), fc5
(5), fc6 (6), fc7 (7), fc8 (8), fc9 (9), fc11
(10), fc13 (11), fc15 (12), fc17 (13), fc19
(14)

LNCEL

cpichRSCP (0), cpichEcN0 (1), notUsed (2)	LNCEL
0...97, step 1	LNCEL
0...62 dB, step 2 Db	UFFIM
0...62 dB, step 2 Db	UFFIM
-119...-25 dBm, step 2 dBm	UFFIM
1 (0), 2 (1)	LNCEL
1...8, step 1	LNCEL
4 (0), 8 (1), 12 (2), 16 (3), 20 (4), 24 (5), 28 (6), 32 (7), 36 (8), 40 (9), 44 (10), 48 (11), 52 (12), 56 (13), 60 (14), 64 (15)	LNCEL
2 (0), 3 (1), 4 (2), 5 (3), 6 (4), 7 (5), 8 (6), 10 (7)	LNCEL
3 (0), 4 (1), 5 (2), 6 (3), 7 (4), 8 (5), 10 (6), 20 (7), 50 (8), 100 (9), 200 (10)	LNCEL
8ms (0), 16ms (1), 24ms (2), 32ms (3), 40ms (4), 48ms (5), 56ms (6), 64ms (7)	LNCEL
0dB (0), 2dB (1), 4dB (2), 6dB (3)	LNCEL
-120 dBm (0), -118 dBm (1), -116 dBm (2), -114 dBm (3), -112 dBm (4), -110 dBm (5), -108 dBm (6), -106 dBm (7), -104 dBm (8), -102 dBm (9), -100 dBm (10), -98 dBm (11), -96 dBm (12), -94 dBm (13), -92 dBm (14), -90 dBm (15)	LNCEL
-1...6, step 1	LNCEL