Wattox PCS

Charge and Discharge Efficiency for 1.725MW PCS



wattox

PCS Charge and Discharge Efficiency

Wattox MPCS-1725-D								
Mode	**Test Method**	**Test Standard**	**Power**	**Efficiency with auxiliary power**				
				1050V	**1200V**	**1300V**	**1400V**	**1500V**
Charging	1. Set the lower limit DC voltage Udc min, rated AC voltage, charging mode, and initial power at -10% Pn. The energy storage converter under test increases power operation in intervals of -10% rated power; 2. Record efficiency value η2 using a power analyzer; 3. Repeat steps 1-2 with specified DC voltages Udc n and Udc max; 4. Based on the maximum efficiency value measured in steps 1-3, fine-tune the corresponding DC and AC voltages to confirm the final maximum efficiency value. Record the actual power and voltage.	Under rated operating conditions, the rectifier and inverter efficiency of the energy storage converter shall not be less than 98.7%.	10%	96,54%	96,27%	96,25%	96,27%	96,54%
			20%	97,60%	97,45%	97,61%	97,52%	97,60%
			30%	97,49%	98,22%	98,13%	98,09%	97,49%
			50%	97,69%	98,35%	98,39%	98,31%	97,69%
			75%	98,19%	98,33%	98,36%	98,33%	98,19%
			100%	98,29%	98,19%	98,22%	98,17%	98,29%
Discharging			10%	96,13%	96,32%	96,40%	96,39%	96,13%
			20%	97,84%	97,72%	97,65%	97,62%	97,84%
			30%	98,41%	98,13%	98,16%	98,10%	98,41%
			50%	98,77%	98,44%	98,46%	98,41%	98,77%
			75%	98,52%	98,44%	98,45%	98,50%	98,52%
			100%	98,31%	98,34%	98,29%	98,27%	98,31%

wattox

