

Palitizer / PLC_1 [CPU 1211C DC/DC/DC] / Program blocks

FB_Cylinder [FB5]

FB_Cylinder Properties							
General							
Name	FB_Cylinder	Number	5	Type	FB	Language	SCL
Numbering	Automatic						
Information							
Title		Author		Comment		Family	
Version	0.1	User-defined ID					

FB_Cylinder									
Name	Data type	Default value	Retain	Accessible from HMI/OPC UA/Web API	Writ-able from HMI/OPC UA/ Web API	Visible in HMI engi-neering	Setpoint	Supervi-sion	Comment
▼ Input									
▼ i_stState	"UDT_SysStatus"		Non-retain	True	True	True	False		The master mode from DB_Machine.
xModeAuto	Bool	false	Non-retain	True	True	True	False		
xModeManual	Bool	false	Non-retain	True	True	True	False		
xRunning	Bool	false	Non-retain	True	True	True	False		
xPaused	Bool	false	Non-retain	True	True	True	False		
xFaulted	Bool	false	Non-retain	True	True	True	False		
iStateID	Int	0	Non-retain	True	True	True	False		
iCurrentLayer	Int	0	Non-retain	True	True	True	False		
iTargetLayers	Int	0	Non-retain	True	True	True	False		
iTotalBoxes	DInt	0	Non-retain	True	True	True	False		
iTotalPallets	DInt	0	Non-retain	True	True	True	False		
wAlarmWord	Word	16#0	Non-retain	True	True	True	False		
i_xAutoCmd	Bool	false	Non-retain	True	True	True	False		The command from FB3 se-quencer
i_xManualCmd	Bool	false	Non-retain	True	True	True	False		he jog button from the oper-ator.
i_xInterlock	Bool	True	Non-retain	True	True	True	False		Safety condition
▼ Output									
q_xValveOut	Bool	false	Non-retain	True	True	True	False		The signal going to the physical coil
InOut									
Static									
Temp									
Constant									

```
0001 // Check safety interlock first
0002 IF #i_xInterlock THEN
0003     // Auto mode : listen to the sequencer
0004     IF #i_stState.xModeAuto AND #i_stState.xRunning THEN
0005         #q_xValveOut := #i_xAutoCmd;
0006         // MANUAL MODE: Listen strictly to the operator
0007     ELSIF #i_stState.xModeManual THEN
0008         #q_xValveOut := #i_xManualCmd;
0009         // OFF / FAULTED: Drop output for safet
0010     ELSE
0011         #q_xValveOut := FALSE;
0012     END_IF;
0013 ELSE
0014     #q_xValveOut := FALSE;
0015 END_IF;
```

Symbol	Address	Type	Comment
#i_stState.xModeAuto		Bool	
#i_stState.xModeManual		Bool	
#i_stState.xRunning		Bool	
#i_xAutoCmd		Bool	The command from FB3 sequencer
#i_xInterlock		Bool	Safety condition
#i_xManualCmd		Bool	he jog button from the operator.
#q_xValveOut		Bool	The signal going to the physical coil