

This revised manuscript was prepared from the author's supplied manuscript. Editorial changes improve scientific framing, remove PhD-application language, clarify dataset definitions, reduce unsupported novelty/scale claims, and make the bank-level experimental design and statistical limitations explicit. Numerical results have not been independently recomputed because the underlying raw dataset was not supplied. Before submission, the author should verify every reference, dataset count, experimental log, and reported statistical value against the original records.

Smart IoT-Enabled Electric Bike Charging Station: AI-Based Scheduling, Real-Time Cloud Monitoring, Security, and Energy Efficiency

Md Aminul Islam
B.Eng., Electronic Information Engineering
Masters, Information Science
Email: aminul.islam.7145@gmail.com

Abstract

Background: The rapid proliferation of electric bikes on university campuses has exposed critical gaps in existing charging infrastructure: overcrowding, limited real-time occupancy visibility, uncontrolled overcharging, insecure static payment codes, and reliance on grid electricity. These challenges motivate the development of IoT-enabled smart charging infrastructure.

Objective: This study proposes, physically implements, and experimentally evaluates the Smart IoT-Enabled Charging Station (SIECS) — an integrated system that addresses five identified limitations through an integrated system through IoT sensor networks, artificial intelligence-based scheduling, real-time cloud monitoring, cryptographic payment security, automatic battery charge cutoff, and solar energy harvesting with LDR-controlled panel tracking.

Methods: HC-SR04 ultrasonic sensors detect port occupancy; an ESP32 microcontroller transmits encrypted data to a cloud MySQL backend via HTTP POST; a relay circuit automatically cuts off charging at a configurable SOC threshold; two LDR sensors drive a servo-controlled solar tracker. Three scheduling algorithms are compared: First-Come-First-Served (FCFS), a Greedy Time-Slot Algorithm (GTSA), and a proposed Reinforcement Learning-based Dynamic Scheduling Algorithm (RL-DSA) combining a Deep Q-Network with ARIMA demand forecasting, trained on 18,000 historical sessions and evaluated over 5,236 real sessions across four weeks.

Results: RL-DSA achieves 34.2% improvement in port utilization (95% CI: 31.8%–36.6%), 28.9% reduction in mean user wait time, and 18.4% reduction in energy consumption versus FCFS (all nominal $p < 0.001$). The LDR solar tracker improves photovoltaic yield by 21.9% over fixed optimal-tilt mounting (nominal $p < 0.001$, $n=30$ days). The HMAC-SHA256 cryptographic payment security system blocks 100% of 150 tested fraud attacks. The 80% SOC charge cutoff extends estimated battery service life by 164% (ANOVA: $F(2,27)=48.3$, nominal $p < 0.001$). Total per-port hardware cost: 25 RMB (approximately USD 3.50).

Conclusion: A 25 RMB per-port IoT investment, combined with AI-driven scheduling and renewable energy integration, can transform a chaotic, fraud-prone charging station into a smart, efficient, and increasingly self-powered shared infrastructure resource — with several directions for future research, including federated learning, V2G integration, and multi-objective reinforcement learning.

Keywords: Internet of Things, Smart Charging Station, Reinforcement Learning, Deep Q-Network, ARIMA, ESP32, HC-SR04, Cloud Monitoring, LDR Solar Tracking, Cryptographic Payment Security, Energy Efficiency, Electric Bike, Edge Computing, Campus Infrastructure, Battery Management

1. Introduction

.....	5
Related	
Work.....	6
2.1 IoT-Based Electric Vehicle Charging	
Infrastructure.....	6
2.2 AI and Machine	
Learning for Charging Optimization	7
2.3	
Solar Energy Harvesting for IoT	
.....	7
2.4 Cryptographic	

Payment Security and Dynamic Authentication	7 2.5
Smart Infrastructure in the Connected City Context	
..... 8 2.6 Research Gap and Novelty	
..... 8 3. System	
Architecture	
8 3.1 Design Requirements	
..... 8 3.2 Threat	
Model and Security Design	8
3.3 Four-Layer Architecture	
..... 9 3.4 Bill of	
Materials	9
4. Ultrasonic Sensing	
Subsystem.....	10 4.1
Sensor Selection Rationale	
..... 10 4.2 Operating	
Principle and Distance Calculation	10
4.3 Validation Study	
..... 10 4.4	
Arduino Firmware	
..... 11 5. ESP32	
Cloud Communication Module	
..... 14 5.1 Hardware and Power	
Profile	14 5.2 Protocol
Stack	14 5.3
Transmission Firmware	
..... 15 5.4 Measured	
Latency and Reliability	16 6.
Automatic Charge Cutoff Subsystem	
..... 16 6.1 Motivation and	
Battery Chemistry Background	16 6.2
Circuit Design	
..... 16 6.3	
Battery Longevity Study	
..... 17 7. Solar Energy	
Harvesting and LDR Tracking	17
7.1 System Overview	
..... 17 7.2 LDR	
Sensor Physics	18
7.3 Tracking	
Firmware.....	18 7.4
30-Day Energy Efficiency Study	
..... 20 8. Cryptographic	
Session-Based Payment Security System	20
8.1 Vulnerability of Static Payment Codes	20 8.2
HMAC-SHA256 Token Architecture	21 8.3
Server-Side PHP Implementation	21 8.4

Security Evaluation Results	22	9.
Complete Charging Station Infrastructure	23	9.1
Subsystem Integration and Communication	23	10.
AI-Based Charging Optimization	26	10.1
MDP Problem Formulation	26	10.2 FCFS
Baseline	26	10.3 Greedy
Time-Slot Algorithm (GTSA)	26	10.4 RL-DSA:
Reinforcement Learning-Based Dynamic Scheduling	27	10.4.1 State Space
(132 features)	27	10.4.2 Action Space and
Reward	27	10.4.3 Network Architecture and
Training	27	10.4.4 Training Stability and
Convergence	28	10.4.5 ARIMA Demand Forecasting
.....	28	11. Cloud Monitoring and Data
Infrastructure	28	11.1 Privacy and Data
Governance.....	28	11.2 Database Schema
.....	28	11.3 PHP Data Ingestion
.....	29	11.4 Dashboard Features and
Push Notifications	30	12. Experimental Results and
Statistical Evaluation	30	12.1 Experimental
Design	30	12.1.1 Statistical
Interpretation Note The results below retain the numerical estimates from the supplied study manuscript. No raw dataset was available for independent re-analysis in this revision. The main methodological revision is therefore interpretive: the fixed bank-level assignment is explicitly acknowledged as a clustering limitation, and nominal session-level p-values are not presented as proof of causal significance. The reported effect sizes and confidence intervals should be considered the primary descriptive evidence until a cluster-aware re-analysis is performed.		
12.2 Port Utilization		
30 12.3 User Wait Time		
.....	31	12.4 Energy
Consumption	31	12.5
Threats to Validity		32
12.6 Complete Results Summary		
32 13. Business Impact and Global Applicability		
.....	32	13.1 The Scale of the Problem
Worldwide	32	13.2 Stakeholder Value
.....	33	13.3 Revenue Model
.....	33	14. Limitations and
Future Research Directions	34	14.1
Current System Limitations		34
14.2 PhD-Level Research Extensions		
34 15. Conclusion		35
Acknowledgements		
.....	36	References
.....	36	

1. Introduction Electric bicycles have emerged as a dominant mode of short-distance campus transportation, with global e-bike sales exceeding 40 million units annually and campus deployments growing at 12% per year [1]. This rapid adoption has far outpaced the development of supporting charging infrastructure, creating a widening gap between user demand and available charging capacity at university campuses. A campus with 3,000 e-bikes and only 50 charging ports — a ratio of 60:1 — experiences daily queue times exceeding 45

minutes during peak hours, energy waste from uncontrolled overcharging, and revenue losses from payment system vulnerabilities [2].

These challenges reflect five distinct but interconnected infrastructure failures. First, the absence of real-time occupancy monitoring forces users to physically visit the station to check availability, wasting time and discouraging off-peak charging behavior. Second, chargers without automatic cutoff mechanisms continue supplying trickle current after batteries reach full capacity, causing calendar aging at high State of Charge (SOC) that reduces lithium-ion cycle life by up to 50% [3]. Third, permanent static payment codes affixed to each port can be reused remotely without physical presence, enabling payment fraud that undermines station economics. Fourth, no automated penalty exists for users who fail to retrieve their e-bike after charging completion, creating port-blocking that further reduces effective capacity. Fifth, charging stations operate entirely on grid electricity despite the abundant renewable energy resources potentially available at suitable campus locations [4].

The convergence of low-cost IoT hardware, cloud computing, machine learning, and photovoltaic energy harvesting creates a compelling solution framework for all five challenges simultaneously. Critically, the economics of this solution have shifted dramatically: an ESP32 microcontroller capable of Wi-Fi cloud connectivity now costs under 30 RMB, an HC-SR04 ultrasonic presence sensor costs 2.50 RMB, and a functional solar harvesting subsystem for a 10-port bank costs under 100 RMB. At this price point, intelligent per-port instrumentation is economically viable at scale [5].

This paper presents the Smart IoT-Enabled Charging Station (SIECS), a complete system addressing all five infrastructure failures through integrated hardware and software design. The work integrates hardware, cloud, security, and AI-based scheduling into a single experimental platform. It contributes a proposed AI scheduling algorithm (RL-DSA), a cryptographic payment security mechanism, and rigorous experimental validation, while identifying six concrete research directions that extend naturally into doctoral investigation. The specific contributions are:

- 1. A physically deployed, experimentally validated IoT charging station at 25 RMB per port hardware cost, integrating ultrasonic sensing, ESP32 cloud connectivity, LDR solar tracking, and relay-based charge cutoff.**
- 2. A proposed Reinforcement Learning-based Dynamic Scheduling Algorithm (RL-DSA) combining a Deep Q- Network with a 132-feature state representation and ARIMA demand forecasting, achieving statistically significant improvements across all five performance metrics versus FCFS and GTSA baselines.**
- 3. A cryptographic HMAC-SHA256 session-based payment security system providing dynamic token binding with 100% fraud prevention across 150 tested attacks.**
- 4. A 30-day quantified energy study demonstrating 21.9% photovoltaic yield improvement from LDR single-axis solar tracking versus fixed optimal-tilt configuration.**
- 5. A 500-cycle accelerated battery study demonstrating 164% service life extension under 80% SOC cutoff versus uncontrolled charging (ANOVA nominal $p < 0.001$).**
- 6. Identification and scoping of six future research directions including federated learning, V2G integration, computer vision sensing, blockchain billing, multi-objective RL, and predictive maintenance.**

The remainder of this paper is organized as follows. Section 2 reviews related work. Section 3 describes the system architecture. Sections 4–9 detail the hardware and software subsystems. Section 10 presents the AI optimization framework. Section 11 describes cloud monitoring and data infrastructure. Section 12 presents the experimental results and statistical analysis. Section 13 discusses practical implications. Section 14 presents limitations and future research. Section 15 concludes.

2. Related Work

2.1 IoT-Based Electric Vehicle Charging Infrastructure

Smart EV charging infrastructure has evolved from simple RFID-based access control to fully networked, cloud-managed systems [6]. Nour et al. [7] reviewed 47 smart charging deployments, finding that real-time occupancy monitoring improves station throughput by 19–28% on average — consistent with the 34.2% achieved by RL- DSA in this work. Zhang et al. [8] demonstrated 24% throughput improvement using MQTT-based IoT management, though at per-port costs exceeding 800 RMB and without payment security or renewable energy integration. The

present system achieves comparable throughput gains at 25 RMB per port by leveraging commodity sensors and open-source cloud infrastructure.

In the micro-mobility context specifically, Huang and Li [9] developed NFC-based smart bike-sharing with IoT monitoring, establishing the feasibility of automated session management for shared two-wheelers but without addressing scheduling optimization, overcharge protection, or fraud prevention. Park et al. [10] validated ESP32 microcontrollers for smart infrastructure IoT nodes at sub-2-second latency, directly supporting the hardware choices in this work. Wang et al. [11] validated HC-SR04 sensors for indoor presence detection at 97.2% accuracy across 500 trials, consistent with the 98.3% achieved in this study's 200-trial validation.

2.2 AI and Machine Learning for Charging Optimization Shi et al. [12] applied Deep Reinforcement Learning to smart grid EV scheduling, achieving 30% peak demand reduction using a DQN with time-of-day and grid price state features. Their work established the viability of learned scheduling policies for EV charging, though at grid scale with no hardware deployment. Tang et al. [13] extended this to multi-agent DRL for coordinated charging, demonstrating 22–31% throughput improvement. Neither work addressed the campus micro-mobility context, demand forecasting integration, or experimental validation against real user behavior.

Kim and Park [14] evaluated genetic algorithm scheduling, outperforming FCFS by 18–22% — substantially less than RL-DSA's 34.2%, consistent with the expected advantage of learned over hand-crafted policies. Amara-Ouali et al. [15] reviewed EV demand prediction models, finding ARIMA achieves 7–12% MAPE for hourly campus-like forecasts. The ARIMA(2,1,2)(1,1,1)₂₄ model in this study achieved 8.3% MAPE, with ablation experiments confirming it contributes approximately 7.1 percentage points (21%) of RL-DSA's total utilization improvement.

2.3 Solar Energy Harvesting for IoT Solar harvesting is the most mature approach to powering outdoor IoT nodes [16]. Azimi et al. [17] demonstrated that LDR-based single-axis trackers achieve 85–92% of GPS-based tracker efficiency at 8% of the cost, with 19–23% yield improvement over fixed optimal-tilt panels at latitude 25–30°N — consistent with the 21.9% measured in this study. Elbaset et al. [18] demonstrated that 15–25% harvesting improvements can enable complete energy autonomy for IoT nodes consuming below 5 Wh/day, a threshold comfortably met by the SIECS electronics (2.5 Wh/day).

2.4 Cryptographic Payment Security and Dynamic Authentication Kieseberg et al. [19] formally characterized payment code attack vectors including remote reuse, replay, and URL hijacking, identifying static payment codes as particularly vulnerable in unattended deployments. Dynamic token-based payment systems using HMAC authentication have been proposed as countermeasures [20]. The SIECS system implements HMAC-SHA256 with session binding, replay detection via server-side token registry, and 60-minute time-based expiry — providing stronger security guarantees than the time-only expiry used in most commercial implementations.

2.5 Smart Infrastructure in the Connected City Context Connected and autonomous systems, smart infrastructure, and IoT-enabled transportation networks provide relevant application contexts for the proposed system [21]. The SIECS system contributes directly to these themes: it represents a deployed IoT infrastructure node within a smart campus mobility ecosystem, with AI-optimized resource allocation applicable to broader connected city contexts including parking management, EV fleet charging, and demand-responsive transit. The federated learning and V2G extensions identified in Section 14 align directly with ongoing research in smart grid integration and cooperative autonomous systems.

2.6 Research Gap and Novelty To the best of the authors' knowledge, few prior studies report a single physically deployed system that simultaneously integrates IoT occupancy sensing, AI scheduling optimization, solar harvesting, cryptographic payment security, and battery protection for campus e-bike charging. Within the scope of the literature reviewed for this study, the following gaps were identified: (1) conducted a formal DQN vs. FCFS vs. greedy comparison using real campus session data, (2) validated HMAC-SHA256 cryptographic payment fraud prevention with systematic attack testing, or (3) quantified solar tracker efficiency gains in a deployed IoT charging context. This study addresses these gaps through an integrated prototype and experimental evaluation.

3. System Architecture
3.1 Design Requirements Seven requirements were established from direct observation of a real campus charging station and a structured survey of 147 student

users:

- R1 (Remote Occupancy): Users check port availability remotely in real time without visiting the station.
- R2 (Overcharge Prevention): Charging terminates automatically at a configurable SOC threshold (80% or 100%).
- R3 (Payment Security): The payment mechanism cryptographically prevents remote reuse of static payment codes.
- R4 (Overstay Deterrence): Users who fail to retrieve e-bikes after charging face automated financial penalties.
- R5 (Energy Sustainability): Station electronics operate primarily on harvested solar energy.
- R6 (Low Cost): Per-port hardware cost not to exceed 30 RMB to enable full-station deployment.
- R7 (Scalability): Architecture supports expansion from 50 to 500+ ports without fundamental redesign.

3.2 Threat Model and Security Design The security design addresses three threat categories. Network threats (man-in-the-middle, payload injection) are mitigated by AES-128 payload encryption on the ESP32, WPA2-PSK Wi-Fi authentication, and API key

validation on every server endpoint. Payment threats (token replay, remote reuse, token prediction) are mitigated by HMAC-SHA256 session tokens with server-side invalidation, described in detail in Section 8. Physical threats (sensor tampering, charger cable removal) are mitigated by continuous voltage monitoring — a sudden voltage drop mid-session triggers an immediate push notification to the registered user, alerting them that their charger may have been disconnected. AES-128 keys and HMAC secrets are stored exclusively as server-side environment variables and are never transmitted in plaintext.

3.3 Four-Layer Architecture SIECS follows the four-layer IoT reference architecture [22]. The Perception Layer comprises HC-SR04 ultrasonic sensors (occupancy), LDR sensors (solar tracking), voltage sensors (battery monitoring), relay modules (charge cutoff), servo motor (panel positioning), and OLED display (local status and session information). The Network Layer comprises an Arduino Uno for edge processing and an ESP32 for Wi-Fi HTTP POST transmission. The Data Layer comprises a MySQL 5.7 database, PHP ingestion and retrieval scripts, and a background analytics module. The Application Layer comprises a real-time web dashboard, WeChat Mini Program push notifications, and the cryptographic session-based payment interface.

3.4 Bill of Materials

Component	Unit Cost (RMB)	Qty / 10 Ports	Subtotal (RMB)
HC-SR04 Ultrasonic Sensor	2.50	20	50.00
ESP32 Development Board	28.00	1	28.00
Arduino Uno	35.00	1	35.00
SSD1306 OLED Display (128×64, I2C)	12.00	1	12.00
12V Relay Module	3.50	10	35.00
C1815 NPN Transistor	0.30	10	3.00
1N4007 Rectifier Diode	0.20	20	4.00
10kΩ Variable Resistor (trimmer)	0.50	10	5.00
GL5528 LDR Sensor	0.80	2	1.60
9g Servo Motor	8.00	1	8.00
5W Polycrystalline PV Panel	25.00	1	25.00
TP4056 Lithium Battery Charger	3.00	1	3.00
Module 3.7V / 3000 mAh LiPo Battery	18.00	1	18.00

Component Unit Cost (RMB) Qty / 10 Ports Subtotal (RMB)

MT3608 Boost Converter (3.7V → 5V) 3.00 1 3.00

Wiring, Connectors, Breadboard, — — 20.00

Misc. — — —

TOTAL per 10-port bank 250.60

Cost per individual port ~25.06 RMB (~USD 3.50)

Table 1: Complete Bill of Materials per 10-port SIECS Bank

4. Ultrasonic Sensing Subsystem

4.1 Sensor Selection Rationale The HC-SR04 ultrasonic distance sensor was selected over PIR, capacitive, and camera-based alternatives on five criteria: cost (2.50 RMB), detection range (2–450 cm, suitable for the 75 cm occupancy threshold), beam angle (< 15°, minimizing inter-port crosstalk), compatibility with 5V Arduino logic levels, and validated accuracy in peer-reviewed literature [11]. PIR sensors were rejected for susceptibility to thermal false positives; capacitive sensors for insufficient range (< 10 cm); cameras for privacy concerns, high cost, and edge processing requirements.

4.2 Operating Principle and Distance Calculation The HC-SR04 transmits eight 40 kHz ultrasonic pulses upon receiving a 10 μs HIGH pulse on its TRIG pin. The ECHO pin goes HIGH for the duration of the acoustic

round-trip travel time t (microseconds). Distance in centimetres is:

$$d = (t \times 0.0343) / 2$$

where 0.0343 cm/ μ s is the speed of sound at 20°C. Temperature compensation ($\pm 0.17\%$ per °C) was applied in firmware for the 15–35°C operating range encountered in the deployment environment. A 75 cm occupancy threshold was selected after empirical validation: e-bikes present consistently produce readings below 70 cm; vacant ports consistently produce readings above 80 cm; the 5 cm hysteresis band eliminates threshold-straddling oscillation.

4.3 Validation Study Detection accuracy was measured across 200 physical trials: 50 trials each for four e-bike types (standard frame, folding frame, cargo frame, and thick-canvas-seat frame), at ambient temperatures sampled from 15°C, 25°C, and 35°C, with and without moderate ambient noise (50–65 dB). Results: 197/200 correct detections (98.3% accuracy), 0 false positives, 3 false negatives (all in the thick-canvas-seat condition, attributable to extreme

acoustic absorption). The false negative rate of 1.7% in this condition is acceptable given its rarity in practice; redundant inductive sensing is recommended for environments with high proportions of canvas-upholstered e-bikes.

Figure 1: Working principle of the HC-SR04 ultrasonic sensor — transmitter T emits a 40 kHz burst of 8 pulses; receiver R detects the echo; distance d is calculated from round-trip travel time t

Figure 2: HC-SR04 sensor module — key specifications: 0.3 cm resolution, $< 15^\circ$ beam angle, < 2 mA current, 2–450 cm detection range, 5V logic compatible

4.4 Arduino Firmware Two HC-SR04 sensors (Ultrasonic 1 and Ultrasonic 2) are mounted 20 cm above the port surface at 45° downward angle. EchoPin 1 $\rightarrow$ D2, TrigPin 1 $\rightarrow$ D3, EchoPin 2 $\rightarrow$ D4, TrigPin 2 $\rightarrow$ D5. Sequential polling with

60 ms dead time prevents acoustic crosstalk. Five-sample averaging per reading reduces noise variance by a factor of $\sqrt{5} \approx 2.24$.

// HC-SR04 Dual-Sensor Occupancy Detection — Arduino Uno

```
#define TRIG1 3 #define ECHO1 2
#define TRIG2 5 #define ECHO2 4
#define THRESHOLD_CM 75
#define SAMPLES 5

void setup() {
  Serial.begin(9600);
  pinMode(TRIG1,OUTPUT); pinMode(ECHO1,INPUT);
  pinMode(TRIG2,OUTPUT); pinMode(ECHO2,INPUT);
}

float measureDistance(int trig, int echo) {
  float sum = 0;
  for(int i=0; i<SAMPLES; i++) {
    digitalWrite(trig,LOW); delayMicroseconds(2);
    digitalWrite(trig,HIGH); delayMicroseconds(10);
    digitalWrite(trig,LOW);
    sum += (pulseIn(echo,HIGH) * 0.0343) / 2.0;
    delay(10);
  }
  return sum / SAMPLES;
}

void loop() {
  float d1 = measureDistance(TRIG1,ECHO1);
  delay(60); // dead time prevents crosstalk
  float d2 = measureDistance(TRIG2,ECHO2);
  // Transmit to ESP32 via UART
  Serial.print("P1:"); Serial.print(d1<THRESHOLD_CM?"OCC":"VAC");
  Serial.print(",D1:"); Serial.print(d1,1);
  Serial.print(",P2:"); Serial.print(d2<THRESHOLD_CM?"OCC":"VAC");
  Serial.print(",D2:"); Serial.println(d2,1);
  delay(5000); // 5-second polling interval
```

```
}

```

Figure 3: HC-SR04 wiring to Arduino Uno — 5V to VCC, D2 to ECHO, D3 to TRIG, GND to GND

Figure 4: Arduino IDE showing distance measurement code and Serial Monitor output during live data collection

Figure 5: Block diagram — Arduino Uno interfaces HC-SR04 sensors, OLED display, and ESP32 communication module

5. ESP32 Cloud Communication Module 5.1 Hardware and Power Profile The ESP32 (Xtensa LX6 dual-core, 240 MHz) receives sensor data from Arduino via UART, encrypts it with AES-128 using the hardware acceleration unit, and transmits to the cloud server via HTTP POST every 30 seconds. AES-128 key distribution uses a pre-shared key stored in ESP32 NVS (Non-Volatile Storage), never transmitted in plaintext. On the server, the PHP endpoint decrypts using the same pre-shared key. This symmetric scheme is appropriate for a closed deployment where ESP32 nodes are physically secured; asymmetric TLS is recommended for production deployments.

Power measurements: 160 mA active transmission (~2 s per 30-s cycle), 10 mA light sleep (28 s per cycle).

Average current: $(160 \times 2 + 10 \times 28) / 30 \approx 20$ mA. At 5V supply, average power ≈ 100 mW. The solar subsystem (Section 7) provides a 19.2 Wh daily surplus, corresponding to a sustainable supply of 19,200 mWh / 24h / 5V ≈ 160 mA — comfortably exceeding the 20 mA average draw.

5.2 Protocol Stack Protocol / OSI Layer Implementation Security Feature Technology Physical (L1) IEEE 802.11 b/g/n ESP32 internal RF 2.4 GHz, DSSS / OFDM Data Link (L2) Wi-Fi MAC ESP32 hardware WPA2-PSK, CCMP encryption Network (L3) IPv4 DHCP from campus Private subnet, no public IP router Transport (L4) TCP ESP32 WiFiClient Three-way handshake, retransmission Application HTTPS / HTTP POST HTTPClient library AES-128 payload encryption, API (L7) key auth Table 2: SIECS Communication Protocol Stack with Security Features

5.3 Transmission Firmware // ESP32 — Encrypted HTTP POST to Cloud Server #include <WiFi.h> #include <HTTPClient.h>

```
const char* ssid = "CAMPUS_WIFI";
const char* password = "WIFI_PASSWORD";
const char* serverURL = "https://yourserver.com/post-data.php";
const char* apiKey = "YOUR_API_KEY"; // stored in NVS in production

void sendToServer(String p1,float d1,String p2,float d2,float v){
  if(WiFi.status()!=WL_CONNECTED){WiFi.begin(ssid,password);delay(5000);}
  HTTPClient http;
  http.begin(serverURL);
  http.addHeader("Content-Type","application/x-www-form-urlencoded");
  String payload = "api_key="+String(apiKey)
  +"&port1_status="+p1+"&port1_distance="+String(d1,2)
  +"&port2_status="+p2+"&port2_distance="+String(d2,2)
  +"&voltage="+String(v,2);
  int code = http.POST(payload);
  Serial.println(code=="200?"Sent OK":"Error:"+String(code));
  http.end();
}

void loop(){
  // Read Arduino UART, parse sensor data, then:
  static unsigned long last=0;
  if(millis()-last>=30000){ sendToServer(p1,d1,p2,d2,v); last=millis(); }
}
```

Figure 6: SIECS network topology — ESP32 transmits HTTP POST via campus Wi-Fi router to hosting server; PHP scripts write to MySQL database; dashboard served to any browser worldwide

5.4 Measured Latency and Reliability Pipeline Stage Mean (s) Std. Dev. (s) 95th Pct. (s) Sensor → Arduino processing 0.05 0.01 0.07 UART → ESP32 0.01 0.003 0.02 Wi-Fi → Server HTTP POST 0.90 0.35 1.62 PHP processing + DB write 0.80 0.28 1.38 Dashboard poll + render 1.05 0.42 1.91 Total end-to-end 2.81 0.88 6.20
Table 3: End-to-End Latency Measurements (n=1,000 transmission cycles, 4-week period)

Packet loss: 0.8%; all packets recovered by TCP retransmission within the 30-second window. System uptime: 99.1% (3.7 hours downtime across two campus-wide Wi-Fi outages). The 2.81 second mean latency is well within the 30-second update tolerance for occupancy monitoring applications.

6. Automatic Charge Cutoff Subsystem 6.1 Motivation and Battery Chemistry Background
Lithium-ion and LiFePO4 batteries experience accelerated capacity fade when held at 100% SOC due to elevated electrolyte oxidation at high electrode potentials — a mechanism known as calendar aging at high SOC [3]. The US National Renewable Energy Laboratory recommends limiting charging to 80% SOC to maximize cycle life [23]. At a typical campus station without automatic cutoff, chargers continue supplying trickle current indefinitely after the battery nominally reaches full charge, resulting in both calendar aging and energy waste (estimated 8– 12% of total charging energy lost to trickle current in the baseline configuration).

6.2 Circuit Design The circuit uses: C1815 NPN transistor (control switch), 12V relay K1 (power cutoff actuator), two 1N4007 diodes (D1: relay back-EMF protection; D2: polarity protection), 100Ω resistor R1 (base current limiter), 10kΩ fixed resistor R3 (pull-down), and 10kΩ variable resistor R2 (threshold calibration). LED1 = active charging; LED2 = charge complete / cutoff triggered.

When battery voltage is below threshold: R2/R3 divider supplies insufficient base drive; transistor stays cut-off; relay NC contact keeps charging path closed. When voltage reaches threshold (3.9 V/cell for 80% SOC; 4.2 V/cell for 100% SOC): transistor saturates; relay energizes; NC contact opens; charging terminates. R2 allows field calibration without circuit modification.

Figure 7: Automatic battery charge cutoff circuit — relay K1 (12VDC) controlled by NPN transistor Q1 (C1815); threshold set by variable resistor R2 (10kΩ); back-EMF protection diode D1 (1N4007); LED1 indicates active charging, LED2 indicates cutoff triggered

6.3 Battery Longevity Study Three groups of ten 48V/12Ah LiFePO4 e-bike batteries were cycled at 0.5C charge/discharge for 500 cycles:

Capacity @ 500 Projected Cycles to
Group Cutoff Strategy 95% CI
Cycles 80% Threshold
Control None (continuous trickle) 67.3% ±2.1% ~700
100% SOC Relay at 4.2 V/cell 79.8% ±1.8% ~1,100
Cutoff
80% SOC Relay at 3.9 V/cell 91.2% ±1.4% ~1,850
Cutoff

Table 4: Battery Capacity Retention at 500 Cycles — Accelerated Study (n=10 per group)

One-way ANOVA: $F(2,27)=48.3$, nominal $p<0.001$. Post-hoc Tukey HSD: all pairwise group differences significant ($p<0.01$). The 80% SOC strategy achieves 23.9 percentage points higher capacity retention than the control. The projected cycle-life values in Table 4 correspond to an estimated increase from approximately 700 to 1,850 cycles (about 164% relative to the 700-cycle baseline); this projection should be treated as an accelerated-study estimate rather than a direct field-life measurement. For a typical 48V/12Ah e-bike battery costing 400 RMB, this represents a per-user saving of approximately 560 RMB over the extended lifetime.

7. Solar Energy Harvesting and LDR Tracking 7.1 System Overview The solar subsystem comprises a 5W polycrystalline PV panel, TP4056 charger module (max 1A), 3.7V/3000mAh LiPo battery, MT3608 boost converter (3.7V→5V, max 2A), two GL5528 LDR sensors, and a 9g servo motor. The subsystem provides complete energy autonomy for all SIECS electronics with a 19.2 Wh daily surplus. Over a 50-port station (five 10-port banks), annual grid offset = $5 \times 19.2 \times 365 / 1000 \approx 35$ kWh, equivalent to approximately 17.5 kg CO₂ avoided annually

(at the average Chinese grid emissions factor of 0.5 kgCO₂/kWh [24]).

7.2 LDR Sensor Physics GL5528 LDRs exhibit photoconductive behavior: incident photons with energy greater than the semiconductor bandgap (approximately 1.8 eV for CdS) excite electrons from valence to conduction band, increasing carrier density and reducing resistivity. Resistance ranges from ~1 MΩ (dark) to ~2 kΩ (1000 lux direct sunlight), providing a three-decade dynamic range. In the potential divider configuration with $R_0=10\text{k}\Omega$, $V_{\text{out}} = V_{\text{cc}} \times R_{\text{LDR}} / (R_0 + R_{\text{LDR}})$ maps irradiance to a 0–5V signal, converted by the Arduino 10-bit ADC to 0–1023 (lower value = brighter light).

Figure 8: Light-Dependent Resistor (LDR) operating principle — resistance decreases under illumination as photon absorption creates electron-hole pairs in the semiconductor

7.3 Tracking Firmware // LDR Single-Axis Solar Tracker #include <Servo.h> #define LDR_L A0 #define LDR_R A1 #define SRV_PIN 9 #define DEADBAND 50 // ADC counts (~0.5 degree equivalent) #define STEP 2 // degrees per adjustment #define SAMPLES 5 // ADC readings to average Servo srv; int angle=90;

```
int avgRead(int pin){
  long s=0;
  for(int i=0;i<SAMPLES;i++){s+=analogRead(pin);delay(10);}
  return s/SAMPLES;
}
void setup(){ srv.attach(SRV_PIN); srv.write(90); Serial.begin(9600); }
void loop(){
  int L=avgRead(LDR_L), R=avgRead(LDR_R), diff=L-R;
  if(abs(diff)>DEADBAND){
    // Lower ADC = brighter. Rotate toward brighter side.
    angle=constrain(angle+(diff>0?-STEP:STEP),10,170);
    srv.write(angle);
  }
  Serial.print("L:");Serial.print(L);
  Serial.print(" R:");Serial.print(R);
  Serial.print(" Ang:");Serial.println(angle);
  delay(500);
}
```

Figure 9: LDR solar tracking block diagram — Arduino reads both LDR sensors, computes differential, and commands servo motor to align PV panel; harvested energy charges LiPo battery through TP4056 module

Figure 10: Potential divider circuit for LDR output voltage — V_{cc} , fixed resistor R_0 , LDR, and output voltage V_o connected to Arduino analog input pin

Figure 11: Servo feedback control loop — Micro Controller sends position commands to Servo Control Circuit, which drives the motor; position potentiometer provides feedback to close the control loop

7.4 30-Day Energy Efficiency Study vs. Avg. Daily Std. vs. Configuration 95% CI Fixed Output (Wh) Dev. Horizontal Tilt Fixed horizontal (0°) 14.2 ±0.8 (13.8–14.6) Baseline — Fixed optimal tilt (25°) 17.8 ±0.6 (17.5–18.1) +25.4% Baseline LDR single-axis tracker 21.7 ±0.9 (21.3–22.1) +52.8% +21.9% Table 5: 30-Day Solar Energy Output Study — 5W PV Panel (n=30 days per configuration, latitude 25°N)

One-way ANOVA: $F(2,87)=112.4$, nominal $p<0.001$. Tukey HSD: all pairwise differences significant (nominal $p<0.001$). The 21.7 Wh mean daily harvest exceeds electronics consumption (2.5 Wh) by 19.2 Wh, confirming complete energy autonomy. The 21.9% improvement over fixed optimal-tilt is consistent with the 19–23% range reported by Azimi et al. [17] for single-axis LDR trackers at similar latitudes.

8. Cryptographic Session-Based Payment Security System
8.1 Vulnerability of Static Payment Codes A structured survey of 147 campus e-bike users found that 56 respondents (38.1%) had used a remotely reused static payment code to initiate charging payment without physically being present at the port. Operator records confirmed approximately 47 fraudulent payment incidents per week and estimated monthly revenue loss of approximately 580 RMB at the studied station. Three distinct fraud patterns were identified: (1) remote payment for a port another user physically occupies; (2) sharing copied payment codes among friends to avoid

payment; (3) reserving ports remotely without intending to charge promptly, causing port-blocking. The survey was conducted anonymously; Institutional Review Board exemption was obtained prior to data collection.

Figure 12: Static payment code at the existing campus charging station — permanently affixed and reusable remotely, enabling unrestricted fraudulent payment and port reservation abuse

8.2 HMAC-SHA256 Token Architecture Upon occupancy detection, the server generates a cryptographic session token:

$T_i = \text{HMAC-SHA256}(K_{\text{secret}}, \text{port_id} \parallel \text{session_id} \parallel \text{unix_timestamp})$

K_{secret} is a 256-bit server-side secret stored exclusively as an environment variable. The session_id is a monotonically increasing counter providing uniqueness even within the same second. The token is embedded in a secure payment URL, displayed on the OLED screen, and invalidated immediately upon session termination.

Validation checks: (1) valid HMAC for the given port and session; (2) token not previously used (server-side token registry prevents replay); (3) token age ≤ 60 minutes.

8.3 Server-Side PHP Implementation <?php // Cryptographic session token generation and payment management require_once 'payment/session_manager.php';

```
function generateSessionToken($portId, $sessionId) {
    $key = getenv('SIECS_SECRET_KEY'); // never hardcoded
    $data = $portId.'|'.$sessionId.'|'.time();
    $token = hash_hmac('sha256', $data, $key);
    $db = getDBConnection();
    $db->prepare('INSERT INTO session_tokens
        (token,port_id,session_id,created_at,expires_at,used)
        VALUES(?,?,?,NOW(),DATE_ADD(NOW(),INTERVAL 60 MINUTE),0)')
    ->execute([$token,$portId,$sessionId]);
    return $token;
}

function generatePaymentLink($portId, $sessionId) {
    $token = generateSessionToken($portId, $sessionId);
    $url = 'https://yourserver.com/pay?t='.$token.'&p='.$portId;
    // Token embedded in payment URL; displayed on OLED as short URL or NFC
    payload
    return $url;
    return $url; // returned to ESP32 for OLED display
}

// Validate token on payment
function validateToken($token, $portId) {
    $db = getDBConnection();
    $stmt = $db->prepare('SELECT * FROM session_tokens
        WHERE token=? AND port_id=? AND used=0
        AND expires_at > NOW()');
    $stmt->execute([$token,$portId]);
    if($stmt->rowCount()===0) return false;
    $db->prepare('UPDATE session_tokens SET used=1 WHERE token=?')
    ->execute([$token]);
    return true;
}
?>
```

Figure 13: Circuit design of the cryptographic payment display module — Arduino Uno connected to SSD1306 OLED display (128×64 pixels, I2C) on breadboard; session payment URL rendered from server-generated HMAC token

Figure 14: Complete integrated circuit — cryptographic payment module combined with HC-SR04 ultrasonic sensor; session payment token is generated only upon confirmed physical e-bike presence, preventing remote fraud

8.4 Security Evaluation Results Attack Vector Static Code Exposure HMAC Token Defense Test Result Remote scan after session Permanently valid Token invalidated at session 100/100 blocked end end (nominal $p < 0.001$) Token replay (same session N/A — static Server registry rejects reuse 50/50 blocked rescan) (nominal $p < 0.001$) Brute-force token prediction N/A 2^{256} HMAC-SHA256 Computationally space infeasible Photo during active session Valid indefinitely Valid ≤ 60 min; invalidated Attack window on disconnect reduced to session only Table 6: Security Evaluation — 150 Systematic Attack Tests (100 remote scan + 50 replay attempts)

9. Complete Charging Station Infrastructure 9.1 Subsystem Integration and Communication All SIECS subsystems communicate through the Arduino Uno as the central edge controller.

The ultrasonic sensing loop (Section 4) runs at 5-second intervals and outputs occupancy and distance data via UART to the ESP32. The solar tracker (Section 7) runs concurrently on the same Arduino via interrupt-driven servo updates every 500 ms, sharing no I/O pins with the sensing subsystem. The charge cutoff circuit (Section 6) operates fully autonomously in hardware — the Arduino monitors the relay state via a digital input pin and encodes cutoff events in the UART stream. The OLED display refreshes every 5 seconds with latest occupancy, voltage, elapsed time, and the current session payment token. The ESP32 batches all incoming UART data and transmits to the cloud server every 30 seconds. This architecture ensures that each subsystem continues to function independently even if the cloud connection is lost — the cutoff circuit stops overcharging, the display shows local status, and the solar tracker continues harvesting energy regardless of network state.

Figure 15: SIECS function module design — Arduino edge controller interfaces all perception-layer sensors and actuators; ESP32 gateway connects to cloud infrastructure (Server Application, Business, and Data Service layers); end users access via Data Presentation Layer

Figure 16: Ultrasonic subsystem block diagram — Arduino controls Ultrasonic 1 and Ultrasonic 2 sensors mounted 20 cm above port surface; both sensor readings are combined for reliable occupancy determination

Figure 17: Complete SIECS system integration diagram — all five subsystems shown: ultrasonic sensing array, auto charge cutoff circuit, ESP32 cloud database pipeline, cryptographic payment module with OLED, and solar panel with LiPo battery and voltage booster

10. AI-Based Charging Optimization **10.1 MDP Problem Formulation** The scheduling problem is formulated as a finite-horizon Markov Decision Process. Let $P=\{p_1, \dots, p_N\}$ be N charging ports and $Q(t)$ the user queue at time t . Each user u_i is characterized by (arrival_time, requested_duration, battery_level, priority). The objective is to maximize:

$$U = \alpha \cdot \text{Throughput} + \beta \cdot \text{Fairness} + \gamma \cdot \text{EnergyEfficiency} + \delta \cdot \text{PortUtilization}$$

Throughput = completed sessions/hour. Fairness = $1/(1+\text{MaxWait})$. EnergyEfficiency = $1 - \text{WastedEnergy}/\text{TotalEnergy}$. PortUtilization = fraction of port-hours productively occupied. Weights tuned by grid search on 20% validation holdout: $\alpha=0.35$, $\beta=0.30$, $\gamma=0.20$, $\delta=0.15$.

10.2 FCFS Baseline First-Come-First-Served assigns the first available port to the first-arriving user. $O(1)$ complexity, no training required, trivially fair in arrival order. Limitations: no demand prediction, no energy awareness, vulnerable to monopolization by early long-duration arrivals during high-demand periods.

10.3 Greedy Time-Slot Algorithm (GTSA) At each 5-minute scheduling epoch, GTSA greedily assigns users to ports by maximizing immediate utility gain. $O(|Q| \times |P_{\text{avail}}|)$ per epoch — approximately 0.8 ms at $N=50$, negligible relative to the 5-minute epoch. Algorithm GTSA Input: P_{avail} (available ports), Q (user queue ordered by arrival) Output: Assignment $A: Q \rightarrow P_{\text{avail}}$ 1: WHILE $Q \neq \emptyset$ AND $P_{\text{avail}} \neq \emptyset$ DO 2: $(u^*, p^*) \leftarrow \text{argmax}_{\{u \in Q, p \in P_{\text{avail}}\}} \text{utility}(u, p, \text{state})$ 3: $A(u^*) \leftarrow p^*$; $Q \leftarrow Q \setminus \{u^*\}$; $P_{\text{avail}} \leftarrow P_{\text{avail}} \setminus \{p^*\}$ 4: RETURN A

utility(u, p, state):
 $= \alpha \cdot (1 - |p.\text{freeTime} - u.\text{duration}| / \text{MAX_DURATION}) // \text{duration fit}$
 $+ \beta \cdot (\text{currentTime} - u.\text{arrivalTime}) / \text{MAX_WAIT} // \text{wait urgency}$
 $+ \gamma \cdot \text{solarRate}(\text{currentTime}) \cdot (1 - u.\text{batteryLevel}) // \text{green priority}$

10.4 RL-DSA: Reinforcement Learning-Based Dynamic Scheduling **10.4.1 State Space** (132 features) • 50 binary port occupancy flags • 50 normalised per-port charging durations (0–1) • 1 queue length (normalised) • 20 normalised user wait times (zero-padded) • 2 time-of-day features: $\sin(2\pi h/24)$ and $\cos(2\pi h/24)$ for cyclic encoding • 7 day-of-week one-hot features • 1 normalised solar generation rate (0–1) • 1 ARIMA next-hour demand forecast (normalised)

10.4.2 Action Space and Reward 51 discrete actions: assign front-of-queue user to port p_i (actions 1–50) or defer to next epoch (action 51). Reward: $R(s, a) = U(\text{assignment}(s, a)) - 0.1 \cdot \text{DeferralPenalty}$, where DeferralPenalty=1 if defer, else 0. Regularization coefficient 0.1 discourages excessive deferral without

suppressing legitimate strategic deferral.

10.4.3 Network Architecture and Training Layer Neurons / Output Activation Trainable Parameters Input 132
— — **Hidden Layer 1 256 ReLU 34,048 Hidden Layer 2 128 ReLU 32,896 Output 51 (Q-values) Linear 6,579**
Total — — 73,523 Table 7: RL-DSA Deep Q-Network Architecture

Hyperparameter Value Hyperparameter Value
Optimizer Adam (lr=0.001) Discount factor γ 0.95
Replay buffer 10,000 transitions Minibatch size 64
Target net update Soft, $\tau=0.01$ ϵ start $\rightarrow$ end 1.0 $\rightarrow$ 0.05
 ϵ decay schedule Linear over 500 Training episodes 800
episodes
Convergence episode 523 (± 18 across 5 Validation reward 0.847 ± 0.012
runs)
Train / val split 80% / 20% ARIMA MAPE 8.3%
Table 8: RL-DSA Hyperparameters and Training Results

10.4.4 Training Stability and Convergence To assess training stability, the DQN was trained independently five times with different random seeds. Convergence occurred at episode 523 ± 18 (mean $\pm$ std) across runs, with validation rewards of 0.847 ± 0.012 . The low variance (coefficient of variation: 1.4%) confirms that the training procedure is stable and the learned policy is not sensitive to random initialization. The Q-value estimates for the five most-common state configurations varied by less than 2.3% across the five trained models, indicating consistent policy learning. Inference time: 2.1 ms per scheduling decision on the cloud server (Intel Core i5-8250U), negligible relative to the 5-minute epoch.

10.4.5 ARIMA Demand Forecasting A seasonal ARIMA(2,1,2)(1,1,1)₂₄ model was selected by AIC criterion from a grid search over (p,d,q) in $\{0,1,2\} \times \{0,1\} \times \{0,1,2\}$ and (P,D,Q) in $\{0,1\} \times \{0,1\} \times \{0,1\}$. Fitted on 4,380 hourly observations (6 months). Validation MAPE: 8.3% vs. 14.7% for seasonal naive baseline (43.5% improvement). Ablation: removing the ARIMA feature (feature 132) from the state vector reduces RL-DSA port utilization improvement from 34.2% to 27.1%, confirming the forecast contributes 7.1 percentage points (21%) of total RL-DSA improvement.

11. Cloud Monitoring and Data Infrastructure 11.1 Privacy and Data Governance User data collected by SIECS includes WeChat OpenID (hashed), port occupancy timestamps, charging duration, and energy consumption per session. No personally identifiable information (PII) beyond the hashed identifier is stored. Phone numbers, if provided for non-WeChat notification delivery, are stored as SHA-256 hashes. Data is retained for 24 months for analytics and then purged. These practices are consistent with China's Personal Information Protection Law (PIPL) and, for any future deployments in North America, with applicable US state privacy regulations. For an international deployment context such as a University of Michigan campus, GDPR- equivalent anonymization (differential privacy noise on aggregate analytics) would be applied.

11.2 Database Schema CREATE TABLE port_status (port_id INT PRIMARY KEY, occupancy ENUM('VACANT','OCCUPIED','FULL_AWAITING') NOT NULL, distance_cm FLOAT, voltage_v FLOAT, last_updated TIMESTAMP DEFAULT CURRENT_TIMESTAMP ON UPDATE CURRENT_TIMESTAMP); CREATE TABLE charging_sessions (

session_id INT AUTO_INCREMENT PRIMARY KEY,
port_id INT NOT NULL, user_id INT,
start_time TIMESTAMP, end_time TIMESTAMP,
duration_min INT, energy_wh FLOAT,
cutoff_reason ENUM('AUTO_FULL','USER_DISCONNECT','TIMEOUT'),
FOREIGN KEY (port_id) REFERENCES port_status(port_id)
);
CREATE TABLE session_tokens (
token CHAR(64) PRIMARY KEY,
port_id INT NOT NULL, session_id INT NOT NULL,

```

created_at TIMESTAMP DEFAULT CURRENT_TIMESTAMP,
expires_at TIMESTAMP, used TINYINT(1) DEFAULT 0
);
CREATE INDEX idx_port_updated ON port_status(last_updated);
CREATE INDEX idx_session_port ON charging_sessions(port_id, start_time);

```

11.3 PHP Data Ingestion <?php // post-data.php — validated, SQL-injection-safe data ingestion

```

header('Content-Type: application/json');
if($_SERVER['REQUEST_METHOD']!='POST'){http_response_code(405);exit;}
if(($_POST['api_key']?'')!=getenv('SIECS_API_KEY')){ http_response_code(403);echo
json_encode(['error'=>'Unauthorized']);exit; } $portId =
filter_input(INPUT_POST,'port_id',FILTER_VALIDATE_INT); $status =
in_array($_POST['port1_status']??'','OCCUPIED','VACANT') ? $_POST['port1_status'] : 'VACANT';
$dists = filter_input(INPUT_POST,'port1_distance',FILTER_VALIDATE_FLOAT); $voltage =
filter_input(INPUT_POST,'voltage',FILTER_VALIDATE_FLOAT); try { $db=$db??new
PDO('mysql:host=localhost;dbname=siecs_db', getenv('DB_USER'),getenv('DB_PASS'),
[PDO::ATTR_ERRMODE=>PDO::ERRMODE_EXCEPTION]); $db->prepare('INSERT INTO port_status
(port_id,occupancy,distance_cm,voltage_v) VALUES(?,?,?,?) ON DUPLICATE KEY UPDATE
occupancy=VALUES(occupancy), distance_cm=VALUES(distance_cm),voltage_v=VALUES(voltage_v),
last_updated=NOW()') ->execute([$portId,$status,$dists,$voltage]); echo
json_encode(['status'=>'ok','port_id'=>$portId]); } catch(PDOException $e){
http_response_code(500);error_log('SIECS:'. $e->getMessage()); } ?>

```

11.4 Dashboard Features and Push Notifications

Feature Description	Update Frequency	Live Occupancy	Grid
5×10 color-coded port grid (green=vacant, Every 30 seconds red=occupied, amber=overstay)			
Voltage Time Series Chart.js line chart of charging voltage per active Every 30 seconds session Usage Heatmap 24h × 7-day			
occupancy heatmap from 6 months of Daily rebuild historical data Energy Dashboard Daily/weekly kWh per port; anomaly flags for outlier Daily rebuild consumption Charge Complete Alert Push notification when auto cutoff triggers Within 30 seconds of event Charger Disconnect Alert Push notification on mid-session voltage drop to zero Within 30 seconds Overstay Warning Push notification 30 minutes after charge complete if Triggered at 30-min mark e-bike not retrieved Optimal Time AI-predicted low-demand window notification Hourly from ARIMA Recommendation forecast			

Table 9: Web Dashboard Features and Push Notification Events

12. Experimental Results and Statistical Evaluation

12.1 Experimental Design A four-week controlled experiment was conducted at a real campus charging station (50 ports, 5 banks of 10). Weeks 1–2 collected baseline FCFS data. Weeks 3–4 used a concurrent A/B/C design: banks 1–2 assigned to FCFS (n=2,184 sessions), banks 3–4 to GTSA (n=2,007 sessions), bank 5 to RL-DSA (n=1,045 sessions). Assignment was fixed by bank rather than randomized per session to avoid scheduling policy contamination. All three algorithms operated on identical hardware with identical sensor configurations. Statistical analysis used independent-samples t-tests for continuous metrics and Fisher's exact test for categorical metrics. Effect sizes are reported as Cohen's d. All reported differences are significant at nominal $p < 0.001$ unless stated.

12.1.1 Statistical Interpretation Note The results below retain the numerical estimates from the supplied study manuscript. No raw dataset was available for independent re-analysis in this revision. The main methodological revision is therefore interpretive: the fixed bank-level assignment is explicitly acknowledged as a clustering limitation, and nominal session-level p-values are not presented as proof of causal significance. The reported effect sizes and confidence intervals should be considered the primary descriptive evidence until a cluster-aware re-analysis is performed.

12.2 Port Utilization Mean Util. Peak-Hour Algorithm 95% CI vs. FCFS Cohen's d (%) Util. (%) FCFS (Baseline) 58.3 (56.6–60.0) 91.7 ± 3.1 — — GTSA 68.1 (66.6–69.6) 94.2 ± 2.8 +16.8% 1.24 (large) RL-DSA 78.2

(76.9–79.5) 96.8 ± 2.2 +34.2% 2.31 (very large) Table 10: Port Utilization Comparison (n sessions per algorithm as above, all vs. FCFS significant at nominal p<0.001)

The RL-DSA advantage (Cohen's d=2.31, very large effect) is attributable to two learned behaviors: (1) strategic deferral of low-urgency short-duration requests during high-demand windows, filling those windows with higher-priority sessions; (2) proactive assignment during predicted demand surges (from ARIMA forecast), reducing simultaneous multi-port idling. Ablation removing the ARIMA feature reduces RL-DSA improvement to +27.1%, confirming 7.1 pp (21%) is attributable to forecasting.

12.3 User Wait Time Mean Wait 95th Pct. Max Algorithm 95% CI vs. FCFS Cohen's d (min) (min) (min) FCFS 18.7 (17.8–19.6) 47.3 83.4 — — GTSA 14.2 (13.5–14.9) 38.6 64.2 –24.1% 0.54 (medium) RL-DSA 13.3 (12.7–13.9) 31.4 52.7 –28.9% 0.62 (medium) Table 11: User Wait Time Comparison (all vs. FCFS differences significant at nominal p<0.001)

The 33.6% reduction in 95th percentile wait time and 36.8% reduction in maximum wait time under RL-DSA indicate that the learned policy not only improves average performance but specifically prevents the extreme outlier delays that generate the most user dissatisfaction. This tail-risk reduction is particularly valuable for campus users with time-constrained schedules.

12.4 Energy Consumption Daily Energy Overcharge Configuration 95% CI vs. FCFS (kWh) Events/Day FCFS (no cutoff) 42.6 (41.1–44.1) 23.4 ± 4.2 — GTSA + Auto Cutoff 37.2 (36.0–38.4) 14.7 ± 3.1 –12.7% RL-DSA + Auto Cutoff 34.8 (33.7–35.9) 2.1 ± 1.3 –18.4% Table 12: Daily Energy Consumption and Overcharge Events (all differences nominal p<0.001)

The 91% reduction in overcharge events (23.4→2.1/day) is primarily attributable to the hardware auto cutoff circuit. RL-DSA contributes an additional 5.7 pp energy reduction by preferentially scheduling sessions during peak solar generation periods, reducing net grid draw. The 2.1 residual daily overcharge events are attributable to sensor calibration drift at two ports; monthly recalibration is expected to reduce this to near zero.

12.5 Threats to Validity Internal validity: the A/B/C bank assignment is fixed rather than randomized per session, which could introduce confounds if port banks differ in demand characteristics. Analysis of pre-experiment FCFS data across all five banks showed no significant difference in arrival rates between banks (F(4,115)=0.84, p=0.50), supporting the assumption of comparable baseline demand.

External validity: the study was conducted at a single campus station during a four-week period in spring semester. Demand patterns may differ across seasons, campus types, and geographic regions. The generalizability of the RL-DSA policy to stations with different port counts, user populations, or solar irradiance profiles requires validation through the federated learning extensions described in Section 14.

12.6 Complete Results Summary GTSA vs. RL-DSA vs. Metric p-value Effect Size (d) FCFS FCFS Port utilization +16.8% +34.2% < 0.001 2.31 (very large) Mean wait time –24.1% –28.9% < 0.001 0.62 (medium) 95th pct. wait time –18.4% –33.6% < 0.001 0.71 (medium) Max wait time –23.1% –36.8% < 0.001 0.85 (large) Daily energy consumption –12.7% –18.4% < 0.001 0.78 (large) Overcharge events/day –37.2% –91.0% < 0.001 3.12 (very large) Payment fraud incidents — –100% < 0.001 — Solar yield vs. fixed tilt — +21.9% < 0.001 2.08 (very large) Battery life extension — +164% vs. no < 0.001 3.47 (very large) cutoff Table 13: Complete Experimental Results with 95% Confidence Intervals, p-values, and Effect Sizes

13. Business Impact and Global Applicability 13.1 The Scale of the Problem Worldwide The infrastructure gap documented in this study is not limited to Chinese university campuses. In the United States, e-bike adoption is growing at approximately 20% annually, with college campuses among the highest- density deployment environments [25]. University of Michigan campuses, for example, have seen e-bike and e- scooter ridership increase by over 300% since 2019. Municipal and campus parking authorities in the US, Europe, and Southeast Asia face identical challenges: no real-time occupancy visibility, no automated battery protection, and no fraud-resistant payment infrastructure. The SIECS architecture — at USD 3.50 per port — is directly applicable in these contexts.

Figure 18: Real-world campus charging station during peak hours — overcrowding, no occupancy visibility, no smart management; this is the baseline condition that SIECS directly addresses

13.2 Stakeholder Value • E-bike users: Remote occupancy checking eliminates approximately 12 minutes of wasted travel per charging cycle. 28.9% wait time reduction. Charging completion push notifications. Battery lifespan extended approximately 164% under 80% SOC cutoff — saving each user an estimated USD 55 in replacement battery costs over 3 years. • Charging station operators: 34.2% higher throughput (serving 34% more users with identical hardware — equivalent to adding 17 virtual ports to a 50-port station). 18.4% electricity cost reduction. Complete elimination of payment fraud. Automated overstay fee collection. Data-driven maintenance identification. • Universities and municipalities: Smart campus credentials. Reduced energy costs. Scalable IoT infrastructure foundation applicable to parking, transit, and building management. Alignment with sustainability goals and US Department of Energy initiatives for smart grid and clean transportation.

13.3 Revenue Model

Price	Service Tier	Target Customer	Key Features (USD/month)
0.15	Real-time occupancy via app or web	Basic Individual rider	Occupancy + optimal time alerts + slot booking
0.50	Battery Care	E-bike owner	80% SOC auto-cutoff module + battery health tracking
2.10	Station Pro	Station operator	Full analytics + AI scheduling + fraud

Price

Service Tier Target Customer Key Features

(USD/month)

prevention + API

Campus University / 175 / year Full platform + hardware + deployment

License municipality support

Table 14: SIECS Service Tiers — USD Pricing for North American Deployment Context

Illustrative market scenario for US university campuses (approximately 4,000 institutions, average 15,000 students, 10% e-bike ownership rate): 6 million potential Basic-tier users. At USD 0.15/month average and 5% penetration: USD 5.4 million annual consumer revenue, excluding Station Pro and Campus License revenue.

14. Limitations and Future Research Directions

14.1 Current System Limitations • **Sensor vulnerability:** HC-SR04 produces false negatives with highly acoustically absorbent materials (1.7% false negative rate in thick-canvas tests). Redundant inductive sensing or low-cost radar (e.g., HLK-LD2410, ~8 RMB) would eliminate this vulnerability. • **Network dependency:** Campus Wi-Fi outages caused 3.7 hours of reduced cloud functionality. A local fallback mode — offline charge cutoff, occupancy on OLED, and local session logging — would maintain core functions during outages. • **Hosting scalability:** The free-tier hosting used in the prototype has concurrent connection limits. Production deployment requires Alibaba Cloud, Tencent Cloud, AWS, or Azure hosting with guaranteed uptime SLAs. • **Solar capacity:** The 5W panel powers only electronics. Meaningful contribution to e-bike charging energy requires 50–100W panels per bank, increasing the per-bank hardware cost by approximately 200 RMB. • **RL-DSA transferability:** Policy was trained on data from one station. Generalization to stations with different demand patterns requires transfer learning or federated training. • **Single-site validation:** The 4-week, single-station experimental design limits external validity. Multi-site replication across diverse campus environments is needed.

14.2 PhD-Level Research Extensions Six research directions are identified that extend directly from this work into PhD-level investigation:

7. Federated Learning for Multi-Station Policy Optimization: A federated DQN framework enabling multiple stations across different campuses to collaboratively improve a shared scheduling policy without exchanging raw user data. Research questions: How should heterogeneous demand patterns be weighted in federated aggregation? What is the minimum number of stations needed to achieve convergence superior to single-station training? This direction aligns with active research in federated learning for smart grid systems [13].

8. Computer Vision and Edge AI for Occupancy Detection: Replacing per-port ultrasonic

sensors with shared overhead cameras running YOLOv8 on a Raspberry Pi 5 edge node. Research questions: What is the minimum camera resolution and frame rate for reliable e-bike detection? How should privacy-preserving on-device inference (no image transmission) be architected? Can visual features (battery indicator lights, plug connection state) provide richer state information than binary presence detection?

9. Multi-Objective Reinforcement Learning for Dynamic Policy Adaptation: Extending RL-DSA to Pareto-optimal multi-objective optimization using Proximal Policy Optimization (PPO) with a learnable reward weight vector. Research questions: Can the system automatically adapt the $\alpha/\beta/\gamma/\delta$ weighting in response to real-time operational context (examination period, sports event, weather)? What is the computational overhead of online weight adaptation versus offline policy switching?

10. Vehicle-to-Grid Integration for Campus Demand Response: As e-bike batteries scale toward 48V/20Ah, SIECS infrastructure can coordinate bidirectional charging to provide demand response services during campus peak pricing windows. Research questions: What bidirectional charging protocol is most cost-effective for e-bike batteries? How should V2G revenue be shared between the station operator and battery-donating users to maintain participation incentives?

11. Blockchain Smart Contract for Transparent Billing: Replacing the centralized PHP payment backend with an Ethereum smart contract to provide immutable, auditable billing records. Research questions: What is the gas cost and latency overhead of on-chain session recording versus a hybrid (hash-on-chain, data-off-chain) approach? How does blockchain billing affect user trust and adoption?

12. Autoencoder-Based Predictive Maintenance: Using the 18,000-session historical dataset to train an LSTM autoencoder for early detection of failing charger units based on anomalous voltage curve patterns. Preliminary analysis identified 6 ports with 15–20% higher energy consumption than the station average, suggesting detectable degradation signatures. Research questions: What reconstruction error threshold optimally balances false positive maintenance alerts against missed failure detections? Can failure prediction lead time of 2–4 weeks (sufficient for preventive maintenance scheduling) be achieved?

15. Conclusion This paper has presented the design, prototype deployment, and experimental evaluation of the Smart IoT-Enabled Charging Station (SIECS). The system simultaneously addresses five critical failures in campus e-bike charging infrastructure — occupancy invisibility, uncontrolled overcharging, payment fraud, grid dependency, and inefficient port allocation — through integrated IoT hardware, AI scheduling, cloud monitoring, cryptographic payment security, and solar energy harvesting.

The reported results show substantial differences across the evaluated performance dimensions. Because the experimental policies were assigned at the charging-bank level rather than randomized at the individual-session level, the reported session-level p-values should be interpreted as nominal rather than fully confirmatory; effect sizes and confidence intervals are therefore emphasized. The proposed RL-DSA algorithm achieves 34.2% improvement in port utilization ($d=2.31$) and 28.9% reduction in mean wait time versus the FCFS baseline, with ablation studies confirming that ARIMA demand forecasting contributes 21% of the total scheduling improvement. The HMAC-SHA256 cryptographic payment security system blocks 100% of 150 tested fraud attacks. The LDR solar tracker improves daily PV yield by 21.9% ($d=2.08$) and provides complete electronics energy autonomy with a 19.2 Wh daily surplus. The automatic 80% SOC charge cutoff extends battery service life by 164% in a 500-cycle accelerated study ($d=3.47$).

The measured prototype hardware cost of approximately 25 RMB per port indicates a potentially low-cost deployment model; however, large-scale economic viability requires further field validation, installation costs, maintenance costs, and production-grade hardware assessment. The six future research directions identified —

federated learning, computer vision sensing, multi-objective RL, V2G integration, blockchain billing, and predictive maintenance — represent a coherent three-to-four year doctoral research program that addresses fundamental open problems in AI-optimized IoT infrastructure.

The identified future directions include federated learning for multi-campus policy generalization and multi-objective reinforcement learning for dynamic operational adaptation. These directions provide opportunities for future research in connected systems, smart infrastructure, and AI-driven resource optimization.

Acknowledgements

The author thanks Professor Lang Xun for expert supervision and sustained encouragement throughout the undergraduate research that forms the foundation of this work, and Shoaib Mahmud Tasin for contributions to the networking subsystem and mobile application development. The author also acknowledges the campus Facilities Management Office for granting access to the charging station for data collection and prototype deployment over the four-week experimental period. This work received no external financial support.

References

- [1] Fishman, E. and Cherry, C. (2016). E-bikes in the mainstream: Reviewing a decade of research. *Transport Reviews*, 36(1), 72–91.
- [2] Nour, B., Cherkaoui, S. and Ksentini, A. (2020). Quality of service aware network slicing for electric vehicles charging management. *IEEE Transactions on Vehicular Technology*, 69(12), 14220–14232.
- [3] Bloom, I., Jones, S.A., Battaglia, V.S., Henriksen, G.L. and Christophersen, J.P. (2003). Effect of cycling regimes on lithium capacity fade. *Journal of Power Sources*, 111(2), 152–159.
- [4] Shaikh, F.K. and Zeadally, S. (2016). Energy harvesting in wireless sensor networks: A comprehensive review. *Renewable and Sustainable Energy Reviews*, 55, 1041–1054.
- [5] Zanella, A., Bui, N., Castellani, A., Vangelista, L. and Zorzi, M. (2014). Internet of Things for smart cities. *IEEE Internet of Things Journal*, 1(1), 22–32.
- [6] Yilmaz, M. and Krein, P.T. (2013). Review of battery charger topologies for plug-in electric vehicles. *IEEE Transactions on Power Electronics*, 28(5), 2151–2169.
- [7] Nour, B., Ksentini, A. and Cherkaoui, S. (2022). Toward smart EV charging: Survey on IoT-enabled management systems. *IEEE Internet of Things Journal*, 9(11), 8152–8171.
- [8] Zhang, L., Li, Y. and Tang, T. (2020). IoT-based smart EV charging management using MQTT protocol. *IEEE Internet of Things Journal*, 7(8), 7372–7383.
- [9] Huang, C. and Li, J. (2019). NFC-based smart bike-sharing with IoT monitoring. *Sensors*, 19(12), 2774.
- [10] Park, S., Kim, H. and Lee, M. (2021). ESP32-based low-cost IoT sensor platform for smart infrastructure. *IEEE Sensors Journal*, 21(12), 13247–13256.
- [11] Wang, F., Zhao, Q. and Liu, S. (2020). Performance evaluation of HC-SR04 for indoor presence detection. *IEEE Transactions on Instrumentation and Measurement*, 69(9), 6840–6849.
- [12] Shi, W., Li, J., Cao, G. and Shen, D. (2019). Deep reinforcement learning for EV charging scheduling in smart grids. *Applied Energy*, 255, 113861.
- [13] Tang, X., Chen, H., Liu, T. and Li, K. (2021). Multi-agent deep reinforcement learning for coordinated EV charging. *IEEE Transactions on Smart Grid*, 12(4), 3283–3294.
- [14] Kim, B. and Park, J. (2020). Genetic algorithm scheduling for shared EV charging stations. *Energy*, 201, 117570.
- [15] Amara-Ouali, Y., Goude, Y., Massart, P., Poggi, J.M. and Yan, H. (2021). A review of electric vehicle load open data and models. *Energies*, 14(8), 2233.
- [16] Hester, R. and Harrison, R. (eds.) (2022). *Energy Harvesting for IoT Applications*. Royal Society of Chemistry.
- [17] Azimi, S., Hamzawy, E. and Farouk, H. (2019). Comparative study of LDR and GPS-based solar tracking systems. *Solar Energy*, 190, 139–147.
- [18] Elbaset, A.A., Ali, H. and Abd-El Sattar, M. (2014). Novel seven-parameter model for photovoltaic modules. *Energy Conversion and Management*, 82, 369–381.
- [19] Kieseberg, P., Leithner, M., Mulazzani, M., Munroe, L., Schrittwieser, S., Sinha, M. and Weippl, E. (2010). QR code security. *Proceedings of MoMM 2010*, 430–435.

- [20] He, D., Kumar, N., Zeadally, S. and Wang, H. (2018). Certificateless provable data possession for smart grid. *IEEE Transactions on Industrial Informatics*, 14(3), 1055–1064.
- [21] University of Michigan–Dearborn CECS (2023). Research in Connected and Autonomous Systems. Available at: <https://umdearborn.edu/cecs/research>.
- [22] Patel, K.K. and Patel, S.M. (2016). Internet of Things: Definition, characteristics, architecture, enabling technologies. *International Journal of Engineering Science and Computing*, 6(5), 6122–6131.
- [23] Smith, K., Saxon, A., Keyser, M., Lundstrom, B., Deng, Z. and Pesaran, A. (2017). Life prediction model for Li-ion battery energy storage systems. *Proceedings of American Control Conference*, 4062–4068.
- [24] International Energy Agency (2023). China Electricity CO2 Emissions Factor. IEA Statistics. Paris: IEA.
- [25] Popovich, N., Gordon, E., Shladover, S.E., Imani Masouleh, L. and Kelley, S. (2022). Electric bicycle adoption in the United States: A systematic review. *Transport Reviews*, 42(4), 512–531.
- [26] McMahon, M., Tuite, D. and Kaveh, M. (2023). Federated learning for distributed IoT resource management. *IEEE Internet of Things Journal*, 10(6), 4921–4935.
- [27] Liu, Y. and Tang, M. (2020). QR code-based mobile payment adoption in China. *Electronic Commerce Research and Applications*, 41, 100978.
- [28] Sutton, R.S. and Barto, A.G. (2018). *Reinforcement Learning: An Introduction*. 2nd ed. MIT Press.
- [29] Box, G.E.P., Jenkins, G.M., Reinsel, G.C. and Ljung, G.M. (2015). *Time Series Analysis: Forecasting and Control*. 5th ed. Wiley.
- [30] Mnih, V., Kavukcuoglu, K., Silver, D. et al. (2015). Human-level control through deep reinforcement learning. *Nature*, 518(7540), 529–533.