

Dell PowerStoreOS 4.3.0.0 Release Notes

Find information about upgrading to this release of PowerStoreOS 4.3.0.0: What is new, what is resolved, and any known issues and their workarounds.

Release Type: Minor (MI)

Topics:

- [Revision history](#)
- [Product description](#)
- [New features](#)
- [Changed features](#)
- [Resolved issues](#)
- [Known issues](#)
- [Limitations](#)
- [Environmental and system requirements](#)
- [Installation and upgrade considerations](#)
- [Where to get help](#)

Revision history

Table 1. Document revision history

Revision	Date	Description
A00	December 2025	Initial release notes for PowerStoreOS 4.3.0.0 (Build: 2611831)
A01	January 2026	Added PSSSL09F-191 to Resolved issues

Product description

The ground-breaking Dell PowerStore storage system achieves new levels of operational simplicity and agility, using a container-based architecture, advanced storage technologies, and intelligent automation to unlock the power of your data.

Based on a scale-out architecture and hardware-accelerated advanced data reduction, PowerStore clusters are designed to deliver enhanced resource utilization and performance that keeps pace with application and system growth.

PowerStore T and PowerStore Q appliances provide organizations with all the benefits of an enterprise unified storage platform for block, file and vVol data, while enabling flexible growth with the intelligent scale-up and scale-out capability of appliance clusters.

Features include:

- All NVMe Platform:
 - Active/active architecture
 - Container-based PowerStoreOS
 - Block, File, and vVols
 - NVMe Flash and Storage Class Memory (SCM) media support
 - Front-End Connectivity:
 - FC: 32 Gb NVMe/FC, 32/16/8 Gb FC
 - Ethernet: 100/25/10 GbE, NVMe/TCP: 100/25/10 GbE iSCSI and File
 - Compact 2U starting form factor
- Enterprise Data Services and Data Reduction:
 - Inline deduplication and compression

- Native asynchronous and synchronous replication
- Snapshots and space efficient thin clones
- Advanced drive failure protection and sparing technology
- Simple and intelligent Management and Serviceability:
 - Embedded management
 - Built in AI for simple, autonomous storage administration and proactive health analytics
 - APEX AIOps Infrastructure Observability
 - VM Visibility
 - Anytime Upgrade Program (Lifecycle Extension)
 - Integration with automation framework
- Flexible and Granular Scalability:
 - Scale up in single drive increments, up to 5.9 PBe per PowerStore Gen 2 appliance and 6.16 PBe per PowerStore 500 appliance
 - Scale out to four appliances, up to 24.64 PBe per cluster
 - Scale down
- VMware: VASA 4.0\vvols 3.0 and VASA 3.0\vvols 2.0 support

PowerStore X model customers: For the latest how-to technical manuals and guides for your model, download the PowerStore 3.2.x Documentation Set from the [PowerStore Info Hub](#).

New features

The following features were added in this release:

Table 2. New features in PowerStoreOS 4.3.0.0

Feature name	Feature description
30 TB QLC SSDs	Added support for 30 TB SSDs in PowerStore 3200Q and 5200Q appliances, increasing capacity density and improving cost efficiency.
Dynamic licensing	Introduced dynamic licensing to simplify the management of Dell product licenses. When Support Connectivity is enabled on a PowerStore cluster, the system automatically obtains a license from Dell. For clusters without Support Connectivity, the offline license registration process has been improved to make license management easier.
Fast drive copy	Added the ability to copy the contents of an SSD to a new SSD in cases of drive wear, simplifying SSD replacement and improving system serviceability. An automatic mode engages when an SSD reaches 97% wear that copies the data to a new SSD, allowing the safe removal of the worn-out SSD.
Multiparty authorization	Added support for multiparty authorization (MPA). When enabled, operations that are considered critical, such as volume deletion, require secondary approval from another user before they can proceed.
NFSv4.2	Added support for NFSv4.2 with advanced features to enhance performance, security, and functionality for enterprise file workloads.
REST API volume group mapping	Added REST API operations that enable mapping a volume group to a host or host group in a single request. All volumes in the volume group are mapped in one operation, eliminating repetitive per-volume mappings and simplifying provisioning workflows.
Synchronous replication over Fibre Channel for block resources	Added support for synchronous replication over Fibre Channel (FC) for block resources to enable use of the existing network infrastructure, enhance security, and ensure fault domain separation.
Asynchronous replication over Fibre Channel for file resources	Added support for asynchronous replication over Fibre Channel (FC) for file resources to enable use of the existing network infrastructure, enhance security, and ensure fault domain separation.
File Metro replication with automatic failover	Added support for MetroSync with active-passive NAS configurations and witness-based failover to support seamless disaster recovery and replace Unity MetroSync deployments.

Table 2. New features in PowerStoreOS 4.3.0.0 (continued)

Feature name	Feature description
File top talkers	Added support for real-time monitoring of I/O activity on PowerStore file systems and NFS datastores through the REST API, enabling performance optimization and workload troubleshooting.
File service command API integration	Enabled access to a subset of file-related service commands through the REST API, simplifying troubleshooting and improving NAS server management.
IP packet reflect for NAS server interfaces	Added support for IP packet reflect on NAS servers. When enabled, outbound packets return directly to the originating host or router, bypassing routing and Address Resolution Protocol (ARP) lookups to improve network efficiency.
Redirected restore	Added support for centralized NAS servers to redirect restore operations, reducing the impact on production NAS servers.

Changed features

The following features have changed in this release:

Table 3. Changed features in PowerStoreOS 4.3.0.0

Feature name	Feature description
Customizable user dashboards	Added support for user-customizable dashboards in PowerStore Manager. Users can personalize dashboards by adding, removing, and rearranging widgets, including new capacity and performance chart widgets. This enhancement allows for faster troubleshooting and more efficient monitoring of critical system metrics, while also allowing users to save templates tailored for specific use cases.
File import	Updated the In-Band Migration Tool (IMT) to support migrating NFSv4-enabled file systems from Unity to PowerStore. This enhancement enables seamless migration without requiring protocol reconfiguration or downgrades. NOTE: NAS servers with NFSv4 enabled can be imported from Unity systems to PowerStore systems running PowerStoreOS 4.3 or later. However, NFSv4.2 advanced features such as security labels and sparse files do not persist after the import.
FQDN with LDAP	Added support for Fully Qualified Domain Names (FQDNs) in NAS LDAP client configurations, simplifying server updates and reducing the need for reconfiguration.
Improved cluster rollback	Added the ability to reinitiate automatic cluster rollback if a rollback fails during a non-disruptive upgrade (NDU).
PowerStore Manager UI enhancements	Introduced usability enhancements in PowerStore Manager to reduce errors, streamline workflows, and provide a more intuitive management experience: • Added confirmation dialogs for migration and Metro Witness actions • Added more granular retention policy options • Added the ability to export the Watchlist • Expanded QoS management capabilities • Simplified port speed modification

Resolved issues

The following high severity issues are resolved in this release:

Table 4. Issues resolved in PowerStoreOS 4.3.0.0

Issue ID	Description
PSSLDF-32943	When the storage system encounters metadata inconsistencies, it can generate an xtrace snapshot. However, the volatile xtrace snapshot can be unexpectedly collected by data collection (DC) to the

Table 4. Issues resolved in PowerStoreOS 4.3.0.0 (continued)

Issue ID	Description
	dump package using other profiles than the xtraceSnap profile, such as the essential profile. This issue may cause the loss of the volatile xtrace snapshot when the DC dump package containing the snapshot exceeds the retention time.
PSSLDF-32407	When a storage system detects auto-recoverable metadata inconsistencies, an xtrace snapshot can be generated silently without a fault alert. Since users are unaware of the xtrace snapshot, it may remain uncleared for a long time. If a more severe metadata inconsistency is detected that needs an xtrace snapshot, the snapshot cannot be generated because the previous xtrace snapshot still exists.
PSSLDF-30651	In rare cases, the source appliance may experience a Data Unavailable (DU) condition when resuming a replication session after a partial copy due to misaligned resume and transfer addresses.
PSSLDF-28383	When a non-disruptive upgrade (NDU) from PowerStoreOS 4.0.x to 4.1.x is performed, a required configuration file for the internal metrics database may not be created. If the metrics database service stops and the node is rebooted, the database may be re-initialized, causing PowerStore Manager to become inaccessible.
PSSLDF-26992	A metro session modify role operation may fail, leaving the session in a <code>Modify_Role_In_Progress</code> state.
PSSLDF-25385	Alerts may be triggered when the Platform Manager process is restarted because connection information may fail to update promptly.
PSSLDF-25255	When a Common Antivirus Agent (CAVA) configuration file (<code>viruschecker.conf</code>) is uploaded to a NAS server, the configuration information may not be applied to the antivirus settings in PowerStore Manager.
PSSLDF-25131	PowerStore Manager may not support creating two NAS file systems with the same name on different NAS servers during replication configuration.
PSSLDF-24728	LDAP Group Search may fail to work when the Server Type is set to OpenLDAP and the group Member Attribute is set to <code>memberUid</code> .
PSSLDF-24477	If a boot volume is assigned LUN 0 when it is mapped to a host or host group, adding new initiators to the host or host group may fail.
PSSLDF-23212	Running the <code>svc_repair</code> command on a PowerStore 500 storage system may timeout at 60 minutes if a firmware upgrade is required in addition to the normal repair action.
PSSLDF-23124	A PowerStore 3200Q or 5200Q storage system may experience a Data Unavailable (DU) event while the secondary M.2 drive is replaced or repaired.
PSSLDF-20823	The error message <code>There are no mapped ports to storage</code> may incorrectly appear on the Network IPs page in PowerStore Manager when ports are mapped only for replication.
PSSLDF-20123	NAS replications may remain in the <code>Synchronizing</code> state when a non-disruptive upgrade (NDU) is performed on the peer system.
PSSLDF-20041	When the load on a PowerStore system is very high, the scripts responsible with bringing up NAS services on a node may encounter an internal timing issue that causes the NAS container to restart multiple times.
PSSLDF-19853	Due to rsync daemon errors, a storage system may remain unconfigured after completing the Initial Configuration Wizard (ICW), and installing a health check package may also fail.
PSSLDF-19740	If the System Manager (SYM) node receives an emergency shutdown during peer node failover, a Data Unavailable (DU) event may occur during a node failback. This issue can occur when the journal status of the peer is prematurely set to stale, and the journal cannot be recovered.
PSSLDF-19298	Asynchronous replication over Fibre Channel may experience degraded performance during the initial sync phase if I/O module 1 is used for the connection between storage systems.
PSSLDF-18639	If a PowerStore system is powered on but remains unconfigured for an extended period before cluster creation, an out-of-memory (OOM) condition may occur due to the accumulation of repeated cached queries.
PSSLDF-18627	The Pre-Upgrade Health Check may fail to detect when a host is connected to only one node of an appliance, allowing the non-disruptive upgrade (NDU) to proceed and potentially causing a Data Unavailability (DU) event on the host.

Table 4. Issues resolved in PowerStoreOS 4.3.0.0 (continued)

Issue ID	Description
PSSLDF-17316	An appliance node may reboot due to a bad memory pointer encountered during memory deallocation.
PSSLDF-16799	I/O timeouts may occur for up to five minutes and result in a Data Unavailable (DU) condition until both nodes reboot.
PSSLDF-16688	Performing a non-disruptive upgrade (NDU) or rebooting a node may cause the <code>slot GUID</code> of a drive to be reported as all zeros, and the slot state may be set to <code>MGMT_SLOT_STATE_FOREIGN</code> .
PSSLDF-16683	An error may occur while attempting to get or list ONV parameters using the <code>svc_onv_customizing</code> service script.
PSSLDF-16616	Importing duplicate third-party certificates may fail on a storage system that is connected to a remote storage system.
PSSLDF-16416	In rare cases, the <code>REMOTE_SYSTEM_COMMUNICATION_DOWN</code> alert may continue to appear in PowerStore Manager even after it has been cleared.
PSSLDF-15242	If a cluster was originally deployed with PowerStoreOS 2.1 or earlier, the secondary node of an appliance may enter service mode during a non-disruptive upgrade (NDU) from PowerStoreOS 4.1.x to a later version.
PSSLDF-15161	In rare cases, the <code>ONV_BOND_STATE_FAILED</code> alert may be raised and fail to clear automatically because the corresponding events for creating and clearing this alert are handled simultaneously, and the event to clear the alert fails.
PSSLDF-14858	When NVMe reservation commands are run during a non-disruptive upgrade (NDU), delayed commands may cause the NVMe driver to fail, which results in an NDU failure.
PSSLDF-14714	Performing a non-disruptive upgrade (NDU) on the secondary appliance of a multi-appliance cluster may fail if the bulk metrics feature is enabled . The failure occurs due to a conflict between the NDU and the start of bulk metrics processing.
PSSLDF-14376	If the ZeroMQ (ZMQ) server is stopped, there is a low possibility that the Pacemaker proxy service stop may timeout and cause a node reboot. This issue can result in temporary loss of management access during the node reboot.
PSSLDF-13785	When configuring many Global Storage IPs (GSIPs) in a cluster, the Pacemaker may experience performance degradation due to the resulting large Cluster Information Base (CIB). This issue can lead to high CPU usage and delays in cluster operations.
PSSLDF-13358	The KMIP enable command may fail due to a timeout if the system is under heavy load or if management services are failing over between nodes.
PSSLDF-13291	Management rebalance may fail under certain high CPU utilization conditions, resulting in management unavailability.
PSSLDF-12996	If the network environment is unstable or the network settings between appliances are misconfigured, the iBasic transport protocol may encounter a node reboot due to an unexpected state.
PSSLDF-12897	If a storage system fails to properly discover new drives and they are initialized with a drive type of <code>MGMT_DRIVE_TYPE_UNKNOWN</code> , the primary node may reboot repeatedly and enter service mode.
PSSLDF-12459	Some SNMP Notifications may not be sent for alerts that are generated in quick succession.
PSSLDF-12015	PowerStore Manager may display the wrong parent host group in the breadcrumbs when a member host is selected from the Host Information > Initiators tab.
PSSLDF-11954	Removing the last mapping from a volume during high-scale SCSI reservation activity may cause a reservation data mismatch, causing xenv to restart. This issue can result in degraded performance and may escalate to a Data Unavailable (DU) condition.
PSSLDF-10864	An appliance node may report metrics incorrectly, such as showing I/O on a disconnected port or presenting incorrect metrics for a selected port. This mismatch can occur after the deletion of a user-defined bond (UDB), which causes the SCSI target to be redistributed across previously aggregated ports.
PSSLDF-8750	Some system health checks may time out because they take longer than expected to complete.

Table 4. Issues resolved in PowerStoreOS 4.3.0.0 (continued)

Issue ID	Description
PSSLDF-4567	If the xtremapp process is abnormally interrupted while there is active Remote Direct Memory Access (RDMA) traffic between nodes, it may become unresponsive when it tries to stop, which can result in an unexpected node reboot.
PSSLDF-2386	A job with the description <code>GetCiqHealthScoreCommand</code> and no associated Resource Action , Resource Type , or Resource Name may be displayed on the Jobs monitoring tab in PowerStore Manager.
PSSLDF-158	Recovery from a failed non-disruptive upgrade (NDU) on a multi-appliance cluster that is configured as Unified (Block and File) storage may fail when retrying the NDU.
PSSL13G-190	If the Microsoft Management Console (MMC) snap-in is used to change the Common AntiVirus Agent (CAVA) configuration on a NAS server, the changes may not be reflected in PowerStore Manager.
PSSL09F-191	If a PowerStore cluster is deployed using PowerStoreOS 2.x or earlier, Data Path (DP) trace collection may be disabled on the cluster after it is upgraded to PowerStoreOS 4.0 or later.
PSSL09E-580	A non-disruptive upgrade (NDU) may fail if duplicate NTP servers are configured on the storage system.
PSSL09A-278	On a PowerStore 500 appliance, the <code>svc_repair</code> error message that is displayed when the operation is not confirmed correctly is unclear and may cause confusion about the next steps.
PSSL08A-416	If a STIG-enabled system performs a service action that requires root escalation, an Advanced Intrusion Detection Environment (AIDE) scan may raise a false positive tampering alert.
PSSL08A-406	In rare cases, performing a non-disruptive upgrade (NDU) may fail because a software component attempts to read data from a table before the data is populated.
PSSL03B-163	The Data Path (DP) may become unresponsive and restart when flush operations reach the maximum retry count.
PSSL02D-554	A remote retrieve session for a full or bare-metal recovery of a remote snapshot from PowerProtect Data Domain may fail when the size of the protected volume is greater than 32 GB and the size is not a multiple of 2 MB.
PSSL01F-282	Using the host REST API to attach or detach a volume to or from a host that is a member of a host group may fail with an internal error.
PSSL01B-630	If an RxDefinitions package is downloaded but not installed before a non-disruptive upgrade (NDU) to PowerStoreOS 4.1 is performed, the package cannot be deleted from PowerStore Manager.
PSSL01A-239	Performing a non-disruptive upgrade (NDU) from PowerStoreOS 2.x to 3.6 and then to 4.x may result in invalid drive wear metrics. This issue may trigger a false <code>System drives are experiencing high wear rates</code> alert, which remains active until it is manually cleared.

Known issues

The following high severity issues remain unresolved in this release:

Table 5. Known issues in PowerStoreOS 4.3.0.0

Issue ID	Description	Workaround
PSSLDF-38769	If a node on the preferred side of a Metro session goes down or reboots, the status of the Metro session may change to Fractured.	None. The Metro session recovers automatically.
PSSLDF-38520	In a scaled replication environment, I/O may be disrupted if the IP packet reflect feature is toggled on or off while discard changes is performed after a planned failover.	Do not discard changes after a planned failover while toggling the IP packet reflect feature on or off.
PSSLDF-34371	If the System Manager (SYM) is running on Node B, upgrading the drive firmware on SSDs in a SAS expansion enclosure may fail.	Contact your service provider.

Table 5. Known issues in PowerStoreOS 4.3.0.0 (continued)

Issue ID	Description	Workaround
PSSLDF-17458	System Health Check messages in PowerStore Manager are displayed in English, regardless of the selected display language.	None.
PSSL04A-664	An error may occur while accessing an appliance performance chart after performing a non-disruptive upgrade (NDU) from PowerStoreOS 4.2 to 4.3. This error can occur if the charting preferences in the appliance performance chart were modified and saved while running an older version of PowerStoreOS.	Restart PowerStore Manager, then click Reset User Preferences in the User Preferences dialog box.
PSSL04A-650	In rare cases, the Historical Capacity widget on the Capacity dashboard may fail to display data while viewing the last 24 hours of data.	Select a different value from the View drop-down, go to a different page and then go back to the Capacity dashboard page, or refresh the Capacity dashboard page.
PSSL02A-927	The data connection state of a remote system with Fibre Channel connectivity may change to Complete data connection loss after upgrading from PowerStoreOS 4.2 to 4.3.	Perform a Verify and Update operation on the remote system to update the data connection state.

Limitations

The following limitations exist in this release:

Table 6. Limitations in PowerStoreOS 4.3.0.0

Functional area	Limitation
Data Protection	When a planned failover operation is attempted while some of the source file systems are quarantined, the replication session states of those file systems may be shown as Failed on the source cluster and Operating Normally on the destination cluster. The NAS server replication session remains in a partial failover state until the source file systems are recovered, and the failover operation is re-attempted.
Import	Unified (File) import is not supported for Unity systems running Operating Environment (OE) version 5.4.1, 5.5.1, or 5.5.2. For a list of OE versions that support Unified (File) import, see the Supported platforms for NAS server import table in the PowerStore Simple Support Matrix on the PowerStore Info Hub .
Install or Upgrade	A Solaris host with native multipathing (MPxIO) must be running Oracle Solaris 11.4 SRU 35 or later to handle volume failover during an NDU. Contact your service provider for NDU support on earlier versions of Solaris.
Storage – Block	Deleting a host group during an Add Appliance operation fails even though PowerStore Manager reports that the host group was successfully removed.
Storage - File	Customers that use an SFTP client to access file data on a PowerStore T model cluster may experience access issues after upgrading to PowerStoreOS 3.0 or later because support for the following insecure key exchange (KEX) algorithms have been removed: - diffie-hellman-group-exchange-sha1 - diffie-hellman-group14-sha1 The access issue occurs if the customer is using an outdated SFTP client that only supports the KEX algorithms that were removed from the PowerStoreOS. To resolve this issue, the customer must upgrade to a newer version of the SFTP client.
Storage - File	The maximum supported number of Access Control Entries (ACE) that can be added to an Access Control List (ACL) for an SMB share is 650.
Storage - File	If an Access Control List (ACL) is set on an SMB share using a security identifier (SID) that can be resolved to a user, the SID is converted to the format domain\username.
Storage - File	Cloning write-once read-many (WORM) files on a File-Level Retention (FLR) enabled file system is not supported.

Table 6. Limitations in PowerStoreOS 4.3.0.0 (continued)

Functional area	Limitation
Support Connectivity	Support Connectivity cannot be enabled on PowerStore models that are configured with IPv6 for the management network. Support Connectivity is not supported over IPv6.

Environmental and system requirements

This section describes environmental and system requirements in this release.

Host configuration requirements

For host connectivity to PowerStore appliances, see the [E-Lab Navigator Host Connectivity Guides](#).

Simple Support Matrix

For compatibility and interoperability information, see the PowerStore Simple Support Matrix, which can be downloaded from the [PowerStore Info Hub](#).

Installation and upgrade considerations

Always check the **Drivers & Downloads** page on the [Dell Technologies Support site](#) to see if a newer version of PowerStoreOS is available. It is required that customers maintain Dell Technologies software and supported products at the minimum-supported release levels as specified in KB article 000205512: *Minimum, Recommended, and Latest Code Versions for Dell Technologies Servers, Storage, and Networking products*. It is highly recommended to upgrade to the latest or recommended (LTS) version of PowerStoreOS to receive optimal support. For the latest information about supported upgrade paths, see KB article 000175213: *PowerStoreOS Matrix*.

Installation considerations

Before installing a PowerStore cluster, review the documents that are listed under the PowerStore Deployment Guides section of the [PowerStore Info Hub](#).

Upgrade considerations

NOTE: PowerStoreOS 4.x is not supported on PowerStore X model appliances.

Before upgrading the PowerStore cluster, review the *PowerStore Software Upgrade Guide*, which can be downloaded from the [PowerStore Info Hub](#). For systems with Support Connectivity enabled, upgrade packages can be automatically downloaded to the system when they become available on Support. The PowerStore upgrade packages are also available for download from the Support site. However, the upgrade packages can only be accessed when you are logged into the Dell Support Site using an account that is associated with the PowerStore cluster.

NOTE: When using the PowerStore Command Line Interface (CLI), it is recommended that you use the PowerStore CLI version that accompanies each major release of PowerStoreOS. For example, use PowerStore CLI version 4.1 with PowerStoreOS version 4.1.x, use PowerStore CLI version 4.2 with PowerStoreOS version 4.2.x, and use PowerStore CLI version 4.3 with PowerStoreOS version 4.3.x.

Download the upgrade package for a PowerStore T or PowerStore Q cluster

If automatic download is not enabled on your PowerStore cluster, download the PowerStore upgrade package from the Support site.

1. Open a browser and go to the [Dell Technologies Support site](#).
2. Sign into the support account that is associated with your PowerStore cluster.
3. Go to the product page for your PowerStore model, and then go to **Drivers & Downloads**.
4. Identify the PowerStore upgrade package to download by reading the package descriptions. The PowerStore upgrade package is named `PowerStore T OS Upgrade 4.3.0.0-2611831`.
5. Click Download to download the PowerStore upgrade package. The name of the downloaded PowerStore upgrade package is `PowerStoreT-4.3.0.0-2611831-retail.tgz.bin`.
6. See the PowerStore T and PowerStore Q Software Upgrade Guide for instructions on upgrading your PowerStore cluster.

Where to get help

The [Dell Technologies Support site](#) contains important information about products and services including drivers, installation packages, product documentation, knowledge base articles, and advisories.

A valid support contract and account might be required to access all the available information about a specific Dell Technologies product or service.

Notes, cautions, and warnings

 **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.