

Description of new functions of **Wi-Fi** reporting data frame (2024 version):

1.1 Heartbeat login frame

Example: Table number 111111111111 heartbeat frame (default period 3 minutes)

EE EE EE 68 11 11 11 11 11 68 91 04 B3 B3 B3 B3 97 16

When the platform receives a heartbeat frame, it only needs to reply with a consistent message. If it does not reply for three consecutive times, the meter restarts the module.

1.2 645-2007 (wifi reporting and query data block):

Reading identifier: 0x028011FF

Reading function code: 0x11

Data item (BCD format) Unit Bytes		
Remaining amount (XXXXXX.XX) (reserved) 4 bytes		
Overdraft amount (XXXXXX.XX) (reserved) 4 bytes		
Voltage A (XXX.X) 2 bytes	In	
Voltage B (XXX.X) 2 bytes	In	
Voltage C (XXX.XXX) 2 bytes	In	
Current A (XXX.XXX) 3 bytes	A	
Current B (XXX.XXX) 3 bytes	A	
Current C (XXX.XXX) 3 bytes	A	
Total power (XX.XXXX) 3 bytes	KW	
Power A (XX.XXXX) 3 bytes	KW	
Power B (XX.XXXX) 3 bytes	KW	
Power C (XX.XXXX) 3 bytes	KW	
Total power factor (X.XXX) 2 bytes		
Phase A power factor (X.XXX) 2 bytes		
Phase B power factor (X.XXX) 2 bytes		
Phase C power factor (X.XXX) 2 bytes		
Total power consumption (XXXXXX.XX) 4 bytes	Kwh	
Total power consumption (XXXXXX.XX) 4 bytes	Kwh	
Peak total power consumption (XXXXXX.XX) 4 bytes	Kwh	
Total power consumption (XXXXXX.XX) 4 bytes	Kwh	
Total electricity consumption in the valley (XXXXXX.XX) 4 bytes	Kwh	
Running status word (hex) 2 bytes		
		65 bytes

Operation status word description:

Bit15	Bit14	Bit13	Bit13	Bit11	Bit10	Bit9	Bit8
Power supply							switch

state							Relay
0: Cancel 1: Power conservation	Reserved	Reserved	Reserved	Reserved	Reserved	0: Close	 1: Turn off the power
Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Keep	Keep	Keep	Keep	Keep			