

# VibTrans Quick Start

## – Prognosis-Tech VibPro A308 and MOXA UC-8112

modified date: Dec 27 2019

I-Ta Hsieh (ita.hsieh@prognosis-tech.com)

0. We recommend to upgrade UC-8112's firmware from version 3.1 to 3.2 . Version 3.2 is not yet released yet and could be downloaded [here](#)

The method to upgrade firmware is through the serial console mode and could be referred to The latest UC-8000 user manual.

Reference: MOXA UC-8100 series manual. See section 6.2 .

<https://www.moxa.com/getmedia/22fd4408-751d-4208-b218-d76a7bb970cc/moxa-arm-based-computer-linux-user-manual-for-debian-9-manual-v4.1.pdf>

1. Log in SSH from the ethernet

```
# Add an IP on the hosted machine
sudo ifconfig INTERFACE_NAME 192.168.4.10 netmask 255.255.0.0
```

```
# connect through SSH to UC-8xxx LAN port 2 (password: moxa)
ssh moxa@192.168.4.127
```

2. 3G/4G connection

```
# check SIM card status
sudo cell_mgmt sim_status
```

```
# create connection
sudo cell_mgmt start PIN=PIN_CODE APN=APN_NAME
```

```
# check the status of LTE connection
sudo cell_mgmt status
```

3. Get MURANO provision

```
# Create IoT connector on EXOSITE
```

```
## On ExoSite's upper panel → Home → IoT Connectors → ADD IOT CONNECTOR (create an object of IoT connector and click to enter)
```

```
## In the left panel of the page → Settings (at the bottom of the panel) → Protocol → change protocol from "MQTT" to "HTTP Device API"
```

```
# To create an "Device"
```

```
## "Device" section on the left panel → NEW DEVICE(s) → fill the name of the device in "Identity" column → ADD
```

```
# Check the product ID
```

```
# edit murano_par.py
```

```
# Get Murano provision and make the I/O to Murano be configured
./murano_activate_io_config.py
```

4. Edit trans\_par.py  
(To be complete)

5. run pytrans.py  
./pytrans.py  
# if you would like to see the screen log  
./pytrans.py --log

6. Replacing the startup script (rc.local)  
# edit PIN\_CODE and APN\_NAME in /home/moxa/pytrans/rc.local  
# backup the original rc.local  
sudo cp /etc/c.local /etc/c.local.bak  
# copy the modified  
sudo cp /home/moxa/pytrans/rc.local /etc/c.local

#### Appendix:

If you would like remove “the mean of the acceleration” (in order to get rid of the measurement of the acceleration of the gravity), you could execute “./remove\_mean.py” (To be formally released before Jan 8 2020. And I suggested to monitor standard deviation directly instead of RMS) after installing the sensor