

CCNA Practice Question Bank

100+ Exam-Style Questions with Answers & Full Explanations

How to use it: Try each question BEFORE reading the answer. The explanation tells you why the right answer is right AND why the traps are wrong — that's what builds real understanding. Aim to consistently score **85%+** before your exam. Questions are grouped by the 6 official exam domains.

Domain 1 — Network Fundamentals

Q1. Which device operates primarily at Layer 2 of the OSI model?

A. Router B. Switch C. Firewall D. Load balancer

Answer

B. Switch. A switch forwards frames using MAC addresses, which is Layer 2 (Data Link). A router works at Layer 3 (IP addresses). Trap: firewalls and load balancers can work at higher layers.

Q2. What is the correct order of TCP's three-way handshake?

A. ACK, SYN, SYN-ACK B. SYN, ACK, SYN-ACK C. SYN, SYN-ACK, ACK D. SYN-ACK, SYN, ACK

Answer

C. SYN, SYN-ACK, ACK. The initiator sends SYN, the receiver replies SYN-ACK, the initiator finishes with ACK. Memorize this order — it's tested a lot.

Q3. Which protocol is connectionless and does NOT guarantee delivery?

A. TCP B. UDP C. HTTP D. FTP

Answer

B. UDP. UDP is fast, connectionless, and doesn't confirm delivery — good for voice/video/DNS. TCP is the reliable, connection-oriented one.

Q4. What is the data unit at Layer 3 called?

A. Frame B. Segment C. Packet D. Bit

Answer

C. Packet. Layer 4 = segment, **Layer 3 = packet**, Layer 2 = frame, Layer 1 = bits. Memory trick: "Some People Fear Birthdays."

Q5. Which port number does HTTPS use?

A. 80 B. 21 C. 443 D. 22

Answer

C. 443. HTTPS = 443 (secure web). HTTP = 80, FTP = 21, SSH = 22.

Q6. A host has IP **169.254.10.5**. What most likely happened?

A. It got an address from DHCP B. It was assigned a public IP C. It could not reach a DHCP server (APIPA) D. It is using a loopback

Answer

C. APIPA. The 169.254.x.x range is auto-assigned when a device can't reach a DHCP server. It's a big clue that DHCP is broken or unreachable.

Q7. Which cable type connects two switches together (without Auto-MDIX)?

A. Straight-through B. Crossover C. Rollover D. Fiber only

Answer

B. Crossover. Similar devices (switch-switch, PC-PC, router-router) need a **crossover** cable. Different devices use straight-through. Rollover is for console access.

Q8. How many bits are in an IPv6 address?

A. 32 B. 48 C. 64 D. 128

Answer

D. 128 bits. IPv4 = 32 bits, MAC = 48 bits, **IPv6 = 128 bits**, written as 8 groups of 4 hex digits.

Q9. Which of the following is a private IPv4 address?

A. 8.8.8.8 B. 172.32.0.1 C. 192.168.5.20 D. 200.1.1.1

Answer

C. 192.168.5.20. Private ranges: 10.0.0.0/8, 172.16–31.0.0, 192.168.0.0/16. Note 172.**32** is OUTSIDE the private range (only 16–31), so B is a trap.

Q10. What does the Transport layer use to identify which application traffic belongs to?

A. MAC addresses B. IP addresses C. Port numbers D. VLAN tags

Answer

C. Port numbers. Ports (like 80, 443, 22) identify the app/service. IP finds the host; the port finds the app on that host.

Q11. Which IPv6 address type replaces the IPv4 broadcast?

A. Anycast B. Multicast C. Unicast D. Loopback

Answer

B. Multicast. IPv6 has **no broadcast** — it uses multicast to reach groups. Classic exam fact.

Q12. Convert binary 10101100 to decimal.

A. 172 B. 168 C. 160 D. 174

Answer

A. 172. $128 + 32 + 8 + 4 = 172$. (Bits on: 128, 32, 8, 4.)

Q13. Which layer of the TCP/IP model maps to OSI Layers 5, 6, and 7?

A. Transport B. Internet C. Application D. Network Access

Answer

C. Application. The TCP/IP Application layer combines OSI Session, Presentation, and Application.

Q14. What is the broadcast MAC address?

A. 00:00:00:00:00:00 B. FF:FF:FF:FF:FF:FF C. 01:00:5E:00:00:01 D. FE80::1

Answer

B. FF:FF:FF:FF:FF:FF. All F's = broadcast (everyone listens). D is an IPv6 link-local, not a MAC.

Q15. A fiber run must go 10 km between buildings. Which media is appropriate?

A. Cat6 copper B. Multimode fiber C. Single-mode fiber D. Coaxial

Answer

C. Single-mode fiber. Single-mode (tiny core, laser) goes many kilometers. Multimode is for shorter in-building runs; copper maxes ~100 m.

Domain 2 — Network Access (Switching, VLANs, Wireless)

Q16. What does a switch do when it receives a frame with an unknown destination MAC?

A. Drops it B. Floods it out all ports except the incoming one C. Sends it to the default gateway D. Buffers it forever

Answer

B. Floods it out all other ports. This is "unknown unicast flooding." Once the destination replies, the switch learns its port and stops flooding.

Q17. Which command puts switch port Fa0/1 into VLAN 10?

A. `vlan 10` B. `switchport access vlan 10` C. `switchport trunk vlan 10` D. `ip vlan 10`

Answer

B. `switchport access vlan 10` (entered under `interface fa0/1`). You'd also set `switchport mode access`.

Q18. Which standard is used to tag frames on a trunk link?

A. 802.11 B. 802.1Q C. 802.3 D. 802.1X

Answer

B. 802.1Q. "Dot1Q" inserts a 4-byte VLAN tag. 802.11 = Wi-Fi, 802.3 = Ethernet, 802.1X = port authentication.

Q19. On an 802.1Q trunk, which VLAN's traffic is sent untagged by default?

- A. VLAN 0 B. VLAN 1 (native) C. VLAN 1000 D. All VLANs

Answer

B. VLAN 1 (the native VLAN). Native VLAN traffic crosses the trunk untagged. Both switches must agree on the native VLAN.

Q20. What is the purpose of Spanning Tree Protocol?

- A. Speed up routing B. Prevent Layer 2 loops C. Assign IP addresses D. Encrypt traffic

Answer

B. Prevent Layer 2 loops. STP blocks redundant paths so broadcasts don't circle forever (broadcast storms), while keeping a backup ready.

Q21. In STP, how is the root bridge chosen?

- A. Highest IP address B. Lowest bridge ID (priority + MAC) C. Fastest port D. Most connections

Answer

B. Lowest bridge ID. Bridge ID = priority + MAC. Lowest priority wins; if tied, lowest MAC wins.

Q22. Which feature lets a switch port skip STP's listening/learning states for end devices?

- A. BPDU Guard B. PortFast C. EtherChannel D. Root Guard

Answer

B. PortFast. It moves an access port straight to forwarding. Use only on ports connected to end devices, never switch-to-switch.

Q23. What happens by default when a port-security violation occurs?

- A. Port logs only B. Port drops traffic silently C. Port shuts down (err-disabled) D. Port reboots

Answer

C. Port shuts down. Default violation mode is **shutdown** (err-disabled). Other modes: protect (silent drop) and restrict (drop + log).

Q24. Which LACP mode combination will successfully form an EtherChannel?

A. passive/passive B. active/passive C. auto/auto D. on/active

Answer

B. active/passive. LACP needs at least one side active. passive/passive fails (both wait). on/active mismatches protocols (on = no negotiation).

Q25. Which two channels do NOT overlap on the 2.4 GHz band (pick the standard set)?

A. 1, 2, 3 B. 1, 5, 9 C. 1, 6, 11 D. 2, 7, 12

Answer

C. 1, 6, 11. These are the non-overlapping 2.4 GHz channels — using them avoids interference.

Q26. Which wireless security standard is the most secure?

A. WEP B. WPA C. WPA2 D. WPA3

Answer

D. WPA3. Newest and strongest. WEP is broken, WPA is weak, WPA2 is good, WPA3 is best.

Q27. In a lightweight wireless architecture, what protocol do APs use to talk to the WLC?

A. CDP B. CAPWAP C. LLDP D. GRE

Answer

B. CAPWAP. Lightweight APs tunnel to the Wireless LAN Controller using CAPWAP for control and (optionally) data.

Q28. Router-on-a-stick uses what to route between VLANs on one physical link?

A. Loopbacks B. Subinterfaces C. SVIs D. Trunk ACLs

Answer

B. Subinterfaces. The router creates one subinterface per VLAN, each with `encapsulation dot1q <vlan>` and an IP that acts as the gateway.

Q29. Which command shows which VLAN each access port belongs to?

A. `show mac address-table` B. `show vlan brief` C. `show ip route` D. `show cdp neighbors`

Answer

B. `show vlan brief`. It lists VLANs and their assigned ports. Great first check for VLAN misconfigurations.

Q30. What is the default native VLAN, and why change it?

A. VLAN 0; performance B. VLAN 1; security (avoid VLAN hopping) C. VLAN 99; redundancy D. VLAN 4094; naming

Answer

B. VLAN 1; for security. Changing the native VLAN away from the default helps prevent double-tagging VLAN-hopping attacks.

Domain 3 — IP Connectivity (Routing & OSPF)

Q31. In the routing table, what does the letter `R` mean?

A. A static route B. A connected route C. An OSPF-learned route D. An offline route

Answer

C. OSPF-learned. C = connected, S = static, O = OSPF, D = EIGRP, R = RIP, B = BGP.

Q32. A router has two routes to the same network: one via OSPF, one static. Which is used?

A. OSPF (AD 110) B. Static (AD 1) C. Both load-balance D. Neither

Answer

B. Static (AD 1). Lower administrative distance wins. Static (1) beats OSPF (110). Connected (0) beats everything.

Q33. Which administrative distance does a directly connected route have?

A. 0 B. 1 C. 90 D. 110

Answer

A. 0. Connected = 0 (most trusted). Static = 1, EIGRP = 90, OSPF = 110, RIP = 120.

Q34. What does a router do with a packet if no matching route exists and there is no default route?

A. Floods it B. Sends to gateway of last resort C. Drops it D. Buffers it

Answer

C. Drops it. No route + no default = the packet is discarded (often with an ICMP unreachable). A default route (0.0.0.0/0) would catch it.

Q35. Which command creates a default route toward next hop 203.0.113.1?

A. `ip route 0.0.0.0 0.0.0.0 203.0.113.1` B. `ip default 203.0.113.1` C. `ip route default 203.0.113.1` D. `default-gateway 203.0.113.1`

Answer

A. `ip route 0.0.0.0 0.0.0.0 203.0.113.1`. 0.0.0.0/0 matches everything not otherwise known. (`ip default-gateway` is only for a switch/host, not routing.)

Q36. When two routes to the same destination have different prefix lengths, the router chooses the one that is:

A. Learned first B. Most specific (longest prefix) C. From the lowest AD D. Load-balanced

Answer

B. Longest prefix match. A /24 beats a /16 for a matching destination — the more specific route wins, regardless of AD (AD only breaks ties for the same prefix).

Q37. What metric does OSPF use to choose the best path?

A. Hop count B. Bandwidth-based cost C. Delay D. Ticks

Answer

B. Cost (based on bandwidth). Cost = reference bandwidth ÷ link bandwidth. Faster links = lower cost = preferred. (RIP uses hop count.)

Q38. Two OSPF routers won't become neighbors. Which mismatch could be the cause?

A. Different hostnames B. Different interface descriptions C. Different area or subnet D. Different clock time

Answer

C. Different area or subnet. Neighbors must match area, subnet, hello/dead timers, authentication, and MTU. Hostnames/descriptions don't matter.

Q39. In OSPF, what must the backbone area always be?

A. Area 1 B. Area 10 C. Area 0 D. Area 255

Answer

C. Area 0. The backbone is always Area 0; all other areas connect to it.

Q40. What is a wildcard mask of `0.0.0.255` equivalent to matching?

A. A single host B. A whole /24 network C. Everything D. A /16 network

Answer

B. A whole /24. Wildcards are the inverse of subnet masks. 0 = must match, 255 = anything. 0.0.0.255 matches all hosts in one /24.

Q41. Which command correctly advertises 10.1.1.0/24 into OSPF area 0?

A. `network 10.1.1.0 255.255.255.0 area 0` B. `network 10.1.1.0 0.0.0.255 area 0` C. `network 10.1.1.0 area 0`
D. `advertise 10.1.1.0/24`

Answer

B. `network 10.1.1.0 0.0.0.255 area 0`. OSPF uses a **wildcard** mask, not a subnet mask, in the network statement.

Q42. How does OSPF pick its Router ID if not set manually?

A. Lowest interface IP B. Highest loopback, else highest active physical IP C. The MAC address D. Randomly

Answer

B. Highest loopback, otherwise highest active physical interface IP. Best practice is to set `router-id` manually for predictability.

Q43. A floating static route is created by:

A. Lowering its metric B. Giving it a higher administrative distance than the primary C. Adding a wildcard mask D. Using a /32

Answer

B. Higher AD. A backup ("floating") static route has a higher AD so it's only installed if the primary route disappears.

Q44. Which routing protocol type builds a full map of the network and runs SPF?

A. Distance vector B. Link state C. Path vector D. Static

Answer

B. Link state. OSPF (link state) builds an LSDB and runs Dijkstra/SPF. RIP is distance vector; BGP is path vector.

Q45. What is the OSPF cost of a 100 Mbps link using the default reference bandwidth?

A. 1 B. 10 C. 19 D. 100

Answer

A. 1. Default reference is 100 Mbps, so a 100 Mbps link = $100/100 = 1$. (10 Mbps = 10.) Note: STP cost for 100 Mbps is 19 — don't confuse them!

Domain 4 — IP Services (DHCP, DNS, NAT, NTP, SNMP)

Q46. What is the correct order of the DHCP process?

A. Offer, Discover, Request, Ack B. Discover, Offer, Request, Ack C. Request, Offer, Discover, Ack D. Discover, Request, Offer, Ack

Answer

B. Discover, Offer, Request, Ack (DORA). Client discovers, server offers, client requests, server acknowledges.

Q47. Which service translates domain names into IP addresses?

A. DHCP B. DNS C. NAT D. NTP

Answer

B. DNS. DNS is the internet's phone book — name to IP. DHCP hands out addresses, NAT translates addresses, NTP syncs time.

Q48. Your home router lets 20 devices share one public IP. What technology is this?

A. Static NAT B. Dynamic NAT C. PAT (NAT overload) D. Proxy ARP

Answer

C. PAT / NAT overload. Many private hosts share ONE public IP, distinguished by port numbers. This is what home routers do.

Q49. DHCP clients are on a different subnet than the DHCP server. What must you configure on the router?

A. `ip default-gateway` B. `ip helper-address <server>` C. `ip nat inside` D. `ip route`

Answer

B. `ip helper-address`. It relays the DHCP broadcast to the server across subnets (since routers don't forward broadcasts).

Q50. Which port does DNS primarily use?

A. 53 B. 67 C. 80 D. 123

Answer

A. 53. DNS = 53 (UDP mostly, TCP for big transfers). 67/68 = DHCP, 80 = HTTP, 123 = NTP.

Q51. Which DNS record maps a name to an IPv6 address?

A. A B. AAAA C. CNAME D. MX

Answer

B. AAAA. A = IPv4, **AAAA = IPv6**, CNAME = alias, MX = mail server.

Q52. Why is NTP important on network devices?

A. Faster routing B. Accurate timestamps for logs and certificates C. More bandwidth D. Encryption

Answer

B. Accurate time. Logs, security certs, and troubleshooting all depend on synchronized clocks. NTP keeps them aligned.

Q53. Which SNMP version adds encryption and authentication?

A. SNMPv1 B. SNMPv2c C. SNMPv3 D. SNMPv2

Answer

C. SNMPv3. It adds authentication and encryption. v1 and v2c send community strings in clear text — avoid for security.

Q54. In NAT terminology, the private address of a host BEFORE translation is the:

A. Inside local B. Inside global C. Outside local D. Outside global

Answer

A. Inside local. Inside local = private (before), inside global = public (after). Outside terms refer to the remote host.

Q55. A syslog message at severity level 0 means:

A. Debugging B. Informational C. Emergency (system unusable) D. Warning

Answer

C. Emergency. Level 0 = Emergency (most severe). Level 7 = Debug (least). Remember: lower number = more urgent.

Domain 5 — Security Fundamentals

Q56. Which part of the CIA triad ensures data isn't secretly altered?

A. Confidentiality B. Integrity C. Availability D. Authentication

Answer

B. Integrity. Confidentiality = secrecy, **Integrity = data stays correct/unaltered**, Availability = it's up when needed.

Q57. Which attack fills a switch's MAC table to force flooding?

A. VLAN hopping B. MAC flooding C. DHCP starvation D. ARP spoofing

Answer

B. MAC flooding. It overflows the CAM table so the switch floods frames (attacker can sniff). Defense: **port security**.

Q58. Which feature stops a rogue DHCP server on an untrusted port?

A. BPDU Guard B. DHCP snooping C. Port-security D. DAI

Answer

B. DHCP snooping. It marks trusted ports (toward the real server) and blocks DHCP offers from untrusted ports.

Q59. Which protocol should replace Telnet for remote device management?

A. FTP B. HTTP C. SSH D. SNMPv1

Answer

C. SSH. SSH (port 22) encrypts the session. Telnet (23) is clear text — never use it in production.

Q60. In AAA, what does the second "A" (Authorization) determine?

A. Who you are B. What you're allowed to do C. What you did D. Where you are

Answer

B. What you're allowed to do. Authentication = who you are, Authorization = what you can do, Accounting = what you did.

Q61. Which AAA protocol encrypts the entire packet and uses TCP?

A. RADIUS B. TACACS+ C. Kerberos D. LDAP

Answer

B. TACACS+. Cisco's TACACS+ uses TCP and encrypts the whole packet — great for device admin. RADIUS uses UDP and encrypts only the password.

Q62. In 802.1X, what role does the switch play?

A. Supplicant B. Authenticator C. Authentication server D. Client

Answer

B. Authenticator. The switch/AP is the "bouncer." The device is the supplicant; RADIUS is the authentication server.

Q63. Which command encrypts plain-text passwords in the running config?

- A. `enable secret` B. `service password-encryption` C. `crypto key generate rsa` D. `password-encrypt on`

Answer

B. `service password-encryption`. It scrambles clear-text passwords (like console/line) in the config. `enable secret` is separately hashed already.

Q64. Which defense protects against ARP spoofing (man-in-the-middle)?

- A. Port-security B. Dynamic ARP Inspection (DAI) C. BPDU Guard D. STP

Answer

B. `Dynamic ARP Inspection`. DAI validates ARP packets against the DHCP snooping database, blocking forged ARP replies.

Q65. A site-to-site VPN between two offices typically uses:

- A. SSL only B. IPsec C. Telnet D. GRE only

Answer

B. `IPsec`. Site-to-site VPNs use IPsec to encrypt traffic between office routers across the public internet.

Domain 5b — Access Control Lists (ACLs)

Q66. What is at the end of every ACL, even if not typed?

- A. permit any B. an implicit deny all C. a log entry D. nothing

Answer

B. `Implicit deny all`. Anything not explicitly permitted is denied. Forgetting a `permit` can block everything.

Q67. A standard ACL filters based on what?

- A. Source and destination IP B. Source IP only C. Port numbers D. MAC addresses

Answer

B. Source IP only. Standard ACLs (1–99) match source only. Extended ACLs (100–199) match source, destination, protocol, and port.

Q68. Where should a standard ACL be placed?

A. Close to the source B. Close to the destination C. On every interface D. On the trunk

Answer

B. Close to the destination. Because it only sees source IP, placing it far from the destination could block traffic you meant to allow. (Extended ACLs go close to the source.)

Q69. In ACL processing, which rule wins?

A. The last match B. The first match C. The most specific D. The lowest number

Answer

B. The first match. ACLs are read top-to-bottom; the first matching line is applied and the rest are skipped. Order matters!

Q70. Which statement permits only host 192.168.1.10?

A. `permit 192.168.1.10 0.0.0.255` B. `permit host 192.168.1.10` C. `permit any` D. `permit 192.168.1.0 0.0.0.0`

Answer

B. `permit host 192.168.1.10` (same as `permit 192.168.1.10 0.0.0.0`). Wildcard 0.0.0.0 means an exact match on that one host.

Domain 6 — Automation & Programmability

Q71. In SDN, which plane makes forwarding decisions?

A. Data plane B. Control plane C. Management plane D. Physical plane

Answer

B. Control plane. The control plane is the "brain" (decides paths); the data plane is the "muscle" (forwards packets). SDN centralizes the control plane.

Q72. A northbound API on a controller communicates with:

A. Switches B. Routers C. Applications/scripts D. The data plane

Answer

C. Applications/scripts (upward). Northbound = to apps/humans (REST). Southbound = down to devices (NETCONF/OpenFlow).

Q73. Which HTTP method is used to RETRIEVE data from a REST API?

A. POST B. GET C. PUT D. DELETE

Answer

B. GET. GET reads, POST creates, PUT updates/replaces, DELETE removes.

Q74. Which data format uses curly braces and key/value pairs and is most common in REST APIs?

A. XML B. YAML C. JSON D. CSV

Answer

C. JSON. JSON uses { } with "key": value. YAML uses indentation; XML uses tags.

Q75. Which automation tool is agentless and uses YAML playbooks?

A. Puppet B. Chef C. Ansible D. SaltStack

Answer

C. Ansible. Agentless (nothing installed on devices), uses easy YAML playbooks. Puppet and Chef use agents.

Q76. What is the main benefit of network automation?

A. More cables B. Consistent, fast, error-free configuration at scale C. Slower changes D. Replacing all routers

Answer

B. Consistent, fast, error-free configuration at scale. Automation removes repetitive manual typos and enforces one consistent config across many devices.

Q77. Cisco DNA Center is an example of:

A. A router B. An SDN controller C. A firewall D. A switch OS

Answer

B. An SDN controller. DNA Center centrally manages, automates, and monitors the network (intent-based networking).

Domain 7 — Configuration & Troubleshooting Scenarios

Q78. After configuring an interface, `show ip interface brief` shows "administratively down." What fixes it?

A. `no shutdown` B. `ip address` C. Reboot D. `enable`

Answer

A. `no shutdown`. "Administratively down" means the port is manually disabled. `no shutdown` on the interface enables it.

Q79. You can ping 8.8.8.8 but not google.com. What's broken?

A. Routing B. DNS C. NAT D. The cable

Answer

B. DNS. IP connectivity works (ping by IP succeeds), but name resolution fails — a DNS server problem.

Q80. Two switches won't form a trunk. Which is a likely cause?

A. Different hostnames B. Native VLAN or mode mismatch C. Different IOS versions D. Different port numbers

Answer

B. Native VLAN / mode mismatch. Mismatched native VLANs or trunk modes (e.g., access vs trunk) stop trunking and can raise errors.

Q81. A PC gets 169.254.x.x. What should you check first?

A. DNS server B. DHCP reachability (server/relay/VLAN) C. The default route D. STP

Answer

B. DHCP reachability. APIPA means the client couldn't reach a DHCP server — check the server, the `ip helper-address`, and the VLAN/port.

Q82. A link is slow with many errors. One side is full-duplex, the other half. This is a:

A. Speed mismatch B. Duplex mismatch C. VLAN mismatch D. MTU mismatch

Answer

B. Duplex mismatch. Mismatched duplex causes collisions/late collisions and slowness. Set both ends the same (or both to auto).

Q83. Which command shows the path packets take and where they stop?

A. `ping` B. `tracert` C. `show ip route` D. `show cdp neighbors`

Answer

B. `tracert`. It reveals each hop along the path, helping you find where connectivity breaks.

Q84. A port-security-enabled port is err-disabled after a violation. How do you recover it?

A. `no shutdown` only B. `shutdown` then `no shutdown` C. Reload D. Delete the VLAN

Answer

B. `shutdown` then `no shutdown`. You must bounce the interface (and clear the cause) to bring an err-disabled port back.

Q85. Which command shows OSPF neighbors and their states?

A. `show ip ospf neighbor` B. `show ip route` C. `show running-config` D. `show ip protocols`

Answer

A. `show ip ospf neighbor`. It lists neighbors and states (e.g., FULL). Great for diagnosing why routers aren't exchanging routes.

Q86. A host's gateway is 192.168.1.65 /26, and the host is 192.168.1.130 /26. Why no internet?

A. Wrong DNS B. Host and gateway are in different subnets C. Bad cable D. STP blocking

Answer

B. Different subnets. .65 is in subnet .64–.127; .130 is in subnet .128–.191. The host can't use a gateway outside its own subnet.

Q87. Which command saves the running configuration so it survives a reboot?

A. `write erase` B. `copy running-config startup-config` C. `reload` D. `show startup-config`

Answer

B. `copy running-config startup-config` (or `write memory`). Running-config lives in RAM and is lost on reboot unless saved.

Q88. `show cdp neighbors detail` is most useful for:

A. Seeing routing tables B. Discovering a neighbor's IP and platform C. Checking VLANs D. Viewing ACLs

Answer

B. Neighbor IP/platform. CDP reveals directly connected Cisco device details (name, port, model, IP) — handy for mapping.

Q89. A switch's MAC address table is empty for a device that's clearly connected and powered. What's a likely reason?

A. The device hasn't sent any frames yet B. STP is off C. Wrong IOS D. NAT is disabled

Answer

A. It hasn't sent frames yet. Switches learn MACs from **source** addresses of incoming frames. A silent device won't be learned until it transmits.

Q90. Which show command quickly confirms an interface is "up/up" with its IP?

A. `show vlan brief` B. `show ip interface brief` C. `show mac address-table` D. `show version`

Answer

B. `show ip interface brief`. It lists interfaces, IPs, and status/protocol (up/up). Fast Layer 1/2 sanity check.

Domain 8 — More Fundamentals & Mixed Review

Q91. How many usable hosts are in a /27 subnet?

A. 32 B. 30 C. 62 D. 14

Answer

B. 30. Host bits = 5, $2^5 - 2 = 30$.

Q92. Which address is the broadcast for 192.168.1.0/26's second subnet?

A. 192.168.1.63 B. 192.168.1.127 C. 192.168.1.128 D. 192.168.1.191

Answer

B. 192.168.1.127. Block size 64: subnets .0, .64, .128, .192. Second subnet = .64-.127, so broadcast = **.127**.

Q93. Which IPv6 address is a link-local address?

A. 2001:db8::1 B. FE80::1 C. ::1 D. FF02::1

Answer

B. FE80::1. Link-local addresses start with FE80::/10. ::1 is loopback; FF02:: is multicast; 2001:: is global unicast.

Q94. What does :: mean in an IPv6 address?

A. End of address B. One or more groups of all zeros (used once) C. A separator only D. A loopback

Answer

B. A run of all-zero groups, collapsed once. You may use :: only a single time per address to avoid ambiguity.

Q95. Which protocol automatically lets an IPv6 host build its own address from the router's prefix?

A. DHCPv4 B. SLAAC C. ARP D. NAT

Answer

B. SLAAC. Stateless Address Autoconfiguration lets a host form its own IPv6 address using the advertised prefix — no DHCP needed.

Q96. Which of these is a Layer 1 problem?

A. Wrong VLAN B. Unplugged/broken cable C. Missing default route D. ACL blocking

Answer

B. Broken cable. Physical media issues (cables, connectors, no link light) are Layer 1. VLANs are L2, routing/ACLs are L3+.

Q97. What is the purpose of a default gateway on a host?

A. Resolve names B. Reach devices on other networks C. Assign IPs D. Encrypt traffic

Answer

B. Reach other networks. The gateway (router interface) forwards traffic destined for outside the local subnet.

Q98. Which command tests basic connectivity to an IP?

A. `ping` B. `show run` C. `configure terminal` D. `copy`

Answer

A. `ping`. It sends ICMP echo requests. `!!!!!` = success, `.....` = no reply.

Q99. A trunk carries VLANs 10 and 20, but VLAN 20 traffic isn't passing while VLAN 10 works. What's a likely cause?

A. Wrong hostname B. VLAN 20 not allowed on the trunk C. Duplex mismatch D. Wrong DNS

Answer

B. VLAN 20 not in the allowed list. Check `switchport trunk allowed vlan` — VLAN 20 may be pruned/omitted. Also confirm VLAN 20 exists on both switches.

Q100. Which two are valid reasons to use VLANs? (Choose the best single answer.)

A. Faster CPUs B. Segment broadcast domains and improve security C. Replace routers D. Increase cable length

Answer

B. Segment broadcast domains and improve security. VLANs shrink broadcast domains and isolate groups (e.g., students vs admin). Routing between them still needs a router/L3 switch.

Q101. Which is TRUE about a /30 subnet?

A. It has 4 usable hosts B. It has 2 usable hosts, ideal for router links C. It's used for large LANs D. It has no broadcast

Answer

B. 2 usable hosts, ideal for point-to-point router links. /30 = 4 addresses total, minus network and broadcast = 2 usable.

Q102. In the frame, which field detects transmission errors?

A. Preamble B. Source MAC C. FCS (Frame Check Sequence) D. Type

Answer

C. FCS. The Frame Check Sequence at the end validates the frame's integrity; a bad FCS means the frame is discarded.

Q103. Which command sets a device to only allow SSH (not Telnet) for remote logins?

A. `transport input ssh` B. `transport input all` C. `no ip telnet` D. `login local`

Answer

A. `transport input ssh` (under `line vty`). It restricts remote access to SSH only, blocking insecure Telnet.

Q104. What best describes "longest prefix match"?

A. Trusting the lowest AD B. Choosing the most specific matching route C. Load balancing D. Picking the oldest route

Answer

B. Most specific matching route. Among matching routes, the one with the longest prefix (e.g., /24 over /16) is used to forward the packet.

Q105. You need 6 subnets from a /24, each with room for ~25 hosts. Which mask fits BOTH needs?

A. /26 B. /27 C. /28 D. /25

Answer

B. /27. /27 gives 8 subnets (≥ 6) and 30 hosts each (≥ 25). /26 gives only 4 subnets (too few); /28 gives 14 hosts (too few).

How to Use These Results

- **Score yourself by domain.** If you miss several in one domain (say OSPF or ACLs), go back to that chapter in the main guide and re-drill.
- **Re-take after a few days.** Spacing your practice helps memory stick.
- **Target 85%+ consistently** before booking the exam.
- **Pair with labs.** Reading answers isn't enough — configure these things in Packet Tracer to make them permanent.

Good luck — you're building real skills now!

— End of Practice Question Bank —