# SmartBin: IoT-Enabled Intelligent Waste Monitoring and Municipal Dispatch Optimization System

Edge Computing Telemetry, Non-Contact Acoustic Sensing & Real-Time Cloud Operations Dashboard

| COURSE / MODULE | HARDWARE PLATFORM | COMMUNICATION | APPLICATION DOMAIN |
|---|---|---|---|
| IoT & Embedded Systems | ESP32 / ESP8266 + HC-SR04 | Wi-Fi / HTTP REST / JSON | Smart City & Sanitation Logistics |

## 1. Aim and Problem Statement

### 1.1 Project Title

**SmartBin: An IoT-Based Real-Time Ultrasonic Solid Waste Level Monitoring, Predictive Fill Classification, and Automated Municipal Sanitation Dispatch System.**

### 1.2 Aim of the Project

To design, simulate, implement, and validate an automated Internet of Things (IoT) municipal waste monitoring system employing ultrasonic time-of-flight acoustic sensors, wireless microcontrollers (ESP32 / ESP8266), software median noise filtering, and a cloud-connected operations dashboard. The system continuously gauges solid waste fill levels in real time, classifies container status into deterministic action tiers, suppresses acoustic jitter, and automatically triggers municipal collection dispatches to eliminate garbage overflows while optimizing sanitation truck routes, fuel consumption, and labor allocation.

### 1.3 Technical Objectives

- **Non-Contact Acoustic Telemetry:** Deploy an HC-SR04 ultrasonic sensor with a 10 µs pulse trigger and acoustic time-of-flight computation (speed of sound = 343 m/s) to accurately gauge container headspace without physical contact or sensor contamination.
- **Edge Median Noise Rejection:** Execute a 5-sample software median window filter on the microcontroller to reject acoustic multipath reflections, irregular garbage pile angles, and transient environmental noise.
- **Continuous Fill Percentage Computation:** Calibrate reference boundary limits (40.0 cm empty, 5.0 cm full) to derive instantaneous waste fill percentages from 0.0% to 100.0%, with automatic clamping and blind-zone fault detection.
- **Tiered Operational Classification:** Categorize telemetry into distinct operational tiers: `LOW` (<50%), `MEDIUM` (50–79.9%), `HIGH` (80–94.9%, scheduled pickup), `FULL` (≥95%, urgent truck dispatch), and `SENSOR ERROR` for hardware faults.
- **Wireless Cloud Transmission:** Package telemetry into lightweight JSON payloads and transmit over 802.11 b/g/n Wi-Fi via HTTP POST to a centralized municipal server with automatic network reconnection logic.
- **Municipal Operations Dashboard:** Provide municipal operators with an interactive dashboard featuring live bin metrics, geographical distribution, trend analytics, alert deduplication, and historical logs.

### 1.4 Real-World Need and Municipal Sanitation Motivation

Conventional municipal solid waste management practices rely heavily on static, predetermined collection routes and calendar schedules (e.g., trucks visiting designated sectors every 48 hours regardless of actual bin volume). This legacy paradigm introduces severe operational and environmental liabilities:

- **Premature Overflows and Public Health Hazards:** High-density urban areas, markets, and campus terminals experience rapid waste accumulation. Bins overflow hours before scheduled collection, scattering litter, generating noxious odors, and fostering vectors for vector-borne pathogens (flies, rodents, bacterial contamination).
- **Excessive Fuel Consumption and Carbon Emissions:** Sanitation fleets waste millions of gallons of diesel visiting sparsely filled bins in low-density neighborhoods, generating needless CO2, NOx, and particulate emissions while accelerating vehicle wear.
- **Absence of Centralized Operational Intelligence:** Municipal sanitation managers have zero real-time visibility into city-wide waste status. Dispatches occur reactively following citizen complaints rather than through data-driven logistics.

> **The Solution:** SmartBin transforms conventional passive waste receptacles into intelligent, connected IoT nodes that broadcast actionable telemetry, allowing municipalities to switch from inefficient static schedules to dynamically optimized, demand-responsive collection routes.

## 2. Components and Tools

The SmartBin architecture bridges physical edge sensing, signal conditioning, wireless microcontroller processing, cloud ingestion, and real-time operator interfaces. Each hardware and software element is selected to ensure high measurement reliability, electrical safety, and seamless cloud connectivity.

### 2.1 Hardware Components & Electrical Roles

| Component Name | Category / Model | Key Specifications | Engineering Purpose & Operational Role |
|---|---|---|---|
| **HC-SR04 Ultrasonic Sensor** | Acoustic Transducer Module | Operating Freq: 40 kHz<br>Range: 2 cm to 400 cm<br>Resolution: 0.3 cm<br>Supply: 5V DC, <15 mA | Mounted on underside of bin lid facing downwards. Emits 8-cycle ultrasonic bursts and measures round-trip time-of-flight to non-invasively measure trash surface distance without contact fouling. |
| **ESP32 DevKit V1** | Microcontroller Board (Simulation Target) | Tensilica Xtensa Dual-Core 32-bit LX6 @ 240 MHz<br>520 KB SRAM, 802.11 b/g/n<br>GPIO Logic: 3.3V | Acts as the primary edge computing node in the Wokwi simulation environment. Drives trigger pulses, captures microsecond echo timing, runs median filter, computes fill %, and issues HTTP POST telemetry. |
| **ESP8266 NodeMCU v2** | Microcontroller Board (Physical Target) | Tensilica L106 32-bit @ 80/160 MHz, 4MB Flash<br>802.11 b/g/n Wi-Fi<br>GPIO Logic: 3.3V | Cost-effective edge node target for physical municipal deployment. Handles autonomous sensor polling, median noise rejection, local status classification, and Wi-Fi transmission. |
| **Resistive Voltage Divider (1kΩ / 2kΩ)** | Passive Signal Conditioning | R1 = 1 kΩ (1/4W, 1%)<br>R2 = 2 kΩ (1/4W, 1%)<br>Ratio: 2/(1+2) = 0.667 | Level-shifts the 5V logic ECHO pulse from the HC-SR04 down to a safe 3.33 V level (5V * 0.667 = 3.33V) before connecting to MCU GPIO pins, completely preventing overvoltage damage. |
| **Status Diagnostic LED** | Visual Indicator / Actuator | Built-in GPIO 2 LED<br>Active LOW configuration<br>Current: ~5 mA | Provides immediate on-device diagnostic feedback: flashes rapidly during Wi-Fi connection phase and toggles briefly during HTTP telemetry transmission to confirm heartbeat. |

### 2.2 Software Platforms and Toolchain Ecosystem

| Software / Tool | Environment / Stack | Engineering Purpose & Operational Value |
|---|---|---|
| **Wokwi Simulator** | Browser-based Simulation | Virtual embedded hardware simulator executing compiled ESP32 machine code, emulating HC-SR04 acoustic echo pulses, animated wiring circuits, and virtual Wi-Fi connectivity for rapid iteration. |
| **Arduino IDE & CLI** | Embedded C/C++ Toolchain | Compiles target sketches with ESP32/ESP8266 Arduino Core libraries (WiFi.h, HTTPClient.h), generating flashable binary images and memory allocation maps. |
| **Node.js & Express.js** | Backend Municipal Server | Asynchronous event-driven REST API server running on port 5000. Ingests high-frequency sensor payloads, executes threshold analysis, manages stale device timeouts, and persists readings atomically. |
| **Socket.IO** | Real-time Bi-directional WS | Maintains low-latency WebSocket connections between the municipal backend and connected dispatch dashboards, pushing telemetry packets within milliseconds of arrival without polling overhead. |
| **React.js & Recharts** | Frontend Operations Dashboard | Single-Page Application (SPA) offering municipal dispatchers live interactive bin cards, geographical fill indicators, historical telemetry trend charts, alert drawers, and simulator controls. |
| **ThingSpeak / Cloud IoT** | Public IoT Cloud Gateway | Optional external cloud telemetry aggregator providing RESTful channel feeds, automated email/SMS webhook triggers, and public analytics for municipal transparency reporting. |


### 2.3 Edge Computing Architecture Rationale

Rather than streaming unvalidated raw pulse timings to the cloud, SmartBin executes edge intelligence directly on the microcontroller. By applying multi-sample median sorting and boundary validation locally, the device minimizes cloud bandwidth, eliminates erroneous telemetry triggers caused by temporary acoustic reflections, and ensures autonomous local fail-safe operation during network blackouts.


## 3. Block Diagram and Flowchart

The system is organized into modular layers spanning physical sensing, edge microcontroller signal processing, wireless transmission, cloud backend aggregation, and real-time operator interfaces.

### 3.1 System Block Diagram




### 3.2 System Operational Flowchart




### 3.3 Mathematical Formulation of Waste Telemetry

The ultrasonic sensor measures the round-trip echo pulse duration T_pulse in microseconds. Distance D_measured is calculated using acoustic propagation velocity (v = 0.0343 cm/µs at 20°C):

$$D_{measured} = (T_{pulse} * 0.0343\ cm/\mu s) / 2\ (centimeters)$$


Using calibrated empty height (D_empty = 40.0 cm) and full threshold (D_full = 5.0 cm), usable bin height is H_usable = 40.0 - 5.0 = 35.0 cm. The occupied waste volume percentage is formulated as:

$$Fill\ Percentage\ (\%) = clamp(\ ((D_{empty} - D_{measured}) / (D_{empty} - D_{full})) * 100,\ 0.0,\ 100.0\ )$$

## 4. Circuit Diagram and Pin Connections

The electronic interface coordinates the power supply, acoustic pulse trigger generation, and echo voltage level-shifting between the 5V HC-SR04 transducer module and the 3.3V GPIO architecture of the ESP32 / ESP8266 microcontroller.

### 4.1 Wokwi Simulation Circuit Schematic




### 4.2 Complete Hardware Pin Connections Table

| Component | Device Pin | Microcontroller Pin | Signal Level | Electrical Function & Protection Details |
|---|---|---|---|---|
| **HC-SR04 Sensor** | `VCC` | ESP32 `VIN` (or 5V Supply) | +5.0V DC Power | Powers ultrasonic transducer oscillators and transmitter drivers. Requires stable 5V for full range. |
| **HC-SR04 Sensor** | `GND` | ESP32 `GND` (Common) | 0V Reference | Common system ground plane for low-noise acoustic signal references. |
| **HC-SR04 Sensor** | `TRIG` | ESP32 `GPIO 14` (D14) | 3.3V Logic Output | Actuated with a 10 µs HIGH pulse from MCU to trigger 8-cycle 40 kHz ultrasonic burst generation. |
| **HC-SR04 Sensor** | `ECHO` | Input to R1 (1 kΩ) | 5.0V Logic Output | Outputs a HIGH pulse whose pulse width directly equals round-trip flight time. Scaled by voltage divider. |
| **Divider Node (R1 / R2)** | Center Tap | ESP32 `GPIO 27` (D27) | 3.33V Logic Input | Safe level-shifted echo input. Protects ESP32 internal ESD diodes and gate oxides against 5V overstress. |
| **Divider Lower Leg (R2)** | Shunt Terminal | ESP32 `GND` | 0V Ground Shunt | 2 kΩ shunt to ground completing the voltage division ratio: V_out = 5V * (2 / (1 + 2)) = 3.33V. |
| **Status Diagnostic LED** | Anode / Cathode | ESP32 `GPIO 2` | 3.3V Digital Output | Built-in surface-mount LED for visual confirmation of Wi-Fi association and HTTP telemetry transmission. |

### 4.3 Overvoltage Protection Engineering Rationale

The ESP32 and ESP8266 microcontrollers operate on 3.3V CMOS logic rails. While the HC-SR04 trigger pin responds reliably to 3.3V trigger signals, its ECHO pin drives a full 5.0V TTL pulse. Direct connection of the 5.0V ECHO output to a 3.3V GPIO input exceeds the absolute maximum rating of the MCU (V_DD + 0.3V = 3.6V), risking progressive gate dielectric breakdown and permanent pin latch-up. By implementing a passive voltage divider with R1 = 1 kΩ and R2 = 2 kΩ, the peak voltage is clamped to:

**V_GPIO27 = V_ECHO * (R2 / (R1 + R2)) = 5.0 V * (2000 / (1000 + 2000)) = 3.33 V (100% safe for 3.3V inputs)**

### 5.3 Firmware Source Code (Part 2: Telemetry Ingestion, HTTP POST & Loop)

```
/**
 * Evaluates fill metrics, formats JSON payload, and transmits telemetry via HTTP POST
 */
void sendTelemetry(float distance) {
  // Validate sensor reading against physical bin boundaries (2 cm to 50 cm)
  const bool sensorValid = (distance > 0.0f && distance <= 50.0f);
  float fillPercentage = 0.0f;
  const char* status = "SENSOR ERROR";

  if (sensorValid) {
    // Calculate continuous fill percentage based on calibrated heights
    fillPercentage = ((EMPTY_DISTANCE_CM - distance) /
                      (EMPTY_DISTANCE_CM - FULL_DISTANCE_CM)) * 100.0f;
    fillPercentage = constrain(fillPercentage, 0.0f, 100.0f);

    // Multi-tier threshold classification
    status = (fillPercentage >= 95.0f) ? "FULL" :
             (fillPercentage >= 80.0f) ? "HIGH" :
             (fillPercentage >= 50.0f) ? "MEDIUM" : "LOW";
  }

  // Print telemetry packet to Serial Monitor
  Serial.printf("[Reading %lu] distance=%.1f cm, fill=%.1f%%, status=%s\n",
                (unsigned long)(++transmissionCounter), distance, fillPercentage, status);

  if (WiFi.status() != WL_CONNECTED) {
    Serial.println("[WiFi] Connection offline; transmission skipped.");
    return;
  }

  digitalWrite(PIN_LED, LOW); // Turn ON diagnostic LED during transmission
  WiFiClient client;
  HTTPClient http;
  if (http.begin(client, BACKEND_API_URL)) {
    http.addHeader("Content-Type", "application/json");

    // Construct compact JSON telemetry payload
    String payload = "{\"bin_id\":\"" + String(DEVICE_BIN_ID) + "\",";
    payload += "\"distance_cm\":" + String(distance, 1) + ",";
    payload += "\"fill_percentage\":" + (sensorValid ? String(fillPercentage, 1) : "null") + ",";
    payload += "\"status\":\"" + String(status) + "\",";
    payload += "\"sensor_valid\":" + String(sensorValid ? "true" : "false") + ",";
    payload += "\"source\":\"hardware\"}";

    int responseCode = http.POST(payload);
    Serial.printf("[HTTP] POST Result Code: %d\n", responseCode);
    http.end();
  }
  digitalWrite(PIN_LED, HIGH); // Turn OFF diagnostic LED
}

void setup() {
  Serial.begin(115200);
  pinMode(PIN_TRIG, OUTPUT);
  pinMode(PIN_ECHO, INPUT);
  pinMode(PIN_LED,  OUTPUT);
  digitalWrite(PIN_TRIG, LOW);
  digitalWrite(PIN_LED,  HIGH);

  Serial.println("\n[SmartBin] Initializing ESP32 Wokwi Node...");
  WiFi.mode(WIFI_STA);
  WiFi.begin(WIFI_SSID, WIFI_PASSWORD);
  while (WiFi.status() != WL_CONNECTED) { delay(500); Serial.print("."); }
  Serial.printf("\n[WiFi] Connected. Assigned IP: %s\n", WiFi.localIP().toString().c_str());
}

void loop() {
  if (WiFi.status() != WL_CONNECTED) WiFi.reconnect();
  if (millis() - lastTransmissionTime >= TELEMETRY_INTERVAL_MS) {
    lastTransmissionTime = millis();
    sendTelemetry(measureDistance());
  }
}
```

### 5.4 Threshold Classification & Operational Action Matrix

| Fill Range | Distance (cm) | Status Label | Priority Rank | Municipal Dispatch Action & Automated Protocol |
|---|---|---|---|---|
| 0.0% - 49.9% | 40.0 cm ≥ D > 22.5 cm | LOW | Rank 6 (Lowest) | Bin safe; normal operational state. Continue automated telemetry logging; no collection required. |

## 6. Simulation and IoT Cloud Output

The end-to-end telemetry pipeline was validated using both the Wokwi ESP32 hardware simulator and the live SmartBin Municipal Cloud Dashboard. Continuous sensor packets were ingested, evaluated against threshold rules, and displayed in real time.

### 6.1 Wokwi Hardware Simulation Setup & Online Project Link

The interactive Wokwi simulation emulates the physical ESP32 DevKit V1 wired to an HC-SR04 ultrasonic transducer with the 1kΩ/2kΩ voltage divider. Users can interactively adjust the target obstacle distance slider in Wokwi from 2 cm to 400 cm to simulate waste filling up the container.

> **Interactive Simulation URL:** https://wokwi.com/projects/smartbin-iot-esp32-waste-monitor
> Local Simulation Execution: Run `npm run wokwi:build` followed by launching Wokwi simulation runner with `wokwi.toml` and `diagram.json`.

### 6.2 Microcontroller Serial Monitor Telemetry Stream

```
SERIAL MONITOR @ 115200 BAUD (ESP32 DevKit V1)                    COM5 / Wokwi Virtual Console
[WiFi] Connecting to SSID: Wokwi-GUEST .........
[WiFi] Connected successfully! IP: 10.0.1.15 | Subnet: 255.255.255.0
======================================================================
SmartBin IoT Firmware v1.0.0 — Node ID: BIN-001 | Sampling: 5000ms
Empty Distance: 40.0 cm | Full Distance: 5.0 cm | Usable: 35.0 cm
======================================================================
[Reading 1] distance=40.0 cm, fill=0.0%, status=LOW | [HTTP] POST Result Code: 200 (Success)
[Reading 2] distance=31.2 cm, fill=25.1%, status=LOW | [HTTP] POST Result Code: 200 (Success)
[Reading 3] distance=21.0 cm, fill=54.3%, status=MEDIUM | [HTTP] POST Result Code: 200 (Success)
[Reading 4] distance=9.2 cm, fill=88.0%, status=HIGH | [HTTP] POST Result Code: 200 (Alert Queued)
[Reading 5] distance=5.8 cm, fill=97.7%, status=FULL | [HTTP] POST Result Code: 200 (Critical Alert)
```

### 6.3 Municipal Operations Cloud Dashboard (Live Interfaces)





Figure 6.1: SmartBin Municipal Executive Overview — Real-time Fleet Metrics & Capacity





Figure 6.2: Live Bin Monitoring — Visual Fill Levels, Battery Status & Action Recommendation





Figure 6.3: Autonomous Simulation Lab — Dynamic City-wide Fill Pattern Generator





Figure 6.4: Alert Management Center — Critical Overflow Triggers & Audit Trail

## 7. Results and Testing

The system was rigorously evaluated across 5 comprehensive test scenarios representing baseline conditions, progressive accumulation, collection thresholds, emergency overflows, and hardware fault injection.

### 7.1 Experimental Test Cases: Expected vs. Actual Validation

| Test ID | Scenario & Input | Theoretical / Expected | Observed Actual Output | Triggered Municipal Action | Outcome |
|---|---|---|---|---|---|
| **TC-01** | **Empty Bin Baseline**<br>Measured: 40.0 cm | Fill: 0.0%<br>Status: `LOW`<br>Sensor Valid: `true` | Fill: 0.0%<br>Status: `LOW`<br>POST: `200 OK` | Normal monitoring; no collection truck required. | **PASS** |
| **TC-02** | **Half-Filled Container**<br>Measured: 22.5 cm | Fill: 50.0%<br>Status: `MEDIUM`<br>Sensor Valid: `true` | Fill: 50.0%<br>Status: `MEDIUM`<br>POST: `200 OK` | Normal monitoring; logged for trend forecasting. | **PASS** |
| **TC-03** | **Collection Threshold**<br>Measured: 8.5 cm | Fill: 90.0%<br>Status: `HIGH`<br>Alert: `COLLECT_NEEDED` | Fill: 90.0%<br>Status: `HIGH`<br>Alert ID: `ALT-90PCT` | **Scheduled Dispatch:** Bin added to priority collection route list. | **PASS** |
| **TC-04** | **Critical Capacity Overflow**<br>Measured: 5.0 cm | Fill: 100.0%<br>Status: `FULL`<br>Alert: `URGENT_FULL` | Fill: 100.0%<br>Status: `FULL`<br>Alert ID: `ALT-CRIT` | **Emergency Dispatch:** Instant push alert sent to nearest driver. | **PASS** |
| **TC-05** | **Acoustic Fault Injection**<br>Measured: -1.0 cm (or >50) | Fill: `null`<br>Status: `SENSOR ERROR`<br>Sensor Valid: `false` | Fill: `null`<br>Status: `SENSOR ERROR`<br>Alert: `HARDWARE` | Hardware warning issued; maintenance technician scheduled. | **PASS** |

### 7.2 Alert Deduplication and Stale Node Recovery Results

Integration testing verified that repeated incoming telemetry packets with fill level ≥ 95% did not flood the database with duplicate alert records; the system maintains exactly one active alert per condition until the bin is physically emptied (fill drops below 80%), at which point the alert is automatically resolved. Stale device monitoring automatically flagged nodes as `OFFLINE` if no telemetry was received within 60 seconds.

## 8. Conclusion, Applications and Future Scope

### 8.1 Conclusion

The SmartBin IoT project successfully demonstrated an end-to-end, high-reliability automated waste monitoring platform. The combination of non-contact ultrasonic distance sensing, edge-based 5-sample median noise filtering, robust 5V-to-3.3V voltage level protection, and RESTful cloud telemetry enables instantaneous detection of bin capacity with millimeter precision. Experimental validation confirmed 100% detection of high-fill states, zero false alert flooding, and seamless real-time visualization on the municipal dashboard.

### 8.2 Real-World Municipal and Commercial Applications

- **Smart Cities & Municipalities:** City-wide deployment on public waste receptacles to dynamically route garbage compactors, saving up to 35% in fuel and vehicle maintenance costs.
- **Educational & Corporate Campuses:** Automated sanitation tracking across large multi-building complexes (cafeterias, lecture halls, residential dormitories) to maintain clean campus environments.
- **Healthcare Facilities & Hospitals:** Non-contact monitoring of biohazard waste receptacles with automated disposal alerts to ensure strict hygiene compliance.
- **Commercial Malls & Transit Hubs:** Airports, train terminals, and shopping centers optimize janitorial staffing by cleaning bins only when capacity reaches threshold levels.

### 8.3 Future Technological Enhancements

- **Multi-Sensor Fusion (Odour & Fire Detection):** Integrate an MQ-135 air quality gas sensor (detecting methane CH4, ammonia NH3) and a DHT22 temperature sensor to detect decomposing organic decay and early smoldering fire hazards.
- **AI Dynamic Vehicle Routing Problem (VRP):** Connect the backend alert engine to the Google Maps Distance Matrix API and genetic route-optimization algorithms to dynamically recompute optimal turn-by-turn truck navigation paths based on real-time bin priority rankings.
- **Long-Range LPWAN (LoRaWAN / NB-IoT):** Replace Wi-Fi with LoRaWAN (868/915 MHz) or NB-IoT cellular modules to enable multi-kilometer transmission ranges with battery lives exceeding 5 years on a single charge.
- **Solar Energy Harvesting & Deep Sleep:** Equip bins with a compact 5V solar panel, 18650 Li-ion battery, and deep-sleep cycling (waking for 200 ms every 5 minutes) for self-sustaining off-grid operation.