REVISION APPROVALS

REV	ECN NO.	DESCRIPTION	DATE	BY	CHK	DES	ENG	SUPV
1	-	INITIAL RELEASE	2-28-2026	-	-	-	-	-

MAINS AC POWER DISTRIBUTION

J1
SCHURTER KMF1.1211.11
PE
L
F1
S
PE
F2
N
N7
FUSE, 5x20mm 250VAC 50mA SLOW BLOW
N8
FUSE, 5x20mm 250VAC 200mA SLOW BLOW
N9
FUSE, 5x20mm 250VAC 200mA SLOW BLOW
N10
FUSE, 5x20mm 250VAC 1A SLOW BLOW
N11
FUSE, 5x20mm 250VAC 2A SLOW BLOW
N12
FUSE, 5x20mm 250VAC 2A SLOW BLOW
N13
FUSE, 5x20mm 250VAC 1.5A SLOW BLOW
N14
FUSE, 5x20mm 250VAC xxxA SLOW BLOW
Housing
N15
FUSE, 5x20mm 250VAC xxxA SLOW BLOW
Housing
N16
FUSE, 5x20mm 250VAC xxxA SLOW BLOW
Housing
J2
Phoenix 1044423
AC_LAMP_L
AC_LAMP_N
J4
Phoenix 1044423
FAN1_L
FAN1_N
J5
Phoenix 1044423
FAN2_L
FAN2_N
J6
Phoenix 1044423
15V_PS_L
15V_PS_N
J7
Phoenix 1044423
12VA_PS_L
12VA_PS_N
J8
Phoenix 1044423
12VB_PS_L
12VB_PS_N
J9
Phoenix 1044423
5V_PS_L
5V_PS_N
J10
Phoenix 1044423
SPARE
J11
Phoenix 1044423
SPARE
J12
Phoenix 1044423
SPARE
N4
FUSE DRAWER 4301.1405
N3
FUSE, 5x20mm 250VAC 6.3A SLOW BLOW
N1
GND STUD -- #10-32x1 1/2" 18-8 SS
N2
GND NUT 10-32 FLANGE 18-8 SS
N101
REAR PANEL LABEL
FUSED: 6.3A
FLA: 6A
MAINS INPUT FILTER AND CHASSIS GROUND
N6
Phoenix 3030271
10 Pos Jumper
N5
Phoenix 3030271
10 Pos Jumper

LOW VOLTAGE POWER SUPPLIES

U1
VLD15-100M
15V_PS_L
15V_PS_N
AC_L
AC_N
PE
OUT+
SENSE+
COM
SENSE-
OUT-
+15V
+15VS
15V_RET
-15VS
-15V
J13
N20
Phoenix 3047248
TB ENDCAP
J17
+15V_LED
+15V_OUT
+15V_TP
J18
15V_RET_LED
15V_RET_OUT
15V_RET_TP
J19
-15V_LED
-15V_OUT
-15V_TP
U2
VA12NT200M
12VA_PS_L
12VA_PS_N
+12VA
+12VA_S
12VA_RET_S
12VA_RET
J14
N22
Phoenix 3047248
TB ENDCAP
J20
+12VA_LED
+12VA_OUT
+12VA_TP
J21
12VA_RET_LED
12VA_RET_OUT
12VA_RET_TP
U3
VA12NT200M
12VB_PS_L
12VB_PS_N
+12VB
+12VB_S
12VB_RET_S
12VB_RET
J15
N21
Phoenix 3047248
TB ENDCAP
J22
+12VB_LED
+12VB_OUT
+12VB_TP
J23
12VB_RET_LED
12VB_RET_OUT
12VB_RET_TP
U4
TD5-150M+
5V_PS_L
5V_PS_N
+5V
+5VS
5V_RET
-5VS
-5V
J16
N23
Phoenix 3047248
TB ENDCAP
J24
+5V_LED
+5V_OUT
+5V_TP
J25
5V_RET_LED
5V_RET_OUT
5V_RET_TP
J26
-5V_LED
-5V_OUT
-5V_TP
5V_RET_TP
12VA_RET_TP
12VB_RET_TP
15V_RET_TP
GND

FRONT PANEL INDICATORS

LA1
120VAC LAMP
AC_LAMP_L
AC_LAMP_N
N30
Phoenix 3210208
+5V_LED
TP101
2142-2
N31
Phoenix 3210208
-5V_LED
TP102
2142-2
N32
Phoenix 3210208
+12VA_LED
TP103
2142-2
N33
Phoenix 3210208
+12VB_LED
TP104
2142-2
N34
Phoenix 3210208
+15V_LED
TP105
2142-2
N35
Phoenix 3210208
-15V_LED
TP106
2142-2
TP107
2142-0
GND
N102
Phoenix 3076031
D1
N103
Phoenix 3076031
D2
N104
Phoenix 3076031
D3
N105
Phoenix 3076031
D4
N106
Phoenix 3076031
D5
N107
Phoenix 3076031
D6
N24
Phoenix 3036796
R101
200R
N25
Phoenix 3036796
R1
200R
N26
Phoenix 3036796
R4
900R
N27
Phoenix 3036796
R3
900R
N28
Phoenix 3036796
R6
1k2
N29
Phoenix 3036796
R5
1k2
N36
Phoenix 3076036
DISCO TB ENDCAP
N108
Phoenix 3038590
TB ENDCAP

OUTPUT CONNECTOR

J3
Souriau_RT001412SNH
+15V_OUT A
15V_RET_OUT B
-15V_OUT C
+12VA_OUT D
12VA_RET_OUT E
+12VB_OUT F
12VB_RET_OUT G
+5V_OUT H
5V_RET_OUT J
-5V_OUT K
L
M
SH
N37
Output Power Cable

FRONT PANEL FANS

M1
NMB 08038PB-A1L-EA-00
FAN1_L 1
2 FAN1_N
M3
NMB 08038PB-A1L-EA-00
FAN2_L 1
2 FAN2_N

MISC MECHANICAL

N38
Bridle Ring
McMaster
1706T92
N17
TS3575SL
5" DIN Rail
N39
Bracket
McMaster
15275A63
N19
TS3575SL
15" DIN Rail
N18
Phoenix 0800886
DIN ENDSTOP

APPLICATION

DRAWN BY	M. Capotosto	2-28-2026
CHECKED BY		
DESIGN APPROVAL		
ENG'PHY APPROVAL	J. Mead	2-28-2026
GROUP LEADER	D. Padrazo	
CEE/CME	NA	NA
DIVISION HEAD	NA	NA
Q.A.	NA	NA
SAFETY/RSC	NA	NA
DEPARTMENT CHAIRMAN	NA	NA

NSLS-II
BROOKHAVEN NATIONAL LABORATORY
UPTON, N.Y. 11973

TITLE: ACMI-II Power Supply Wiring Diagram

SIZE	DRAWING NUMBER:	REV.
B	TBD	-

Q.A. CATEGORY A3 | SCALE: N.A. | WEIGHT: N.A. | SHEET 1 OF 1

REV -
SHT 1 OF 1
TBD
DWG NO

KiCad E.D.A. 9.0.6