

Visual Computing

Janis Hutz

<https://janishutz.com>

October 1, 2026

1 Computer Vision

1.1 Digital Image

Def Image $f: \mathbb{R}^n \rightarrow S$, for greyscale $n = 2$, $S = \mathbb{R}^+$, in digital form: $I: \{1, \dots, X\} \times \{1, \dots, Y\} \rightarrow S$

Rem Pinhole size affects blur, **Lens Camera** as sol.

Rem Charge Coupled Device (CCD) sensor reads line-by-line (rolling shutter), then each line pixel-by-pixel

Def Sensor array is an array of *photosites* (bucket of el. charge $\propto$ light intensity), then read via ADC.

Rem Blooming Caused by photosite saturation

Def Dark Current CCDs give non-zero output in darkness, fluctuates randomly

Def CMOS Sensor Each photo sensor has own amplifier, **more noise, lower sensitivity**, “smart” pixels bc. CMOS

Def Sampling Repeated measurement on certain interval, **Reconstruction** is inverse. Issues: **undersampling** (lose information), **oversampling** (too large files).

Def Nyquist Frequency highest signal freq that can be accurately captured, half of sampling rate

Def Quantization Lossy discretization of analogue value, simple versions have $k = 2^b$ values for b bits

Rem Quantization “on” y -axis, Sampling “along” x -axis

Def Res. Geometric: PPI; Radiometric: Bits/Pixel

Def Signal-Noise-R. (SNR) Image quality index: $s = F \div \sigma$, with $F = \frac{1}{XY} \sum_{x=1}^X \sum_{y=1}^Y f(x, y)$.

Def Add. Gaussian Noise $I(x, y) = f(x, y) + c$, with $c \sim \mathcal{N}(0, \sigma^2)$, s.t. $p(c) = \frac{1}{\sqrt{2\pi\sigma^2}} e^{-\frac{c^2}{2\sigma^2}}$

Def Poisson Noise $p(k) = \frac{\lambda^k e^{-\lambda}}{k!}$

1.2 Filtering & Convolution

Def Moving Average New image G where $G[x, y]$ is average of surrounding pixels and $F[x, y]$

Def Linear Shift-Invariant Filter. New pixels lin. comb. of neighbours, *shift-invariant* = doing same for all pixels. Good for: smoothing, noise reduction, sharpening

Def Linear Operation L lin. if $L[\alpha I_1 + \beta I_2] = \alpha L[I_1] + \beta L[I_2]$, $I'_j = \sum_{i=1}^N \alpha_{ij} I_i$ for $j \in \{1, \dots, N\}$

Def Linear Filtering $I'(x, y) = \sum_{(i,j) \in N(x,y)} K(i, j) I(x + i, y + j)$ with I the input image and K the **kernel** of operation, $N(x, y)$ neighbourhood function for pixel (x, y) . Shift-Invariant if K doesn't depend on (x, y) (i.e. same weights everywhere)

Def Kernel Typically matrix, center of matrix is $(0, 0)$

Def Correlation $I'(x, y) = \sum_{j=-k}^k \sum_{i=-k}^k K(i, j) I(x + i, y + j)$

Def Conv. $I'(x, y) = \sum_{j=-k}^k \sum_{i=-k}^k K(-i, -j) I(x + i, y + j)$

Gen.: $g(x) = (f * h)(x) = \int_{-\infty}^{\infty} f(\tau) h(x - \tau) d\tau$, $h(\tau)$ kernel

Rem If $K(i, j) = K(-i, -j)$, then Convolution = Corr.

Rem Convolution is linear: $[(af + bg) * h](x) = a(f * h)(x) + b(g * h)(x)$, commutative: $(f * h)(x) = (h * f)(x)$, associative: $(f * g) * h = f * (g * h)$; Diff: $\frac{d}{dx} (f * h)(x) = f * h'$

Rem At edge of image, extrapolate, options: clip filter (black), wrap around, copy edge, reflect across edge

Def Gaussian Kernel $G_\sigma = \frac{1}{2\pi\sigma^2} e^{-\frac{x^2+y^2}{2\sigma^2}}$. The smoothing amount depends on σ and window size.

Rem $g(x, y) = g(x)g(y)$, with $g(x) = \frac{1}{\sqrt{2\pi\sigma^2}} \exp\left(-\frac{x^2}{2\sigma^2}\right)$. Efficient implementation: First rows 1D, then cols 1D

1.3 Edge Detection

Def Scale Space Collection of img at diff scales & smooth.

Rem Finite diff. for $\frac{\partial f(x, y)}{\partial x} \approx \frac{f(x+1, y) - f(x, y)}{1}$, filter: $[1, -1]$. Can use par der. for edge detection

Def Gradient $\nabla f = [\frac{\partial f}{\partial x}, \frac{\partial f}{\partial y}]$, dir of most rapid change. **Edge strength** (magnitude): $M(x, y) = \|\nabla f\|$.

Noise makes edge detection hard, smooth first, then edge is peak in $\frac{\partial}{\partial x} (h * f)$. **Angle** $\alpha(x, y) = \arctan\left(\frac{\partial f}{\partial y} \div \frac{\partial f}{\partial x}\right)$

Thm $\frac{\partial}{\partial x} (h * f) = \left(\frac{\partial h}{\partial x}\right) * f$

Def Laplacian $\nabla^2 f = \frac{\partial^2 f}{\partial x^2} + \frac{\partial^2 f}{\partial y^2}$

Def LoG $\nabla^2 G(x, y) = \frac{1}{2\pi\sigma^2} \left(\frac{x^2+y^2-2\sigma^2}{\sigma^2}\right) \exp\left(-\frac{x^2+y^2}{2\sigma^2}\right)$

Edge is at zero-crossing of $\left(\frac{\partial^2}{\partial^2 x} h\right) * f$. σ affects scale of edges detected (larger σ = stronger edges)

Def Canny E.D. **1** smooth w/ Gaussian, **2** gradient magnitude & angle, **3** Nonmaxima suppression to gradient mag. image, **4** double thresholding to detect strong and weak edge pixels, **5** reject weak edge pixels not connected with strong edge pixels

Def Non-Max-Suppression Quantize edge normal to four dir, if $M(x, y)$ smaller than either neighbour in dir, suppress, else keep

Def Thresholding Via thresholds $\theta_{\text{high}} \div \theta_{\text{low}} \in [2, 3]$ (typ)

1.3.1 Line Fitting

Generally challenging, missing information

Def RANSAC Random Sample Consensus:

1. Rand. sel. *seed group* of p. w/ base transf. est.
2. Compute transformation from seed group
3. Find *inliers* to this transformation
4. If inliers sufficiently large, recompute least-squares estimate of transformation on all inliers

Sample count: w frac of inliers, n points define hypothesis ($n = 2$ for lines), k samples chosen. Prob. sample of n points correct: w^n , prob all k samples fail: $(1 - w^n)^k$, i.e. **choose k high to keep below failure rate**

Def Hough Transform Voting technique, main idea:

1. Vote for all possible lines on which edge could lie
2. Look for line candidates that get many votes
3. Noise features votes should be inconsistent

1.4 Fourier Transform

Def Sinusoid $f(x) = A \cdot \sin(2\pi ux + \psi)$ with ψ phase shift, equiv: $A \cos(\psi) \sin(2\pi ux) + A \sin(\psi) \cos(2\pi ux)$

Def Complex Exponential $e^{i\theta} = \cos(\theta) + i \sin(\theta)$, complex conj. $e^{-i\theta} = \cos(\theta) - i \sin(\theta)$. For sinusoid: $\theta = 2\pi ux$.

Def Cont. Time F. Ser Sig as sum of sinusoids, $f(x) = \sum_{k=-\infty}^{\infty} c_k e^{i2\pi kx \div T}$, with T the period and c_k fourier coeff.

Def Cont. Time F. Transf $F(u) = \sum_{\mathbb{R}} f(x) e^{-2\pi ux} dx$, $f(x) = \sum_{\mathbb{R}} F(u) e^{i2\pi ux} du$. $F(u)$ is typ complex valued,

Def Ampl. Spec $A(u) = \|F(u)\|$

Def Phase Spec $\phi(u) = \arg F(u) = \arctan\left(\frac{\Im(F(u))}{\Re(F(u))}\right)$

Def DFT used for analyzing discrete data. Applies base change to values via matrix multiplication. More general:

$$F(k) = \sum_{n=0}^{N-1} x_n e^{-i2\pi kn \div N} \text{ for } k \in \{0, 1, \dots, N-1\}$$

For image:

$$F(u, v) = \sum_{x=0}^{N-1} \sum_{y=0}^{M-1} I(x, y) \cdot e^{-i2\pi\left(\frac{ux}{N} + \frac{vy}{M}\right)}$$