

ngspice-46 — Full Change Report

Every modification and its reason (original → current)

Ngspice + OpenVAF Enhancements project

July 2026

Contents

ngspice-46 — Full Change Report	3
1. The OSDI ABI, version 0.4 → 0.7	3
2. The OSDI runtime — src/osdi/	4
3. Analyses — src/spicelib/analysis/	5
4. Frontend — src/frontend/	6
5. Parser and device registry — src/spicelib/	7
6. Maths — src/mathlib/	8
7. Build system	8
8. Per-enhancement index	8

ngspice-46 — Full Change Report

Every modification applied to ngspice-46 in this project, with its reason. The baseline is the pristine ngspice-46 source tree (as vendored in the project's `original/` snapshot, which already contains OpenVAF-Reloaded's stock OSDI support); the current state is the tree committed in this repository under `ngspice-46/`. Each entry links the enhancement write-up in [enhancements_doc/](#) that carries the full engineering detail and the verifying example suite. The companion document [openvaf_changes_full-report.md](#) covers the compiler side.

Maintenance note: this report is updated whenever an enhancement touches ngspice sources. If you are reading it alongside a newer tree, the per-enhancement index at the end tells you the last change it covers.

Scope summary. One new source file and 33 modified ones carry all the functional changes (~2,000 substantive diff lines). A further ~100 `Makefile.in` files and `config.h.in` differ only because the auto-tools were regenerated with a current libtool ([E-77](#)); they contain no hand-written changes and are not listed individually. Everything below is behavior, interface, or diagnostics.

1. The OSDI ABI, version 0.4 → 0.7

`src/osdi/osdi.h` is the authoritative C contract between ngspice and the `.osdi` objects `openvaf-r` produces. The project extended it four times — twice additively (new exported symbols old loaders simply never look up), twice with genuine version bumps (layout changes):

Change	Kind	Enhancement	Why
<code>OSDI_ABSDELAY_COUNT</code> / <code>OSDI_ABSDELAY_INFO</code> exports	additive sym- bols	E-1	<code>absdelay()</code> needs simulator-side waveform history and synthetic delay-equation rows; the descriptors tell ngspice which nodes/offsets each delay slot uses
<code>OSDI_LAST_CROSSING_COUNT</code> / <code>OSDI_LAST_CROSSING_INFO</code> exports	additive sym- bols	E-6	<code>last_crossing()</code> needs waveform history and crossing interpolation — same additive pattern as <code>absdelay</code>
<code>OsdNode.nodeset</code> field	ABI 0.5 (node stride change)	E-45	Verilog-A net initializers (<code>electrical a = 5.0;</code>) become solver initial-guess nodesets; every node record carries the hint
<code>num_ac_stim_src</code> / <code>ac_stim_sources</code> / <code>load_ac_stim</code> descriptor tail	ABI 0.6 (de- scriptor grows)	E-51	full <code>ac_stim()</code> support: a Verilog-A module can be the AC stimulus, so the descriptor must enumerate its AC right-hand-side sources
<code>load_noise</code> destination stride 1 → 2 (signed (<code>flat</code> , <code>react</code>) power pairs)	ABI 0.7	E-54	correct noise physics: operating-point-dependent factors and <code>ddt()</code> -shaped ($j\omega$) noise need a complex amplitude per source, $re + j\omega \cdot im$, so coherent same-named sources (LRM 4.6.4) sum with correct sign and frequency shape

Two additive flag conventions ride on the existing `eval()` interface (not version bumps):

- `EVAL_FLAG_IS_FINAL_STEP` (bit 1 ≪ 21) in the `eval input` flags — `@(final_step)` firing ([E-53](#));
- `eval return` flags for `$finish/$stop` requests and `$discontinuity`-driven step rejection ([E-55](#)).

Pairing consequence: this ngspice requires $\text{OSDI} \geq 0.7$ and rejects older objects with a clear version message; `.osdi` files from older compilers must be recompiled ([E-54](#)).

2. The OSDI runtime — `src/osdi/`

osdiaccept.c — new file ([E-55](#), [E-1](#), [E-6](#))

The accepted-timepoint hook (`DEVaccept`) OSDI previously lacked. It advances the `absdelay/last_crossing` waveform histories only at *accepted* points (so rejected timesteps don't corrupt the delay lines) and reads the per-attempt latched `$finish/$stop` request flags at the one boundary where honoring them is safe. Why: acting on `$stop` mid-Newton-iteration was treated as a step failure and ground the timestep into a rejection loop; `$finish` was ignored outright.

osdidefs.h (104 diff lines)

- `OsdiExtraInstData` grows the per-instance fields behind every runtime feature: `dt/temp` offsets with given-flags (instance temperature), `eval_flags`, `absdelay` waveform-history rows and pre-allocated KLU/SPARSE matrix-pointer sets for the delay-equation rows (re-pointed on every DC↔AC transition, mirroring the regular Jacobian handling), and the `last_crossing` history ([E-1](#), [E-6](#), [E-55](#)).
- `ALIGN` macro renamed `OSDI_ALIGN`: the macOS SDK's `<sys/param.h>` defines an unrelated `ALIGN`, producing a redefinition warning in every OSDI translation unit ([E-77](#)).

osdiitf.h / **osdiext.h**

The registry-entry structure gains the `absdelay/last_crossing` descriptor pointers, and `OSDIpendingRequests()` is exported so the analyses can ask "did any device request `$finish/$stop` at this accepted point?" ([E-1](#), [E-6](#), [E-55](#)).

osdiregistry.c (68 diff lines)

- Loads the `absdelay/last_crossing` descriptor arrays from each `.osdi` and threads them into the registry entries ([E-1](#), [E-6](#)).
- Requires $\text{OSDI} \geq 0.7$ ([E-54](#)).

osdiinit.c (8 diff lines)

- Registers the `DEVaccept` hook ([E-55](#)).
- Publishes the synthetic instance-temperature parameter under both spellings, `dt` and the conventional `dtemp` every built-in device uses; `n1 a b mod dtemp=10` used to fail with "unknown parameter" while the underlying plumbing was exact ([E-80](#)).

osdiload.c (441 diff lines — the largest OSDI change)

- Stamps the `absdelay` synthetic rows (`y_synth`, `z`) for DC, AC and transient, driving the delay from the recorded history ([E-1](#)).
- Evaluates `last_crossing` from the recorded waveform with linear interpolation between the bracketing timepoints ([E-6](#)).
- Passes the final-step flag through to `eval()` ([E-53](#)).
- Latches `eval`-return flags per timepoint attempt (`point_eval_flags`, OR-ed across Newton iterations, reset per attempt) so `$finish/$stop` under solution-dependent conditions survive to the accepted-point boundary ([E-55](#)).

- Folds the stride-2 signed noise-power pairs ($\text{fac} \cdot |\text{fac}|$ semantics) when transferring `load_noise` results (E-54, E-42).

osdisetup.c (178 diff lines)

- Creates the synthetic delay-equation unknowns and matrix entries for `absdelay` (E-1).
- Applies the OSDI nodesets (`OsdNode.nodeset`) as solver initial guesses (E-45).
- A `$fatal/$finish` raised during setup (models rejecting their configuration by design — HiSIM's `$port_connected` guards) used to surface as ngspice's baffling *"impossible error — can't occur"*; it now reads *"a Verilog-A device rejected its configuration during setup"* (E-56).

osdiacld.c (89 diff lines)

- AC loading gains the `ac_stim` right-hand-side injection: the partitioned AC-stimulus source array is loaded through `load_ac_stim` and added to the AC RHS with exact magnitude and phase, `$mfactor` applied linearly (deterministic signals scale with multiplicity) (E-51, E-26).
- Complex ($j\omega$ -shaped) noise coupling entries participate in the AC matrix (E-54).

osdinoise.c (93 diff lines)

- Per-instance grouping of same-named noise sources: coherent summation of complex amplitudes ($a + j\omega \cdot b \cdot T$ before squaring, per LRM 4.6.4 — same-named sources correlate (including exact anti-phase cancellation), differently-named ones stay independent (E-42).
- Reads the stride-2 signed pairs of ABI 0.7 (E-54).

osditrunc.c (34 diff lines)

- Honors `$discontinuity(n)`'s next-step clamp: a negative `bound_step` sentinel from the model limits the step after the event (E-24).
- Honors the step-rejection return flag: when an event fired inside the step, `OSDIt trunc` requests `delta/8` (with a $20 \cdot \text{CKTdelmin}$ termination floor) so the integrator bisects onto the discontinuity instead of extrapolating across it (E-55).

osdi/Makefile.am

Adds `osdiaccept.c` to the build (E-55).

3. Analyses — **src/spicelib/analysis/**

dctran.c (46 diff lines)

- Advances OSDI delay/crossing histories via the accept path and skips history corruption on rejected steps (E-1, E-6).
- Issues the dedicated `@(final_step)` evaluation at the converged end of a successful transient (E-53).
- Honors accepted-point `$finish` (ends the analysis cleanly, firing `final_step` at the requesting point), `$stop` (pauses resumably), and aborts with a clear error on `$fatal`'s `E_PANIC` instead of retrying it as nonconvergence (E-55).

dcop.c (9) and **acan.c** (10)

- Fire `@(final_step)` at their successful end (an operating point fires both step events — a single point is first *and* last) (E-53).

- An AC job's operating-point phase carries the analysis name bit (only the name — adding the reactive `CALC_*` bits would wrongly enable integration at an op), so `analysis("ac")` holds through the whole AC run per LRM 4.6.1 and `@(initial_step("ac"))` fires in AC (E-53).

dctrcurv.c (150) + **include/ngspice/trcvdefs.h** (13)

- Generic `.dc @inst[param]` sweeps (a new sweep code): the DC sweep previously hardcoded `Vsource/Isource/Resistor/temperature`, so sweeping any other device parameter was a fatal error. The generic sweep resolves `@inst[param]` through the device's own parameter tables, refreshes per point via `DEVtemperature` (for OSDI exactly the `alter` path), nests with other sweep variables, and restores the original value afterwards (E-62).
- Fires `final_step` at the last sweep point; honors a `$finish` raised mid-sweep (E-53, E-55).

noisean.c (37)

- A singular AC matrix during noise analysis crashed ngspice with a SIGABRT: the code ignored `NIacIter`'s return and the adjoint solve asserted on the unfactored matrix. It now aborts cleanly ("AC solution failed at ... Hz") (E-56).
- Honors deferred `$finish/$stop` raised at the noise operating point and fires `final_step` on success (E-55, E-53).

span.c (31) + **cktspdum.c** (14)

- 1-port S-parameter analyses enabled: the "we need at least two ports" error was over-strict (a 1-port is a plain reflection measurement; the matrix machinery is N-general) — and it was hiding the `cadjoint` crash fixed in `dense.c` (E-64).
- **Rbase** published into the `sp` plot from port 1's `z0`, making the Touchstone writers work with no manual `let Rbase = 50` incantation (E-64).
- Stock NaN fixed in **donoise** noise-parameter extraction: the uncorrelated noise conductance G_u is analytically zero for fully-correlated single-source topologies, and floating-point rounding could land `sqrt(Ycor2 +  $G_u/R_n$ )`'s argument at $-10^{-18} \rightarrow \text{NaN}$ for the noise figure. Clamped to the physical range ≥ 0 — found by parity testing against an OSDI resistor that produced the exact textbook NF where the built-in returned NaN (E-63).

cktdisto.c (16)

- `.disto` silently reported zero distortion for OSDI devices — the distortion kernel needs higher-order Taylor coefficients the OSDI ABI cannot provide (first derivatives only), and such devices were skipped without a word. A prominent warning now names each affected OSDI device type (E-62).

4. Frontend — **src/frontend/**

postcoms.c (414 diff lines) + **postcoms.h** + **commands.c** (16)

The Touchstone I/O subsystem (E-64, E-72):

- **wrsnp** (with `wrs2p` dispatching to the same handler): Touchstone v1 for any port count — the classic 2-port `S11 S21 S12 S22` column order preserved byte-identically, $N \geq 3$ in the spec's row-major layout with at most four complex pairs per line;
- writer options `wrsnp <file> [ri|ma|db] [s|y|z] [hz|khz|mhz|ghz]`, any combination in any order: MA/DB formats, Y/Z parameters (normalized to `Rbase`, $Y \cdot R / Z/R$, per the v1 spec), frequency units — the option line reflects every choice;

- **rdsnp**: reads any Touchstone v1 file into a new plot with a Hz frequency scale and complex vectors matching the .sp plot's conventions (MA/DB converted back, Y/Z de-normalized, the 2-port column order handled, Rbase published so imports round-trip) — measured data diffs against simulation in one let expression.

Why: E-63 showed the S-parameter *analysis* was exact but its results could not leave ngspice in the industry-standard format (wrs2p demanded a never-created Rbase vector), and nothing could bring VNA data in.

outitf.c (16)

- Integer operating-point variables recorded per point: getSpecial masked with IF_REAL only, so an integer opvar saved with .save @n1[flag] produced garbage in transient vectors (E-32).
- The plot-memory guard's message printed %Id — a Windows-only printf length modifier that is undefined behavior elsewhere and rendered the message as the numberless "memory required (Id Bytes)". Now %zu: real byte counts on every platform (E-77).

resource.c (27)

ft_ckptspace() — the "approaching max data size" warning (RSS > 95% of RSS + free RAM) — now honors **set no_mem_check** (the same opt-out the fatal output-size estimate in outitf.c respects; one variable governs both memory guards) and warns once per excursion above the threshold, re-arming below 90%, instead of repeating on every check through a long analysis (E-81).

display.c (1)

#undef NODEV before the local macro definition — the macOS SDK's <sys/param.h> defines an unrelated NODEV (E-77).

5. Parser and device registry — **src/spicelib/**

parser/inpgtok.c (10)

A **.model** card override silently dropped its first parameter when the type name and the opening parenthesis had no space between them (modname devtype(p1=v1 ...)): INPgetNetTok's scan did not treat (as a token boundary, so the type token swallowed the paren and the first parameter name. Found while verifying event-function counters whose model-card overrides mysteriously kept defaults (E-8).

parser/inpgmod.c (5)

find_model_parameter() dereferenced *(device->numModelParms), which is NULL for built-ins that take no model cards (VCVS, CCCS, ...) — any *referenced* .model m vcvs() card segfaulted, with no OSDI involved at all (an ordinary MOS instance sufficed). This was the true root of the long-documented "module named like a built-in crashes" gotcha. One NULL guard; both shapes now produce clean, located errors (E-76).

devices/dev.c (51)

- Duplicate device-type registration warned and skipped: osdi_add_device() appended every descriptor unconditionally, and the model-card lookup scans front-to-back — so a module name duplicated across two loaded libraries silently resolved to the *first* registration (loading an updated model library gave the stale device with no hint), and a module named like a built-in corrupted

model creation. Registration now checks the table case-insensitively and skips duplicates loudly (E-76).

- **pre_osdi** path dedup: loading an already-loaded file notes it and skips — with the remedy stated: *“restart ngspice to load a recompiled file”* (E-76, E-81).

osdi/osdiparam.c (E-93)

Setting a fixed (**localparam**) OSDI parameter from the netlist used to be swallowed silently: openvaf exports every **localparam** as a parameter, its “given” flag is forced false, and the written value is overwritten by the parameter-init default — so `.model ... N=8` on a frozen structural width parameter changed nothing, with no feedback. **OSDIparam/OSDIiParam** now test the new **PARAM_FLAG_FIXED** descriptor flag (set by openvaf, a free bit of the parameter **flags** field) and emit *“parameter 'N' is a fixed (localparam) value and cannot be set from the netlist; ignored”* instead of silently dropping it (E-93).

6. Maths — **src/maths/**

dense/dense.c (11 substantive lines; the file also carries a whitespace/line-ending normalization from editing)

cadjoint() had no 1×1 base case: its cofactor loop allocated 0×0 and then negative-sized minors, killing ngspice with `malloc: can't allocate -8 bytes` — the crash that had been hiding behind the “at least two ports” guard in **span.c**. The adjugate of [a] is [1] (the empty minor’s determinant is 1 by convention), making `cinverse` of a 1×1 equal `1/a`; a 100 Ω load on a 50 Ω port now writes a proper `.s1p` with `S11 = 1/3` exactly (E-64).

sparse/spfactor.c (6)

The Markowitz-product overflow guards compare a double against **LARGEST_LONG_INTEGER** (= **LONG_MAX**), which is not exactly representable as a double; the conversion is now explicit — identical semantics, intentional and warning-free (E-77).

7. Build system

xspice/icm/makedefs.in (4)

The XSPICE codemodel (`.cm`) link rule hardcoded the pre-macOS-10.3 idiom `-bundle -flat_namespace -undefined suppress`, deprecated loudly by the modern linker on all 14 codemodel links (CI macOS builds included). Now `-bundle -undefined dynamic_lookup` — the modern spelling for plugins whose host symbols resolve at load time (E-77).

Autotools regeneration (the ~100 **Makefile.in** files + **config.h.in**)

Regenerated by `./autogen.sh` with libtool 2.5.4 during the zero-warning work — a build tree whose configure predates libtool 2.4.7 selects the deprecated `darwin -undefined suppress` flag whenever **MACOSX_DEPLOYMENT_TARGET** is unset. No hand-written content (E-77).

8. Per-enhancement index

Every enhancement that touched ngspice, oldest first:

Enhancement	osdi files	One line
E-1	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c, osdisetup.c, dctrans.c (+accept path)	absdelay(): synthetic delay rows + waveform history
E-6	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c	last_crossing(): history + interpolated crossings
E-8	parser/ingtok.c	.model card first-parameter drop fix
E-24	osditrunc.c	\$discontinuity next-step clamp
E-25	osdi callbacks (get_simparams)	expose analysis_name + simulator simparams
E-32	outitf.c	integer opvars recorded per point
E-42	osdinoise.c	coherent same-named noise grouping (LRM 4.6.4)
E-45	osdi.h (ABI 0.5), osdisetup.c	Verilog-A nodesets applied to the solver
E-51	osdi.h (ABI 0.6), osdiacld.c	full ac_stim AC-RHS injection
E-53	dctrans.c, dcomp.c, dctrans.c, acan.c, noisean.c, osdiload.c	@(final_step) + analysis-name phase bits
E-54	osdi.h (ABI 0.7), osdinoise.c, osdiload.c, osdiacld.c, osdiregistry.c	node-free complex noise factors, stride-2 pairs
E-55	osdiaccept.c (new), osdiload.c, osditrunc.c, osdiinit.c, dctrans.c, dctrans.c, osdiitf.h, Makefile.am	\$finish/\$stop/\$fatal honored; \$discontinuity step rejection
E-56	noisean.c, osdisetup.c	noise SIGABRT fix; setup-rejection diagnostics
E-62	dctrans.c, trcvdefs.h, cktdisto.c	generic .dc @inst[param] sweeps; .disto warning
E-63	span.c	donoise NaN clamp (stock defect, found by parity)
E-64	span.c, cktspdum.c, dense.c, postcoms.c/.h, commands.c	Touchstone export, auto-Rbase, 1-port .sp, cadjoint 1x1
E-72	postcoms.c/.h, commands.c	Touchstone round 2: MA/DB/Y/Z/units + rdsnp reader
E-76	dev.c, inpgmod.c	duplicate-registration warning, load dedup, stock .model segfault fix
E-77	osdidefs.h, display.c, outitf.c, spfactor.c, makedefs.in (+autotools regen)	zero-warning build, 33 → 0
E-80	osdiinit.c	dtemp instance-parameter alias
E-81	resource.c, dev.c	memory-warning opt-out + once-per-excursion; reload-note hint
E-93	osdi.h, osdiparam.c	warn (not silently ignore) when a netlist sets a PARA_FLAG_FIXED (localparam) OSDI parameter

(E-25's *simparam* exposure lives in the OSDI callback table populated at load time; its diff rides inside the *osdiload.c/callbacks* changes.)

Every entry above is guarded by a verify script under [examples/](#) and was regression-checked against the full example arsenal, the compiler's integration suite, and the VA_TEST industry-model corpus at the time it landed.