
SECTION -B

Q-1) Create VLAN 10 named Management and VLAN 20 named Staff on the switch. Assign specific access ports to each VLAN. Verify the VLAN assignments using show vlan brief





```
Switch> enable
Switch# configure terminal
Enter configuration commands, one per line.  End with CNTL/Z.
Switch(config)#
Switch(config)# vlan 10
Switch(config-vlan)# name Management
Switch(config-vlan)# exit
% Creating VLAN 10...
Switch(config)#
Switch(config)# vlan 20
Switch(config-vlan)# name Staff
Switch(config-vlan)# exit
% Creating VLAN 20...
Switch(config)#
Switch(config)# interface range fa0/1-4
Switch(config-if-range)# switchport mode access
Switch(config-if-range)# switchport access vlan 10
Switch(config-if-range)# exit
Switch(config)#
Switch(config)# interface range fa0/5-8
Switch(config-if-range)# switchport mode access
Switch(config-if-range)# switchport access vlan 20
Switch(config-if-range)# exit
Switch(config)# end
Switch#
Switch# show vlan brief

VLAN  Name                             Status        Ports
----- -------------------------------- ------------  ---------------------------------
1     default                          active        Fa0/9, Fa0/10, Fa0/11, Fa0/12
                                                     Fa0/13, Fa0/14, Fa0/15, Fa0/16
10    Management                       active        Fa0/1, Fa0/2, Fa0/3, Fa0/4
20    Staff                            active        Fa0/5, Fa0/6, Fa0/7, Fa0/8
1002  fddi-default                     active
1003  token-ring-default               active
1004  fddinet-default                  active
1005  trnet-default                    active

Switch# _
```

Q-2) Task 2: Configure an 802.1Q Trunk Link Establish a trunk connection so traffic for multiple VLANs can pass between the switch and router. (Applied — one concept combined with port-mode configuration.) Configure the switch port connecting to the router as an 802.1Q trunk. Restrict the trunk to allow only VLAN 10 and VLAN 20. Verify trunk status using show interfaces trunk. Confirm there is no native VLAN mismatch between the switch and router.



Router

```
Router>en
Router#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
Router(config)#int g0/0
Router(config-if)#no shut

Router(config-if)#
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0, changed state to up

Router(config-if)#exit
Router(config)#int g0/0.10
Router(config-subif)#
%LINK-3-UPDOWN: Interface GigabitEthernet0/0.10, changed state to down

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0.10, changed state to up

Router(config-subif)#en
Router(config-subif)#encapsulation dot1q 10
Router(config-subif)#ip address 192.168.10.1 255.255.255.0
Router(config-subif)#exit
Router(config)#int g0/0.20
Router(config-subif)#
%LINK-3-UPDOWN: Interface GigabitEthernet0/0.20, changed state to down

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0.20, changed state to up

Router(config-subif)#encapsulation dot1q 20
Router(config-subif)#ip address 192.168.20.1 255.255.255.0
Router(config-subif)#exit
Router(config)#do wr
Building configuration...
[OK]
Router(config)#
```

Switch

```
Switch>en
Switch#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
Switch(config)#vlan 10
Switch(config-vlan)#name team
Switch(config-vlan)#exit
Switch(config)#vlan 20
Switch(config-vlan)#name hr
Switch(config-vlan)#exit
Switch(config)#int f0/1-2
                 ^
% Invalid input detected at '^' marker.

Switch(config)#int range f0/1-2
Switch(config-if-range)#switchport mode access
Switch(config-if-range)#switchport access vlan 10
Switch(config-if-range)#exit
Switch(config)#int range f0/3-4
Switch(config-if-range)#switchport mode access
Switch(config-if-range)#switchport access vlan 20
Switch(config-if-range)#exit
Switch(config)#int f0/5
Switch(config-if)#switchport mode trunk
Switch(config-if)#switchport trunk allowed vlan 10,20
Switch(config-if)#exit
Switch(config)#do wr
Building configuration...
[OK]
Switch(config)#
%LINK-5-CHANGED: Interface FastEthernet0/5, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface FastEthernet0/5, changed state to up

Switch(config)#exit
Switch#
%SYS-5-CONFIG_I: Configured from console by console

Switch#show interfaces trunk
Port        Mode         Encapsulation  Status        Native vlan
Fa0/5       on           802.1q         trunking      1


Port        Vlans allowed on trunk
Fa0/5       10,20

Port        Vlans allowed and active in management domain
Fa0/5       10,20

Port        Vlans in spanning tree forwarding state and not pruned
Fa0/5       10,20

Switch#
```

Task 3: Configure Router-on-a-Stick for Inter-VLAN Routing Enable communication between VLAN 10 and VLAN 20 through router sub-interfaces. (Intermediate — two concepts used together: sub-interfacing and routing.) Create two sub-interfaces on the router's trunkconnected interface, one per VLAN. Assign correct IP addressing and 802.1Q encapsulation with the matching VLAN ID on each sub-interface. Enable routing so hosts in VLAN 10 and VLAN 20 can reach each other. Verify connectivity with a successful ping between hosts in different VLANs.



Router

```
Router>en
Router#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
Router(config)#int g0/0
Router(config-if)#no shut

Router(config-if)#
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0, changed state to up

Router(config-if)#exit
Router(config)#int g0/0.10
Router(config-subif)#
%LINK-3-UPDOWN: Interface GigabitEthernet0/0.10, changed state to down

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0.10, changed state to up

Router(config-subif)#en
Router(config-subif)#encapsulation dot1q 10
Router(config-subif)#ip address 192.168.10.1 255.255.255.0
Router(config-subif)#exit
Router(config)#int g0/0.20
Router(config-subif)#
%LINK-3-UPDOWN: Interface GigabitEthernet0/0.20, changed state to down

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0.20, changed state to up

Router(config-subif)#encapsulation dot1q 20
Router(config-subif)#ip address 192.168.20.1 255.255.255.0
Router(config-subif)#exit
Router(config)#do wr
Building configuration...
[OK]
Router(config)#
```

```
Router#show ip interface brief
Interface              IP-Address      OK? Method Status                Protocol
GigabitEthernet0/0     unassigned      YES unset  up                    up
GigabitEthernet0/0.10  192.168.10.1    YES manual up                    up
GigabitEthernet0/0.20  192.168.20.1    YES manual up                    up
GigabitEthernet0/1     unassigned      YES unset  administratively down down
GigabitEthernet0/2     unassigned      YES unset  administratively down down
Vlan1                  unassigned      YES unset  administratively down down
Router#show ip route
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
       D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
       N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
       E1 - OSPF external type 1, E2 - OSPF external type 2, E - EGP
       i - IS-IS, L1 - IS-IS level-1, L2 - IS-IS level-2, ia - IS-IS inter area
       * - candidate default, U - per-user static route, o - ODR
       P - periodic downloaded static route

Gateway of last resort is not set

     192.168.10.0/24 is variably subnetted, 2 subnets, 2 masks
C       192.168.10.0/24 is directly connected, GigabitEthernet0/0.10
L       192.168.10.1/32 is directly connected, GigabitEthernet0/0.10
     192.168.20.0/24 is variably subnetted, 2 subnets, 2 masks
C       192.168.20.0/24 is directly connected, GigabitEthernet0/0.20
L       192.168.20.1/32 is directly connected, GigabitEthernet0/0.20

Router#
```

Switch

```
Switch>en
Switch#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
Switch(config)#vlan 10
Switch(config-vlan)#name team
Switch(config-vlan)#exit
Switch(config)#vlan 20
Switch(config-vlan)#name hr
Switch(config-vlan)#exit
Switch(config)#int f0/1-2
                     ^
% Invalid input detected at '^' marker.

Switch(config)#int range f0/1-2
Switch(config-if-range)#switchport mode access
Switch(config-if-range)#switchport access vlan 10
Switch(config-if-range)#exit
Switch(config)#int range f0/3-4
Switch(config-if-range)#switchport mode access
Switch(config-if-range)#switchport access vlan 20
Switch(config-if-range)#exit
Switch(config)#int f0/5
Switch(config-if)#switchport mode trunk
Switch(config-if)#switchport trunk allowed vlan 10,20
Switch(config-if)#exit
Switch(config)#do wr
Building configuration...
[OK]
Switch(config)#
%LINK-5-CHANGED: Interface FastEthernet0/5, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface FastEthernet0/5, changed state to up

Switch(config)#exit
Switch#
%SYS-5-CONFIG_I: Configured from console by console

Switch#show interfaces trunk
Port        Mode         Encapsulation  Status        Native vlan
Fa0/5       on           802.1q         trunking      1


Port        Vlans allowed on trunk
Fa0/5       10,20

Port        Vlans allowed and active in management domain
Fa0/5       10,20

Port        Vlans in spanning tree forwarding state and not pruned
Fa0/5       10,20

Switch#
```


Verify connectivity



Q4 -Capture and Analyze Inter-VLAN Traffic Use Wireshark to observe how frames change as they cross from switch to router and back. (Integrative — multi-step flow combining VLANs, trunking, and routing.) Capture ICMP traffic while pinging between a VLAN 10 host and a VLAN 20 host. Identify the specific frames that cross the router via the trunk link. Document the source/destination MAC and IP addresses observed at each hop. Explain how the frame headers change as traffic passes from switch to router and back.

To capture and analyze ICMP traffic between a host in VLAN 10 and a host in VLAN 20, observe the traffic as it crosses the switch-router trunk, and document how Layer-2 (MAC/VLAN) headers change while the Layer-3 IP addresses remain end-to-end.

Topology :




Simulation Filter Configuration

Packet Tracer Simulation Mode was used. ARP and ICMP were selected so that the ICMP Echo Request/Reply traffic could be isolated from unrelated protocols.




ICMP Capture

After resetting the simulation, an ICMP ping was generated from PC0 to PC2. The Event List shows the ICMP packet moving from PC0 to Switch0, then to Router0, back through Switch0, and finally to PC2. The reverse path carries the ICMP Echo Reply.




Frame Analysis at the Switch

The Switch0 PDU information shows the Ethernet frame entering the switch and the outgoing frame carrying a Dot1Q header toward the router. This confirms that the switch-router connection is carrying tagged VLAN traffic.




Frame Analysis at Router0

At Router0, the inbound ICMP packet is shown with source IP 192.168.10.2 and destination IP 192.168.20.2. The ICMP message is Type 8, which is an Echo Request. The Layer-2 information is tagged with 802.1Q.



Detailed Inbound 802.1Q and IP Header

The detailed inbound PDU shows TCI = 0x000A. Hexadecimal 0x000A equals decimal 10, therefore the incoming frame is tagged as VLAN 10. The same PDU shows the ICMP packet with source IP 192.168.10.2 and destination IP 192.168.20.2.



Observed Header Values

The following values are taken directly from the captured Packet Tracer PDU information.

Hop / Frame	Source MAC	Destination MAC	Source IP	Destination IP	VLAN / Tag
Switch0 → Router0 (observed)	0001.C953.9E7D	0001.C953.5001	192.168.10.2	192.168.20.2	VLAN 10 (TCI 0x000A)
Router0 outbound (observed)	0001.C953.5001	0040.0B8C.7355	192.168.10.2	192.168.20.2	Dot1Q shown; outbound VLAN tag value not visible in captured screenshot

How the Frame Headers Change

When the ICMP packet travels from VLAN 10 toward VLAN 20, the IP packet is routed by Router0. The Layer-2 Ethernet information is therefore rebuilt for the next Layer-2 segment. The captured values demonstrate that the MAC addresses change across the routed hop, while the source and destination IP addresses remain 192.168.10.2 and 192.168.20.2.

Before / inbound to Router0	MAC: 0001.C953.9E7D → 0001.C953.5001 IP: 192.168.10.2 → 192.168.20.2 VLAN tag: 10
After / outbound from Router0	MAC: 0001.C953.5001 → 0040.0B8C.7355 IP: 192.168.10.2 → 192.168.20.2 New Layer-2 frame is created
Main observation	MAC addresses change at the routed hop; IP source/destination remain end-to-end for this ICMP exchange.

The Inter-VLAN ICMP traffic was successfully captured in Cisco Packet Tracer Simulation Mode. The capture shows an 802.1Q-tagged frame entering Router0 on VLAN 10, carrying an ICMP Echo Request from 192.168.10.2 to 192.168.20.2. Router0 routes the packet toward the destination

network and creates a new Layer-2 frame, changing the MAC addresses while preserving the endto-end IP addresses. This demonstrates the interaction of VLANs, trunking, Layer-2 switching, and Layer-3 routing.