CONNECTOR TABLE

REF DES	PART NUMBER	DESCRIPTION
P1	D38999/26FJ35PA	CONNECTOR PLUG - PIN CONTACTS
J2	D38999/26FJ35SA	CONNECTOR PLUG - SOCKET CONTACTS

SCHEMATIC LABELS

C1 SHIELD TO P1 BACKSHELL

C1 SHIELD TO J2 BACKSHELL

WIRE LIST

WIRE NO.	FROM	PIN	TO	PIN	SIGNAL NAME	GAGE	COLOR	LENGTH
C1-1	P1	5	J2	E	CAN_H	24	WHT/GRN	48 IN
C1-2	P1	6	J2	F	CAN_L	24	WHT/BLU	48 IN

BILL OF MATERIALS

ITEM	QTY	PART NUMBER	DESCRIPTION	REF DES
1	1	D38999/26FJ35PA	CONNECTOR PLUG PIN	P1
2	1	D38999/26FJ35SA	CONNECTOR PLUG SOCKET	J2
3	4	M39029/58-360	CONTACT PIN 22D	P1
4	4	M39029/56-348	CONTACT SOCKET 22D	J2
5	1	M85049/128-1	BACKSHELL EMI SHIELD BAND TYPE	P1
6	1	M85049/128-2	BACKSHELL EMI SHIELD BAND TYPE	J2

DRAWING NOTES

1. CABLE C1 IS A TWISTED SHIELDED PAIR.
2. TERMINATE C1 SHIELD 360 DEG TO THE BACKSHELL AT P1 AND J2 USING A SHIELD BAND.
3. USE THE MANUFACTURER SPECIFIED BAND INSTALLATION TOOL OR A DOCUMENTED QUALIFIED ALTERNATE.