CONNECTOR TABLE

REF DES	PART NUMBER	DESCRIPTION
P1	D38999/26FJ35PA	CONNECTOR PLUG - PIN CONTACTS
J2	D38999/26FJ35SA	CONNECTOR PLUG - SOCKET CONTACTS

SCHEMATIC LABELS

P1 CLAMP BACKSHELL

J2 CRIMP RING BACKSHELL

WIRE LIST

WIRE NO.	FROM	PIN	TO	PIN	SIGNAL NAME	GAGE	COLOR	LENGTH
W1	P1	1	J2	A	+28V	22	RED	36 IN
W2	P1	2	J2	B	RETURN	22	BLK	36 IN
W3	P1	3	J2	C	DATA_H	24	WHT/GRN	40 IN
W4	P1	4	J2	D	DATA_L	24	WHT/BLU	40 IN

BILL OF MATERIALS

ITEM	QTY	PART NUMBER	DESCRIPTION	REF DES
1	1	D38999/26FJ35PA	CONNECTOR PLUG PIN	P1
2	1	D38999/26FJ35SA	CONNECTOR PLUG SOCKET	J2
3	4	M39029/58-360	CONTACT PIN 22D	P1
4	4	M39029/56-348	CONTACT SOCKET 22D	J2
5	1	M85049/38S15W	CLAMP STYLE STRAIN RELIEF BACKSHELL	P1
6	1	SYN-CR-15	BACKSHELL CRIMP RING	J2

DRAWING NOTES

1. ASSEMBLE THE P1 CLAMP BACKSHELL WITH THE SPECIFIED SMALL FLAT BLADE DRIVER.
2. CRIMP THE J2 BACKSHELL RING WITH THE MANUFACTURER SPECIFIED CRIMP RING TOOL.
3. ALTERNATE TOOLING IS ALLOWED ONLY WHEN DOCUMENTED AS EQUIVALENT FOR THE PART AND PROCESS.