UniFi Security Checklist

26 settings to check on any UniFi network: home or small business. Menu names follow UniFi Network 9.x and may differ slightly by version.

1 · ADMIN ACCOUNTS & ACCESS

- [ ] **Turn on MFA for your UI account.** Anyone who logs in to unifi.ui.com can control your whole network.
  account.ui.com → Security
- [ ] **Give every admin their own account.** No shared logins, so you can see who changed what.
- [ ] **Remove admins who no longer need access.** Former employees, past installers, one-time helpers.
- [ ] **Use least privilege.** Give people view-only or site-limited roles when they don't need full admin.
- [ ] **Set a strong device SSH password, or turn SSH off.** Settings → System → Advanced → Device Authentication

2 · FIRMWARE & UPDATES

- [ ] **Keep UniFi OS and the Network application current.** Security fixes ship in these updates.
- [ ] **Schedule automatic device updates** for a quiet overnight window, or patch manually every month.
- [ ] **Skim the release notes before major upgrades.** Ubiquiti moves fast, and you'll occasionally want to wait a week.

3 · NETWORK SEGMENTATION (VLANS)

- [ ] **Separate networks for trusted devices, IoT, guests and cameras.** One flat network means one compromised device reaches everything.
- [ ] **Put smart TVs, speakers, plugs and thermostats on the IoT network,** not your main LAN.
- [ ] **Put cameras and NVRs on their own network** with no internet access unless they need it.
- [ ] **Mark the guest network as a guest/hotspot network** so clients are isolated from each other and from your LAN.

4 · FIREWALL

- [ ] **Upgrade to the zone-based firewall** (Network 9.0+) and give each VLAN a zone that matches its trust level.
- [ ] **Block IoT → Internal and Guest → Internal.** Only allow specific exceptions such as casting or printing.
- [ ] **Allow Internal → IoT** so your phone can still control smart devices; return traffic is handled automatically.

- [ ] **Audit port forwards.** Delete any you don't recognize, and never forward RDP, SMB or camera ports to the internet.
- [ ] **Turn off UPnP** unless something specifically requires it, and if it does, restrict it to that one network.

5 · WI-FI

- [ ] **Use WPA3, or WPA2/WPA3 mixed for older devices.** Never leave a network open or on WEP.
- [ ] **Use long, unique passphrases for each SSID,** and change the guest password regularly.
- [ ] **Keep the number of SSIDs low (3–4 max).** Every extra SSID costs airtime and adds attack surface.

6 · THREAT PROTECTION & REMOTE ACCESS

- [ ] **Turn on intrusion prevention (IPS)** in Security settings if your gateway supports it.
- [ ] **Use a VPN (WireGuard or Teleport) for remote access,** not open ports.
- [ ] **Restrict remote management** to MFA-protected UI accounts only.

7 · MONITORING & BACKUPS

- [ ] **Turn on automatic backups,** and download a copy to keep somewhere off the device.
- [ ] **Set up notifications** for devices going offline and for security events.
- [ ] **Check the client list monthly.** Find out what any unknown device is, or block it.

Want a second set of eyes? KJJ Tech, an official UniFi partner, will go through this whole list on your network over screen-share. Flat $750 for up to 5 hours, with a written fix list. kjjtech.com/remote-unifi-services.html