

IRQ	Vector#		System Use	MASK Address	MASK (1= ENABLED, 0=DISABLED)	
IRQL7A	11110000	(0xF0)	Debugger (Button)	0x3000 0200	0b10000000	
IRQL6A	11100001	(0xE1)	PTC #1 (Programmable Timer)	0x3000 0200	0b01000000	
IRQL6B	11100010	(0xE2)	PTC #2 (Programmable Timer)	0x3000 0200	0b00100000	
IRQL5A	11010001	(0xD1)	NIC	0x3000 0200	0b00010000	
IRQL5B	11010010	(0xD2)	IDE 1	0x3000 0200	0b00001000	
IRQL5C	11010100	(0xD4)	IDE 2	0x3000 0200	0b00000100	
IRQL5D	11011000	(0xD8)	EXPANSION_I5	0x3000 0200	0b00000010	
IRQL4A	11000001	(0xC1)	UART 1	0x3000 0200	0b00000001	
IRQL4B	11000010	(0xC2)	UART 2	0x3000 0201	0b10000000	
IRQL4C	11000100	(0xC4)	EXPANSION_I4	0x3000 0201	0b01000000	
IRQL3A	10110001	(0xB1)	USB	0x3000 0201	0b00100000	
IRQL3B	10110010	(0xB2)	EXPANSION_I3	0x3000 0201	0b00010000	
IRQL2A	10100001	(0xA1)	VIDEO	0x3000 0201	0b00001000	
IRQL2B	10100010	(0xA2)	EXPANSION_I2	0x3000 0201	0b00000100	
IRQL1A	10010001	(0x91)	RTC	0x3000 0201	0b00000010	
IRQL1B	10010010	(0x92)	POWER CONTROLLER	0x3000 0201	0b00000001	
				MASK must be written with 8 bit writes (2 of them)		
				0x3000 0202	Bit 0 = POWER OFF if == 1	
					Bit 1 = SYSTEM RESET if == 1	