Preventative Maintenance Procedures

Thermal Processors

All Models

Customer Name: _____

Processor S/N: _____

Processor F/W Rev: _____

1. ☐ Verify program **parameters**.
2. ☐ Confirm if customer is replacing **Dev Scrub cover and Dev Filter** on a scheduled basis. These are consumable items customer should be familiar with.

Drive Sections

1. ☐ Operate machine and **observe transport rollers**.
2. ☐ In Dev section, ensure **short plate roller gears** are properly tightened.
3. ☐ In Dev section, ensure **scrub roller is operating properly**. Make sure gears are not loose in dev scrub box housing. Make sure non-drive side of scrub is held down by clamp. On older P processors, Dev Scrub Gear box should be updated.
4. ☐ Check **drive chain** tension. Watch for any roller skipping as plate feeds through.

Developer Tank

1. ☐ Check Developer **Temp and Conductivity**
2. ☐ Check Developer **Circulation**
3. ☐ Confirm Developer **Dwell Time**

Wash

1. ☐ Check all **Spray Bars** for proper flow. Ensure they are kept clean. Ensure no holes are clogged. Ensure flow is not too high which may cause splashing into Dev Tank.
2. ☐ Check **Drainage** of Wash tanks. Make sure water is flowing down drain and not building up in Tank which may indicate a clogged drain pipe.
3. ☐ Check **Dev Water Tank.** On **Z** machine, ensure water is going down drain overflow tubes. On **P** machine, ensure water is flowing through drain holes in side of tank toward main drain tank. Make sure these drain holes are clean.

Replenishment

1. ☐ Make sure **replenish pumps** function properly.
2. ☐ Check **Gum Pump** replenish flow. Poppet valves may need to be changed if gum does not flow.
3. ☐ Check for **kinks, leaks** in replenish tubing
4. ☐ Confirm **Dev Replenish pumps** are calibrated correctly

Gum

1. ☐ Check for proper **gum flow** across roller.
2. ☐ Make sure **application roller** is clean. If **Gum Blade**, check to see if it is working properly. These are bent if not left in up position when processor is not being used.

Cleaning

Customer is responsible for cleaning of processor. If processor is not maintained well, problems may occur. Point out items to customer that are dirty and could be maintained better.

1. ☐ Check **Dev Water Tank.** If not cleaned properly, a buildup will occur which could cause a clogged drain.

2. ☐ Check **Dev Water Tank Rollers.** These rollers will get dirty if not cleaned monthly. Check Dev Water Tank squeeze roller. This roller prevents water backing into Dev Tank. Must be kept clean.

3. ☐ Check **Wash Tank**. Depending on water condition, algae may buildup here.

4. ☐ Check **Rinse Scrub Roller**. Depending on water condition, algae may buildup here.

Chiller

1. ☐ Check **Water Level**

2. ☐ The chiller should be **drained, cleaned** and re-filled at least quarterly by customer.

3. ☐ **RTE- 7** chiller is air cooled. The front grill must be removed and condenser area cleaned/vacuumed.

See the following page for a list of commonly used PM Parts

Notes:

_____

_____

_____

_____

_____

_____

_____

_____

Common PM Parts for Thermal Processors

Poppet for Dev, Water	35587
Poppet for Z gum pump suction side	20-261
Poppet for Z gum pump discharge side	20-260

Z gum pump unit	15000-180

Dev poppet on Z uses a gasket instead of O-ring. Re-use this gasket.