

Flash Operations

Reading a Word from Flash

To read one dword from Flash memory, use the following command line:

```
1 # flint -d <device> rr addr
```



device	The device the dword is read from.
addr	The address of the word to read.

Example:

```
1 # flint -d /dev/mst/mt4099_pci_cr0 rw 0x20
```

Writing a dword to Flash

To write one dword to Flash memory, use the following command line:

```
1 # flint -d <device> ww addr data
```

where:



device	The device the dword is written to.
addr	The address of the word to write.
data	The value of the word.

Example:

```
1 # flint -d /dev/mst/mt4099_pci_cr0 ww 0x10008 0x5a445a44
```

Writing a dword to Flash Without Sector Erase

To write one dword to Flash memory without sector erase , use the following command line:

```
1 # flint -d <device> wwne addr data
```

where:



device	The device the dword is written to..
addr	The address of the word to write.
data	The value of the word.

Example:

```
1 # flint -d /dev/mst/mt4099_pci_cr0 wwne 0x10008 0x5a445a44
```

Note that the result may be dependent on the Flash type. Usually, bitwise and between the specified word and the previous Flash contents will be written to the specified address.

Erasing a Sector

To erase a sector that contains a specified address, use the following command line:

```
1 # flint -d <device> e addr
```

where:



device	The device the dword is erased from.
addr	The address of a word in the sector that you want to erase.

Example:

```
1 # flint -d /dev/mst/mtusb-1 e 0x1000
```

Querying Flash Parameters

To query flash parameters use the following command line:

```
1 # flint -d <device> [-ocr] hw query
```

where:



device	The device to query.
--------	----------------------

Example:

```
1 # flint -d /dev/mst/mt4115_pciconf0 hw query
```

Last updated: September 18, 2019



Previous page
[Disabling/Enabling Access to the Hardware](#)

Next page



[Firmware Timestamping for Multi-Host Environment](#)

🔮 Use with AI ▾



- Privacy Policy
- Your Privacy Choices
- Terms of Service
- Accessibility
- Corporate Policies
- Product Security
- Contact