

• FFmpeg编译为OpenHarmony .so库 - 分步指令

步骤1：设置环境变量

bash

```
export OHOS_SDK="/c/Users/panruiqi/AppData/Local/OpenHarmony/Sdk/15/native"
export OHOS_LLVM="${OHOS_SDK}/llvm/bin"
export CROSS_PREFIX="aarch64-unknown-linux-ohos-"
export PATH="${OHOS_LLVM}:${PATH}"
```

步骤2：验证工具链

bas

```
which aarch64-unknown-linux-ohos-clang
llvm-ar --version
```

步骤3：配置FFmpeg

bash

```
./configure \
  --disable-gpl \
  --disable-nonfree \
  --enable-runtime-cpudetect \
  --disable-gray \
  --enable-swscale-alpha \
  --disable-programs \
  --disable-ffmpeg \
  --disable-ffplay \
  --disable-ffprobe \
  --disable-doc \
  --disable-htmlpages \
  --disable-manpages \
  --disable-podpages \
  --disable-ttpages \
  --disable-avdevice \
  --enable-avcodec \
  --enable-avformat \
  --enable-avutil \
  --enable-swresample \
  --enable-swscale \
  --disable-postproc \
  --enable-avfilter \
  --disable-avresample \
  --enable-network \
  --disable-d3d11va \
  --disable-dxva2 \
  --disable-vaapi \
  --disable-vdpau \
```

```
--disable-videotoolbox \
--disable-encoders \
--enable-encoder=png \
--enable-encoder=mjpeg \
--enable-encoder=bmp \
--enable-encoder=aac \
--enable-encoder=flac \
--enable-encoder=pcm_s16be \
--enable-encoder='pcm_s16*' \
--enable-encoder=pcm_s8 \
--enable-encoder=pcm_s24be \
--disable-decoders \
--enable-decoder=aac \
--enable-decoder=aac_latm \
--enable-decoder=pcm_s16be \
--enable-decoder='pcm_*' \
--enable-decoder=ac3 \
--enable-decoder=eac3 \
--enable-decoder=adpcm_ima_wav \
--enable-decoder=flv \
--enable-decoder=h264 \
--enable-decoder='mp3*' \
--enable-decoder=vp6f \
--enable-decoder=flac \
--enable-decoder=hevc \
--enable-decoder=vp8 \
--enable-decoder=vp9 \
--enable-decoder=mpeg4 \
--enable-decoder=mpeg2video \
--enable-decoder=mjpeg \
--enable-decoder=bmp \
--enable-decoder=png \
--enable-decoder=gif \
--enable-decoder=webp \
--enable-decoder=vorbis \
--enable-decoder=opus \
--enable-decoder=mp2 \
--disable-hwaccels \
--disable-muxers \
--enable-muxer=mp4 \
--enable-muxer=mov \
--enable-muxer=wav \
--enable-muxer=adts \
--enable-muxer=mjpeg \
--enable-muxer=webp \
--enable-muxer=image2 \
--enable-muxer=image2pipe \
--enable-muxer=mp3 \
--enable-muxer=hls \
--disable-demuxers \
--enable-demuxer=aac \
--enable-demuxer=concat \
--enable-demuxer=data \
--enable-demuxer=flv \
--enable-demuxer=hls \
--enable-demuxer=live_flv \
--enable-demuxer=mov \
--enable-demuxer=mp3 \
```

```
--enable-demuxer=mpegps \
--enable-demuxer=mpegts \
--enable-demuxer=mpegvideo \
--enable-demuxer=flac \
--enable-demuxer=hevc \
--enable-demuxer=webm_dash_manifest \
--enable-demuxer=ijklivehook \
--enable-demuxer=mjpeg \
--enable-demuxer=wav \
--enable-demuxer=gif \
--enable-demuxer=image_png_pipe \
--enable-demuxer=image_bmp_pipe \
--enable-demuxer=image_webp_pipe \
--enable-demuxer=image2 \
--enable-demuxer=avi \
--enable-demuxer=rtsp \
--disable-parsers \
--enable-parser=aac \
--enable-parser=aac_latm \
--enable-parser=ac3 \
--enable-parser=h264 \
--enable-parser=flac \
--enable-parser=hevc \
--enable-parser=mjpeg \
--enable-parser=png \
--enable-bsfs \
--disable-bsf=chomp \
--disable-bsf=dca_core \
--disable-bsf=dump_extradata \
--disable-bsf=imx_dump_header \
--disable-bsf=mjpeg2jpeg \
--disable-bsf=mjpega_dump_header \
--disable-bsf=mov2textsub \
--disable-bsf=mp3_header_decompress \
--disable-bsf=mpeg4_unpack_bframes \
--disable-bsf=noise \
--disable-bsf=remove_extradata \
--disable-bsf=text2movsub \
--enable-protocols \
--enable-protocol=async \
--disable-protocol=bluray \
--disable-protocol=concat \
--disable-protocol=crypto \
--disable-protocol=ffrtmpcrypt \
--enable-protocol=ffrtmphttp \
--disable-protocol=gopher \
--disable-protocol=icecast \
--disable-protocol='librtmp*' \
--disable-protocol=libssh \
--disable-protocol=md5 \
--disable-protocol=mmsh \
--disable-protocol=mmst \
--enable-protocol=rtmp \
--enable-protocol=rtsp \
--enable-protocol=rtp \
--enable-protocol=udp \
--enable-protocol=tcp \
--disable-protocol=sctp \
```

```
--disable-protocol=srtp \  
--disable-protocol=udplite \  
--disable-protocol=subfile \  
--disable-protocol=unix \  
--disable-devices \  
--disable-filters \  
--enable-filter=atempo \  
--enable-filter=amix \  
--enable-filter=volume \  
--enable-filter=aformat \  
--enable-filter=aresample \  
--enable-filter=setpts \  
--enable-filter=scale \  
--disable-iconv \  
--disable-audiotoolbox \  
--disable-videotoolbox \  
--disable-linux-perf \  
--disable-bzlib \  
--cc=aarch64-unknown-linux-ohos-clang \  
--cxx=aarch64-unknown-linux-ohos-clang++ \  
--ar=llvm-ar \  
--ranlib=llvm-ranlib \  
--ld=aarch64-unknown-linux-ohos-ld.lld \  
--strip=llvm-strip \  
--prefix=/path/to/install \  
--enable-cross-compile \  
--extra-cflags=' ' \  
--extra-ldflags=' ' \  
--target-os=linux \  
--arch=aarch64 \  
--disable-inline-asm \  
--enable-static \  
--enable-shared \  
--disable-neon \  
--disable-asm \  
--sysroot="${OHOS_SDK}/sysroot"
```

注意：请将 `/path/to/install` 替换为您想要安装库的目标路径

步骤4：编译

bash

```
make -j$(nproc)
```

步骤5：安装

bash

```
make install
```

步骤6：验证生成的库

bash

```
ls -lh /path/to/install/lib/*.so
```

说明:

- `-j$(nproc)` 使用多核并行编译, 加快速度
- `--disable-programs` 只编译库, 不编译ffmpeg命令行工具 (可选)
- 如需编译工具, 去掉 `--disable-programs` 参数