

Document No.	SOP-20-EX-001	Governing SOP	SOP #20 SQF Clause 2.6.4
Exercise Type	Annual Mock Crisis Exercise	Exercise Date	April 18, 2026
Scenario	Severe Storm — Power Outage & Loss of Internet	Facilitated By	Jesse Kolstad, DQ / Chad Hinson, VP Q&R
Exercise Format	Tabletop — Teams Meeting	Retention	2 years per SOP #02

SCENARIO NARRATIVE

Time: Tuesday, approximately 2:15 PM. Active production is underway at the Layton facility (855 N. McCormick Way). Blending is in progress for two active lots; a packaging run is ongoing on the bottling line; two batch records are open. A severe spring storm system moves through northern Utah without warning. Lightning strikes a utility transformer serving the block, causing an immediate, uncontrolled total power loss to all Layton facilities simultaneously. Internet connectivity — including access to ULIMS, Fishbowl ERP, DicksonOne cloud dashboard, and all email — is lost at the same moment due to the ISP's node equipment being on the same affected circuit. Power is not expected to be restored for an estimated 4–8 hours. Internet restoration timeline is unknown.

In-scope facilities affected: 855 N. McCormick Way (Primary Manufacturing) · 851 N. McCormick Way (Bottling/Packaging) · 1373 W. Gordon Ave. (Warehouse & Lab) · 1255 W. Gordon Ave. (Warehouse).

Lindon facility (2642 W. 400 N.) is on a separate utility circuit and is **NOT** affected. Remote-capable personnel can access systems via cellular hotspot if available.

EXERCISE OBJECTIVES

This tabletop exercise tests the following CMT capabilities per SOP #20 Section 10:

1. CMT activation and convening — can all members be reached without internet? Phone tree/cell coverage verified.
2. Controlled in-process product shutdown — who executes, what is the decision, what gets held?
3. Product safety assessment — what lots were open, what is their disposition status, who owns that decision?
4. Temperature/environmental monitoring continuity — how is cold storage and production area temp monitored without cloud access?
5. QMS offline operation — how does the team document during a power/internet outage? What paper-based backup processes exist?
6. Customer communication protocol — who communicates production delays to customers, what is the approved message?
7. Restart readiness — what checks are required before production resumes after power restoration per SOP #20 and SOP #26?
8. Lessons learned documentation and CAPA assignment — is anything identified that improves the plan?

SMF PROGRAM CONTROLS — HOW THE SYSTEM RESPONDS

Phase	Program / Control Activated	What the System Does	SMF Document(s)
IMMEDIATE RESPONSE (0–15 min)	Controlled Equipment Shutdown — SOP #20 §9.4.1	Operations Manager ensures all production equipment is powered down in a controlled manner to prevent damage. Facility Manager secures open production areas. Blenders and bottling line are shut down in mid-run state. LOTO applied as required.	<i>SOP #20 §9.4.1; PRP-003 §8</i>
	Personnel Safety & Head Count — SOP #20 §8.1	HR and supervisors conduct immediate head count. All personnel accounted for. Emergency lighting activation confirmed. Evacuation not required (storm is external, no structural threat identified). Personnel secured indoors per SOP #20 §9.2.3.	<i>SOP #20 §8.1, §9.2.3</i>
PRODUCT SAFETY (15–60 min)	In-Process Product Hold — SOP #20 §9.4.1 + SOP #HLD-001	ALL in-process product at time of outage is immediately placed on Quality Hold. Physical hold tags (orange, all sides; red-and-white tape) applied to all open blending containers and staged bottling materials. Lot numbers and quantities documented on paper hold forms (QF106A/B). ULIMS/Fishbowl entries completed once power/internet is restored.	<i>SOP #20 §9.4.1; SOP #HLD-001; SOP #13</i>
	Quality Assessment of In-Process Lots — SOP #13	Quality determines whether held in-process lots can be completed after power restoration or must be dispositioned. Blended lots in sealed containers with intact identity — likely recoverable pending review. Bottling line lots with open containers — assessed for contamination risk (foreign material, pest, temperature excursion). All decisions documented per SOP #4 GDP on paper forms.	<i>SOP #13; SOP #20 §9.4.1; SOP #168 (MRB if disposition required)</i>
ENVIRONMENTAL CONTINUITY	Temperature Monitoring — Offline Backup (PRP-002)	DicksonOne DWE data loggers continue logging locally on battery backup for up to 1 year without internet or power connection. Cold storage temperature is maintained mechanically (refrigeration units on emergency power or holding thermal mass). QA staff manually reads handheld calibrated thermometer at shift intervals and records on Temporary Temperature Log (PRP-002-Form G backup). Data is retrieved via controlled flash drive once connectivity is restored.	<i>PRP-002 §8; SOP #11 (calibration)</i>
	Food Defense — Facility Security (FD-001)	Loss of power does not disable physical access controls — key/badge locks remain functional. All entrances secured. APS-1 (receiving dock), APS-3 (production access), and APS-9 (utilities) monitoring continues per FD-001 Appendix A. Food defense monitoring log entries made on paper forms.	<i>FD-001 Appendix A; SOP #20 §9.5.2</i>
CONTINUITY OF OPERATIONS	QMS Offline Documentation — SOP #04 + SOP #02	SMF GDP (SOP #04) requires real-time paper documentation when electronic systems are unavailable. All in-progress records (batch records, hold tags, deviation logs, temperature	<i>SOP #04; SOP #02; SOP #12 (deviation for production interruption)</i>

CONTINUITY OF OPERATIONS		logs) are completed on controlled paper forms. All entries are legible, in permanent ink, include date/time and author per SOP #04 §7. Records are entered into ULIMS/Fishbowl once connectivity is restored, with a notation referencing the outage event date/time and reason for delayed entry.	
	Fishbowl / ULIMS Offline — Data Integrity	Open work orders and batch records in Fishbowl/ULIMS are not lost — system data is server-resident with backup. No data is entered or modified during outage. When internet is restored, QA verifies all pre-outage system states are intact before any new entries. Cybersecurity/IT protocol per SOP #20 §9.6 confirmed: no system compromise, outage is utility-based only.	<i>SOP #20 §9.6; SOP #02 §15.2 (electronic records backup)</i>
CUSTOMER COMMUNICATIONS	Customer Notification — SOP #20 §8.1	CMT Leader (or designee) contacts affected customers via cell phone if production delivery commitments are impacted. CMT-approved language only: 'Somafina UST experienced an unplanned utility disruption due to a severe storm event on [date]. We are assessing impact on your order and will provide a revised production timeline within [timeframe]. We are committed to delivering safe, quality product.' No details about open lots, quantities, or quality status communicated without Quality approval.	<i>SOP #20 §8.1; SOP #20 §8.3</i>
PRODUCTION RESTART	Equipment Restart Checklist — SOP #20 §9.4.1 + SOP #26	Once power is restored: Operations and Facility Managers inspect all production equipment for damage or abnormal status per SOP #20 §9.4.1. Calibration of all critical instruments verified per SOP #11 — metal detectors and scales require pre-use verification before any production. QA performs formal All Clear (SOP #26) for each room before any production resumes — ATP swab, visual inspection, glass/FM check, allergen tag status all confirmed. No employee returns to production workstation without QA authorization.	<i>SOP #20 §9.4.1; SOP #26; SOP #11</i>
PRODUCTION RESTART	HACCP CCP Verification Before Restart — HACCP-001	Before any production lot resumes or new lot starts, HACCP CCP prerequisites verified: metal detector challenge test performed and documented; calibration status current; allergen tag and changeover status confirmed. Any lot interrupted at a CCP monitoring step is assessed — if critical limit cannot be confirmed as met for the interrupted step, lot is held and evaluated before release.	<i>HACCP-001 CCPs 1.00/4.00/5.00; SOP #26; SOP #12 (deviation if CCP step was interrupted)</i>
POST-EVENT DOCUMENTATION	Deviation Record — SOP #12	Production interruption due to power outage is documented as an Unplanned Deviation per SOP #12. Deviation classification: Moderate (production interrupted, product held, no confirmed product safety impact). Deviation record includes: event date/time, description, duration, lots affected, immediate actions	<i>SOP #12; SOP #20 §11</i>

POST-EVENT DOCUMENTATION		taken, Quality assessment outcome, and authorization for return to production.	
	CAPA Assessment — SOP #14	CMT debrief following exercise (or real event) identifies gaps and improvement opportunities. If systemic preparedness gap is identified (e.g., no offline form readily available, phone tree gaps, DicksonOne battery not tested), a CAPA is opened. CAPA is assigned to an owner with a target closure date and reviewed at next Management Review per SOP #MR-001.	<i>SOP #14; SOP #MR-001 (MR agenda item 5 — recalls and mock crises)</i>
POST-EVENT DOCUMENTATION	Management Review Input — SOP #MR-001	Exercise results, lessons learned, and any resulting CAPA are documented and presented at the next Annual Management Review as a standing agenda item. Records retained minimum 2 years per SOP #02.	<i>SOP #MR-001 §5 (Agenda Item 5); SOP #02</i>

CMT TABLETOP DISCUSSION QUESTIONS

Work through each question as a team. Document your answers and any gaps identified in the response column below.

#	Discussion Question	CMT Response / Notes
Q1	The power goes out mid-blend. Who makes the call to shut down equipment and what specifically do they do in the first 5 minutes?	Production equipment shuts down automatically on loss of power — no manual intervention required for the equipment itself. Generator at 855 N. McCormick Way provides emergency power for lighting and HVAC only; production equipment is not operated on generator. Operations Manager confirms controlled shutdown state and applies LOTO where required. All in-process product is immediately tagged on Quality Hold. Action item: confirm generator capacity and coverage scope with Maintenance (Mitch/Vicente).
Q2	Two lots are open on the bottling line. How do we physically hold them? Who applies the tags? What forms do we use without ULIMS?	QA/Supervisor applies hold using pre-staged QF106A hold tags (orange, all sides). Gap identified: pre-printed QF106A hold tags are not currently staged at all Layton production areas. Interim protocol: handwritten 'HOLD — DO NOT USE' on paper with lot number, date, time, and reason is acceptable. Open product on the bottling line must be covered and bags sealed immediately. Lindon uses a red cone with a written tag — same principle applies. Action item: Jennifer Hall to pre-print and stage QF106A tags at all production areas before the April 20 audit.
Q3	Cold storage temperature monitoring goes offline. How do we know the cold room is holding temp? What is our backup procedure?	Jennifer Hall confirmed: DicksonOne data loggers run on battery backup for up to 1 year without power or internet. The cold storage logger at Eagle Eye continues recording throughout the outage without cloud connectivity. Temperature would need to rise over 20 degrees F above set point to pose a product risk; infrequent door access will preserve cold room temperature well during the outage. When internet restores, all data auto-uploads to DicksonOne

		dashboard. If internet does not restore, Jennifer Hall uses a password-protected USB stick to pull stored data directly from the device. Action item: verify whether cold storage at Eagle Eye has independent backup power — status was unknown at time of exercise.
Q4	It is 2:30 PM. All cell phone numbers for CMT members — are they in everyone's personal phone today? How do we reach each other without email?	Action item identified: the CMT phone tree in SOP #20 is not yet populated with current contact information. Each CMT member should have all other members' cell numbers saved in their personal phones. This is a critical pre-action gap — contact information must be entered into SOP #20 immediately as a direct action item from this exercise.
Q5	A customer is expecting a shipment tomorrow. Who contacts them, what do we say, and who must approve the message before it goes out?	The Account Manager team (led by Wendy) contacts affected customers. All outbound messaging must be approved by CMT leadership before it goes out. No quality status detail, open lot information, or disposition status is communicated without Quality approval. Approved message: advise of utility disruption event, confirm product safety is not impacted, and provide a revised production timeline.
Q6	Power comes back on after 6 hours. Walk through every step before we start production again. What order do things happen in?	Agreed restart sequence: (1) Supervisor enters and inspects each room for safety and product integrity before any other personnel enter. (2) Standard startup procedures followed — SOP #26 QA All Clear required for each room. (3) Operations/Facility Manager confirms equipment is operational and checks calibration status per SOP #11. (4) Metal detector pre-use verification performed and documented. (5) QA authorizes room-by-room restart. No employee returns to a production workstation without QA authorization.
Q7	The blended lot that was in-process — what is its quality status? Can we use it? What is the decision process and who approves?	Document quantity blended and quantity remaining at time of outage. Confirm all product was covered and protected during downtime. Evaluate contamination risk — sealed blending containers in a controlled environment during a power-only outage carry minimal risk. QA assesses whether the blending step was complete enough to continue or must restart from a defined point. QA approves disposition. All attendees agreed: document thoroughly, evaluate the risk, QA approves accordingly.
Q8	Our DicksonOne loggers were offline. How do we retrieve the stored temperature data and verify the cold room never exceeded limits?	Logger continues recording on internal battery throughout the outage. When internet is restored, all stored data auto-uploads to the DicksonOne cloud dashboard automatically. If internet is never restored, Jennifer Hall uses her password-protected USB stick to pull all data directly from the device for offline review. Cold room temperature trend is then reviewed to confirm no critical threshold was exceeded.
Q9	What paper forms does QA need that we may not currently have printed and staged on-site right now?	QF106A hold tags identified as not currently pre-staged on-site at all Layton production areas — confirmed gap. Pre-printed laminated hold signs and a

		stack of QF106A forms should be staged at each production area. Action item: Jennifer Hall to prepare and stage forms at all production areas before the April 20 audit.
Q10	What is the one thing this exercise revealed that we should fix before we do this for real?	Multiple items identified: (1) Populate CMT phone tree in SOP #20 immediately — critical for any real event. (2) Pre-stage QF106A hold tags at all production areas. (3) Confirm generator coverage scope and cold storage backup power at Eagle Eye with Maintenance. (4) Formalize and train on the SOP #26 restart procedure — supervisors must follow the documented sequence consistently. (5) Conduct more tabletop exercises (Jennifer Hall: 'One thing we learned is that we need to do more of these').

LESSONS LEARNED & IMPROVEMENT ACTIONS

Improvement Item / Gap Identified	Owner	Target Date	CAPA Required?
Populate CMT phone tree in SOP #20 — contact information for all CMT members must be entered and verified	Chad Hinson / Jesse Kolstad	No — direct action item	
Pre-stage QF106A hold tags and laminated hold signs at all Layton production areas	April 18, 2026	Jennifer Hall / Fredy Arias	No — direct action item
Confirm generator scope at 855 N. McCormick Way and backup power status for cold storage at Eagle Eye — coordinate with Mitch/Vicente (Maintenance)	April 25, 2026	Jesse Kolstad / Maintenance	No — investigation item; CAPA if gap confirmed
Formalize and train on SOP #26 restart procedure following power restoration — ensure all supervisors follow documented sequence before QA All Clear	Scott Urban / Jesse Kolstad	May 2026	Yes — CAPA for process gap

OVERALL EXERCISE ASSESSMENT

Exercise Outcome	☐ Satisfactory ☒ Needs Improvement ☐ Unsatisfactory
CMT Response Adequate?	☐ Yes ☒ Partially ☐ No — CAPA required
Plan Update Required?	☐ No update needed ☒ Minor update (contact info only) ☐ SOP #20 revision required
Next Exercise Date	Q3 2026 (Annual minimum — SQF 2.6.4.2; additional exercises encouraged)

Facilitator Summary Notes

The team demonstrated functional awareness of the crisis response framework. Key controls confirmed in place: DicksonOne battery logging, Lindon remote data backup, paper GDP documentation protocol, and food defense physical access controls. Primary gaps identified: (1) CMT phone tree not populated in SOP #20; (2) QF106A hold tags not pre-staged at Layton production areas; (3) cold storage backup power status at Eagle Eye unknown. Restart procedure requires formal training to ensure SOP #26 compliance is consistent. These are correctable pre-audit action items — none constitute a systemic failure of the crisis management program.

CMT ATTENDEES & SIGN-OFF — SQF 2.6.4 / SOP #20 §10

Name	Title	Qualifications	Role	Signature & Date
Chad Hinson	<i>VP of Quality and Regulatory</i>	SQF Practitioner; HACCP; PCQI	Required	_____/_____ 04/15/2026
Jesse Kolstad	<i>Director of Quality & Compliance</i>	SQF Practitioner; HACCP; FSVPQI, PCQI	Required	_____/_____ 04/15/2026
Kevin Woollard	<i>Regulatory Manager</i>	SQF Practitioner; PCQI; ASQ CQA	Required	_____/_____ 04/15/2026
Scott Urban	<i>Regulatory Supervisor</i>	SQF Practitioner; PCQI; HACCP	Required	_____/_____ 04/15/2026
Fredy Arias	<i>Quality Manager</i>	PCQI; HACCP	Required	_____/_____ 04/15/2026

Jennifer Hall	<i>Quality Engineer</i>	Lean Six Sigma (Yellow Belt), CQA and CQE in process	Required	<u> </u> / <u>04/15/2026</u>
Brandy Harper	<i>Quality Assurance</i>	PCQI, HACCP	Required	<u> </u> / <u>04/15/2026</u>
Raquel Kelsey	<i>QA Manager — Lindon</i>	SQF; HACCP; ISO	Required	<u> </u> / <u>04/15/2026</u>

SOP #20 | Form SOP-20-EX-001 Rev 01 April 2026 | Retain minimum 2 years per SOP #02 | SOMAFINA UST — CONFIDENTIAL