

AI Platform

Multi-agent AI architecture with Hermes, OpenClaw, Open Design, and OpenWebUI.

Quick Start

Recovery from scratch:

```
bash scripts/bootloader.sh
```

Current state:

```
cat STATE.md
```

Health check:

```
bash scripts/hermes-health.sh
```

Backup:

```
bash scripts/hermes-backup.sh
```

Structure

```
ai-platform/  
├── README.md           # This file  
├── STATE.md            # Current state snapshot  
├── QUICK-REF.md        # Emergency recovery commands  
├── blueprints/  
│   └── ARCHITECTURE.md # Full architecture docs  
├── configs/  
│   ├── hermes-gateway.service  
│   ├── open-design.service  
│   ├── openclaw-gateway.service  
│   ├── ollama-override.conf # Ollama systemd override (CRITICAL)  
│   └── docker-compose.yml  
└── scripts/  
    ├── bootloader.sh    # Full automated setup  
    ├── hermes-backup.sh  
    └── hermes-health.sh
```

Components

- **Hermes** - Messaging gateway (Telegram) + terminal agent
- **OpenClaw** - Multi-agent system (30+ agents)
- **Open Design** - Design AI stack
- **OpenWebUI** - Web UI for local LLMs (Docker)
- **Ollama** - Local model inference (RTX 2060 GPU)

Critical Rules

1. All services bind to 127.0.0.1 only
2. Telegram handled by Hermes only (OpenClaw Telegram disabled)
3. Ollama Docker bridge disabled
4. File permissions: 600 for secrets, 700 for sensitive dirs
5. Pinned Docker images (no latest tags)
6. **Ollama models MUST be on Linux filesystem** (`/var/lib/ollama/`), NOT `/mnt/d/` (too slow, causes timeouts)

Ollama Setup (After Bootloader)

```
# 1. Apply systemd override
sudo cp configs/ollama-override.conf
/etc/systemd/system/ollama.service.d/override.conf
sudo sed -i "s/User=lurkr/User=${USER}/"
/etc/systemd/system/ollama.service.d/override.conf
sudo sed -i "s/Group=lurkr/Group=${USER}/"
/etc/systemd/system/ollama.service.d/override.conf

# 2. Create model storage
sudo mkdir -p /var/lib/ollama
sudo chown ${USER}:${USER} /var/lib/ollama

# 3. Pull models
ollama pull granite4.1:8b

# 4. Restart
sudo systemctl daemon-reload && sudo systemctl restart ollama
```