INPUT 115VAC 1 PHASE, 60HZ
L1 = 1.98 FLA @115VAC
SCCR = 5kA

PLG1 LEV2611 POWER IN — POWER IN 115VAC CABLE
B L1 BLACK 10AWG
W N WHITE 10AWG
G GND GREEN 10AWG

TERMINAL L1 — L1 BLACK 12AWG
TERMINAL N — N WHITE 12AWG
TERMINAL GND

DISC1 PANEL DISCONNECT
L1 T1 L2 T2 L3 T3

L1 BLACK 12AWG — L1-A BLACK 12AWG — CB1 4AMP CIRCUIT BREAKER (1 2) — L1-A1 BLACK 12AWG
N WHITE 12AWG — N-1 WHITE 12AWG — N-1 WHITE 12AWG

PS1 10AMP POWER SUPPLY
L1 + +24V BLUE 12AWG
N - 0V WHITE/BLUE 12AWG

CB2 10AMP CIRCUIT BREAKER (1 2)
24E-1 BLUE 12AWG

SPD1 SPEED CONTROLER
1 +24V — 24E-1 BLUE 18AWG
2 0V — 0V WHITE/BLUE 18AWG
3 SPEED — SPD BLUE 18AWG

PLG2 LEV2613 POWER OUT — POWER OUT 115VAC CABLE
B L1 BLACK 10AWG
W N WHITE 10AWG
G GND GREEN 10AWG

DOOR GND — GND GREEN 12AWG — TERMINAL GND — GND GREEN 12AWG — GND — 0V WHITE/BLUE 12AWG

NOTE: KEEP ALL DC WIRES 4" MINIMUM CLEARANCE FROM 115VAC WIRES

TERMINAL SPD — SPD BROWN 18AWG
5-PIN MICRO FEMALE RECEPTACLE
DIR GREY 18AWG
RUN BLACK 18AWG
0V WHITE 18AWG
24E-1 BLUE 18AWG

EXTERNAL DEVICE CONNECTION
SEE DRAWINGS:
MXCS-M9, MXCS-M11
MXCS-P9, MXCS-P11

TERMINAL 24E-1
24E-1 BLUE 12AWG
24E-1 BLUE 12AWG
24E-1 BROWN 22AWG

TERMINAL 24E-1 — 24E-1 BLUE 12AWG
24E-1 BLUE 18AWG — REVERSE 5AMP CIRCUIT BREAKER (1 2) — DIR BLUE 18AWG — TERMINAL DIR — DIR GREEN 18AWG
24E-1 BLUE 18AWG
24E-1 BLUE 18AWG — CR-DN (11 14) — RUN BLUE 18AWG — TERMINAL RUN — RUN BLACK 18AWG
24E-1 RED 18AWG

PB1 START/STOP SWITCH — START STOP CABLE
TERMINAL PB1-SP 1
2
R 3
G 4
24E-1 BROWN 22AWG
PB1-SP WHITE 22AWG
0V BLUE 22AWG
PB1 BLACK 22AWG

PB2 START/STOP SWITCH — START STOP CABLE
TERMINAL PB2-SP 1
2
R 3
G 4
24E-1 BROWN 22AWG
PB2-SP WHITE 22AWG
0V BLUE 22AWG
PB2 BLACK 22AWG

TERMINAL'S
0V BLUE 18AWG
0V WHITE/BLUE 18AWG
0V WHITE/BLUE 12AWG
0V BLUE 22AWG
PB1 BLACK 22AWG — CR1 (A1 A2) — 0V WHITE/BLUE 18AWG
0V
CR1: MODLINX PB1 START / STOP 1N.O.

0V BLUE 22AWG
PB2 BLACK 22AWG — CR2 (A1 A2) — 0V WHITE/BLUE 18AWG
0V
CR2: MODLINX PB2 START / STOP 1N.O.

0V BLUE 22AWG
0V GREEN 16AWG
CR-DN: MODLINX RUN RUN SIGNAL TO CARDS 1 N.O.

LT1 CIRCUIT 1 LIGHT WITH CABLE
24E-1 BLACK 22AWG
24E-1 BLACK 22 AWG
NOT CONNECTED
BROWN 22 AWG
NOT CONNECTED
WHITE 22 AWG
0V BLUE 22 AWG

NOTE: REMOVE WHITE AND BROWN WIRE AT INSULATION, HEAT SHRINK EXPOSED END

24E-1 BLUE 18AWG — CR-DN (A1 A2) — 110 BLUE 18AWG
TERMINAL 110
110 BLUE 16AWG
110 BLUE 18AWG

INFEED INTERFACE #1 FEMALE 6-PIN MINI RECEPTACLE
110 BLUE 16AWG
0V GREEN 16AWG
121 RED 16AWG
130 ORANGE 16AWG
IINSP1 BLACK 16AWG
IINSP2 WHITE 16AWG

DISCHARGE INTERFACE #1 MALE 6-PIN MINI CABLE
111 BLUE 16AWG
0V GREEN 16AWG
120 RED 16AWG
130 ORANGE 16AWG
DINSP1 BLACK 16AWG
DINSP2 WHITE 16AWG

111 BLUE 16AWG — CR-BP (11 12) — 110 BLUE 18AWG

BYPASS 5AMP CIRCUIT BREAKER (1 2)
125 BLUE 18AWG — 120 BLUE 18AWG
TERMINAL 120
120 BLUE 18AWG
120 RED 16AWG

121 RED 16AWG — CR1 (11 14) — 122 BLUE 18AWG — CR2 (11 14) — 120 BLUE 18AWG

TERMINAL IINSP1
TERMINAL IINSP2
TERMINAL DINSP1
TERMINAL DINSP2

TERMINAL 125
125 BLUE 18AWG — 125 BLUE 18AWG — CR-BP (21 24) — 130 BLUE 18AWG
TERMINAL 130
130 ORANGE 16AWG
130 ORANGE 16AWG
125 BLUE 18AWG

24E-1 BLUE 18AWG — CR-BP (A1 A2) — 125 BLUE 18AWG
CR-BP: BYPASS RELAY 1N.C. 1N.O.

THE NEED FOR SAFETY DEVICES VARIES WITH EACH APPLICATION OF THIS PRODUCT. THIS DRAWING MAY NOT INCLUDE ALL APPROPRIATE SAFETY DEVICES FOR YOUR APPLICATION. AS SYSTEMS INTEGRATOR, PLEASE ADVISE YOUR CUSTOMER OF DEVICES THAT ARE APPROPRIATE FOR HIS/HER APPLICATION, BASED ON YOUR SAFETY ASSESSMENT. DEVICES MAY INCLUDE, BUT ARE NOT LIMITED TO THOSE SUCH AS, ADDITIONAL GUARDING, SAFETY CONTROLS, BARRICADES, END STOPS, ETC. COMPLIANCE WITH ALL FEDERAL, STATE, OSHA AND LOCAL LAWS OR CODES ARE THE RESPONSIBILITY OF BOTH YOU, AS THE SYSTEMS INTEGRATOR/DISTRIBUTOR, AND THE END USER.

PROPRIETARY INFORMATION
THIS DRAWING IS THE CONFIDENTIAL PROPERTY OF CONVEYX CORP. AND IS TRANSMITTED IN CONFIDENCE. THE REPRODUCTION, DISCLOSURE, OR USE, IN WHOLE OR PART, OF THE DESIGN OR THE DETAILS CONTAINED HEREIN IS PROHIBITED WITHOUT THE EXPRESS WRITTEN PERMISSION OF CONVEYX CORP.

REVISED
Destroy Previous Dwg. with the same number
DATE: 04/08/2020

NOTE: INDIVIDUAL WIRES TO ALL POINTS OF TERMINATION. DO NOT DOUBLE PLACE WIRES

LABEL ALL WIRES AND CABLES 1" FROM END

TITLE: MOD-LINX POWER SUPPLY ASSY: 24VDC 10AMP OUTPUT, 115VAC-1 PHASE INPUT, MOD LINX CHILD 2 DRIVE CARDS, SCHEMATIC
SIZE: D
DWG. NO.: PS10115MLC2-2
DRAWN BY:
WEIGHT:
DATE:

D PS10115MLC2-2
CXC_MXPS-ASSY