



SW/FW Release note 2025.05.01

Introduction.

This document gives a short description of the new functions, features and bug fixes introduced in this release of the DADman control software and the updated firmware. The released functionality is applicable for the products AX32, DX32, Penta and DAD Thunder | Core series, MOM, Avid MTRX, Avid MTRX Studio, Avid MTRX II and Dynaudio Control 01, generally denominated the Products in this document.

This new release includes updated functionality for configuring Control | Pack via DADman. Furthermore grouping functionality of microphone gain has been implemented for MTRX, MTRX II, AX32, Penta and Thunder | Core.

The details are listed below.

DADman control software:	MacOS	New
Compatible with MacOS 10.13 to 10.15 and MacOS 11, 12, 13, 14 and 15 with Intel or Apple silicon processor	v.5.8.1 build 6	
Please see note below on MacOS 15 compatibility		
Windows 10 and 11	Windows	New
	v.5.8.1 build 6	
Thunder Core driver software:	MacOS	No change
DAD Thunderbolt 3 Core Audio Driver:	v.1.2.2	
Compatible with macOS 11, 12, 13, 14 and 15 Apple Silicon and Intel Computers		
DAD Thunderbolt 3 Windows ASIO driver	Windows	No change
Compatible with Windows 10 and 11	v. 1.1.2	
Main board firmware for:		
AX64, AX Center, Core256, Avid MTRX II and Control 01	v.1.1.1.1	New
Dante 256 IPCore (Dante version 4.1.1.1)	v.1.0.2.1	No change



Main board firmware for:

AX32, DX32, Penta 720, Penta 721s, Avid MTRX	v.2.4.5.1	New
Brooklyn 2 Dante module (Dante version 4.0.9.1)	v.1.0.2.1	
Brooklyn 3 Dante module (Dante version 4.2.3.8)	v.1.1.0.2	No change

Main board firmware for:

MTRX Studio	v.1.1.5.1	No change
MTRX Studio Dante 64 IPCore (Dante version 1.3.7.1)	v.1.0.0.4	No change

New in DADman

- Grouping of mic input channels applicable for all products except MTRX Studio (requires FW update).
- For Control | Pack reordering of routing presets in the Routing Preset dialog. (requires firmware update)
- Trigger status visible in the Routing Preset dialog
- Mac OS only: Sorting of devices by clicking column headers in the Device List dialog.

New in the firmware

Please note that all settings in your unit will be reset to default after the firmware updates - so make sure you have saved your settings file before starting the update.

The mic channel grouping feature:

- Grouped parameters are gain and mute (phantom power and phase are not grouped).
- If you change the gain of one channel in a group, the other channels in that group will follow maintaining their initial channel to channel offset.
- If you only want to set the gain of one channel in a group you can use the "alt/option" key in combination with a mouse click, mouse move, mouse scroll or arrow up/down.
- Holding the "alt/option" down key down when clicking the gain text box below the gain slider will change the gain of the selected channel only.
- If you only want to mute/unmute one channel in a group you can use the "alt/option" key in combination with a mouse click.

General

- General key modifiers for sliders in DADman when using mouse or arrow up/down keys:
- Shift: Increased resolution
- Ctrl(windows) + mouse click: Set default.
- Cmd(mac) + mouse click: Set default
- The "alt/option" key can be used in combination with Shift , Ctrl or Cmd and will in this case only change the selected channel.



Eucon behavior for grouped channels

- Sliders changes the group gain.
- gain can be set by using the gain knob in input strip.
- Mute is only available as a mute of all members in a group.

Bug Fix, Main fixes:

- Various fixes and improvements in the Routing Preset dialog
- DADman windows: Improved Routing Preset meter graphics.
- DADman windows: Crash on midi handling
- DADman mac: Fixed graphics problems when handling large DADman views on displays with scaled resolution.
- DADman mac: Status color update error in routing preset dialog.