

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Page 1 of 10 Template Version 1.1 - 8/14/18

**For**  
**Interconnection Customer: Delaware River Solar**  
**Applicant: Jessina Riano**  
**2253 kW Solar Generator System**  
**18 O'Haire Road, Wallkill NY 10941**

**Interconnection to Orange & Rockland Utilities**  
**NY Western Division**  
**East Wallkill Substation**  
**13.2 kV Feeder 15-6-13**

---

THIS DOCUMENT AND ANY ATTACHMENTS HERETO ("DOCUMENT") IS MADE AVAILABLE BY ORANGE & ROCKLAND UTILITIES UPON AND SUBJECT TO THE EXPRESS UNDERSTANDING THAT: (A) NEITHER ORANGE & ROCKLAND UTILITIES NOR ANY OF ITS OFFICERS, DIRECTORS, AFFILIATES, AGENTS, OR EMPLOYEES MAKES ANY WARRANTY, ASSURANCE, GUARANTY, OR REPRESENTATION WITH RESPECT TO THE CONTENTS OF THE DOCUMENT OR THE ACCURACY OR COMPLETENESS OF THE INFORMATION CONTAINED OR REFERENCED IN THE DOCUMENT, AND (B) ORANGE & ROCKLAND UTILITIES, ITS OFFICERS, DIRECTORS, AFFILIATES, AGENTS, AND EMPLOYEES SHALL NOT HAVE ANY LIABILITY OR RESPONSIBILITY FOR INACCURACIES, ERRORS, OR OMISSIONS IN, OR ANY BUSINESS OR POLICY DECISIONS MADE BY ANY DIRECT OR INDIRECT RECIPIENT IN RELIANCE ON, THIS DOCUMENT OR THE INFORMATION CONTAINED OR REFERENCED THEREIN; ALL SUCH LIABILITY IS EXPRESSLY DISCLAIMED.

---

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>  Page 2 of 10
	<b>Distributed Energy Resources - NYSSIR</b>	Template Version 1.1 - 8/14/18

**TABLE OF CONTENTS**

<u><b>Section</b></u>	<u><b>Page</b></u>
<b>1.0 INTRODUCTION</b>	<b>3</b>
<b>2.0 EXECUTIVE SUMMARY</b>	<b>3</b>
<b>3.0 COMPANY EPS PARAMETERS</b>	<b>3</b>
<b>4.0 INTERCONNECTION CUSTOMER SITE</b>	<b>4</b>
<b>5.0 SYSTEM IMPACT ANALYSIS</b>	<b>4</b>
<b>6.0 MITIGATIONS FOR SYSTEM IMPACT ANALYSIS FAILURES</b>	<b>7</b>
<b>7.0 CONCEPTUAL COST ESTIMATE</b>	<b>9</b>
<b>8.0 REVISION HISTORY</b>	<b>10</b>

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Page 3 of 10 Template Version 1.1 - 8/14/18

## 1.0 INTRODUCTION

This report presents the analysis results of the Orange and Rockland Utilities (“Orange and Rockland” or the “Company”) interconnection study based on the proposed interconnection and design submittal from the Interconnection Customer in accordance with the Company CESIR Study Requirements Rev. 1.6. The intent of this report is to assess this project’s feasibility, determine its impact to the existing electric power system (EPS), determine interconnection scope and installation requirements, and determine costs associated with interconnecting the Interconnection Customer’s generation to the Company’s Electric Power System (EPS). This Coordinated Electric System Impact Review (CESIR) study; according to the New York State Standardized Interconnection Requirements (NYSSIR) Section I.C Step 6; identifies the scope, schedule, and costs specific to this Interconnection Customer’s installation requirements.

## 2.0 EXECUTIVE SUMMARY

The total estimated planning grade cost of the work associated with the interconnection of the Interconnection Customer is **\$2,587,678.**

The interconnection was found to be feasible with modifications to the existing Company EPS and operating conditions, which are described in detail in the body of this Study.

The study was performed between daylight hours of 0800-2000 hrs.

## 3.0 COMPANY EPS PARAMETERS

<b>Substation</b>	<b>East Wallkill</b>
Transformer Name (list multiple where normally tied to common bus)	215
Transformer Peak Load (kW)	N/A
Contingency Condition Load, N-1 Criteria (kW) (as applicable)	N/A
Daytime Light Load (kW)	-1008
Generation: Total, Connected, Queue (kW)	13232, 5513, 7719
Contingency Condition Generation: Total, Connected, Queue (kW)	N/A
Supply Voltage (kV)	69
Transformer Maximum Nameplate Rating (kVA)	35000
Distribution Bus Voltage Regulation	LTC
Transmission GFOV Status	Not installed
Bus Tie	Open
Number of Feeders Served from this Bus	3

<b>Connecting Feeder/Line</b>	<b>15-6-13</b>
Peak Load on feeder (kW)	7770
Daytime Light Load on Feeder (kW)	-350
Feeder Primary Voltage at POI (kV)	13.2
Line Phasing at POI	3

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Page 4 of 10 Template Version 1.1 - 8/14/18

Circuit distance from POI to substation	4.07 miles
Distance from POI to nearest 3-phase, (if applicable)	N/A
Line Regulation	N
Line/Source Grounding Configuration at POI	Effective
Other Generation: Total, Connected, Queue (kW)	11109, 3856, 7253

<b>System Fault Characteristics without Interconnection Customer DG at POI with System Upgrades described in Section 6</b>	
Interconnection Customer POI Location (Pole X/Y)	50742/53850
I 3-phase (3LLL)	2547 Amps
I Line to Ground (3I0)	2531 Amps
Z1 (100 MVA base)	0.5056 + j1.8480 PU
Z0 (100 MVA base)	0.5571 + j1.7839 PU

#### 4.0 INTERCONNECTION CUSTOMER SITE

The Interconnection Customer is proposing a new primary service connection at a new customer location. The primary voltage at the POI is currently 4.8kV 3-phase. This will need to be upgraded to 13.2kV 3-phase.

The proposed generating system consists of:

- 5,928 PV modules each rated 535 Watts.
- 1 Inverters derated to 2253 kW at 600 Volts (SUNGROW, SG 3425 UD-MV)
- 1 Generator Step Up transformer, 3425 kVA, YG-Y winding configuration, 13,200 primary volts, 600 secondary volts.

#### 5.0 SYSTEM IMPACT ANALYSIS

The analysis was run at the rated project size in normal system configuration connected to the feeder 15-6-13. The following table shows the impact study results of 2253 kW at 1.0 power factor project interconnecting to the distribution system.

#	Category	Criteria	Limit	Result
1	Voltage	Overvoltage	< 105% (ANSI C84.1)	Pass
	With the addition of the subject generator the maximum voltage as modeled on the Feeder is 105% of nominal.			
2	Voltage	Undervoltage	> 95% (ANSI C84.1)	Pass
	With the addition of the subject generator the minimum voltage as modeled on the Feeder is 102% of nominal.			
3	Voltage	Substation Regulation for Reverse Power	<100% minimum load criteria	Fail

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>		Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>		Page 5 of 10 Template Version 1.1 - 8/14/18

	The total generation on the project Bank #215 is 13.23 MW. The total minimum load on the Bank is -1.01MW. Therefore, the generation to load ratio is -1312.89%.			
<b>4</b>	Voltage	Feeder Regulation for Reverse Power	<100% Minimum load to generation ratio	Fail
	Reverse power observed through voltage regulators UID 1621305, 3P 219A & UID 1628873, 3P 219A upstream of the subject project.			
<b>5</b>	Voltage	Fluctuation	<3% steady state from proposed generation on feeder	Pass
	The greatest voltage fluctuation on the feeder occurs at proposed project point of interconnection (POI). The resulting fluctuation at the feeder location is 1.50% due to this project's generation output stepping from 0% to 100%.			
<b>6</b>	Voltage	Fluctuation	<5% steady state from aggregate DER on substation bus	Pass
	The maximum component voltage fluctuation on the system is 2.178% due to all generation output stepping from 0% to 100%.			
<b>7</b>	Voltage	Fluctuation	Regulator tap movement exceeds 1 position, generation change of 75% of nameplate rating does not result in voltage change > ½ the bandwidth of any feeder voltage regulating device.	Pass
	Not applicable (no voltage regulators on the study feeder).			
<b>8</b>	Voltage	Flicker	Screen H Flicker	Pass
	The Pst for the location with the greatest voltage fluctuation is 0.04 and the emissions limit is 0.35.			
<b>9</b>	Equipment Ratings	Thermal (continuous current)	< 100% thermal limits assuming no load	Fail
	The subject generator's full output current is 98.5 A. Fuse 6091113 & Fuse 6091744 is overloaded when the proposed project is connected to the system.			
<b>10</b>	Equipment Ratings	Withstand (fault current)	<90% withstand limits	Pass/Fail
	This screen will be evaluated in the EGPC study and CESIR results will be updated.			
<b>11</b>	Protection	Unintentional Islanding	Unintentional Islanding Document & Company Guidelines	Fail

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>		Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>		Page 6 of 10 Template Version 1.1 - 8/14/18

	The subject generator is a 2.253 MW PV generation system. The study fails Step 1 and Step 4 of the SANDIA Anti-Islanding Screen.			
<b>12</b>	Protection	Protective device coordination	Company Guidelines	Pass/ <b>Fail</b>
	This screen will be evaluated in the EGPC study and CESIR results will be updated.			
<b>13</b>	Protection	Fault Sensitivity	Rated capabilities of EPS equipment	Pass/ <b>Fail</b>
	This screen will be evaluated in the EGPC study and CESIR results will be updated.			
<b>14</b>	Protection	Ground Fault Detection	Reduction of reach > 10% (by Utility)	Pass/ <b>Fail</b>
	This screen will be evaluated in the EGPC study and CESIR results will be updated.			
<b>15</b>	Protection	Overvoltage - Transmission System Fault	Company 3V0 criteria	<b>Fail</b>
	The generation to load ratio on the serving distribution system has failed the Company's planning threshold in which transmission ground fault overvoltage become an electrical hazard due to the distribution source contribution. An evaluation of the existing EPS has been performed and it has been determined that protection mitigation methods are required.			
<b>16</b>	Protection	Overvoltage - Distribution System Fault	< 138% voltage rise	Pass/ <b>Fail</b>
	This screen will be evaluated in the EGPC study and CESIR results will be updated.			
<b>17</b>	Protection	Effective Grounding	IEEE 142 ( $0 < R_0/X_1 < 1$ ; $0 < X_0/X_1 < 3$ )	Pass
	With subject generator interconnected the modeled $R_0/X_1$ is 0.29 PU and the $X_0/X_1$ is 0.94 PU.			
<b>18</b>	SCADA	Required EMS Visibility for Generation Sources	Monitoring & Control Requirements	<b>Yes</b>
	The 2.253 MW subject generator triggers the requirement for SCADA reporting to the Utility.			
<b>19</b>	Auto-Loop or Other			<b>Fail</b>
	There is an alternate circuit configuration when Mid-Point Recloser at X/Y: 49296/54022, UID: 4295135 opens and there is loss of load on 15-6-13. CDG-00502 will need to disconnect when this recloser opens, pending the EGPC study results.			

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Page 7 of 10 Template Version 1.1 - 8/14/18

## 6.0 MITIGATIONS FOR SYSTEM IMPACT ANALYSIS FAILURES

Detail below is intended to provide sufficient information and clarity to give the Interconnection Customer an understanding to the relationship of costs and scope associated with the DER interconnection and the system modifications due to the DER impact. This includes any required EPS equipment upgrades. Where scope items are identified, associated labor, equipment rentals and indirect project support functions (such as engineering and project management) are intended and implied.

Upgrade Required	Failures Addressed
<ul style="list-style-type: none"> <li>3V0 protection and reverse power capability are needed at substation.</li> </ul>	Substation Regulation for Reverse Power; Overvoltage - Transmission System Fault
<ul style="list-style-type: none"> <li>Reverse power capability is needed for voltage regulators UID 1621305 &amp; UID 1628873 upstream of the subject project.</li> </ul>	Project Feeder Regulation for Reverse Power;
<ul style="list-style-type: none"> <li>Upgrade fuse 6091113 &amp; fuse 6091744 to 200A.</li> </ul>	Thermal (Continuous current)
<ul style="list-style-type: none"> <li>Operate at CDG-00502 at 2253kW and must enable Voltage Reactive Power Control (Volt-Var) in accordance with O&amp;R Smart Inverter Settings</li> </ul>	O&R Requirements
<ul style="list-style-type: none"> <li>Implement reclose delay on upstream protective devices to avoid reclosing into live island</li> </ul>	Risk of Islanding
<ul style="list-style-type: none"> <li>Perform Effective Grounding Protection Coordination Study to determine size of grounding transformer or zig-zag required</li> </ul>	Withstand (fault current), Protective device coordination, Fault Sensitivity, Ground Fault Detection, Overvoltage - Distribution System Fault
<ul style="list-style-type: none"> <li>Install primary metering at PCC</li> </ul>	Monitoring and control
<ul style="list-style-type: none"> <li>Install electronic recloser at PCC</li> </ul>	Monitoring and control
<ul style="list-style-type: none"> <li>SCADA communications and reporting for proposed DG site</li> </ul>	Monitoring and control

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>  Page 8 of 10
	<b>Distributed Energy Resources - NYSSIR</b>	Template Version 1.1 - 8/14/18

Additional details on the scope of each option can be found below:

The substation upgrades required to facilitate the proposed installation include the following:

- Install 3V0 protection.
- Reverse power flow capability needs to be addressed.
- Upgrade existing substation meter with bi-directional meter.

The Distribution upgrades required to facilitate the proposed installation include the following:

- Upgrade the POI voltage from 4.8kV to 13.2kV.
  - Shift the Step Transformer (UID: 6053283) from cmp 6092072 to cmp 2321305.
  - Reconductor 13000 feet of 3-ph Conductor to 477 AAC, from cmp 6112231 to cmp 2250497. Install 150 feet of new 3-ph conductor
- Reverse power flow capability needs to be addressed for voltage regulators 1621305 & 1628873.
- Operate at CDG-00502 at 2253kW and must enable Voltage Reactive Power Control (Volt-Var) in accordance with O&R Smart Inverter Settings
- Upgrade fuse 6091113 & fuse 6091744 to 200A.
- Install electronic recloser at the PCC.
- Implement reclose delay on upstream protective devices to avoid reclosing into live island.

This study was conducted based upon this facility being served by the interconnecting circuit during normal utility operating conditions. The terms, conditions, notification requirements, and other obligations of both the Company and the facility pertaining to disconnection of the facility are set forth in the applicable section(s) of the NYSSIR and the Interconnection Agreement that will be executed for the project(s) that were studied in this CESIR. Any change in system size and/or design is subject to the requirements of the NYSSIR, as well as supplemental documents developed by the Interconnection Technical Working Group and Interconnection Policy Working Group.



<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Page 9 of 10 Template Version 1.1 - 8/14/18

## 7.0 CONCEPTUAL COST ESTIMATE

The following items are a good faith estimate for the scope and work required to interconnect the project estimated under rates and schedules in effect at the time of this study in accordance with the most recent version of the NYSSIR.

### Planning Grade Estimate

Description	Cost
Upgrade existing Conductor to 477 (13000ft, 3-phase)	\$1,638,000
Install new 477 Conductor (150ft, 3-phase)	\$5,850
Install Recloser (2)	\$160,000
Junction Pole, 20 Distribution Transformers, Stepdown Transformer, Upgrade voltage regulators to 13.2kV	\$190,000
Primary Metering Cluster	\$6,800
Commissioning Time Post Installation	\$5,500
Submittal Review, Redbook development, Site Inspections	\$5,000
SCADA Monitoring/Power Quality Meter	\$40,000
Contingency (15%)	\$307,673
<b>Total Distribution Estimate</b>	<b>\$2,358,823</b>

### Substation Costs: 3V<sub>0</sub> installation

Description	Cost
Engineering, Design, Drafting, Admin	\$80,020
Labor	\$71,680
Material	\$47,304
Contingency (15%)	\$29,851
<b>Total Substation Estimate</b>	<b>\$228,855</b>

The total interconnection cost estimate: \$2,358,823 + \$228,855 = **\$2,587,678**

<b>ORANGE &amp; ROCKLAND UTILITIES, INC.</b>	<b>Coordinated Electric System Interconnect Review</b>	Doc. # <b>CDG-00502</b>  Page 10 of 10
	<b>Distributed Energy Resources - NYSSIR</b>	Template Version 1.1 - 8/14/18

Notes:

1. These estimated costs are based upon the results of this study and are subject to change. All costs anticipated to be incurred by the Company are listed.
2. The Company will reconcile actual charges upon project completion and the Interconnection Customer will be responsible for all final charges, which may be higher or lower than estimated according to the NYSSIR I.C step 11.
3. This estimate does not include the following:
  - additional interconnection study costs, or study rework
  - additional application fees,
  - applicable surcharges,
  - property taxes,
  - overall project sales tax,
  - future operation and maintenance costs,
  - adverse field conditions such as weather and Interconnection Customer equipment obstructions,
  - extended construction hours to minimize outage time or Company's public duty to serve,
  - the cost of any temporary construction service, or
  - any required permits.
4. Cost adders estimated for overtime would be based on 1.5 and 2 times labor rates if required for work beyond normal business hours. Per Diems are also extra costs potentially incurred for overtime labor.

## 8.0 REVISION HISTORY

<u>Revision</u>	<u>Date</u>	<u>Description of Revision</u>
1.0	04/20/2023	Initial document