

黑鹰A704排针信号定义及约束					
J1					
Pin Name	Signal Name	Type	Bank	Description	Trace Length
1	GND	POWER	无	Gound	无
2	GND	POWER	无	Gound	无
3	+5V	POWER	无	5V Power Supply,4.8V~5.3V	无
4	+5V	POWER	无	5V Power Supply,4.8V~5.3V	无
5	+5V	POWER	无	5V Power Supply,4.8V~5.3V	无
6	+5V	POWER	无	5V Power Supply,4.8V~5.3V	无
7	GND	POWER	无	Gound	无
8	GND	POWER	无	Gound	无
9	M22_L15N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
10	N22_L15P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
11	M20_L18N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
12	N20_L18P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
13	L20_L14N_SRCC_15	IO/LVDS/SRCC	Bank15	Default LVCMOS33	1404MIL
14	L19_L14P_SRCC_15	IO/LVDS/SRCC	Bank15	Default LVCMOS33	1404MIL
15	N19_L17N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
16	N18_L17P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
17	K19_L13N_MRCC_15	IO/LVDS/MRCC	Bank15	Default LVCMOS33	1404MIL
18	K18_L13P_MRCC_15	IO/LVDS/MRCC	Bank15	Default LVCMOS33	1404MIL
19	GND	POWER	无	Gound	无
20	GND	POWER	无	Gound	无
21	L18_L16N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
22	M18_L16P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
23	M16_L24N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
24	M15_L24P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
25	W22_L7N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
26	W21_L7P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
27	V20_L11N_SRCC_14	IO/LVDS/SRCC	Bank14	Default LVCMOS33	1606MIL
28	U20_L11P_SRCC_14	IO/LVDS/SRCC	Bank14	Default LVCMOS33	1606MIL
29	U21_L4N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
30	T21_L4P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
31	Y22_L9N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
32	Y21_L9P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
33	AA21_L8N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
34	AA20_L8P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
35	R19_L5N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
36	P19_L5P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
37	AB22_L10N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
38	AB21_L10P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
39	GND	POWER	无	Gound	无
40	GND	POWER	无	Gound	无
41	W20_L12N_MRCC_14	IO/LVDS/MRCC	Bank14	Default LVCMOS33	1606MIL
42	W19_L12P_MRCC_14	IO/LVDS/MRCC	Bank14	Default LVCMOS33	1606MIL

43	AB20_L15N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
44	AA19_L15P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
45	T18_L20N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
46	R18_L20P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
47	Y19_L13N_MRCC_14	IO/LVDS/MRCC	Bank14	Default LVCMOS33	1606MIL
48	Y18_L13P_MRCC_14	IO/LVDS/MRCC	Bank14	Default LVCMOS33	1606MIL
49	P17_L21N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
50	N17_L21P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
51	R17_L24N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
52	P16_L24P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
53	V19_L14N_SRCC_14	IO/LVDS/SRCC	Bank14	Default LVCMOS33	1606MIL
54	V18_L14P_SRCC_14	IO/LVDS/SRCC	Bank14	Default LVCMOS33	1606MIL
55	R16_L22N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
56	P15_L22P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
57	R14_L19N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
58	P14_L19P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
59	GND	POWER	无	Gound	无
60	GND	POWER	无	Gound	无
61	W17_L16N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
62	V17_L16P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
63	N14_L23N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
64	N13_L23P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
65	U18_L18N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
66	U17_L18P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
67	AB18_L17N_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
68	AA18_L17P_14	IO/LVDS	Bank14	Default LVCMOS33	1606MIL
69	V8_L21N_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
70	V9_L21P_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
71	Y9_L24N_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
72	W9_L24P_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
73	Y7_L23N_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
74	Y8_L23P_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
75	AB8_L22N_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
76	AA8_L22P_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
77	AB6_L20N_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
78	AB7_L20P_34	IO/LVDS	Bank34	Default LVCMOS33	1714MIL
79	GND	POWER	无	Gound	无
80	GND	POWER	无	Gound	无
J5					
1	GND	POWER	无	Gound	无
2	GND	POWER	无	Gound	无
3	R22_IO_DIN_14	Config/IO	Bank14	Default LVCMOS33	Null
4	N12_PROGRAM_B_0	Config	Bank0	Default LVCMOS33	Null
5	L12_CCLK_0	Config	Bank0	Default LVCMOS33	Null
6	U12_INIT_B_0	Config	Bank0	Default LVCMOS33	Null

7	GND	POWER	无	Gound	无
8	G11_DONE_0	Config	Bank0	Default LVCMOS33	Null
9	J21_L11N_SRCC_15	IO/LVDS/SRCC	Bank15	Default LVCMOS33	1404MIL
10	J20_L11P_SRCC_15	IO/LVDS/SRCC	Bank15	Default LVCMOS33	1404MIL
11	G20_L8N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
12	H20_L8P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
13	H19_L12N_MRCC_15	IO/LVDS/MRCC	Bank15	Default LVCMOS33	1404MIL
14	J19_L12P_MRCC_15	IO/LVDS/MRCC	Bank15	Default LVCMOS33	1404MIL
15	H18_L6N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
16	H17_L6P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
17	G18_L4N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
18	G17_L4P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
19	GND	POWER	无	Gound	无
20	GND	POWER	无	Gound	无
21	G16_L2N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
22	G15_L2P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
23	H15_L5N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
24	J15_L5P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
25	H14_L3N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
26	J14_L3P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
27	G13_L1N_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
28	H13_L1P_15	IO/LVDS	Bank15	Default LVCMOS33	1404MIL
29	G22_L24N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
30	G21_L24P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
31	D21_L23N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
32	E21_L23P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
33	D22_L22N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
34	E22_L22P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
35	F20_L18N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
36	F19_L18P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
37	C20_L19N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
38	D20_L19P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
39	GND	POWER	无	Gound	无
40	GND	POWER	无	Gound	无
41	B22_L20N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
42	C22_L20P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
43	D19_L14N_SRCC_16	IO/LVDS/SRCC	Bank16	Default LVCMOS33	1733MIL
44	E19_L14P_SRCC_16	IO/LVDS/SRCC	Bank16	Default LVCMOS33	1733MIL
45	E18_L15N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
46	F18_L15P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
47	A21_L21N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
48	B21_L21P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
49	C17_L12N_MRCC_16	IO/LVDS/MRCC	Bank16	Default LVCMOS33	1733MIL
50	D17_L12P_MRCC_16	IO/LVDS/MRCC	Bank16	Default LVCMOS33	1733MIL
51	D16_L5N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL

52	E16_L5P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
53	B18_L11N_SRCC_16	IO/LVDS/SRCC	Bank16	Default LVCMOS33	1733MIL
54	B17_L11P_SRCC_16	IO/LVDS/SRCC	Bank16	Default LVCMOS33	1733MIL
55	C15_L3N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
56	C14_L3P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
57	E14_L4N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
58	E13_L4P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
59	GND	POWER	无	Gound	无
60	GND	POWER	无	Gound	无
61	A20_L16N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
62	B20_L16P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
63	E17_L2N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
64	F16_L2P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
65	B16_L7N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
66	B15_L7P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
67	F14_L1N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
68	F13_L1P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
69	B13_L8N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
70	C13_L8P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
71	D15_L6N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
72	D14_L6P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
73	A19_L17N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
74	A18_L17P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
75	A16_L9N_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL
76	A15_L9P_16	IO/LVDS	Bank16	Default LVCMOS33	1733MIL