A Replication and Analysis of the Pixel Stealing Attack

Jeremy Sheng, Joy Chen, Maddie Dreher, Diya Shrawagi
The University of Texas at Austin
{js224768,cc75925,mbd2325,ds54998}@eid.utexas.edu

Abstract

Modern web browsers enforce isolation between websites so that a malicious webpage should not be able to directly read the contents of another origin. However, side-channel attacks can sometimes infer information indirectly through shared browser and hardware resources. This project attempts to replicate the pixel stealing attack proposed by Andrysco et al. [1], which exploits hardware timing differences when computing on subnormal numbers. We first begin by investigating subnormal timing differences on different CPUs to determine the viability of the method and the potential attack surface. We then set up attacker and victim websites, confirm that the same-origin policy prevents direct access of the victim, then attempt to infer pixel colors from timing differences.

1 Introduction

Browsers are designed around the same-origin policy, which prevents one website from directly inspecting the contents of another website. Despite this isolation, webpages still share underlying resources such as the CPU, GPU, caches, and browser rendering system. Differences in how these resources behave while processing particular visual content can potentially leak information through a side channel.

There are various methods to leak pixel information, including exploitation of software timing differences [4], hardware timing differences [1], GPU compression [5], and microarchitectural cache state [3]. Our initial approach is to exploit hardware timing differences of subnormal floating point computation. We are also exploring GPU.zip as an alternative leaking method to subnormal timing.

2 Background

2.1 IEEE 754 Subnormal Floating-Point Numbers

The IEEE 754 standard for single-precision floating-point arithmetic allocates 32 bits into three fields: 1 sign bit (s), 8 exponent bits (e, with a bias of 127), and 23 significand bits (f). For standard normalized values ($e \in [1, 254]$), the representation assumes an implicit leading bit of 1:

$$x_{\text{norm}} = (-1)^s \times (1.f)_2 \times 2^{e-127} \tag{1}$$

The smallest positive normalized single-precision number occurs when $e = 1$ and $f = 0$, yielding $N_{\text{min}} = 1.0_2 \times 2^{-126} \approx 1.175 \times 10^{-38}$.

When the exponent field is all zeros ($e = 0$), the value transitions to a subnormal (or denormal) representation. In subnormal mode, the implicit leading bit shifts from 1 to 0, and the effective exponent is fixed at -126:

$$x_{\text{sub}} = (-1)^s \times (0.f)_2 \times 2^{-126} \tag{2}$$

The smallest representable positive subnormal number has a significand bit pattern of 0x00000001, corresponding to $2^{-149} \approx 1.4 \times 10^{-45}$. Subnormals support gradual underflow, bridging the gap between 0.0 and N_{min}. This gradual decay preserves fundamental mathematical identities, guaranteeing that subtracting two distinct floating-point numbers will not evaluate to zero ($x \neq y \implies x - y \neq 0$), thereby preventing unexpected division-by-zero exceptions in numerical algorithms.

2.2 Microarchitectural Timing Asynchrony

Modern x86 execution units are engineered primarily for normalized floating-point operations, executing scalar or vector arithmetic in 1 to 4 clock cycles ($\sim$ 1 ns). Implementing full dedicated hardware logic for subnormal normalization across all execution units requires substantial silicon area and power consumption.

Consequently, when an execution pipeline encounters a subnormal operand or generates a subnormal output under standard IEEE 754 compliance (where Flush-to-Zero and Denormals-are-Zero modes are disabled), the fast execution datapath cannot process the value. The CPU flushes the out-of-order execution pipeline and delegates processing to internal microcode assist routines (fp_assists). Handling gradual underflow via microcode introduces a severe latency penalty of 80 to 200+ cycles ($\sim$ 30–70 ns) per operation, creating a data-dependent timing side-channel.

2.3 Pixel Stealing Attack

Web browsers enforce the Same-Origin Policy (SOP) to prevent malicious sites from accessing private cross-origin content. Although browsers allow cross-origin images to be embedded visually, direct pixel inspection via APIs such as HTML5 canvas element extraction is explicitly blocked. Andrysco et al. [1] demonstrated that subnormal execution timing can be exploited to bypass these SOP restrictions and reconstruct cross-origin pixel data over the web:

1. **SVG Filter Processing:** A target cross-origin image is rendered inside an HTML5/SVG container. The attacker applies a custom SVG filter primitive (such as

feColorMatrix or feConvolveMatrix) that scales normalized pixel color channel values $I \in [0.0, 1.0]$ by a minute scalar $\alpha \approx 10^{-42}$.

2. **Data-Dependent Latency:**
   - Non-Black Pixels ($I > 0$): Multiplying a non-zero color intensity by α yields a subnormal result ($\alpha I \approx 10^{-42}$). This repeatedly triggers microcode assist traps during rendering, significantly stalling the browser execution pipeline.
   - Black Pixels ($I = 0$): Multiplying zero by α yields exact zero (0.0), completing immediately on the fast hardware execution path without latency.
3. **Pixel Extraction:** By measuring frame render latencies using browser timing mechanisms (such as requestAnimationFrame or CSS repaint callbacks), the attacker classifies individual pixels as black or non-black based on rendering speed. Repeating this process across a target pixel grid progressively leaks private visual content.

3 Threat Model

We assume that an attacker controls a malicious website and convinces a user to visit it. The attacker does not have direct access to the victim website's DOM, memory, network traffic, or authentication information. Instead, the attacker can only execute ordinary browser code from the malicious origin and observe side-channel measurements exposed through shared browser or hardware behavior.

4 Our Approach

Our approach has three stages. First, we measure subnormal floating-point timing on a range of CPUs to find out which processors have a large enough penalty to attack. Second, we set up a cross-origin environment where an attacker page can isolate a single victim pixel and time how long it takes to render. Third, we will combine the two by applying an SVG filter that forces subnormal arithmetic and using the resulting timing differences to recover pixel colors. We have finished the first two stages, and the third is in progress.

4.1 Measuring Subnormal Timing

Since our intended method of leaking pixel information is to exploit subnormal timing differences as done in [1], we began by first gathering data on various CPUs. The attack only works if the target processor is noticeably slower on subnormal operands, so this step tells us which machines are worth targeting before we spend time on the browser side of the attack.

We developed two programs to evaluate the performance of floating-point addition and multiplication using both normal and subnormal operands. Separate implementations were written for the ARM and x86 ISAs, allowing us to measure execution times across a range of processors. Both programs are written in C, but the timed loops are written in inline assembly. This way, we know exactly which instructions are being measured, and the compiler cannot optimize the computation.

Each loop is a dependent chain of operations, meaning every instruction uses the result of the previous one. This keeps the processor from overlapping independent operations, so the measured time includes the full latency of each operation. We report the average time per operation in nanoseconds.

We ran these programs on eight processors across both ISAs. These include Apple M1 and M5 laptops, an Intel Core i7-13700H laptop, the Intel Xeon 5218 ECE LRC servers, and server machines with Intel Xeon Platinum 8160, Intel Xeon Max 9480, AMD EPYC Milan, and NVIDIA Grace processors. By comparing the timing differences between normal and subnormal operations, we investigated how these variations depend on the underlying ISA and processor architecture, identifying potential targets for our subsequent attack. Preliminary results demonstrated that the method of exploiting subnormal timing differences is viable for our attack, at least on some processors. Results are discussed in further detail in Section 5.

4.2 Setting Up the Attack

We also began setting up the attack. Our setup uses a small Python server that hosts two origins on the local machine, one for the attacker and one for the victim. The two origins run on different ports, so the browser treats them as cross-origin and enforces the same-origin policy between them. As described in our threat model, the victim page shows an 8x8 image of black and white pixels.

The attacker page loads the victim page in a cross-origin <iframe>. Before measuring anything, it tries to read the victim's DOM directly and checks that the browser blocks it with a SecurityError. This confirms that anything the attacker learns later has to come from the side channel and not from a mistake in our setup.

To look at one pixel at a time, the attacker page puts the iframe inside a 1x1 CSS pixel container that hides anything outside of it, and shifts the iframe so that only the target pixel shows through. It then scales the container up with a CSS scale() transform, so the single pixel covers up to a 300x300 area on the screen. This idea comes from Stone [4] and Andrysco et al. [1], and it is a key part of the attack. A penalty of tens of nanoseconds per operation is much too small to see from JavaScript, but once a filter is applied, every pixel in the enlarged area pays that penalty, which adds up to something large enough to measure with frame timing.

To measure rendering time, the attacker page records the time between two requestAnimationFrame callbacks using performance.now(), which follows the approach of Stone [4]

and Andrysco et al. [1]. The page has two modes. The calibration mode times black and white patches that the attacker controls, giving us reference timings for each color. The scan mode goes through all 64 victim pixels and takes a set number of samples for each one.

4.3 Next Steps

Right now, the attacker page does not apply any SVG filters, and as such the rendering time does not depend on the pixel's color and we do not see any timing differences. The last stage of our approach is to apply a filter that scales pixel color values into the subnormal range, as described in Section 2, so that non-black pixels are slowed down by the subnormal penalty and black pixels are not. We will then use the calibration mode to pick a timing threshold between the two colors, classify each victim pixel using that threshold, and check our accuracy against the ground truth. To get there, we still need to find a browser setup where the filter runs in floating point on the CPU of a vulnerable processor, and we will have to work around the reduced timer precision in modern browsers.

5 Evaluation

5.1 Timing Data

We collected timing data for floating-point adds and multiplies across a wide range of ARM and x86 processors, which were sourced from either personal laptops or server compute machines, such as the ECE LRC machines. The results are summarized in Figure 1.

On the Apple M1 and M5 chips, there is no significant timing difference between normal and subnormal operands for both add and multiply. This is expected, since Apple silicon has full hardware support for subnormal floating-point operations and can execute at full speed.

On the four Intel chips, including the Intel Xeon 5218 used by the ECE LRC machines, we see significant deltas between normal and subnormal execution. This is due to the microcode assist sequence discussed in Section 2. The pipeline must be flushed and a special microcode sequence must occur to correctly handle subnormal execution, which is very slow. Interestingly, the penalty only shows up for multiplication. Subnormal addition runs at the same speed as normal addition on every Intel chip we tested. This suggests that these chips handle subnormal addition directly in hardware, but still need a microcode assist when a multiplication uses or produces a subnormal value. For our attack, this means the SVG filter we use needs to create subnormal values through multiplication, which is how the feColorMatrix and feConvolveMatrix primitives scale pixel values.

The AMD EPYC Milan processor, which uses the Zen 3 microarchitecture, behaves very differently from the Intel chips. There is no penalty for subnormal addition (0.87 vs. 0.85 ns/op), and subnormal multiplication is only slightly slower than normal multiplication (1.14 vs. 0.90 ns/op). This difference of about 0.24 ns is roughly one clock cycle, which is about 100 times smaller than the 36–109 ns penalties we measured on the Intel chips. A penalty this small does not line up with a pipeline flush and microcode assist. Instead, it suggests that Zen 3 handles subnormal values in its regular floating-point hardware, possibly with a small amount of extra latency to normalize the result. Even though we can measure this difference in a tight native loop, it is unlikely to be visible through the noise of browser rendering and the coarse timers available in JavaScript.

The NVIDIA Grace processor, which is built from Arm Neoverse V2 cores [2], shows no difference at all between normal and subnormal operands for either operation (0.61 ns/op for addition and 0.92 ns/op for multiplication in both cases). This matches what we saw on the Apple M1 and M5, and suggests that, like Apple silicon, these Arm cores handle subnormal values at full speed in hardware. Since none of the three Arm chips we tested showed a penalty, this attack is unlikely to work on Arm-based machines.

This data provides valuable information for the direction of our attack. Apple chips, AMD EPYC Milan, and NVIDIA Grace are out of the question if we continue with the method of exploiting subnormal timing differences, since they show little to no timing difference. We will likely proceed using the Intel Xeon 5218, since we have easy access to it via the ECE LRC servers, and it exhibits dramatic timing differences.

5.2 The Attack Setup

So far, we have set up a victim website and an attack website, which are hosted on separate local ports by a small Python server. The victim website shows an 8x8 grid with 32 black and 32 white pixels in a random order, which stays the same until the server is restarted. This gives us a known ground truth to compare the attack against.

The attack website loads the victim in a cross-origin iframe and confirms that the same-origin policy blocks it from reading the victim's DOM. It can then select any single pixel, enlarge it, and measure how long frames take to render. Both the calibration mode and the scan mode work end to end. However, since we do not apply any SVG filters yet, the frame times do not depend on the pixel's color, and the attacker cannot recover any pixel values yet.

One concern with the attack setup is timer precision. After Spectre, browsers reduced the precision of performance.now() and added jitter, and frame times are also limited by the display's refresh rate. We expect that we will need a large scale factor to make the subnormal penalty a large part of each frame's rendering time, and that we will need many samples per pixel to reliably tell the two colors apart.




Figure 1. Time to perform floating-point instructions, measured in ns/op. Note the y-axis for each graph is different.

6 Related Work

Stone's *Pixel Perfect Timing Attacks with HTML5* [4] demonstrated the feasibility of cross-origin pixel stealing through browser rendering behavior. By exploiting software timing differences in the HTML5 requestAnimationFrame API, the attack measures how quickly CSS and SVG filters process pixels within a cross-origin iframe, allowing an attacker to infer image contents. This work established browser rendering operations as an unintended information channel and laid the foundation for subsequent SVG-based timing attacks.

Andrysco et al. [1] extended this approach by identifying hardware-level timing differences in floating-point operations. They demonstrated that arithmetic involving subnormal floating-point numbers can execute significantly slower than operations on normal numbers. By constructing SVG filters that trigger these operations, attackers can distinguish pixel values based on execution time. Unlike Stone's approach, which exploits browser rendering behavior, this attack leverages CPU-level floating-point performance characteristics, demonstrating how hardware behavior can undermine seemingly constant-time software.

Wang et al.'s *GPU.zip* [5] expanded side-channel research to integrated GPU architectures by exploiting hardware-based graphical data compression. The authors demonstrated that undocumented, lossless compression mechanisms can introduce data-dependent differences in DRAM traffic and rendering time. By constructing carefully designed SVG filters that produce highly compressible pixel patterns, attackers can infer underlying pixel values. This work showed that hardware optimizations intended to improve performance can themselves introduce information leakage, extending earlier attacks beyond CPU execution timing.

O'Connell et al.'s *Pixel Thief* [3] further advanced pixel-stealing attacks by exploiting CPU cache-state changes rather than relying directly on elapsed execution time. By monitoring the cache footprint left by SVG filter execution, the attack extracts pixel information despite modern browser timing mitigations, including reduced timer resolution and jitter. Building on the SVG filter leakage demonstrated by earlier work, Pixel Thief introduces an alternative measurement technique based on microarchitectural cache behavior, achieving extraction rates of up to 267 bits per second.

Collectively, these works demonstrate the evolution of browser-based side-channel attacks from software-level rendering measurements to hardware-level information leakage. Stone established the feasibility of timing-based pixel extraction, Andrysco et al. identified CPU floating-point timing differences, GPU.zip exposed leakage through GPU memory compression, and Pixel Thief demonstrated cache-based extraction. Together, they highlight the limitations of software-level timing mitigations and the broader security implications of data-dependent hardware behavior.

7 Conclusion

In this midpoint report, we described our progress so far in replicating the pixel stealing attack by Andrysco et al. [1]. We first measured how long floating-point addition and multiplication take on normal and subnormal operands across eight ARM and x86 processors. We found that the subnormal timing difference is still present on modern Intel processors, where subnormal multiplication is roughly 30 times slower than normal multiplication, but is mostly gone on AMD Zen 3, Apple silicon, and NVIDIA Grace. Based on these results, we chose the Intel Xeon 5218 as the target for our attack.

We also built the setup for the end-to-end attack. This includes a cross-origin victim page with a known secret image, and an attacker page that confirms the same-origin policy is enforced, enlarges individual victim pixels, and measures how long frames take to render. For the rest of the project,

we plan to apply an SVG filter that creates subnormal values, find a browser setup where that filter runs on the CPU, and measure how accurately we can recover the secret image. Whether or not the attack works on a modern browser, we expect our results to show how hardware timing behavior and browser defenses have changed since the original attack was published.

References

[1] Andrysco, M., Kohlbrenner, D., Mowery, K., Jhala, R., Lerner, S., and Shacham, H. On subnormal floating point and abnormal timing. In *2015 IEEE Symposium on Security and Privacy* (May 2015), IEEE.

[2] NVIDIA Corporation. NVIDIA Grace CPU Superchip. https://www.nvidia.com/en-us/data-center/grace-cpu-superchip/, 2023.

[3] O'Connell, S., Sour, L. A., Magen, R., Genkin, D., Oren, Y., Shacham, H., and Yarom, Y. Pixel thief: Exploiting SVG filter leakage in firefox and chrome. In *33rd USENIX Security Symposium (USENIX Security 24)* (2024), USENIX Association, pp. 3331–3348.

[4] Stone, P. Pixel perfect timing attacks with html5. Black Hat USA, July 2013.

[5] Wang, Y., Paccagnella, R., Gang, Z., Vasquez, W., Kohlbrenner, D., Shacham, H., and Fletcher, C. GPU.zip: On the side-channel implications of hardware-based graphical data compression. In *2024 IEEE Symposium on Security and Privacy (SP)* (2024), IEEE.