

```

#include <ESP8266WiFi.h>

const int buttonPin = D1;  // D2
const int buzzerPin = D2;  // D7

const char* ssid = "";
const char* password = "";

WiFiServer server(80);
String header;

bool buzzerOn = false;
unsigned long buzzerStartTime = 0;
const unsigned long buzzerDuration = 1000; // 1 second
bool buttonPressed = false;

void setup() {
  Serial.begin(115200);

  pinMode(buttonPin, INPUT_PULLUP);
  pinMode(buzzerPin, OUTPUT);
  digitalWrite(buzzerPin, LOW);

  Serial.print("Connecting to ");
  Serial.println(ssid);
  WiFi.begin(ssid, password);

  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }

  Serial.println();
  Serial.println("WiFi connected!");
  Serial.print("IP address: ");
  Serial.println(WiFi.localIP());

  server.begin();
}

void loop() {
  int buttonState = digitalRead(buttonPin);

  // Hantera knapp vid intryck
  if (buttonState == LOW && buzzerOn) {
    buzzerOn = false;
    digitalWrite(buzzerPin, LOW);
    buttonPressed = true;
  }
}

```

```

Serial.println("Button pressed");
delay(200);
}

```

```

WiFiClient client = server.available();
if (client) {
  Serial.println("New Client connected");
  String currentLine = "";
  unsigned long startTime = millis();

  while (client.connected() && millis() - startTime <= 2000) {
    if (client.available()) {
      char c = client.read();
      header += c;
      Serial.write(c);

      if (c == '\n') {
        if (currentLine.length() == 0) {
          // HTTP headers
          client.println("HTTP/1.1 200 OK");
          client.println("Content-type:text/html");
          client.println("Connection: close");
          client.println();

          // Hantera buzzer
          if (header.indexOf("GET /buzzer/on") >= 0 && !buzzerOn) {
            buzzerOn = true;
            buzzerStartTime = millis();
            digitalWrite(buzzerPin, HIGH);
            Serial.println("Web: Buzzer ON");
          }
          else if (header.indexOf("GET /buzzer/off") >= 0) {
            buzzerOn = false;
            digitalWrite(buzzerPin, LOW);
            Serial.println("Web: Buzzer OFF");
          }

          // HTML
          client.println("<!DOCTYPE html><html>");
          client.println("<head><meta name='viewport' content='width=device-width,
initial-scale=1'>");
          client.println("<link rel='icon' href='data:;'>");
          client.println("<style>html { font-family: Helvetica; text-align: center; }");
          client.println(".button { background-color: #195B6A; color: red; padding: 16px 40px;
font-size: 30px; margin: 2px; cursor: pointer; }");
          client.println(".button2 { background-color: #77878A; }</style></head>");
          client.println("<body><h1>ESP Buzzer Server</h1>");

```

```

        if (buttonPressed) {
            client.println("<p><strong>Button was pressed!</strong></p>");
            buttonPressed = false;
        }

        if (!buzzerOn) {
            client.println("<p><a href=\"/buzzer/on\"><button
class=\"button\">ON</button></a></p>");
        } else {
            client.println("<p><a href=\"/buzzer/off\"><button class=\"button
button2\">OFF</button></a></p>");
        }

        client.println("</body></html>");
        client.println();
        break;
    } else {
        currentLine = "";
    }
}
else if (c != '\r') {
    currentLine += c;
}
}
}

header = "";
client.stop();
Serial.println("Client disconnected");
}
}

```