

S-make system API interface document

Table of contents

S-make system API interface document.....	1
1. API interface description of S-make system.....	2
3. Response code:.....	2
2、 API detailed description	2
1. Login interface.....	2
2. Query all lower-level user interfaces.....	5
3. Query all sub-agent interfaces.....	10
4. Modification of user information interface.....	16
5. User logout interface.....	18
Live Location Module.....	19
6. Batch query device real-time location information interface.....	19
Live Location Module.....	23
7. Query trajectory information interface.....	23
Alarm module.....	27
8. Paging query interface for alarm information within a certain time zone of a specified device.....	27
9. The alarm information changes the read interface.....	29
10. Alarm message deletion interface.....	30
command module.....	31
11. Query the command information interface of the specified device within a certain time zone.....	31
12. Save command information interface.....	33
13. Command issuing interface.....	34
14. Instruction setting query interface.....	35
15. Command to set the update interface.....	38
16. Query the unique identification interface of NB equipment.....	40
17. Interface for querying device mileage statistics.....	41
18. Interface for querying device stop point information.....	43
19. Device picture upload interface.....	45
20. CCS equipment sending command interface.....	45
21. NB device sending command interface.....	46
22. Query the unique identification interface of NB equipment.....	47
23. NB device setting subscription address interface.....	48
25. Fuzzy paging query equipment policy information interface.....	50
26. Add policy information interface.....	51
27. Modify policy information interface.....	52
28. Query device battery information interface.....	53
29. Check the device interface to which apikey belongs.....	54
30、 Issuance of oil and electricity cut-off command.....	56
31、 Device bulk transfer.....	57

1. API interface description of S-make system

This document is used to record and describe the API developed by the car here system to help integration developers quickly and accurately grasp the integration method so as to efficiently realize specific business requirements.

agreement:

1. All interfaces need to transmit the apikey value in the header, which needs to be applied by the administrator (you can contact the relevant personnel)

The header input format is:

apikey	d5MXVOLL1t2H63p69kocGQA08_jn9uhD
--------	----------------------------------

The string after Bearer is obtained from the login interface

3. Response code:

parameter	describe
9901	apikey does not exist
9904	invalid apikey
9905	apikey has expired

2、 API detailed description

user module

1. Login interface

Interface function: user login interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/login

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
username	String	username	true
password	String	login password	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data
id	int	User ID
username	String	log-in name
password	String	user password
telephone	String	User phone number
terminalID	String	Device IMEI (normal users only)
carNumber	String	number plate
nickname	String	User's Nickname
user_id	String	User ID of the device
createTime	String	user creation time
picture	String	User ID picture

role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)
state	date	user status
idCard	String	ID number
realname	String	user's real name
expire	int	Whether the user device is expired (ordinary user)
address	boolean	user address
remark	String	Remark
linkman	String	contact person
ancestors	String	Your parent of the device (user)

Response code:

parameter	describe
200	login successful
201	username
202	wrong password
208	user expires
209	Username or password error" (unexpected problem, unexplainable, please try again)

request example

<pre>{ "data": { "address": "", "ancestors": ",2,", "carNumber": "experience Account", "createTime": "2016-03-26 00:00:00", "device": null, "expire": false, "id": 6, "idCard": "",</pre>

```

        "linkman": "",
        "location": null,
        "nickname": "experience Account",
        "password": "0aca74a1ea0f57b07e7dda9775acf118",
        "performance": {
            "deviceNum": 6,
            "id": 1990,
            "saleNum": 18,
            "user_id": 6
        },
        "permission": null,
        "picture": "",
        "realname": "",
        "remark": "",
        "role": 2,
        "salt": "sR9T5V",
        "state": 0,
        "telephone": "",
        "terminalID": "",
        "user_id": 2,
        "username": "experimental account"
    },
    "meta": {
        "message": "200",
        "success": true
    }
}

```

2. Query all lower-level user interfaces

Interface function: query all subordinate users

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/user/findAllUser

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
ID	int	Unique ID	true

return result:

parameter	type	describe
id	int	User ID
username	String	log-in name
password	String	user password
telephone	String	User phone number
terminalID	String	Device IMEI (normal users only)
carNumber	String	number plate
nickname	String	User's Nickname
user_id	String	User ID of the device
createTime	String	user creation time
picture	String	User ID picture
role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)
state	date	User status (1: online; 2: offline; 3: inactive)
idCard	String	ID number
realname	String	user's real name
expire	int	Whether the user device is expired (ordinary user)
address	boolean	user address
remark	String	Remark
linkman	String	contact person

ancestors	String	Your parent of the device
device	object	Device Information
deviceNumber	String	IoT card number
deviceType	String	Equipment type
did	int	Device ID
expirationTime	String	Platform expiration time
hireExpirationTime	String	user expiration time
iccid	String	iccid
iconType	int	Vehicle icon logo
installTime	long	installation time
installState	boolean	installation status
renewalTime	long	Renewal time
terminalID	String	DeviceIMEI

请求示例

```
[
  {
    "address": "",
    "ancestors": ",2,6,",
    "carNumber": "",
    "createTime": "2022-09-07 10:15:48",
    "device": {
      "createTime": null,
      "deviceNumber": "1064830477326",
      "deviceType": "K100B",
      "did": 6573,
      "expirationIntervalTime": 0,
      "expirationTime": "",
      "hireExpirationTime": "",
      "iccid": "",
      "iconType": 1,
      "installState": false,
      "installTime": 0,
      "isChange": 0,
      "renewalTime": 0,
    }
  }
]
```

```

        "terminalID": "864291100234327"
    },
    "expire": false,
    "id": 25535,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "K100B-234327",
    "password": "",
    "performance": null,
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 3,
    "salt": "",
    "state": 3,
    "telephone": "",
    "terminalID": "864291100234327",
    "token": "",
    "user_id": 6,
    "username": "K100B-234327"
},
{
    "address": "",
    "ancestors": ",2,6,",
    "carNumber": "",
    "createTime": "2022-09-07 10:15:48",
    "device": {
        "createTime": null,
        "deviceNumber": "1064878684482",
        "deviceType": "G11",
        "did": 16637,
        "expirationIntervalTime": 0,
        "expirationTime": "2023-02-15",
        "hireExpirationTime": "",
        "iccid": "",
        "iconType": 1,
        "installState": false,
        "installTime": 0,
        "isChange": 0,
        "renewalTime": 0,
        "terminalID": "864297400023815"
    }
},

```

```

    "expire": false,
    "id": 35599,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "G11-023815",
    "password": "",
    "performance": null,
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 3,
    "salt": "",
    "state": 3,
    "telephone": "",
    "terminalID": "864297400023815",
    "token": "",
    "user_id": 6,
    "username": "G11-023815"
  },
  {
    "address": "",
    "ancestors": ",2,6,",
    "carNumber": "浙 C39BT0",
    "createTime": "2022-09-07 10:15:48",
    "device": {
      "createTime": null,
      "deviceNumber": "",
      "deviceType": "G17",
      "did": 39469,
      "expirationIntervalTime": 0,
      "expirationTime": "",
      "hireExpirationTime": "",
      "iccid": "",
      "iconType": 1,
      "installState": false,
      "installTime": 0,
      "isChange": 0,
      "renewalTime": 0,
      "terminalID": "864301000008984"
    },
    "expire": false,
    "id": 58431,

```

```

        "idCard": "",
        "linkman": "",
        "location": null,
        "nickname": "G17-008984",
        "password": "",
        "performance": null,
        "permission": null,
        "picture":
"http://api.carhere.net/images/2020-06-06/864301000008984/1591448942666.jpg",
        "realname": "",
        "remark": "",
        "role": 3,
        "salt": "",
        "state": 3,
        "telephone": "",
        "terminalID": "864301000008984",
        "token": "",
        "user_id": 6,
        "username": "G17-008984"
    }
]

```

3. Query all sub-agent interfaces

Interface function: query all sub-agent interfaces

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/user/findAllAgent

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
id	int	Unique ID	true

return result:

parameter	type	describe
id	int	User ID
username	String	log-in name
password	String	user password
telephone	String	User phone number
terminalID	String	Device IMEI (normal users only)
carNumber	String	number plate
nickname	String	User's Nickname
user_id	String	User ID of the device
createTime	String	user creation time
picture	String	User ID picture
role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)
state	date	User status (1: online; 2: offline; 3: inactive)
idCard	String	ID number
realname	String	user's real name
expire	int	Whether the user device is expired (ordinary user)
address	boolean	user address
remark	String	Remark
linkman	String	contact person
ancestors	String	Your parent of the device

request example

```
[
  {
    "address": "",
    "ancestors": ",2,",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 6,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "experience account",
    "password": "",
    "performance": {
      "deviceNum": 6,
      "id": 6,
      "saleNum": 18,
      "user_id": 2
    },
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 2,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 2,
    "username": "experience account"
  },
  {
    "address": "",
    "ancestors": ",2,6,",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 864506,
    "idCard": "",
    "linkman": "",
```

```

    "location": null,
    "nickname": "Huayi Technology",
    "password": "",
    "performance": {
        "deviceNum": 6,
        "id": 864506,
        "saleNum": 6,
        "user_id": 6
    },
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 2,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 6,
    "username": "Huai"
},
{
    "address": "",
    "ancestors": ", 2, 6, ",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 865432,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "test",
    "password": "",
    "performance": {
        "deviceNum": 8,
        "id": 865432,
        "saleNum": 8,
        "user_id": 6
    },
    "permission": null,
    "picture": "",
    "realname": "",

```

```

    "remark": "",
    "role": 4,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 6,
    "username": "13824666738"
  },
  {
    "address": "",
    "ancestors": ", 2, 6, 864506, ",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 1032713,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "suU0F597",
    "password": "",
    "performance": {
      "deviceNum": 0,
      "id": 1032713,
      "saleNum": 0,
      "user_id": 864506
    },
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 4,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 864506,
    "username": "869016110164155"
  },
  {
    "address": "",

```

```

    "ancestors": ",2,6,",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 1044838,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "Dianshi Mining",
    "password": "",
    "performance": {
        "deviceNum": 1,
        "id": 1044838,
        "saleNum": 1,
        "user_id": 6
    },
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 2,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 6,
    "username": ""Dianshi Mining"
},
{
    "address": "",
    "ancestors": ",2,6,",
    "carNumber": "",
    "createTime": "2022-09-07 10:17:45",
    "device": null,
    "expire": false,
    "id": 1057056,
    "idCard": "",
    "linkman": "",
    "location": null,
    "nickname": "李小飞",
    "password": "",
    "performance": {

```

```

        "deviceNum": 0,
        "id": 1057056,
        "saleNum": 0,
        "user_id": 6
    },
    "permission": null,
    "picture": "",
    "realname": "",
    "remark": "",
    "role": 2,
    "salt": "",
    "state": 0,
    "telephone": "",
    "terminalID": "",
    "token": "",
    "user_id": 6,
    "username": "Li Xiaofei"
}
]

```

4. 4.Modification of user information interface

Interface function: modification of user information interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/user/updateUser

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
id	int	User ID	true
username	String	log-in name	false
password	String	user password	false

telephone	String	User phone number	false
terminalID	String	Device IMEI (normal users only)	false
carNumber	String	number plate	false
nickname	String	User's Nickname	false
user_id	String	User parent foreign key ID	false
createTime	String	user creation time	false
picture	String	User ID picture	false
role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)	false
state	date	User status (1: online; 2: offline; 3: inactive)	false
idCard	String	ID number	false
realname	String	user's real name	false
expire	int	Whether the user device is expired (ordinary user)	false
address	boolean	user address	false
remark	String	Remark	false
linkman	String	contact person	false
ancestors	String	User parent superior relationship	false

return result:

return result:

parameter	type	describe
meta	object	response status
message	String	status
success	boolean	Whether the request was successful
data	object	response data

Response code:

parameter	describe
200	Successfully modified
2 5 1	fail modified

request example

```
{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}
```

5. User logout interface

Interface function: user logout interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/logout

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

return result:

parameter	type	describe
meta	object	response status
message	String	status
success	boolean	Whether the request was successful
data	object	response data

request example

```
{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}
```

Live Location Module

6. Batch query device real-time location information interface

Interface function: batch query device real-time location information

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/location/find

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	necessary
list	[" imei,... "] array type	Device IMEI array	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data
id	int	User ID
username	String	log-in name
password	String	user password
telephone	String	User phone number
terminalID	String	Device IMEI (normal users only)
carNumber	String	number plate
nickname	String	User's Nickname
user_id	String	User parent foreign key ID
createTime	String	user creation time
picture	String	User ID picture
role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)
state	date	user status
idCard	String	ID number
realname	String	user's real name
expire	int	Whether the user device is expired (ordinary user)
address	boolean	user address
remark	String	Remark
linkman	String	contact person

ancestors	String	User parent superior relationship
location	object	real-time location information
acc	boolean	ACC
bdLat	double	Baidu latitude
wxya	double	Baidu longitude
course	int	direction
deviceProtocol	int	Device protocol number
electric	float	Device power
gcjLat	double	Google latitude
gcjLon	double	google longitude
gsm	int	GSM
iccid	String	IoT card number ICCID value
id	String	Unique ID
lat	double	latitude
locationType	String	positioning type
the lon	double	latitude
networkProtocol	String	communication protocol number
speed	int	Equipment speed
stateTime	long	Device communication time (UTC timestamp) When displaying, it is necessary to add 8 hours of milliseconds to the correct time
terminalID	String	Device IMEI number
utcTime	long	Device location time (UTC timestamp) When displaying, it is necessary to

		add 8 hours of milliseconds to the correct time
--	--	--

request example

```
[
  {
    "address": "",
    "ancestors": ", 2, 1063116, ",
    "carNumber": "",
    "createTime": "2022-09-07 11:05:49",
    "device": null,
    "expire": false,
    "id": 1083232,
    "idCard": "",
    "linkman": "",
    "location": {
      "acc": false,
      "bdLat": 22.59224,
      "bdLon": 113.865146,
      "course": 130,
      "deviceNumber": "",
      "deviceProtocol": 1,
      "deviceType": "",
      "electric": 1,
      "gcjLat": 22.586087,
      "gcjLon": 113.858656,
      "gsm": 4,
      "iccid": "898604a4192190656644",
      "id": "",
      "lat": 22.589092,
      "lbs": null,
      "locationType": "Bds",
      "lon": 113.853707,
      "networkProtocol": "",
      "speed": 0,
      "state": 0,
      "stateTime": 1661480597635,
      "temperature": -100,
      "terminalID": "355468590222303",
      "utcTime": 1661479087269,
      "voltage": -1
    },
    "nickname": "GW005A-222303",
  }
]
```

```

        "password": "",
        "performance": null,
        "permission": null,
        "picture": "",
        "realname": "",
        "remark": "",
        "role": 3,
        "salt": "",
        "state": 2,
        "telephone": "",
        "terminalID": "355468590222303",
        "token": "",
        "user_id": 1063116,
        "username": "GW005A-222303"
    }
]

```

Live Location Module

7. Query trajectory information interface

Interface function: query trajectory information interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/track/findByTerminalID

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	necessity
terminalID	String	DeviceIMEI	true
beginTime	long	Start time (UTC timestamp) The start time of the next page is the positioning time of	true

		the last record on the previous page (field: utcTime) The number of milliseconds passed in needs to be subtracted by the number of milliseconds of 8 hours (if it is the positioning time in the last record of the previous page, there is no need to subtract it, because the number of milliseconds of 8 hours has already been subtracted) .	
endTime	long	end time (UTC timestamp) The milliseconds passed in need to be subtracted from the 8 hour milliseconds.	true
pageSize	int	The number of records, judge whether there is a	true

		next page by judging whether the returned array length is greater than the set length	
locationType	String	targeting type The fixed values are as follows: 1. B ds 2. Lbs _ 3. G ps 4. Wifi _	true

return result:

parameter	type	describe
acc	boolean	ACC
bdLat	double	Baidu latitude
wxya	double	Baidu longitude
course	int	direction
supplement	Boolean	Whether supplementary data
electric	float	Device power
gcjLat	double	Google latitude
gcjLon	double	google longitude
gsm	int	GSM
serverTime	String	device fix time
id	String	Unique ID
lat	double	latitude
locationType	String	targeting type

lon	double	latitude
Lac	String	protocol number
mcc	String	location difference code
mnc	String	location difference code
cellID	String	position
speed	int	Equipment travel speed
stateTime	long	Device communication time When displaying, you need to add 8 hours of milliseconds, which is the correct time
terminalID	String	Device IMEI number
utcTime	long	server time When displaying, it is necessary to add 8 hours of milliseconds, which is the correct time

request example

```
{
  "_id": {
    "counter": 5017437,
    "date": "2022-01-10 09:05:37",
    "machineIdentifier": 8538571,
    "processIdentifier": 26996,
    "time": 1641776737000,
    "timeSecond": 1641776737,
    "timestamp": 1641776737
  },
  "terminalID": "869115000722237",
  "supplement": false,
  "locationType": "Bds",
  "acc": true,
  "speed": 45,
  "course": 291,
  "gsm": 4,
  "electric": 1,
  "voltage": 13.9,
  "lat": 33.538152,
  "lon": 119.055398,
  "bdLat": 33.542992,
  "bdLon": 119.067428,
  "gcjLat": 33.536828,
  "gcjLon": 119.060971,
  "mnc": 0,
  "mcc": 460,
  "lac": 21070,
  "cellId": 16454913,
  "stateTime": 1641747937937,
  "utcTime": 1641747927937
}
```

Alarm module

8. Paging query interface for alarm information within a certain time zone of a specified device

Interface function: Paging query interface for alarm information within a certain time zone of a specified device

Request address: [https://api.gwgps12580.com/v1/Ch_manage_controller /api/deviceAlarms/findAll](https://api.gwgps12580.com/v1/Ch_manage_controller/api/deviceAlarms/findAll)

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
terminalID	String	DeviceIMEI	true
beginTime	long	Start time (UTC timestamp)	true
endTime	long	end time (UTC timestamp)	true
pageNum	int	page number	true
pageSize	int	display quantity per page	true
isRead	boolean	Whether it has been read (true: read; false: unread)	true
alarmState	int	Alarm type (when it is 100, query all alarm types)	true

return result:

acc	boolean	ACC
bdLat	double	Baidu latitude
wxya	double	Baidu longitude
course	int	direction
electric	float	Device power
gcjLat	double	Google latitude
gcjLon	double	google longitude
gsm	int	GSM
serverTime	String	device positioning time
id	String	Unique ID
lat	double	latitude
locationType	String	targeting type
the lon	double	latitude
isRead	Boolean	Whether read or not
alarmAddress	String	Alarm address
alarmState	Int	alarm type

request example

```

{
  "content": [
    {
      "acc": false,
      "alarmAddress": "广东省广州市增城市凤馨苑十二街(凤凰城凤馨苑内,美的(汽车城大道店)北562米)",
      "alarmState": 20,
      "bdLat": 23.148043,
      "bdLon": 113.604589,
      "course": 49,
      "electric": 0.05,
      "expireTime": "2019-12-31 07:46:15",
      "gcjLat": 23.142246,
      "gcjLon": 113.598064,
      "gsm": 4,
      "id": "5e0a8c478249cb283417623e",
      "isRead": false,
      "lat": 23.145102,
      "locationType": "Bds",
      "lon": 113.592985,
      "serverTime": 1577720774471,
      "speed": 9,
      "terminalID": "868516110003932",
      "utcTime": 1577720224884
    }
  ],
  "first": false,
  "last": false,
  "number": 1,
  "numberOfElements": 1,
  "size": 1,
  "sort": [
    {
      "ascending": false,
      "descending": true,
      "direction": "DESC",
      "ignoreCase": false,
      "nullHandling": "NATIVE",
      "property": "utcTime"
    }
  ],
  "totalElements": 89,
  "totalPages": 89
}

```

9. The alarm information changes the read interface

Interface function: alarm information change read interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller /api /deviceAlarms/save

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
id	int	Alarm information identification Id	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data

Response code:

parameter	describe
200	Successfully modified
251	fail to modified

request example

```
{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}
```

10. Alarm message deletion interface

Interface function: alarm information delete interface

Request address: [https://api.gwgps12580.com/v1/Ch_manage_controller /api
/deviceAlarms/delete](https://api.gwgps12580.com/v1/Ch_manage_controller/api/deviceAlarms/delete)

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
id	int	Alarm information identification Id	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data

Response code:

parameter	describe
200	successfully deleted
251	failed to delete

request example

```
{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}
```

command module

11. Query the command information interface of the specified device within a certain time zone

Interface function: query the command information interface of the

specified device within a certain time zone

Request address: [https://api.gwgps12580.com/v1/Ch_manage_controller /api
/command/find](https://api.gwgps12580.com/v1/Ch_manage_controller/api/command/find)

Request method: POST

Deliver parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
terminalID	String	DeviceIMEI	true
beginTime	long	Start time (UTC timestamp)	true
endTime	long	end time (UTC timestamp)	true

return result:

parameter	type	describe
id	String	Unique ID
terminalID	String	DeviceIMEI
content	String	command content
agentName	String	Agency name
backContent	String	command reply content
deviceId	String	NB device ID
issTime	long	Command issue time (current timestamp)
excuteTime	long	Execution time (UTC timestamp)

expireTime	date	Expiration
------------	------	------------

request example

```
[
  {
    "agentName": "GW005A-003932",
    "backContent": "OK",
    "content": "SWMODE,0,0#",
    "deviceId": "",
    "excuteTime": 1577706837155,
    "expireTime": "2019-12-31 03:53:57",
    "id": "5e0a55d558484b652368f781",
    "issTime": 1577706837155,
    "terminalID": "868516110003932"
  },
]
```

12. Save command information interface

Interface function: save instruction information interface

Request address: [https://api.gwgps12580.com/v1/Ch_manage_controller /api /command/save](https://api.gwgps12580.com/v1/Ch_manage_controller/api/command/save)

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
terminalID	String	DeviceIMEI	true
content	String	command content	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data

Response code:

parameter	describe
200	Saved successfully
251	save failed

request example

```
{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}
```

13. Command issuing interface

Interface function: command issuing interface

Request address:

http://api.gwgps12580.com/v1/Ch_manage_controller/api/tracker_cmd

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
terminalID	String	DeviceIMEI	true
content	String	equipment directive	False

return result:

parameter	type	describe
terminalID	String	DeviceIMEI

content	String	command reply content
---------	--------	-----------------------

request example

```

{
  "terminalID": "868016930016594",
  "content": "Only the external power supply;GPRS:Link Up;GSM Signal Level:middle;GPS:UNFIXED;ACC:OFF;Defense:OFF;BMS MOS:0,ecd:80"
}

```

14. Instruction setting query interface

Interface function: command setting query interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/order/find

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Whether necessary
terminalID	String	DeviceIMEI	true

return result :

parameter	type	describe
sos1	String	SOS number
sos2	String	SOS number
sos3	String	SOS number
speedLimit	String	Overspeed alarm state
speedLimitType	String	Overspeed alarm type
terminalID	String	DeviceIMEI
tireSetting	String	Tire pressure setting information

vibration	boolean	Vibration alarm status
vibrationType	Int	Vibration alarm type
center	String	center number
cut Electric	boolean	Power failure alarm status
cutElectricType	Int	Power failure alarm type
cutOff	boolean	Fuel cut off state
displacement	boolean	Displacement alarm
displacementLimit	int	Displacement range
displacementType	int	Displacement alarm type
fenceAlarmType	int	Fence alarm type
fenceLat	double	fence longitude
fenceLimit	int	fence size
fenceLon	double	fence latitude
fenceModel	int	fence mode
fenceName	String	fence name
fenceSetTime	long	fence setting time
fenceState	boolean	fence state
id	String	Document ID
limitSpeed	int	overspeed range
limitTime	int	speeding time
lowElectric	boolean	Low battery alarm
lowElectricType	int	Low battery alarm type
sensitiveLevel	int	sensitivity level
workPattern	int	Working mode : 0: intelligent power saving mode, 1: interval working mode, 2, sleep working mode

intervalTime	int	Interval Interval work mode. The time unit is minutes, range 5-1440; sleep mode. The time unit is hour, range (1-2376);
timerCut	String	power off command
powerSwitch	boolean	power off switch
automaticSwitch	boolean	Auto power off switch (false: turn off auto power off, true: turn on auto power off)
offline	object	offline status
ota	object	Ota Information

request example

```
{
  "center": "",
  "cutElectric": true,
  "cutElectricType": 0,
  "cutOff": false,
  "displacement": true,
  "displacementLimit": 135,
  "displacementType": 0,
  "fenceAlarmType": 0,
  "fenceLat": 30.296995558844504,
  "fenceLimit": 177,
  "fenceLon": 120.1787027663623,
  "fenceModel": 2,
  "fenceName": "雅苑",
  "fenceSetTime": 1572971400000,
  "fenceState": true,
  "id": "5d7b0a2558484b76e9b8b452",
  "limitSpeed": 49,
  "limitTime": 10,
  "mileage": 100,
  "sos1": "",
  "sos2": "",
  "sos3": "",
  "speedLimit": true,
  "speedLimitType": 0,
  "terminalID": "808029400062454",
  "vibration": true,
  "vibrationType": 0
}
```

15. Command to set the update interface

Interface function: command setting update interface

Request address:

https://api.gwgps12580.com/v1/Ch_manage_controller/api/order/save

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
sos1	String	SOS number	false
sos2	String	SOS number	false
sos3	String	SOS number	false
speedLimit	String	Overspeed alarm state	false
speedLimitType	String	Overspeed alarm type	false
terminalID	String	DeviceIMEI	false
tireSetting	String	Tire pressure setting information	false
vibration	boolean	Vibration alarm status	false
vibrationType	Int	Vibration alarm type	false
center	String	center number	false
cut Electric	boolean	Power failure alarm status	false
cutElectricType	Int	Power failure alarm type	false
cutOff	boolean	Fuel cut off state	false

displacement	boolean	Displacement alarm	false
displacementLimit	int	Displacement range	false
displacementType	int	Displacement alarm type	false
fenceAlarmType	int	Fence alarm type	false
fenceLat	double	fence longitude	false
fenceLimit	int	fence size	false
fenceLon	double	fence latitude	false
fenceModel	int	fence mode	false
fenceName	String	fence name	false
fenceSetTime	long	fence setting time	false
fenceState	boolean	fence state	false
id	String	Document ID	true
limitSpeed	int	overspeed range	false
limitTime	int	speeding time	false
lowElectric	boolean	Low battery alarm	false
lowElectricType	int	Low battery alarm type	false
sensitiveLevel	int	sensitivity level	false
workPattern	int	Working mode : 0: intelligent power saving mode, 1: interval working mode, 2, sleep working mode	false
intervalTime	int	Interval Interval work mode. The time unit is minutes, range 5-1440; sleep mode. The	false

		time unit is hour, range (1-2376);	
timerCut	String	power off command	false
powerSwitch	boolean	power off switch	false
automaticSwitch	boolean	Auto power off switch (false: turn off auto power off, true: turn on auto power off)	false
offline	object	offline status	false
ota	object	Ota Information	false

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data

Response code:

parameter	describe
200	modify successfully
251	fail to modify

request example

```

{
  "data": null,
  "meta": {
    "message": "200",
    "success": true
  }
}

```

16. Query the unique identification interface of NB equipment

Interface function: query the unique identification interface of NB equipment

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller /api /nb/findDeviceId

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
id	int	Alarm information identification Id	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	response data

request example

```
{
  "data": "d895a0dd000cdcc01895a0dd000cdcc0",
  "meta": {
    "message": "200",
    "success": true
  }
}
```

17. Interface for querying device mileage statistics

Interface function: interface for querying equipment mileage statistics

information

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller/api/stat/find

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true
beginTime	long	Start time (UTC timestamp)	true
endTime	long	end time (UTC timestamp)	true
pageNum	int	page number	true
pageSize	int	number of pages	True

return result:

parameter	type	describe
mileage	float	mileage
normalAlarm	String	normal alarm
helpAlarm	int	SOS
cutOffAlarm	int	cut off alarm
vibrateAlarm	int	Vibration alarm
fenceAlarm	int	fence alarm
speedAlarm	int	Overspeed alarm

demolishAlarm	int	Disassembly alarm
deadZoneAlarm	int	dead zone alarm
displaceAlarm	int	Displacement alarm
onAlarm	int	Power-on alarm
offlineAlarm	int	Offline alarm
batteryAlarm	int	battery alarm
alarmToal	int	Alarm overview
stayTime	int	Duration of stay statistics
statisticDate	Long	statistical date
statisticState	boolean	Statistical identification

request example

```

1  {
2      "content": [
3          {
4              "alarmToal": 1,
5              "batteryAlarm": 0,
6              "cutOffAlarm": 0,
7              "deadZoneAlarm": 0,
8              "demolishAlarm": 0,
9              "displaceAlarm": 0,
10             "fenceAlarm": 0,
11             "helpAlarm": 0,
12             "id": "5f26525470e630c5e4407633",
13             "mileage": 55.90003,
14             "normalAlarm": 0,
15             "offlineAlarm": 1,
16             "onAlarm": 0,
17             "speedAlarm": 0,
18             "statisticDate": 1596297600000,
19             "statisticState": false,
20             "stayTime": 0,
21             "terminalID": "860615001803018",
22             "vibrateAlarm": 0
23         }
24     ],
25     "first": false,
26     "last": true,
27     "number": 1,
28     "numberOfElements": 1,
29     "pageSize": 100000
30 }

```

18. Interface for querying device stop point information

Interface function: query equipment stop point information interface

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller/api/stay/find

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true
beginTime	long	Start time (UTC timestamp)	true
endTime	long	end time (UTC timestamp)	true
pageNum	int	page number	true
pageSize	int	number of pages	True

return result:

parameter	type	describe
bdLat	double	Baidu latitude
wxya	double	Baidu longitude
gcjLat	double	Google latitude
gcjLon	double	Google longitude
id	String	Unique ID
lat	double	latitude
locationType	String	targeting type
lon	double	latitude

terminalID	String	DeviceIMEI
stayTime	int	length of stay
startTime	int	start time
endTime	Long	End Time
expireTime	date	Expiration time

19. Device picture upload interface

Interface function: device image upload

Request URL :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/user/importPic

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true
file	File	picture file	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	Image file network address

20. CCS equipment sending command interface

Interface function: CCS equipment sends commands

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller/ api
/ccs/sendCommand

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
deviceId	String	DeviceIMEI	true
paras	command body		
command	String	command content	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	Image file network address

21. NB device sending command interface

Interface function: NB equipment sends commands

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller/ api
/nb/sendCommand

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
deviceId	String	DeviceIMEI	true
paras	command body		
command	String	command content	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	Image file network address

22. Query the unique identification interface of NB equipment

Interface function: query NB device registration to generate deviceId

Request URL: [https://api.gwgps12580.com/v1/Ch_manage_controller/ api](https://api.gwgps12580.com/v1/Ch_manage_controller/api/nb/findDeviceId)

/nb/findDeviceId

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true

return result:

parameter	type	describe
-----------	------	----------

meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	NB device deviceId

23. NB device setting subscription address interface

Interface function: NB device setting subscription address interface

Request URL :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/nb/subscriptions

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
callbackUrl	String	Device callback address	true
notifyType	String	Command content (deviceDataChanged)	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	object	corresponding content

24. equipment policy information query interface

Interface function: equipment policy information query interface

Request URL :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/insurance/find

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	Equipment Warranty Information	
policyNumber	String	Policy number
realname	String	Policyholder's real name
terminalID	String	DeviceIMEI
address	String	policyholder address
idCard	String	ID number
telephone	String	Phone number
carNumber	String	number plate
insuranceStatus	String	policy status

createTime	date	Insurance period
yearLimit	int	Policy period

25. Fuzzy paging query equipment policy information interface

Interface function: fuzzy paging query policy information interface

Request address :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/insurance/select

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
selectName	String	search name	true
agentId	int	Agency ID	true
pageNum	int	page number	true
pageSize	int	number of pages	true

return result:

parameter	type	describe
ID	int	policy unique ID
policyNumber	String	Policy number
realname	String	Policyholder's real name
terminalID	String	DeviceIMEI
address	String	policyholder address
idCard	String	ID number
telephone	String	Phone number
carNumber	String	number plate

insuranceStatus	String	policy status
createTime	date	Insurance period
yearLimit	int	Policy period

26. Add policy information interface

Interface function: add policy information interface

Request URL :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/insurance/insert

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
policyNumber	String	Policy number	true
realname	String	Policyholder's real name	true
terminalID	String	DeviceIMEI	true
address	String	policyholder address	true
idCard	String	ID number	true
telephone	String	Phone number	true
carNumber	String	number plate	true
insuranceStatus	String	policy status	true
createTime	date	Insurance period	true
yearLimit	int	Policy period	true

return result:

parameter	type	describe
-----------	------	----------

meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	response content	

27. Modify policy information interface

Interface function: modify policy information interface

Request URL :

https://api.gwgps12580.com/v1/Ch_manage_controller/api/insurance/insert

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
ID	int	policy unique identifier	true
policyNumber	String	Policy number	true
realname	String	Policyholder's real name	true
terminalID	String	DeviceIMEI	true
address	String	policyholder address	true
idCard	String	ID number	true
telephone	String	Phone number	true
carNumber	String	number plate	true
insuranceStatus	String	policy status	true
createTime	date	Insurance period	true

yearLimit	int	Policy period	true
-----------	-----	---------------	------

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	response content	

28. Query device battery information interface

Interface function: query device battery information interface

Request URL: https://api.gwgps12580.com/v1/Ch_manage_controller/api/battery/findByTerminalID

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
terminalID	String	DeviceIMEI	true

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	Equipment Warranty Information	
voltage	float	battery voltage

chargeState	int	charging
terminalID	float	DeviceIMEI
electric	float	electricity
temperature	float	battery temperature
useCount	int	Battery charge times
capacity	int	battery capacity
groupVoltage	Float[]	battery pack voltage
groupTemperature	Float[]	battery pack temperature

29. Check the device interface to which apikey belongs

Interface function: check the device interface to which apikey belongs

Request address: https://api.gwgps12580.com/v1/Ch_manage_controller

/api/user/findApiKeyByAllTerminalID

Request method: GET

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

return result:

parameter	type	describe
meta	object	response status
message	String	status code
success	boolean	Whether the request was successful
data	device information	
id	int	User ID
username	String	log-in name
password	String	user password

telephone	String	User phone number
terminalID	String	Device IMEI (normal users only)
carNumber	String	number plate
nickname	String	User's Nickname
user_id	String	User parent foreign key ID
createTime	String	user creation time
picture	String	User ID picture
role	int	User role (1: admin; 2: agent; 3: common user; 4: super user)
state	date	User status (1: online; 2: offline; 3: inactive)
idCard	String	ID number
realname	String	user's real name
expire	int	Whether the user device is expired (ordinary user)
address	boolean	user address
remark	String	Remark
linkman	String	contact person
ancestors	String	User parent relationship family
device	object	Device Information
deviceNumber	String	IoT card number
deviceType	String	Equipment type
did	int	Device ID
expirationTime	String	Platform expiration time
hireExpirationTime	String	user expiration time
iccid	String	iccid

iconType	int	Vehicle icon logo
installTime	long	installation time
installState	boolean	installation status
renewal time	long	Renewal time
terminalID	String	DeviceIMEI

Return example:

```
{
  "data": [
    {
      "address": "",
      "ancestors": ",2,5,",
      "carNumber": "",
      "createTime": "2023-02-25 17:43:02",
      "device": {
        "createTime": null,
        "deviceNumber": "",
        "deviceProtocol": 0,
        "deviceType": "4G28",
        "did": 4,
        "expirationIntervalTime": 0,
        "expirationTime": "2024-02-25",
        "hireExpirationTime": "2024-02-25",
        "iccid": "",
        "iconType": 1,
        "installState": false,
        "installTime": 0,
        "isChange": 0,
        "renewalTime": 0,
        "terminalID": "10009812569"
      },
      "expire": false,
      "id": 8,
      "idCard": "",
      "linkman": "",
      "location": null,
      "newPassword": "",
      "nickname": "4G28-812569",
      "password": "",
      "performance": null,
      "permission": null,
      "picture": "",
      "realname": "",
      "remark": "",
      "role": 3,
      "salt": "",
      "state": 0,
      "telephone": "",
      "terminalID": "10009812569",
      "token": "",
      "user_id": 5,
      "username": "4G28-812569"
    }
  ],
  "meta": {
    "message": "200",
    "success": true
  }
}
```

30、Issuance of oil and electricity cut-off command

Interface function: interface for issuing oil and electricity cut-off commands

Request address :

http://api.gwgps12580 .net/v1/Ch_manage_controller/api/tracker_cmd_Relay

Request method : POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

return result:

parameter	type	describe
terminalID	String	DeviceIMEI
type	int	Type 0: Recovery 1: Oil and electricity cut off

request example

```
{
  "terminalID": "862201740071973",
  "content": "Restore fuel supply:Success!"
}
```

31、Device bulk transfer

Interface function: equipment batch transfer interface

Request address:

http://api.gwgps12580 .net/v1/Ch_manage_controller/api/ user
/transFerDevice

Request method: POST

Pass parameter format: application/json

Header: apikey

Transmission protocol: Http/Https

Parameter description :

parameter	type	describe	Is it necessary
list	array type	Device IMEI (separate multiple devices with commas)	true

agentId	int	agent id	true
id	int	login user id	True

Parameter legend :

```
{ "list": ["17200001159", "6666666665"], "agentId": 1109063, "id": 2 }
```

return result:

parameter	type	describe
meta	object	response status
message	String	status code 401: This device: imei, does not exist, please check and transfer 40 2: The current logged-in user does not have permission to operate this device: imei 403: This device: imei, this agent already exists, please check before transferring 500: The number of devices transferred cannot exceed 500, please check and transfer
success	boolean	Whether the request was successful

Return the legend:

```
▼ {data: null, meta: {message: "转移成功", success: true}}
  data: null
  ▼ meta: {message: "转移成功", success: true}
    message: "转移成功"
    success: true
```