







- Notes
- 1 Make sure that the O-ring is NOT twisting and properly assembled during this mounting process.
 - 2 Use ring terminal M8 for the power contact.
The recommended tightening torque of Ref No. ⑩ and ⑪ is 6.0 to 6.5 N·m.
Be sure to tighten Ref No. ⑩ with the panel installed as shown in Fig.1.
Do not tighten the bolt by itself during inspection.
 - ① The panel material is assumed to be aluminum.
The above recommended torque is the one when aluminum is used.
Depending on the hardness of the material and the smoothness of the surface, the load on the product by tightening the screw will vary.
Therefore, when selecting other materials, please confirm and, if necessary, lower the tightening torque.
Recommended bolt size are as follows.
- Ref No. ⑩ : Screw size M8, Pitch 1.25 Length 10 to 12 mm.
(For panel thickness, Refer to the next page Fig.1)
- Ref No. ⑪ : Screw size M8, Pitch 1.25 Length 12 to 15 mm.
(Assume ring terminal thickness t = 2.5 to 3.)
When using ring terminal with different thickness, choose appropriate bolt size per the thickness.)
To prevent loosening, use LOCTITE 243, HENKEL JAPAN or equivalent.


Mating connector at signal contact side is as follows.				
Connector	GT8E-2S-2C	CL758-0030-6-00		
Crimp contact	GT8E-2022SCF	CL758-0033-4-00	For AWG#20~22	Reel contact
	GT8B-2428SCF	CL758-0055-7-00	For AWG#24~28	Reel contact
	GT8E-2022SC	CL758-0101-2-00	For AWG#20~22	Bulk contact

- 4 Fig.1 shows the recommended panel cut out dimensions.
Roughness on the panel surface indicated by  for water sealing must be $\sqrt{Rz} 3.2$
- 5 This product is delivered with the plug and receptacle unmated as shown in Fig. 4.
- 6 Appearance of each of the plug and receptacle are shown in Fig.2
- 7 Lot No. is marked in one the indicated part shown.
- ⑧ Make sure the locking system firmly completed before using the this product.
Fig.3 indicates rotated position of the plug and the receptacle with locking completed.
Also, 'LOCK' marking on the receptacle can be seen from the plug hole.



- ⚠ WARNING
- 9 Never engage/disengage the plug while the power contacts (Ref No. ③ and Ref. No. ⑥) are energized.
Signal contacts are sequentially connected after the power line in the plug engagement, and disconnected before the power line in the disengagement. Therefore, use the product with the circuit to avoid hot-plugging provided.
Mating sequence of power line and signal line are shown in Fig. 1 along with the appearance and circuit of each state.
 - 10 Rotated position of the plug and the receptacle are is shown as an exapmle.
 - 11 For product handling, refer to the Operation guide ETAD-C0320.
 - 12 Female contact Ref. No. ⑧ is loose before the bolt is attached to Ref. No. ⑩,
and the female contact is movable as shown in Fig. 2, but stabilized to the receptacle after the screw fix.
Therefore the looseness is eliminated for the use and does not affect its performance. (0.2) shown in Fig. ⑧ is the state when the bolt is tightened.
- ⚠ WARNING
- 13 Engage the plug to the receptacle after all the assembly including cable wiring are completed for safety.

6	Hydrogenation acrylonitrile butadiene rubber	(Black)	12	Polybutylene terephthalate	(Black)
5	Polybutylene terephthalate	(Orange)	11	Brass	Nickel plating
4	Copper alloy	Tin plating 1μm MIN	10	Brass	Nickel plating
3	Copper	Silver plating 3μm MIN	9	Hydrogenation acrylonitrile butadiene rubber	(Black)
2	Hydrogenation acrylonitrile butadiene rubber	(Black)	8	Copper alloy	Silver plating 3μm MIN
1	Polybutylene terephthalate	(Orange)	7	Copper alloy	Tin plating 1μm MIN
NO.	MATERIAL	FINISH . REMARKS	NO.	MATERIAL	FINISH . REMARKS
UNITS mm		SCALE 1 : 2	COUNT 1	DESCRIPTION OF REVISIONS DIS-C-00018068	DESIGNED TY. SUZUKI
APPROVED : TP. KOMATSU 20220815				DRAWING NO. EDC-118302-04-00	
CHECKED : HY. KOBAYASHI 20220815				PART NO. EM30MSD(C04)	
DESIGNED : TY. SUZUKI 20220812				CODE NO. CL0138-0200-0-04	
DRAWN : TY. SUZUKI 20220812				DATE 20241001	
HIROSE ELECTRIC CO., LTD.				1/2	


4 Fig.1 The recommended panel dimention (t = 2 to 4.5)



8 Fig.3 State of locked



5 Fig.4 View of packing style




9 Table.1 Connection Timing (Power line and signal line)

Ⓐ-Ⓑ Power line
Ⓒ-Ⓓ Signal line

State	Before mating	Insertion plug	Rotated and Locked	Unlocked	Unmated
Appearance			 Lock complete in mating indication. (The details refer to Fig.3)		
Connection		Power line closed. Signal line open. No power current.	Signal line closed. Power line ON	Signal line open. Power line OFF.	
Circuit diagram	 Plug Receptacle	 Plug Receptacle	 Plug Receptacle	 Plug Receptacle	 Plug Receptacle

3 View of signal contact side



HRS	DRAWING NO.	EDC-118302-04-00	
	PART NO.	EM30MSD(04)	
	CODE NO.	CL0138-0200-0-04	1/2