The Price of Location Privacy: Age of Incorrect Information in Location-Aided UAV Communications

Author information to be added

***Abstract*—Location information increasingly supports wireless resource allocation through location-aided channel prediction and beam selection. Protecting this information can affect transmission reliability and the delivery of correct task updates. We consider a single-antenna unmanned aerial vehicle (UAV) communicating with a multi-antenna base station. The UAV releases a three-dimensional Laplace-perturbed location, and the base station applies maximum a posteriori (MAP) inference before selecting a receive beam. For a prescribed beam map and symmetric binary task source, we relate privacy-dependent outage to average age of incorrect information (AoII). Location-Aware Privacy–Information Selection (LAPIS) selects a fixed reporting budget using simultaneous confidence bounds and independent confirmation. In a conditional empirical model constructed from measured channel state information (CSI), MAP lookup yields an estimated 15.8% lower AoII than direct-report lookup at one tested budget. With 200 selection samples per scenario and budget, point-estimate selection violates the AoII constraint in 65.7% of 1,000 trials, whereas LAPIS has no observed violations and selects larger disclosure budgets. Separate geometric controls show that larger arrays can increase sensitivity to location uncertainty. These results quantify a privacy–reliability tradeoff under explicit model assumptions. Code and reproducibility materials: https://github.com/jwentong/LocationPrivacy.**

***Index Terms*—Location privacy, geo-indistinguishability, location-aided beamforming, age of incorrect information, UAV communications.**

I. Introduction

Spatial intelligence is creating demand for networks that understand where devices operate and how their surroundings affect communication [1]. This is particularly relevant to the low-altitude economy, where unmanned aerial vehicle (UAV) applications require reliable links for sensing, inspection, and logistics in three-dimensional environments [2]. Location consequently becomes more than a navigation coordinate: it links a terminal to environmental knowledge and can guide wireless resource allocation.

Existing research provides several enabling components. Location-based beamforming learns resource decisions from spatial information, including in non-line-of-sight environments [3]. Neural radio-frequency radiance fields (NeRF^2) model radio propagation through a continuous field conditioned on transmitter location [4]. Wireless radiation field reconstruction with Gaussian splatting (WRF-GS) reconstructs spatial spectra using three-dimensional Gaussian splatting [5], while WRF-GS+ improves field representation and prediction [6]. These advances support reusable environmental models and can reduce repeated channel acquisition. Their resource decisions nevertheless depend on the quality of the reported location.

Such uncertainty arises naturally from privacy protection. Accurate location reports expose a device's whereabouts and activities. Geo-indistinguishability protects reports through distance-based differential privacy [7], including three-dimensional mechanisms [8]. Related work protects against physical-layer localization using transmit beamforming [9], studies age of information (AoI) with privacy-aware mobile agents [10], and mitigates location leakage in federated radio-map construction [11]. We examine their operational consequence: how does protecting the location used for resource decisions affect subsequent task-information updates?

Consider a UAV whose location report is used by a multi-antenna base station (BS) to configure a receive beam. Stronger protection can increase inference error and beam mismatch. Radial and angular location errors affect array gain differently, while the link margin determines whether a gain loss causes an outage. Task evolution further determines whether missed packets leave the receiver with an incorrect estimate. Age of incorrect information (AoII) measures how long that estimate remains incorrect [12]. Studies of imperfect channel information [13] and low-altitude multiple-input multiple-output (MIMO) networks [14] motivate connecting resource errors to persistent information errors.

We study this connection in a single-UAV uplink with one transmit antenna and multiple BS receive antennas. A three-dimensional Laplace mechanism protects reports; maximum a posteriori (MAP) inference determines a location-aided receive beam, which is evaluated on the true channel. A separate Markovian task source connects link outcomes to AoII. We protect the report interface and assume the controller has no independent precise radio-frequency (RF) localization. The challenge is to quantify the coupled effects of privacy, inference, directional gain, outage, and source evolution. The contributions are:

- A model connecting three-dimensional report privacy and Bayesian inference to receive-beam decisions and actual transmission outage.
- An analysis that specializes established binary-source AoII models to location-dependent outages, capturing the occurrence and persistence of incorrect task estimates.
- Location-Aware Privacy–Information Selection (LAPIS), a finite-grid procedure combining established concentration bounds with independent confirmation under privacy or AoII requirements.

Experiments using measured channel state information (CSI) and geometric controls quantify the tradeoff. At one tested




Fig. 1. Location-private UAV uplink. A perturbed report drives inference and receive-beam selection. The green ellipse represents a receive beam directed toward the inferred location (orange target), while the task packet traverses the channel at the true location.

budget, MAP lookup yields an estimated 15.8% lower AoII. With 200 selection samples per scenario and budget, point-estimate selection violates the AoII constraint in 65.7% of 1,000 trials, versus no observed violations for LAPIS, which selects larger disclosure budgets (Section V).

II. System Model

A. Network and Update Protocol

In Fig. 1, a single-antenna UAV communicates with a BS at $\mathbf{b} \in \mathbb{R}^3$ using an $M_x \times M_y$ uniform planar array (UPA), $M = M_x M_y$. The UAV hovers at $\mathbf{x} \in \mathcal{X} \subset \mathbb{R}^3 \setminus \{\mathbf{b}\}$ per session; locations define separate scenarios. Power P, array, and packet requirements are fixed across budgets.

Each slot lasts T. At its start, the UAV generates state S_t and a noisy location report. A reliable control path delivers the report before beam configuration and state-packet transmission. The state remains constant within the slot; reception is assessed at its end. Failed packets are discarded. Fixed control overhead leaves data duration τ_d, identically across budgets.

The controller selects beams using reports, the public prior, and a frozen map. Its observations exclude independent precise localization and full instantaneous array CSI. The privacy guarantee covers reports; RF localization requires a separate threat model. Task states are independent of location and channel randomness.

B. Private Location Reporting and Inference

For a fixed budget $\epsilon > 0$, the UAV releases $\mathbf{Z}_t = \mathbf{x} + \mathbf{N}_t$, independently each slot. Following geo-indistinguishability [7], [8], we use the three-dimensional isotropic Laplace density

$$f_\epsilon(\mathbf{z} \mid \mathbf{x}) = \frac{\epsilon^3}{8\pi} \exp(-\epsilon \|\mathbf{z} - \mathbf{x}\|_2). \tag{1}$$

The triangle inequality gives

$$f_\epsilon(\mathbf{z} \mid \mathbf{x}) \le e^{\epsilon \|\mathbf{x} - \mathbf{x}'\|_2} f_\epsilon(\mathbf{z} \mid \mathbf{x}'). \tag{2}$$

Thus $\eta = \epsilon r_0$ is the dimensionless single-report budget within a protection distance r_0; smaller η provides stronger protection. Here ϵ has units m^{-1}. Reports retain their full spatial support. The noise radius satisfies $\|\mathbf{N}_t\|_2 \sim \mathrm{Gamma}(3, 1/\epsilon)$ in shape–scale notation, with mean $3/\epsilon$.

Let $\mathcal{X} = \{\mathbf{x}_j\}_{j=1}^{N_{\mathrm{x}}}$, with $N_{\mathrm{x}} = |\mathcal{X}|$, be a public candidate set with fixed prior probabilities $\pi_j > 0$, $\sum_j \pi_j = 1$. A report $\mathbf{z}_t$ yields posterior

$$\rho_t(j) = \frac{\pi_j e^{-\epsilon \|\mathbf{z}_t - \mathbf{x}_j\|_2}}{\sum_{k=1}^{N_{\mathrm{x}}} \pi_k e^{-\epsilon \|\mathbf{z}_t - \mathbf{x}_k\|_2}}, \quad \widehat{\mathbf{x}}_t = \mathbf{x}_{\arg\max_j \rho_t(j)}. \tag{3}$$

Ties use a fixed rule. The prior and candidate set are public and fixed before reporting. The prescribed receiver applies current-report MAP; optimal attacks, AoII-optimal beam selection, and temporal filtering remain outside the scope. Post-processing preserves (2). For K retained reports, the likelihood ratio is bounded by $e^{K\epsilon\|\mathbf{x}-\mathbf{x}'\|_2}$, which quantifies the cumulative privacy loss across the session.

C. Location-Aided Receive Beamforming

We adapt location-to-beam mapping [3] to uplink combining. For wavelength λ_c and array-relative element locations $\mathbf{r}_m$, the far-field narrowband steering vector for $\mathbf{v} \neq \mathbf{b}$ is

$$\mathbf{u}(\mathbf{v}) = \frac{\mathbf{v} - \mathbf{b}}{\|\mathbf{v} - \mathbf{b}\|_2}, \qquad [\mathbf{a}(\mathbf{v})]_m = e^{\mathrm{j}(2\pi/\lambda_c)\mathbf{r}_m^{\mathsf{T}}\mathbf{u}(\mathbf{v})}. \tag{4}$$

For a UPA, $\mathbf{r}_{m_x,m_y} = (m_x d_x, m_y d_y, 0)^{\mathsf{T}}$, where $0 \le m_x < M_x$ and $0 \le m_y < M_y$, and all coordinates share the array frame. Hence $\|\mathbf{a}(\mathbf{v})\|_2^2 = M$. A Rician baseline is

$$\mathbf{h}_t(\mathbf{x}) = \sqrt{\beta(\mathbf{x})} \left(\sqrt{\frac{\kappa}{\kappa+1}} \mathbf{a}(\mathbf{x}) + \sqrt{\frac{1}{\kappa+1}} \mathbf{g}_t \right), \tag{5}$$

where $\mathbf{g}_t \sim \mathcal{CN}(\mathbf{0}, \mathbf{I}_M)$ is independent and identically distributed (i.i.d.) across slots and independent of report noise, κ is the linear Rician factor, and $\beta(\mathbf{x}) = \beta_0 (\|\mathbf{x} - \mathbf{b}\|_2 / d_0)^{-\nu}$ is the single-element large-scale power gain, with $\beta_0, d_0 > 0$ and $\nu > 0$. The line-of-sight (LOS) limit is obtained as $\kappa \to \infty$.

Given a frozen map output $\boldsymbol{\psi}(\mathbf{v}) \in \mathbb{C}^M \setminus \{\mathbf{0}\}$, the receive beam is

$$\mathbf{w}_t = \mathcal{W}(\widehat{\mathbf{x}}_t) = \frac{\boldsymbol{\psi}(\widehat{\mathbf{x}}_t)}{\|\boldsymbol{\psi}(\widehat{\mathbf{x}}_t)\|_2}, \qquad \|\mathbf{w}_t\|_2 = 1. \tag{6}$$

The geometric model uses $\boldsymbol{\psi}(\mathbf{v}) = \mathbf{a}(\mathbf{v})$; the empirical map uses a covariance eigenvector (Section V). Channel predictions with spatial phase information also support (6). A fixed unit beam handles zero outputs. The digital beam map permits general complex weights and remains fixed during budget optimization.

For unit-energy data symbol s_t and receiver noise $\mathbf{n}_t^{\mathrm{RF}} \sim \mathcal{CN}(\mathbf{0}, \sigma^2\mathbf{I}_M)$, independent of other randomness, the received signal and combined signal-to-noise ratio (SNR) are

$$\begin{aligned} \mathbf{y}_t &= \sqrt{P}\mathbf{h}_t(\mathbf{x})s_t + \mathbf{n}_t^{\mathrm{RF}}, \\ \Gamma_t &= \frac{P|\mathbf{w}_t^{\mathsf{H}}\mathbf{h}_t(\mathbf{x})|^2}{\sigma^2}. \end{aligned} \tag{7}$$

Unit-norm combining leaves noise power σ^2. In pure LOS with the geometry-based rule, the mismatch factor and resulting SNR are

$$\begin{aligned} B_t &= \frac{|\mathbf{a}(\widehat{\mathbf{x}}_t)^{\mathsf{H}}\mathbf{a}(\mathbf{x})|^2}{M^2} \in [0,1], \\ \Gamma_t &= \Gamma_{\mathrm{al}} B_t, \qquad \Gamma_{\mathrm{al}} = P\beta(\mathbf{x})M/\sigma^2. \end{aligned} \tag{8}$$

D. Outage and Task-Information Correctness

With fixed packet length L bits and bandwidth W, we use the ideal coding threshold $\gamma_{\mathrm{th}} = 2^{L/(W\tau_d)} - 1 > 0$. Define

$$Y_t = \mathbf{1}\{\Gamma_t \geq \gamma_{\mathrm{th}}\}, \qquad p_\epsilon(\mathbf{x}) = \Pr(Y_t = 1 \mid \mathbf{x}, \epsilon), \tag{9}$$

and $q_\epsilon(\mathbf{x}) = 1 - p_\epsilon(\mathbf{x})$. Outcomes are i.i.d. conditional on a session location, averaging over report noise and fading. In pure LOS, $p_\epsilon(\mathbf{x}) = \Pr\{B_t \geq \gamma_{\mathrm{th}}/\Gamma_{\mathrm{al}}\}$. At $\kappa = 0$, isotropic scattering makes an independent unit-norm projection direction-invariant, eliminating this directional privacy cost.

Following binary-source AoII models [12], [13], let $S_t \in \{0,1\}$ be a symmetric Markov chain with $\Pr(S_t = 1 - s \mid S_{t-1} = s) = \alpha$ for $s \in \{0,1\}$ and $0 < \alpha \leq 1/2$. Successful packets are decoded correctly; only threshold outage is modeled. At slot end,

$$\widehat{S}_t = \begin{cases} S_t, & Y_t = 1, \\ \widehat{S}_{t-1}, & Y_t = 0. \end{cases} \tag{10}$$

The linear AoII is $\Delta_t^{\mathrm{II}} = TA_t$, where

$$A_t = \begin{cases} 0, & S_t = \widehat{S}_t, \\ A_{t-1} + 1, & S_t \neq \widehat{S}_t. \end{cases} \tag{11}$$

Source reversal can restore correctness between successful receptions; this event resets the slot-end AoII.

III. Problem Formulation

A. From Outage to Average AoII

Specializing the binary-source framework of [12], [13] to our slot-end update convention, write $q = q_\epsilon(\mathbf{x})$. Since transmission outcomes are independent of the task source and past slots, (10)–(11) imply

$$\begin{aligned} \Pr(A_t = 1 \mid A_{t-1} = 0) &= \alpha q \triangleq \mu_0, \\ \Pr(A_t = a+1 \mid A_{t-1} = a) &= (1-\alpha)q \triangleq \mu_1, \quad a \geq 1. \end{aligned} \tag{12}$$

All other transitions return to zero. The stationary probabilities are $\xi_0 = (1-\mu_1)/(1-\mu_1+\mu_0)$ and $\xi_a = \xi_0\mu_0\mu_1^{a-1}$ for $a \geq 1$. Therefore,

$$\begin{aligned} \overline{\Delta}_\epsilon^{\mathrm{II}}(\mathbf{x}) &\triangleq \lim_{N\to\infty} \frac{1}{N}\mathbb{E}\left[\sum_{t=1}^{N} TA_t \mid \mathbf{x}\right] \\ &= T\frac{\alpha q_\epsilon(\mathbf{x})}{[1-(1-\alpha)q_\epsilon(\mathbf{x})]\,[1-(1-2\alpha)q_\epsilon(\mathbf{x})]}. \end{aligned} \tag{13}$$

For $0 < \alpha \leq 1/2$, (13) increases with q, and perfect transmission yields zero slot-end AoII. Monotonicity in ϵ additionally depends on inference and beam selection.

B. Fixed Privacy-Budget Selection

Let $\mathcal{E} \subset (0,\infty)$ be a finite set of candidate budgets, fixed before testing. To select a common budget for a public distribution of hovering scenarios, specify weights $\omega_j \geq 0$, $\sum_j \omega_j = 1$, independently of the private test location, and define

$$J(\epsilon) = \sum_{j=1}^{N_{\mathrm{x}}} \omega_j \overline{\Delta}_\epsilon^{\mathrm{II}}(\mathbf{x}_j). \tag{14}$$

Weights aggregate separate hovering sessions; the MAP prior governs inference within each session. AoII must be averaged after conditioning on location; applying (13) to average outage generally differs.

Given a maximum single-report budget $\eta_{\max}$ at distance r_0, the primary problem is

$$\begin{aligned} (\mathrm{P1}) \quad \min_{\epsilon\in\mathcal{E}} \quad & J(\epsilon) \\ \text{subject to} \quad & \epsilon r_0 \leq \eta_{\max}. \end{aligned} \tag{15}$$

Algorithm 1 selects ϵ offline for the entire session. Repeated reports accumulate privacy loss across the session. For a finite session of K reports with total budget B_{priv} under the repeated-location model, replace the constraint by $K\epsilon r_0 \leq B_{\mathrm{priv}}$. The selected budget remains fixed throughout the session.

An alternative design perspective prioritizes the strongest report protection compatible with an AoII requirement $D_{\max}$:

$$(\mathrm{P2}) \quad \min_{\epsilon\in\mathcal{E}} \ \epsilon r_0 \quad \text{subject to} \quad J(\epsilon) \leq D_{\max}. \tag{16}$$

Figure 2 evaluates the mechanism and AoII mapping. Problems (P1) and (P2) specify alternative requirements. If conditional outages decrease with ϵ, the largest feasible budget solves (P1); no interior optimum is required. Otherwise, candidates are compared under identical link/source conditions, and the selected budget is independently confirmed.

IV. LAPIS: Location-Aware Privacy–Information Selection

Algorithm 1 evaluates a finite grid and selects one fixed reporting budget. The grid, scenarios, prior, beam map, sample counts, and confidence levels are fixed before evaluation; no monotonic outage or convex objective is assumed.




Fig. 2. Empirical-channel privacy cost and analytical validation. Solid MAP curves in (a) use analytical integration; markers and dashed direct-report curves use Monte Carlo (MC). In (c), lines are analytical and markers are direct task-state simulations with nominal pointwise 95% batch-mean intervals for 36 controlled settings.

Algorithm 1 LAPIS: Fixed Privacy-Budget Selection

Require: Public scenarios, prior/weights, grid $\mathcal{E}$, mode and constraint; $N_s, N_c, \delta_s, \delta_c$.
Ensure: Fixed $\epsilon^\star$, confirmation interval/status, and (P1) gap G; or no candidate.
Set $\mathcal{C} = \mathcal{E}$; for (P1), retain $\epsilon r_0 \le \eta_{\max}$.
If $\mathcal{C} = \varnothing$, **return** grid-infeasible.
Draw i.i.d. report-noise seeds and true-channel samples; reuse across budgets.
for each $\epsilon \in \mathcal{C}$ **do**
  Generate reports; apply MAP and the frozen beam map.
  Evaluate true-channel outages via (9); estimate $\widehat{q}_{\epsilon j}$ for each scenario by (17).
  Compute $[L_\epsilon, U_\epsilon]$ via (18)–(19).
end for
if mode is (P1) **then**
  Select $\epsilon^\star$ and compute G by (20); ties favor smaller budgets.
else
  Set $\mathcal{F}_D = \{\epsilon \in \mathcal{C} : U_\epsilon \le D_{\max}\}$.
  If $\mathcal{F}_D = \varnothing$, **return** infeasible when $\min L_\epsilon > D_{\max}$, otherwise unconfirmed; else set $\epsilon^\star = \min \mathcal{F}_D$.
end if
Freeze $\epsilon^\star$; evaluate with N_c new samples per scenario and radius d_c to obtain $[L_c, U_c]$.
return budget, interval, (P1) privacy status and G, or (P2) confirmation iff $U_c \le D_{\max}$; retain the selected budget.

A. Paired Outage Evaluation

For each scenario j and sample ℓ, draw $R_{j\ell} \sim \mathrm{Gamma}(3,1)$, a uniform unit-sphere direction $\mathbf{U}_{j\ell}$, and independent true-channel samples from (5) or the frozen empirical CSI bank. Reuse these draws across budgets, setting

$$\mathbf{z}_{j\ell}(\epsilon) = \mathbf{x}_j + \frac{R_{j\ell}}{\epsilon}\mathbf{U}_{j\ell},$$
$$\widehat{q}_{\epsilon j} = \frac{1}{N_s}\sum_{\ell=1}^{N_s}(1 - Y_{j\ell}(\epsilon)). \tag{17}$$

Each $Y_{j\ell}(\epsilon)$ is computed through (3)–(9) on the same true channel realization. This coupling preserves the marginal distributions and independence across ℓ. Let $F_\alpha(q)$ denote the right-hand side of (13). The plug-in estimate is $\widehat{J}(\epsilon) = \sum_j \omega_j F_\alpha(\widehat{q}_{\epsilon j})$.

To account for finite-sample uncertainty, Hoeffding's inequality [15] and a union bound over $N_{\mathrm{x}}|\mathcal{E}|$ pairs give the simultaneous radius

$$d_s = \sqrt{\frac{\log(2N_{\mathrm{x}}|\mathcal{E}|/\delta_s)}{2N_s}}, \tag{18}$$
$$q^-_{\epsilon j} = [\widehat{q}_{\epsilon j} - d_s]_+, \quad q^+_{\epsilon j} = \min\{1, \widehat{q}_{\epsilon j} + d_s\},$$

where $[a]_+ = \max\{0, a\}$ and $\delta_s \in (0,1)$. Since F_α is increasing, with probability at least $1 - \delta_s$, every candidate satisfies

$$L_\epsilon = \sum_j \omega_j F_\alpha(q^-_{\epsilon j}), \quad U_\epsilon = \sum_j \omega_j F_\alpha(q^+_{\epsilon j}), \tag{19}$$
$$L_\epsilon \le J(\epsilon) \le U_\epsilon.$$

These bounds quantify Monte Carlo error conditional on the prescribed map and channel model. Model mismatch requires a separate assessment.

B. Selection and Independent Confirmation

For (P1), form $\mathcal{F}_\eta = \{\epsilon \in \mathcal{E} : \epsilon r_0 \le \eta_{\max}\}$ and choose

$$\epsilon^\star \in \arg\min_{\epsilon \in \mathcal{F}_\eta} U_\epsilon,$$
$$G = U_{\epsilon^\star} - \min_{\epsilon \in \mathcal{F}_\eta} L_\epsilon. \tag{20}$$

On the simultaneous-coverage event, $J(\epsilon^\star) - \min_{\epsilon \in \mathcal{F}_\eta} J(\epsilon) \le G$; G bounds unresolved grid suboptimality.

For (P2), choose the smallest ϵ satisfying $U_\epsilon \le D_{\max}$. If none qualifies, $\min_\epsilon L_\epsilon > D_{\max}$ indicates grid infeasibility on the coverage event; otherwise feasibility is unconfirmed. An interval straddling the threshold leaves grid optimality unresolved.

Freeze the budget and use N_c independent samples per scenario, replacing d_s in (18)–(19) by $d_c = \sqrt{\log(2N_{\mathrm{x}}/\delta_c)/(2N_c)}$. For (P2), confirm feasibility only if the new upper endpoint is at most $D_{\max}$; otherwise report unconfirmed and retain the selected budget. The union-bound coverage for selection and confirmation is at least $1 - \delta_s - \delta_c$. For the geometry-based beam rule and brute-force MAP, selection costs $O(|\mathcal{E}|N_{\mathrm{x}}N_s(N_{\mathrm{x}} + M))$, followed by one-candidate

TABLE I
SIMULATION AND EMPIRICAL-CHANNEL SETTINGS

Parameter	Value
Privacy distance / budget grid	$r_0 = 10$ m; 61 log-spaced $\eta \in [0.1, 10]$
Default task / threshold	$\alpha = 0.1$; $\gamma_{\mathrm{th}} = 1$; AoII in units of T
Empirical receiver / map cells	64 channels at 2.610 GHz; 10-m cells; 2-m guard
Empirical scenarios / weights	Three cell centers; uniform prior and weights
Configured empirical SNR scale	10 dB at median training channel energy
Mechanism Monte Carlo samples	3×10^5 per scenario and budget
Selection samples (main / sweep)	2×10^4 / 13 sizes, 200–20000
Confirmation samples	$N_c = 10^5$
Confidence / macro repetitions	$\delta_s = \delta_c = 0.025$; 1,000 repetitions
Geometric array control	$M = 1, 16, 64, 256$; $d_x = d_y = \lambda_c/2$
Geometric channel / scenarios	$\kappa = 10$, $\nu = 2$; 75 hovering locations
Geometric report samples	3×10^4 per location and budget

confirmation. Figures 3 and 4 examine array sensitivity and selection reliability.

V. NUMERICAL RESULTS

A. Experimental Setup

Table I gives the settings. One 50-s recording from the MaMIMO-UAV dataset [16] yields 500 location–CSI pairs at 100-ms intervals on one subcarrier. Coverage is 34×43 m horizontally, at takeoff-relative heights 25–27.5 m. A 70/30 split of 10-m cells (seed 20261027), with a 2-m guard, retains 287 training and 102 test snapshots and discards 111. Seven covariance eigenvectors form the frozen nearest-cell beam map. Empirical SNR is $10|\mathbf{w}^{\mathsf{H}}\mathbf{h}|^2/\operatorname{median}_{i\in\mathcal{T}} \|\mathbf{h}_i\|_2^2$, where $\mathcal{T}$ contains training snapshots. This configured SNR scale is uncalibrated. Ages and intervals are normalized by T, unrelated to measurement spacing.

Three occupied held-out cell centers define the public scenarios before reporting, with 7, 17, and 78 CSI snapshots. Snapshots are independently resampled within cells; scenario weights are equal. The representative centers are the protected locations in this experiment. Collinearity and equal priors permit exact MAP integration. The resulting evaluation is conditional on this data-derived grid. Bounds quantify simulation randomness; measurement representativeness, Global Positioning System (GPS) error, and map mismatch require separate validation.

B. Privacy Mechanism and AoII Validation

Figure 2 traces report privacy through the frozen beam map. Increasing η from 0.1 to 10 reduces mean outage from 0.4321 to 0.0571 and normalized AoII from 0.1131 to 0.0072. At $\eta = 1$, MAP achieves normalized AoII 0.0446 versus 0.0530 for direct-report map lookup, an estimated 15.8% reduction. Simultaneous 95% Monte Carlo bounds for the direct baseline give a relative-reduction interval of [13.9%, 17.6%]. At $\eta = 0.1$, direct lookup has lower mean outage but higher mean AoII than MAP. This reflects heterogeneous outages and nonlinear scenario-wise AoII. For 36 controlled source–link settings, 5×10^6 simulated slots per setting give maximum relative deviation 0.78%; nine additional empirical-marginal settings give 1.33%. These tests validate the i.i.d. source–link mapping within the conditional model.

C. Array Size and Directional Sensitivity

Figure 3 uses the geometric model in (5) to isolate aperture effects. Candidate coordinates are $x, y \in \{-100, -50, 0, 50, 100\}$ m and $z \in \{80, 120, 160\}$ m; conditional Rician outage is integrated analytically. At fixed power and $\eta = 0.1$, AoII rises from 0.821 for $M = 16$ to 2.378 for $M = 256$, despite the larger aligned gain. At equal reference aligned-SNR scale, the corresponding values are 0.326 and 3.152. These settings expose the sensitivity of larger arrays to privacy-induced angular error. The $M = 1$ curve is budget-independent, as expected. An additional analytical Rayleigh control gives direction-independent outage.

D. Budget Selection and Reliability

For (P1), LAPIS selects the largest feasible grid point for all four tested caps $\eta_{\max} \in \{0.3, 1, 3, 10\}$, matching the exact grid reference. These are boundary optima. For (P2) with $D_{\max}/T = 0.05$, it selects $\eta = 1$ and independently confirms normalized AoII in $[0.0431, 0.0459]$. At the tighter requirement 0.03, it selects $\eta = 1.848$, whereas the smallest feasible budget under the exact conditional reference is 1.585: finite-sample certification costs additional disclosure.

Figure 4 quantifies this tradeoff for $D_{\max}/T = 0.05$. With $N_s = 200$, point-estimate selection violates the exact empirical-model AoII requirement in 657 of 1,000 runs (65.7%), versus zero observed violations for LAPIS. The two-sided 95% binomial upper endpoint for LAPIS is 0.368%; this endpoint quantifies the remaining statistical uncertainty. LAPIS selects mean budget 2.76 versus 0.85 for the comparator at this sample size; both move toward the conditional-model feasibility boundary as samples increase. All LAPIS candidates in this reliability experiment pass independent confirmation. Independent Bernoulli counts simulate reliability and confirmation; selection uses sampled estimates. At $\eta = 0.858$, AoII is 0.05031, just above the threshold, explaining persistent finite-sample misclassification on the denser grid. Broader measurements are needed for generalization.

VI. CONCLUSION

Location privacy can degrade receive-beam decisions and increase persistent task-information errors. The empirical and geometric experiments quantify this mechanism and its dependence on array size. LAPIS translates privacy or AoII requirements into fixed reporting budgets with explicit simulation uncertainty. Reliable selection in this conditional model requires additional disclosure at small sample sizes.




Fig. 3. Geometric Rician array controls. Fixed power uses reference single-element SNR -5 dB at 150 m. The second control fixes reference LOS aligned-SNR scale at 13.06 dB, adjusting power as $1/M$.




Fig. 4. Conditional empirical-model selection. Reliability uses equivalent Bernoulli links, independent budget streams, and 1,000 repetitions at each of 13 sample sizes. Both methods use identical selection samples and grids. Panel (b) reports selections that violate the exact-model constraint; panel (c) shows their disclosure cost.

References

[1] Z. Wang, Z. Zhou, C.-J. Zhao, and Y. Liu, "Generative site-specific beamforming for next-generation spatial intelligence," 2026, arXiv:2601.02301.

[2] Y. Jiang, X. Li, G. Zhu, H. Li, J. Deng, K. Han, C. Shen, Q. Shi, and R. Zhang, "6G non-terrestrial networks enabled low-altitude economy: Opportunities and challenges," arXiv:2311.09047, 2023, updated 2024.

[3] L. Le Magoarou, T. Yassine, S. Paquelet, and M. Crussière, "Deep learning for location based beamforming with NLOS channels," in *Proc. IEEE ICASSP*, 2022, pp. 8812–8816, doi: 10.1109/ICASSP43922.2022.9747293.

[4] X. Zhao, Z. An, Q. Pan, and L. Yang, "NeRF^2: Neural radio-frequency radiance fields," in *Proc. ACM MobiCom*, 2023, pp. 1–15, doi: 10.1145/3570361.3592527.

[5] C. Wen, J. Tong, Y. Hu, Z. Lin, and J. Zhang, "WRF-GS: Wireless radiation field reconstruction with 3D Gaussian splatting," in *Proc. IEEE INFOCOM*, 2025, pp. 1–10, doi: 10.1109/INFOCOM55648.2025.11044513.

[6] C. Wen, J. Tong, Y. Hu, Z. Lin, and J. Zhang, "Neural representation for wireless radiation field reconstruction: A 3D Gaussian splatting approach," *IEEE Trans. Wireless Commun.*, vol. 25, pp. 7490–7504, 2026, doi: 10.1109/TWC.2025.3631663.

[7] M. E. Andrés, N. E. Bordenabe, K. Chatzikokolakis, and C. Palamidessi, "Geo-indistinguishability: Differential privacy for location-based systems," in *Proc. ACM CCS*, 2013, pp. 901–914, doi: 10.1145/2508859.2516735.

[8] M. Min, L. Xiao, J. Ding, H. Zhang, S. Li, M. Pan, and Z. Han, "3D geo-indistinguishability for indoor location-based services," *IEEE Trans. Wireless Commun.*, vol. 21, no. 7, pp. 4682–4694, 2022, doi: 10.1109/TWC.2021.3132464.

[9] J. J. Checa and S. Tomasin, "Location-privacy-preserving technique for 5G mmWave devices," *IEEE Commun. Lett.*, vol. 24, no. 12, pp. 2692–2695, 2020, doi: 10.1109/LCOMM.2020.3018165.

[10] R. Jin, X. He, and H. Dai, "Minimizing the age of information in the presence of location privacy-aware mobile agents," *IEEE Trans. Commun.*, vol. 69, no. 2, pp. 1053–1067, 2021, doi: 10.1109/TCOMM.2020.3035394.

[11] J. Tian, W. Chen, J. Chen, and P.-Y. Kam, "Geometry-aligned differential privacy for location-safe federated radio map construction," 2025, arXiv:2512.08263.

[12] A. Maatouk, S. Kriouile, M. Assaad, and A. Ephremides, "The age of incorrect information: A new performance metric for status updates," *IEEE/ACM Trans. Netw.*, vol. 28, no. 5, pp. 2215–2228, 2020, doi: 10.1109/TNET.2020.3005549.

[13] Y. Chen and A. Ephremides, "Scheduling to minimize age of incorrect information with imperfect channel state information," *Entropy*, vol. 23, no. 12, Art. no. 1572, 2021, doi: 10.3390/e23121572.

[14] J. Chen, J. Wang, X. Zhang, L. Bai, T. Q. S. Quek, and M. Debbah, "Trustworthiness in the air: Age of incorrect information oriented 6G low-altitude networks," *IEEE Netw.*, vol. 39, no. 6, pp. 164–172, 2025, doi: 10.1109/MNET.2025.3561054.

[15] W. Hoeffding, "Probability inequalities for sums of bounded random variables," *J. Amer. Statist. Assoc.*, vol. 58, no. 301, pp. 13–30, 1963, doi: 10.1080/01621459.1963.10500830.

[16] A. Colpaert, C. Thys, Z. Cui, and S. Pollin, "MaMIMO-UAV 3D Channel State Information Dataset," KU Leuven RDR, 2023, ver. 3.0, dataset, doi: 10.48804/0IMQDF.