

if Statement in C

Theory:

The 'if' statement executes a block of code only if a specified condition is true.

Syntax:

```
if(condition) {  
    // code to execute if condition is true  
}
```

Example:

```
int a = 10;  
if(a > 5) {  
    printf("a is greater than 5");  
}  
  
#CProgramming #IfCondition #CodeSmartly
```

else if Ladder in C

Theory:

Used when multiple conditions need to be checked in sequence. Executes the first true condition.

Syntax:

```
if(condition1) {  
    // code  
}  
else if(condition2) {  
    // code  
}  
else {  
    // code  
}
```

Example:

```
int marks = 75;  
if(marks > 90)  
    printf("Excellent");  
else if(marks > 60)  
    printf("Good");
```

else

```
printf("Try Again");
```

#ElselfLadder #LogicBuilding #CCode

switch Statement in C

Theory:

The 'switch' is used to execute one block of code among many based on the value of a variable.

Syntax:

```
switch(expression) {  
    case value1:  
        // code  
        break;  
    case value2:  
        // code  
        break;  
    default:  
        // default code  
}
```

Example:

```
int day = 2;  
switch(day) {  
    case 1: printf("Monday"); break;  
    case 2: printf("Tuesday"); break;  
    default: printf("Other Day");  
}  
#SwitchCase #ControlFlow #CProgramming
```

for Loop in C

Theory:

The 'for' loop is used to repeat a block of code a known number of times.

Syntax:

```
for(initialization; condition; increment) {  
    // code to execute  
}
```

Example:

```
for(int i = 1; i <= 5; i++) {  
    printf("%d ", i);  
}
```

#ForLoop #LoopLogic #LearnToCode