

For the estimation problem $y_k = x + e_k$, where $e_k \sim \mathcal{U}[0, b]$, we want to find the MVU estimator. We first represent the PDF of the data as

$$p(y_k; x, b) = \begin{cases} \frac{1}{b} & x < y_k < x + b \\ 0 & \text{otherwise} \end{cases} \quad (1a)$$

or alternatively

$$p(y_k; x, b) = \frac{1}{b} [\sigma(y_k - x) - \sigma(y_k - (x + b))] \quad (1b)$$

Hence,

$$\begin{aligned} p(\mathbf{y}; x, b) &= \frac{1}{b^N} \prod_{k=1}^N [\sigma(y_k - x) - \sigma(y_k - x - b)] \\ &= \frac{1}{b^N} [\sigma(\min y_k - x) - \sigma(\max y_k - x - b)] \end{aligned} \quad (1c)$$

Since we cannot approach the problem of finding MVU using CRLB, I use the Rao-Blackwell-Lehmann-Scheffe theorem. The theorem gives that for any unbiased estimator $\tilde{\theta}$ and sufficient statistics $\mathbf{T}(\mathbf{y})$, $\hat{\theta} = E(\tilde{\theta} | \mathbf{T}(\mathbf{y}))$ is unbiased and $\text{Var}(\hat{\theta}) \leq \text{Var}(\tilde{\theta})$. Additionally, if $\mathbf{T}(\mathbf{y})$ is complete, then $\hat{\theta}$ is MVU.

It is also shown in [1] that if the dimension of the sufficient statistics is equal to the dimension of the parameter, then the MVU estimator is given by $\hat{\theta} = g(\mathbf{T}(\mathbf{y}))$ for any function $g(\cdot)$ that satisfy

$$E(g(\mathbf{T})) = \theta \quad (2)$$

Hence, if we can find the sufficient statistics, and if we can show that it is complete, then we can find the MVU estimator. For that, we can use the Neyman-Fisher theorem that gives the sufficient statistic $\mathbf{T}(\mathbf{y})$ if we can factorize the PDF as

$$p(\mathbf{y}; \theta) = g(\mathbf{T}(\mathbf{y}), \theta) h(\mathbf{y}) \quad (3)$$

In our problem, from (1c) for $\theta = [x, b]^T$ we can say $h(\mathbf{y}) = 1$ and

$$\mathbf{T}(\mathbf{y}) = \begin{bmatrix} \min y \\ \max y \end{bmatrix} = \begin{bmatrix} T_1(\mathbf{y}) \\ T_2(\mathbf{y}) \end{bmatrix} \quad (4a)$$

and

$$E(\mathbf{T}(\mathbf{y})) = \begin{bmatrix} x + \frac{b}{N+1} \\ x + \frac{Nb}{N+1} \end{bmatrix} \quad (4b)$$

Then, any function $g(\cdot)$ that makes (4) unbiased would be MVU.

1 Known b

At this point, I am not sure if the same line of reasoning holds. Since now, b is not a parameter anymore. However, if it holds, since we know b , we can say that both

$$\hat{x}_{min} = \min y - \frac{b}{N+1} \quad (5)$$

$$\hat{x}_{max} = \max y - \frac{Nb}{N+1} \quad (6)$$

are MVU estimators. In other words, the MVU estimator is not unique.

2 Unknown b

This case fits better to the theorem. Since we are only interested in x , I try to make a function that makes T_1 unbiased. Let

$$g(\mathbf{T}(\mathbf{y})) = \begin{bmatrix} T_1 - \frac{1}{N} T_2 \\ T_2 \end{bmatrix} \quad (7a)$$

this gives

$$\mathbb{E}(\mathbf{g}(\mathbf{T}(\mathbf{y}))) = \begin{bmatrix} \frac{N-1}{N}x \\ \times \end{bmatrix} \quad (7b)$$

Hence, an unbiased estimate of x would be given by multiplying first row by $\frac{N}{N-1}$

$$\begin{aligned} \hat{x}_{MVU} &= \frac{N}{N-1} \left(T_1 - \frac{1}{N} T_2 \right) = \frac{N}{N-1} T_1 - \frac{1}{N-1} T_2 \\ &= \frac{N}{N-1} \min y_k - \frac{1}{N-1} \max y_k \end{aligned} \quad (7c)$$

References

- [1] S. M. Kay. *Fundamentals of Statistical Signal Processing: Estimation Theory*. Prentice-Hall, Inc., Upper Saddle River, NJ, USA, 1993.