| pojedynczy pakiet danych : | | | | | | | | | | | | | z transmitera Enlite z sensorem | | | |
|----------------------------|--------|--|---|---|---|---|---|---|---|---|--|---------------|---------------------------------|--|--|--|
| RAW | | | | | | | | | | | | DECODED (hex) | | | | |
| A B | 8 | | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0 | | АВ | | tryb działania transmitera, AB- praca normalna, AA- rozruch | | |
| 5 | C | | 0 | 1 | 0 | 1 | 1 | 1 | 0 | 0 | | 0 F | | stała flaga 0x0F | | |
| 6 | 9 | | 0 | 1 | 1 | 0 | 1 | 0 | 0 | 0 | | 2 | | - | | |
| 8 C | B | | 1 | 0 | 0 | 0 | 1 | 0 | 1 | 1 | | 6 | | numer transmiters | | |
| С | 5 | | 1 | 1 | 0 | 0 | 0 | 1 | 0 | 1 | | В | | numer transmitera hex 26 6B 2C = dec 2517804 | | |
| 5 | D 4 | | 0 | 1 | 0 | 0 | 1 | 1 | 0 | 1 | | 2 C | | | | |
| Е | С | | 1 | 1 | 1 | 0 | 1 | 1 | 0 | 0 | | 0 | | firmware 1.3 | | |
| 4 | 5 5 | | 1 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | | D 0 | | illinware 1.5 | | |
| 5 | 5 | | 0 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | | Е | | | | |
| 4 C | D 9 | | 1 | 1 | 0 | 0 | 1 | 0 | 0 | 1 | | 1 E | | ISIG adjustment value hex 1E = dec 30 | | |
| 6 | 5 | | 0 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | | 5 | | Sequence number | | |
| 4 D | D 0 | | 1 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | | 0 | | | | |
| D | 5 | | 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | | D | | aktualny pomiar glikemii – wartość RAW | | |
| 5 | 5 6 | | 1 | 0 | 0 | 1 | 0 | 1 | 0 | 0 | | 7 | | hex D27 = dec 3367 | | |
| С | 9 | | 1 | 1 | 0 | 0 | 1 | 0 | 0 | 1 | | 0 | | | | |
| 6 | C | | 0 | 0 | 1 | 0 | 1 | 1 | 0 | 0 | | D 4 | | pomiar sprzed 5 minut – wartość RAW hex D4D = dec 3405 | | |
| D 4 | 5 D | | 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | | D 0 | | | | |
| 8 | С | | 1 | 0 | 0 | 0 | 1 | 1 | 0 | 0 | | 0 | | | | |
| B 4 | 5 D | | 1 | 0 | 1 | 1 | 0 | 1 | 0 | 1 | | 5 C | | | | |
| С | Α | | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0 | | 5 | | | | |
| C 4 | 5 D | | 1 | 1 | 0 | 0 | 0 | 1 | 0 | 1 | | C B | | | | |
| D | 0 | | 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | | D | | poziom baterii hex BD = dec 189 | | |
| <u>E</u> | 5 D | | 0 | 1 | 0 | 0 | 0 | 1 | 0 | 1 | | 0 D | | pomiar sprzed 10 minut – wartość RAW | | |
| D | 0 | | 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | | 3 | | hex D3B = dec 3387 | | |
| D 4 | 5 D | | 1 | 1 | 0 | 0 | 0 | 1 | 0 | 1 | | B 0 | | | | |
| D | 0 | | 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | | D | | pomiar sprzed 15 minut – wartość RAW | | |
| 8 4 | 5 D | | 0 | 1 | 0 | 0 | 0 | 1 | 0 | 1 | | 2 C | | hex D2C = dec 3372 | | |
| D | 2 | | 1 | 1 | 0 | 1 | 0 | 0 | 1 | 0 | | 0 | | | | |
| A 4 | 5 D | | 0 | 1 | 0 | 0 | 1 | 1 | 0 | 1 | | D 4 | | pomiar sprzed 20 minut – wartość RAW hex D4E = dec 3406 | | |
| D A | 1 5 | | 1 | 1 | 0 | 1 | 0 | 0 | 0 | 1 | | E 0 | | | | |
| 5 | 5 | | 0 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | | D | | pomiar sprzed 25 minut – wartość RAW | | |
| СВ | 8 | | 1 | 1 | 0 | 0 | 1 | 0 | 0 | 0 | | 4 D | | hex D4D = dec 3405 | | |
| 9 | 6 | | 1 | 0 | 0 | 1 | 0 | 1 | 1 | 0 | | 0 | | | | |
| | | | | | | | | | | | | D 4 | | pomiar sprzed 30 minut – wartość RAW hex D4B = dec 3403 | | |
| | | | | | | | | | | | | В | | 110X 5 15 GGG 6 100 | | |
| | | | | | | | | | | | | 0 D | | pomiar sprzed 35 minut – wartość RAW | | |
| | | | | | | | | | | | | 4 | | hex D4A = dec 3402 | | |
| | | | | | | | | | | | | A 0 | | | | |
| | | | | | | | | | | | | D | | pomiar sprzed 40 minut – wartość RAW | | |
| | | | | | | | | | | | | 8 | | hex D48 = dec 3400 | | |
| | | | | | | | | | | | | 0 | | | | |
| | | | | | | | | | | | | 2 | | | | |
| | | | | | | | | | | | | В 7 | | CRC-16 | | |
| | | | | | | | | | | | | 7 | | | | |
| | | | | | | | | | | | | | | | | |