

# Assignment 2

Quantumania

June 2024

## 1 Quantum Gates

1. Give a quantum circuit that implements the Toffoli gate with only CNOT and single-qubit gates.

$$\text{Toffoli} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \end{bmatrix}$$

2. Design a quantum circuit that implements the Fredkin gate using three Toffoli gates.

$$\text{Fredkin} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \end{bmatrix}$$

3. Now optimize the circuit obtained in 2nd part to use the least Toffoli and  $\pi/8$  gates.

## 2 Quantum Circuits

1. Code up a quantum circuit to increment a 3 bit register  $abc$  in place.
2. Now make a circuit to add a fixed quantity  $s$  to the three bit register  $abc$  in a separate register  $pqr$ . That is, implement the following Oracle.

$$|x\rangle|y\rangle \rightarrow |x\rangle|f(x) + y \mod 8\rangle \quad \text{where } f(x) = x$$