CELT

0.5.0

Generated by Doxygen 1.5.5

Thu Oct 9 07:19:35 2008

Contents

1 Module Index **1**

1.1 Modules 1

2 Data Structure Index **3**

2.1 Data Structures 3

3 File Index **5**

3.1 File List 5

4 Module Documentation **7**

4.1 Encoding and decoding 7

5 Data Structure Documentation **13**

5.1 CELTHeader Struct Reference 13

6 File Documentation **17**

6.1 libcelt/celt.h File Reference 17

6.2 libcelt/celt_types.h File Reference 21

Chapter 1

Module Index

1.1 Modules

Here is a list of all modules:

Encoding and decoding 7

Chapter 2

Data Structure Index

2.1 Data Structures

Here are the data structures with brief descriptions:

CELTHeader (Header data) 13

Chapter 3

File Index

3.1 File List

Here is a list of all documented files with brief descriptions:

libcelt/celt.h (Contains all the functions for encoding and decoding audio streams) 17
libcelt/**celt_header.h** . . . . . **??**
libcelt/celt_types.h (CELT types) 21

Chapter 4

Module Documentation

4.1 Encoding and decoding

Functions

- EXPORT CELTMode * celt_mode_create (celt_int32_t Fs, int channels, int frame_size, int *error)
- EXPORT void celt_mode_destroy (CELTMode *mode)
- EXPORT int celt_mode_info (const CELTMode *mode, int request, celt_int32_t *value)
- EXPORT CELTEncoder * celt_encoder_create (const CELTMode *mode)
- EXPORT void celt_encoder_destroy (CELTEncoder *st)
- EXPORT int celt_encode_float (CELTEncoder *st, const float *pcm, float *optional_synthesis, unsigned char *compressed, int nbCompressedBytes)
- EXPORT int celt_encode (CELTEncoder *st, const celt_int16_t *pcm, celt_int16_t *optional_synthesis, unsigned char *compressed, int nbCompressedBytes)
- EXPORT int celt_encoder_ctl (CELTEncoder *st, int request,...)
- EXPORT CELTDecoder * celt_decoder_create (const CELTMode *mode)
- EXPORT void celt_decoder_destroy (CELTDecoder *st)
- EXPORT int celt_decode_float (CELTDecoder *st, unsigned char *data, int len, float *pcm)
- EXPORT int celt_decode (CELTDecoder *st, unsigned char *data, int len, celt_int16_t *pcm)

4.1.1 Detailed Description

4.1.2 Function Documentation

4.1.2.1 EXPORT int celt_decode (CELTDecoder * *st*, unsigned char * *data*, int *len*, celt_int16_t * *pcm*)

Decodes a frame of audio.

Parameters:

st Decoder state

data Compressed data produced by an encoder

len Number of bytes to read from "data". This MUST be exactly the number of bytes returned by the encoder. Using a larger value WILL NOT WORK.

pcm One frame (frame_size samples per channel) of decoded PCM will be returned here in 16-bit PCM format (native endian).

Returns:

Error code.

4.1.2.2 EXPORT int celt_decode_float (CELTDecoder * *st*, unsigned char * *data*, int *len*, float * *pcm*)

Decodes a frame of audio.

Parameters:

st Decoder state

data Compressed data produced by an encoder

len Number of bytes to read from "data". This MUST be exactly the number of bytes returned by the encoder. Using a larger value WILL NOT WORK.

pcm One frame (frame_size samples per channel) of decoded PCM will be returned here in float format.

Returns:

Error code.

4.1.2.3 EXPORT CELTDecoder* celt_decoder_create (const CELTMode * *mode*)

Creates a new decoder state. Each stream needs its own decoder state (can't be shared across simultaneous streams).

Parameters:

mode Contains all the information about the characteristics of the stream (must be the same characteristics as used for the encoder)

Returns:

Newly created decoder state.

4.1.2.4 EXPORT void celt_decoder_destroy (CELTDecoder * *st*)

Destroys a a decoder state.

Parameters:

st Decoder state to be destroyed

4.1.2.5 EXPORT int celt_encode (CELTEncoder * *st*, const celt_int16_t * *pcm*, celt_int16_t * *optional_synthesis*, unsigned char * *compressed*, int *nbCompressedBytes*)

Encodes a frame of audio.

Parameters:

st Encoder state

pcm PCM audio in signed 16-bit format (native endian). There must be exactly frame_size samples per channel. The input data is overwritten by a copy of what the remote decoder would decode.

optional_synthesis If not NULL, the encoder copies the audio signal that the decoder would decode. It is the same as calling the decoder on the compressed data, just faster.

compressed The compressed data is written here

nbCompressedBytes Number of bytes to use for compressing the frame (can change from one frame to another)

Returns:

Number of bytes written to "compressed". Should be the same as "nbCompressedBytes" unless the stream is VBR. If negative, an error has occured (see error codes). It is IMPORTANT that the length returned be somehow transmitted to the decoder. Otherwise, no decoding is possible.

4.1.2.6 EXPORT int celt_encode_float (CELTEncoder * *st*, const float * *pcm*, float * *optional_synthesis*, unsigned char * *compressed*, int *nbCompressedBytes*)

Encodes a frame of audio.

Parameters:

st Encoder state

pcm PCM audio in signed float format. There must be exactly frame_size samples per channel. The input data is overwritten by a copy of what the remote decoder would decode.

optional_synthesis If not NULL, the encoder copies the audio signal that the decoder would decode. It is the same as calling the decoder on the compressed data, just faster.

compressed The compressed data is written here

nbCompressedBytes Number of bytes to use for compressing the frame (can change from one frame to another)

Returns:

Number of bytes written to "compressed". Should be the same as "nbCompressedBytes" unless the stream is VBR. If negative, an error has occured (see error codes). It is IMPORTANT that the length returned be somehow transmitted to the decoder. Otherwise, no decoding is possible.

4.1.2.7 EXPORT CELTEncoder* celt_encoder_create (const CELTMode * *mode*)

Creates a new encoder state. Each stream needs its own encoder state (can't be shared across simultaneous streams).

Parameters:

mode Contains all the information about the characteristics of the stream (must be the same characteristics as used for the decoder)

Returns:

Newly created encoder state.

4.1.2.8 EXPORT int celt_encoder_ctl (CELTEncoder * *st*, int *request*, ...)

Query and set encoder parameters

Parameters:

st Encoder state

request Parameter to change or query

value Pointer to a 32-bit int value

Returns:

Error code

4.1.2.9 EXPORT void celt_encoder_destroy (CELTEncoder * *st*)

Destroys a an encoder state.

Parameters:

st Encoder state to be destroyed

4.1.2.10 EXPORT CELTMode* celt_mode_create (celt_int32_t *Fs*, int *channels*, int *frame_size*, int * *error*)

Creates a new mode struct. This will be passed to an encoder or decoder. The mode MUST NOT BE DESTROYED until the encoders and decoders that use it are destroyed as well.

Parameters:

Fs Sampling rate (32000 to 64000 Hz)

channels Number of channels

frame_size Number of samples (per channel) to encode in each packet (64 - 256)

lookahead Extra latency (in samples per channel) in addition to the frame size (between 32 and frame_size). The larger that value, the better the quality (at the expense of latency)

error Returned error code (if NULL, no error will be returned)

Returns:

A newly created mode

4.1.2.11 EXPORT void celt_mode_destroy (CELTMode * *mode*)

Destroys a mode struct. Only call this after all encoders and decoders using this mode are destroyed as well.

Parameters:

mode Mode to be destroyed

4.1.2.12 EXPORT int celt_mode_info (const CELTMode * *mode*, int *request*, celt_int32_t * *value*)

Query information from a mode

Chapter 5

Data Structure Documentation

5.1 CELTHeader Struct Reference

Header data.

`#include <celt_header.h>`

Data Fields

- char codec_id [8]
- char codec_version [20]
- celt_int32_t version_id
- celt_int32_t header_size
- celt_int32_t sample_rate
- celt_int32_t nb_channels
- celt_int32_t frame_size
- celt_int32_t overlap
- celt_int32_t bytes_per_packet
- celt_int32_t extra_headers

5.1.1 Detailed Description

Header data.

Header data to be used for Ogg files (or possibly other encapsulation)

Definition at line 45 of file celt_header.h.

5.1.2 Field Documentation

5.1.2.1 char CELTHeader::codec_id[8]

MUST be "CELT " (four spaces)

Definition at line 46 of file celt_header.h.

5.1.2.2 char CELTHeader::codec_version[20]

Version used (as string)

Definition at line 47 of file celt_header.h.

5.1.2.3 celt_int32_t CELTHeader::version_id

Version id (negative for until stream is frozen)

Definition at line 48 of file celt_header.h.

5.1.2.4 celt_int32_t CELTHeader::header_size

Size of this header

Definition at line 49 of file celt_header.h.

5.1.2.5 celt_int32_t CELTHeader::sample_rate

Sampling rate of the original audio

Definition at line 50 of file celt_header.h.

5.1.2.6 celt_int32_t CELTHeader::nb_channels

Number of channels

Definition at line 51 of file celt_header.h.

5.1.2.7 celt_int32_t CELTHeader::frame_size

Samples per frame (per channel)

Definition at line 52 of file celt_header.h.

5.1.2.8 celt_int32_t CELTHeader::overlap

Overlapping samples (per channel)

Definition at line 53 of file celt_header.h.

5.1.2.9 celt_int32_t CELTHeader::bytes_per_packet

Number of bytes per compressed packet (0 if unknown)

Definition at line 54 of file celt_header.h.

5.1.2.10 celt_int32_t CELTHeader::extra_headers

Number of additional headers that follow this header

Definition at line 55 of file celt_header.h.

The documentation for this struct was generated from the following file:

- libcelt/celt_header.h

Chapter 6

File Documentation

6.1 libcelt/celt.h File Reference

Contains all the functions for encoding and decoding audio streams.

```
#include "celt_types.h"
```

Defines

- #define CELT_OK 0
- #define CELT_BAD_ARG -1
- #define CELT_INVALID_MODE -2
- #define CELT_INTERNAL_ERROR -3
- #define CELT_CORRUPTED_DATA -4
- #define CELT_UNIMPLEMENTED -5
- #define CELT_SET_COMPLEXITY(x) CELT_SET_COMPLEXITY_REQUEST, _celt_check_int(x)
- #define CELT_GET_FRAME_SIZE 1000
- #define CELT_GET_LOOKAHEAD 1001
- #define CELT_GET_NB_CHANNELS 1002
- #define CELT_GET_BITSTREAM_VERSION 2000

Typedefs

- typedef struct CELTEncoder CELTEncoder

  Encoder state.

- typedef struct CELTDecoder CELTDecoder
- typedef struct CELTMode CELTMode

Functions

- EXPORT CELTMode * celt_mode_create (celt_int32_t Fs, int channels, int frame_size, int *error)
- EXPORT void celt_mode_destroy (CELTMode *mode)
- EXPORT int celt_mode_info (const CELTMode *mode, int request, celt_int32_t *value)

- EXPORT CELTEncoder * celt_encoder_create (const CELTMode *mode)
- EXPORT void celt_encoder_destroy (CELTEncoder *st)
- EXPORT int celt_encode_float (CELTEncoder *st, const float *pcm, float *optional_synthesis, unsigned char *compressed, int nbCompressedBytes)
- EXPORT int celt_encode (CELTEncoder *st, const celt_int16_t *pcm, celt_int16_t *optional_synthesis, unsigned char *compressed, int nbCompressedBytes)
- EXPORT int celt_encoder_ctl (CELTEncoder *st, int request,...)
- EXPORT CELTDecoder * celt_decoder_create (const CELTMode *mode)
- EXPORT void celt_decoder_destroy (CELTDecoder *st)
- EXPORT int celt_decode_float (CELTDecoder *st, unsigned char *data, int len, float *pcm)
- EXPORT int celt_decode (CELTDecoder *st, unsigned char *data, int len, celt_int16_t *pcm)

6.1.1 Detailed Description

Contains all the functions for encoding and decoding audio streams.

Definition in file celt.h.

6.1.2 Define Documentation

6.1.2.1 #define CELT_BAD_ARG -1

An (or more) invalid argument (e.g. out of range)

Definition at line 60 of file celt.h.

6.1.2.2 #define CELT_CORRUPTED_DATA -4

The data passed (e.g. compressed data to decoder) is corrupted

Definition at line 66 of file celt.h.

6.1.2.3 #define CELT_GET_BITSTREAM_VERSION 2000

GET the bit-stream version for compatibility check

Definition at line 83 of file celt.h.

6.1.2.4 #define CELT_GET_FRAME_SIZE 1000

GET the frame size used in the current mode

Definition at line 76 of file celt.h.

6.1.2.5 #define CELT_GET_LOOKAHEAD 1001

GET the lookahead used in the current mode

Definition at line 78 of file celt.h.

6.1.2.6 #define CELT_GET_NB_CHANNELS 1002

GET the number of channels used in the current mode

Definition at line 80 of file celt.h.

6.1.2.7 #define CELT_INTERNAL_ERROR -3

An internal error was detected

Definition at line 64 of file celt.h.

6.1.2.8 #define CELT_INVALID_MODE -2

The mode struct passed is invalid

Definition at line 62 of file celt.h.

6.1.2.9 #define CELT_OK 0

No error

Definition at line 58 of file celt.h.

6.1.2.10 #define CELT_SET_COMPLEXITY(x) CELT_SET_COMPLEXITY_REQUEST, _celt_check_int(x)

Controls the complexity from 0-10 (int)

Definition at line 73 of file celt.h.

6.1.2.11 #define CELT_UNIMPLEMENTED -5

Invalid/unsupported request number

Definition at line 68 of file celt.h.

6.1.3 Typedef Documentation

6.1.3.1 typedef struct CELTDecoder CELTDecoder

State of the decoder. One decoder state is needed for each stream. It is initialised once at the beginning of the stream. Do ∗not∗ re-initialise the state for every frame

Definition at line 96 of file celt.h.

6.1.3.2 typedef struct CELTEncoder CELTEncoder

Encoder state.

Contains the state of an encoder. One encoder state is needed for each stream. It is initialised once at the beginning of the stream. Do ∗not∗ re-initialise the state for every frame.

Definition at line 91 of file celt.h.

6.1.3.3 typedef struct CELTMode CELTMode

The mode contains all the information necessary to create an encoder. Both the encoder and decoder need to be initialised with exactly the same mode, otherwise the quality will be very bad

Definition at line 101 of file celt.h.

6.2 libcelt/celt_types.h File Reference

CELT types.

6.2.1 Detailed Description

CELT types.

Definition in file celt_types.h.

Index

bytes_per_packet
    CELTHeader, 14

celt.h
    CELT_BAD_ARG, 18
    CELT_CORRUPTED_DATA, 18
    CELT_GET_BITSTREAM_VERSION, 18
    CELT_GET_FRAME_SIZE, 18
    CELT_GET_LOOKAHEAD, 18
    CELT_GET_NB_CHANNELS, 18
    CELT_INTERNAL_ERROR, 19
    CELT_INVALID_MODE, 19
    CELT_OK, 19
    CELT_SET_COMPLEXITY, 19
    CELT_UNIMPLEMENTED, 19
    CELTDecoder, 19
    CELTEncoder, 19
    CELTMode, 20
CELT_BAD_ARG
    celt.h, 18
CELT_CORRUPTED_DATA
    celt.h, 18
celt_decode
    codec, 7
celt_decode_float
    codec, 8
celt_decoder_create
    codec, 8
celt_decoder_destroy
    codec, 8
celt_encode
    codec, 8
celt_encode_float
    codec, 9
celt_encoder_create
    codec, 9
celt_encoder_ctl
    codec, 10
celt_encoder_destroy
    codec, 10
CELT_GET_BITSTREAM_VERSION
    celt.h, 18
CELT_GET_FRAME_SIZE
    celt.h, 18
CELT_GET_LOOKAHEAD
    celt.h, 18
CELT_GET_NB_CHANNELS
    celt.h, 18
CELT_INTERNAL_ERROR
    celt.h, 19
CELT_INVALID_MODE
    celt.h, 19
celt_mode_create
    codec, 10
celt_mode_destroy
    codec, 10
celt_mode_info
    codec, 10
CELT_OK
    celt.h, 19
CELT_SET_COMPLEXITY
    celt.h, 19
CELT_UNIMPLEMENTED
    celt.h, 19
CELTDecoder
    celt.h, 19
CELTEncoder
    celt.h, 19
CELTHeader, 13
    bytes_per_packet, 14
    codec_id, 13
    codec_version, 13
    extra_headers, 14
    frame_size, 14
    header_size, 14
    nb_channels, 14
    overlap, 14
    sample_rate, 14
    version_id, 14
CELTMode
    celt.h, 20
codec
    celt_decode, 7
    celt_decode_float, 8
    celt_decoder_create, 8
    celt_decoder_destroy, 8
    celt_encode, 8
    celt_encode_float, 9
    celt_encoder_create, 9
    celt_encoder_ctl, 10

celt_encoder_destroy, 10
celt_mode_create, 10
celt_mode_destroy, 10
celt_mode_info, 10
codec_id
CELTHeader, 13
codec_version
CELTHeader, 13

Encoding and decoding, 7
extra_headers
CELTHeader, 14

frame_size
CELTHeader, 14

header_size
CELTHeader, 14

libcelt/celt.h, 17
libcelt/celt_types.h, 21

nb_channels
CELTHeader, 14

overlap
CELTHeader, 14

sample_rate
CELTHeader, 14

version_id
CELTHeader, 14